MILITARY SPECIFICATION

OSCILLATOR, HIGH-VOLTAGE: 10549785

This amendment forms a part of Military Specification MIL-0-14850(MU) dated 6 January 1969.

Paragraph 1.1: Delete "5.90 volt dc (nominal)" and substitute "6.00 Vdc."

Paragraph 3.3.1(c): Delete "5.90 ± 0.1" and substitute "6.00 ± .01"

Paragraph 3.3.2(a): Delete "5.90 ± .01" and substitute "6.00 ± .01"

Paragraph 3.3.3: Delete "5.90 ± .01" and substitute "6.00 ± .01"

Paragraph 3.4.1: Delete and substitute:

"3.4.1 Operation.- With input voltage of 6.00 ± .01 volts dc and under all load and source conditions described in Table I, the oscillator shall operate as follows:"

Paragraph 3.4.2(a): Delete "5.80 ± 0.01" and substitute "6.00 ± .01"

Paragraph 3.5(a): Delete "7 volts dc" and substitute "6 ± .01 volts dc"

Paragraph 3.5(b): Delete "7 volts dc" and substitute "6 ± .01 volts dc"

Paragraph 3.5(c): Delete "5.90 ± 0.01" and substitute "6.00 ± .01"

Paragraph 3.6: Delete "7.0 volts dc" and substitute "6.00 ± .01 volts dc"

TABLE II, Characteristic No. 1: Delete "5.9 Vdc" and substitute "6 Vdc"

Paragraph 4.6.8a: Delete "5.80 ± .01" and substitute "6.00 ± .01"

Paragraph 4.6.8k: Delete and substitute:

"k. Measure and record the input current, output voltage and output frequency. The measured input currents, output voltages and output frequencies in c., e., g., i. and k. above shall conform to the requirements of 3.4.1."

FSC 1240

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:55Z
Check the source to verify that this is the current version before use.

Paragraph 4.6.9: Delete "5.80 ± .01" and substitute "6.00 ± .01"

Paragraph 4.6.13a: Delete "7.00 - .01" and substitute "6.00 ± .01"

Paragraph 4.6.13f: Delete "7.00 - .01" and substitute "6.00 ± .01"

Paragraph 4.6.13j: Delete "5.90 ± .01" and substitute "6.00 ± .01"

Paragraph 4.6.14: Delete and substitute:

"4.6.14 Reliability.- Connect the oscillator to a test circuit as shown on Figure 2. Adjust the input voltage to 6.00 ± .01 volts dc; R1 set at zero ohms resistance; the variable light source adjusted to no load; and C1 adjusted for a total capacitance output load of 50 pf on the oscillator. Operate the oscillator(s) continuously, 24 hours per day, for the total cumulative test hours as specified in 4.3.2.2. Measure the input current, output voltage, output frequency and output current. These measurements shall conform to the requirements of 3.4.1 and 3.4.3."

Custodian:

Army - MU

Preparing Activity

Army - MU

Project No. 1240-A494



Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:55Z
Check the source to verify that this is the current version before use.