MILITARY SPECIFICATION

GAS GENERATOR ASSEMBLY

This specification is approved for use by the U.S. Army Armament Research and Development Command and is available for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 This specification contains requirements not normally covered by the drawings and provides quality assurance provisions for the fabrication of parts, assembly and packing for a one piece gas generator used in mine systems.

2. APPLICABLE DOCUMENTS

2.1 Issues of documents. The following documents of the issue in effect on date of invitation for bids or request for proposal, form a part of this specification to the extent specified herein.

SPECIFICATIONS

FEDERAL

QQ-A-1876	Aluminum Foil

MILITARY

MIL-A-48078 -	Ammunition, Standard Quality Assurance Provisions, General Specification For

STANDARDS

MILITARY

FSC: 1345

Beneficial comments (recommendations, additions, deletions) and any pertinent data which may be of use in improving this document should be addressed to: Commander, US Army Armament Research and Development Command, Attn. DRDAR-QA, Dover, New Jersey 07801 by using the self-addressed Standardization Document Improvement Proposal (DD Form 1426) appearing at the end of this document or by letter.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

MIL-STD-105 - Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-202 - Test Methods for Electronic and Electrical Component Parts
MIL-STD-650 - Explosive: Sampling, Inspection and Testing

DRAWINGS (see 6.4)

U.S. ARMY ARMAMENT RESEARCH AND DEVELOPMENT COMMAND

PRODUCT AND PACKING DRAWINGS

8796522 - Marking Diagram and Sealing for Wood Packing Boxes
9298530 - Gas Generator Assembly

2.2 Other publications. The following documents form a part of this specification to the extent specified herein. Unless otherwise indicated, the issue in effect on the date of invitation for bids or request for proposal shall apply.

CODE OF FEDERAL REGULATIONS

TITLE 49 - Transportation, Parts 100-199

(The Code of Federal Regulations is available from the Superintendent of Documents, U.S. Government Printing Office, Washington, D.C. 20402. Orders should specify, "49 CFR 100-199 (latest revision).")

3. REQUIREMENTS

3.1 Material. Materials shall be in accordance with the applicable drawings and specifications.

3.2 Assembly. The assemblies shall comply with all requirements specified on Drawing (Dwg) 9298530, all associated drawings, and with all requirements specified in applicable specifications.

3.3 Moisture content of lead styphnate. The moisture content of the lead styphnate at the loading station at the time of loading shall not exceed three tenths of one percent (0.3%).

3.4 Electrode fuse strength. The electrode shall not break or loosen in the glass when subjected to an axial pull force of eight

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

pounds plus one tenth pounds (8.0 + 0.1 lbs.) for a time duration of forty five (45) seconds when tested in accordance with 4.5.3.

3.5 Environmental conditioning. The gas generator assembly shall function as specified after being subjected to an environmental conditioning of thermal shock and vibration when tested in accordance with 4.5.6.

3.6 First article inspection. . This specification contains technical provisions for first article inspection. Requirements for the submission of first article samples by the contractor shall be as specified in the contract.

3.7 Workmanship. All parts and assemblies shall be fabricated, loaded and assembled in a thorough, workmanlike manner. They shall be free of burrs, sharp edges, cracks, dirt, grease, rust, and other foreign matter. The cleaning method used shall not be injurious to any parts, nor shall the parts be contaminated by the cleaning agents. Exterior surface coatings shall be continuous; however, a few light scratches not exposing base material may be permitted. All required marking and stamping shall be neat and sharply defined.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection and standard quality assurance provisions. Unless otherwise specified herein or in the contract, the provisions of MIL-A-48078 shall apply and are hereby made a part of this detail specification.

4.2 Classification of inspection. The following types of inspection shall be conducted on this item:

a. First Article Inspection

b. Quality Conformance Inspection

4.3 First article inspection

4.3.1 Submission. The contractor shall submit a first article as designated by the contracting Officer for evaluation in accordance with the provisions of 4.3.2. The first article sample shall consist of the following items in sample quantities as indicated.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

Part Description	Drawings	Quantity
Cup, Dimpled	[illegible]	25
Header	[illegible]	25
Header, Bridged Assembly	[illegible]	25
Ignition Assembly	[illegible]	25
Charge Assembly	[illegible]	25
Output Charge	[illegible]	25
Gas Generator Assembly	[illegible]	250

4.3.2 Inspections to be perf-a $UI ?%IL-A-48078 and Table I herein.

4.3.3 Rejection. See MIL-A-44W8. ,

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

TABLE I. First Article Inspection

CLASSIFICATION OF DEFECTS & TESTS

MIL-C-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 2		DRAWING NUMBER See Below NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
	Cup, Dimpled				
	(Dwg. 9298536)				
	Examination for defects	25		3.2	4.4.2.1
	Header				
	(Dwg 9298533)				
	Examination for defects	25		3.2	4.4.2.2
	Pull test	25		3.4	4.5.3
	Header, Bridged Assembly				
	(Dwg. 9298522)				
	Examination for defects	25		3.2	4.4.2.3
	Bridgewire resistance	25		3.2	4.5.9
	Ignition Assembly				
	(Dwg. 9298531)				
	Examination for defects	25			4.4.2.4
	Moisture content of lead styphnate	---		---	MIL-STD-650/4.5.2
	Charge Holder				
	(Dwg. 9298535)				
	Examination for defects	25			4.4.2.5

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

TABLE I. First Article Inspection

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 2 OF 2		DRAWING NUMBER See Below
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
	Output Charge (Dwg. 9298534)				
	Examination for defects	25			4.4.2.6
	Moisture content of black powder	---		---	MIL-STD-650/4.5.1
	Moisture content of lead styphnate	---		---	MIL-STD-650/4.5.2
	Gas Generator Assembly (Dwg. 9298530)				
	Examination for defects	25			4.4.2.7
	Insulation resistance	150		3.2	4.5.5
	Bridgewire resistance	150		3.2	4.5.4
	Environmental conditioning and functioning	25		3.5	4.5.6
	All fire voltage functioning	125		3.2	4.5.7
	Assembly functioning output (+70°F)	80		3.2	4.5.8
	Assembly functioning output (-20°F)	20		3.2	4.5.8

NOTES: Bridgewire resistance and insulation resistance shall be performed on all gage generator assemblies prior to performing all other tests..

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

4.4 Quality Conformance Inspection

4.4.1. Inspection lot formation. Inspection lots shall comply with the lot formation provisions of MIL-A-48078. In addition, inspection lots of gas generator assemblies shall contain:

a. Parts from one lot interfix number from one manufacturer.

b. Normal lead styphnate from one batch or blending of batches which results in homogeneity of all lead styphnate used in loading the entire gas generator assembly lot.

c. Lead styphnate with lacquer (spot charge) from one batch or blending of batches which results in homogeneity of all lead styphnate with lacquer used in loading the entire gas generator assembly lot.

d. Black powder from one batch or blending of batches which results in homogeneity of black powder used in loading the entire output charge assembly lot,

4.4.2 Examination. See MIL-A-48078.

a. Sampling Plans. Unless otherwise specified in the Classification of of Defects and Test Tables, sampling plans for major and minor defects shall be in accordance with MIL-STD-105.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

QUALITY CONFORMANCE INSPECTION

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.1	Cup, Dimpled				9298536
					NEXT HIGHER ASSEMBLY
					9298530
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major 101	Material thickness		0.40%	3.2	Gage
Minor 201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

QUALITY CONFORMANCE INSPECTION

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.2	Header				9298533
					NEXT HIGHER ASSEMBLY
					9298532
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major 101	Pull test of electrodes	10/0/1	---	3.4	4.5.3
Minor 201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE	SHEET 1 OF 1	DRAWING NUMBER
4.4.2.3	Header, Bridged, Assembly		9298532
			NEXT HIGHER ASSEMBLY 9298531

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Bridgewire missing		0.40%	3.2	Visual
102	Bridgewire weld missing or inadequate		0.40%	3.2	Visual/Manual
103	Bridgewire resistance		0.40%	3.2	4.5.9
Minor					
201	Bridgewire material improper			3.2	Certification
202	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

10

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.4	Ignition Assembly				9298531
					NEXT HIGHER ASSEMBLY 9298530
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Lead styphnate on outside diameter of header		100%	3.2	Visual
102	Bridgewire visible through lead styphnate		0.40%	3.2	Visual
103	Lead styphnate cracked or separated (after drying)		0.40%	3.2	Visual
104	Moisture content of lead styphnate		---	3.3	MIL-STD-650/4.5.2
Minor					
201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

QUALITY CONFORMANCE INSPECTION

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.5	Charge Holder				9298535
					NEXT HIGHER ASSEMBLY
					9298534
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Outside diameter		0.40%	3.2	Gage
102	Total length		0.40%	3.2	Gage
103	Material		0.40%	3.2	Certification
Minor					
201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE	SHEET 1 OF 1	DRAWING NUMBER
4.4.2.6	Output Charge		9298534
			NEXT HIGHER ASSEMBLY 9298530

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Outside diameter		0.40%	3.2	Gage
102	Total length		0.40%	3.2	Gage
103	Charge height		0.40%	3.2	Visual
104	Assembly deformed or split		0.40%	3.2	Visual
105	Moisture content of black powder		---	3.2	MIL-STD-650/4.5.1
106	Moisture content of lead styphnate		---	3.3	MIL-STD-650/4.5.2
Minor					
201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.7	Gas Generator Assembly				9298530
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Assembly cracked, punctured or split		100%	3.2	Visual
102	Bare lead wires not shorted (twisted) together		100%	3.2	Visual
103	Cup crimp incomplete		0.40%	3.2	Visual
104	Epoxy seal missing or incomplete		0.40%	3.2	Visual
105	Insulation resistance		100%	3.2	4.5.5
106	Environmental conditioning and functioning	20/0/1	---	3.5	4.5.6
107	Bridgewire resistance	125	100%	3.2	4.5.4
108	All fire voltage functioning	125/2/3	---	3.2	4.5.7
109	Assembly functioning output (+70°F)	80(a)	---	3.2	4.5.8
110	Assembly functioning output (-25°F)	20(a)	---	3.2	4.5.8
111	Outside diameter, max (for specified length)		0.40%	3.2	Gage
112	Length of closed cup, max.		0.40%	3.2	Gage
113	Length of insulation tubing		0.40%	3.2	Gage
Minor					
201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES: (a) All units must fire on first attempt. No failure-to-function allowed; one (1) pressure time failure permitted.

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.8	Carton (Prior to sealing)				See Section 5
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Gas generator assemblies in bundle not completely encased in foil		0.40%		Visual
102	Pocket assembly torn or insecurely closed (when applicable)		0.40%		Visual
Minor					
201	Evidence of poor workmanship		1.0%	3.7	Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

QUALITY CONFORMANCE INSPECTION

CLASSIFICATION OF DEFECTS & TESTS

MIL-G-63386(AR)

PARAGRAPH	TITLE		SHEET 1 OF 1		DRAWING NUMBER
4.4.2.9	Carton, Sealed				See Section 5
					NEXT HIGHER ASSEMBLY
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	Carton damaged to extent that contents are exposed or liable to become exposed		0.40%		Visual
Minor					
201	Marking missing, incorrect or illegible		0.65%		Visual
202	Evidence of poor workmanship		1.0%		Visual

NOTES:

DRDAR-QA Form 160 Jul 77 Replaces SARPA-QA Form 2567 Feb 74 Which is Obsolete

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

4.4.3 Testing. Testing is described in the First Article and Quality Conformance Inspection Tables.

4.4.4 Inspection equipment. The inspection equipment required to perform the examinations and tests prescribed herein is described in the Paragraph Reference/Inspection Method column in the tables starting with Paragraph 4.4.2.1. The contractor shall submit for approval inspection equipment designs in accordance with the terms of the contract. See section 6 of MIL-A-48078 and 6.3 herein.

4.5 Test methods and procedures

4.5.1 Moisture and volatiles content of black powder. The contractor shall provide adequate controls to insure compliance with the applicable requirements. The moisture and volatiles content of the explosive charge shall be determined at the loading station at the time of loading. This determination shall be made at least once each four (4) hours of production. Sampling of the explosive charge shall be in accordance with MIL-STD-650, Method 101.5. In addition, if the moisture and volatiles content fails to comply with he requirements specified on the applicable drawing, and loading has not begun, the explosive charge material shall be rejected until corrective action has been taken as verified by repeating the moisture and volatiles content determination. If loading has begun, charge holder assemblies loaded with the non-conforming explosive charge shall be rejected.

4.5.2 Moisture content of lead styphnate. The contractor shall provide adequate controls to insure compliance with the applicable requirements. The moisture content of both lead styphnates shall be determind at the loading station at the time of loading. This determination shall be made at least once each eight (8) hours of production. Sampling of both styphnates shall be in accordance with the applicable specifications. In addition, if the moisture content fails to comply with the requirement specified in 3.3, and loading has not begun, the styphnate shall be rejected until corrective action has been taken as verified by repeating the moisture content determination. If loading has begun, Gas Generator assemblies loaded with the non-conforming styphnates shall be rejected. The moisture content shall be determined as follows: using appropriate safety precautions, weigh approximately two (2) grams of the plant-dried sample accurately within 0.1 mg into a tared stoppered weighing dish. The dish shall be covered with a sheet of polytrafluoroethylene. The procedure of MIL-STD-650, Method 101.6 shall be used with the exception that the sample shall be dried at 60° ± 5°C, for three (3) hours.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

4.5.3 Pull test of electrodes of header. The header shall be assembled in an approved fixture and the procedure of MIL-STD-202, Method 211, Test Condition A shall be used with the exception that the applied force shall be 8.0 ± 0.1 pounds per electrode for 45 seconds. The force shall be a gradually applied static axial load. Any header in which either electrode moves or loosens shall be classed defective. This test is a destructive test. Parts so tested shall not be returned to the lot.

4.5.4 Bridgewire resistance of gas generator assembly. Prior to shorting (twisting) the lead wires, the assembly shall be connected to approved equipment and the bridgewire (lead to lead) resistance measured to determine compliance with the requirement specified on the applicable drawing. The measurement shall be made with a meter capable of measurement to the nearest 0.01 ohm. The current applied shall be limited to one (1) milliampere max.

4.5.5 Insulation resistance of gas generator assembly. The resistance between the shorted (twisted) lead wires and the dimpled cup shall be determined using the procedure specified on the applicable drawing and MIL-STD-202, Method 302, Test Condition B. The specified voltage shall be applied for two (2) seconds minimum. Examination shall be made to determine compliance with the insulation resistance requirement specified on the applicable drawing as well as any evidence of insulation failure such as loosening, cracking, or charring of the insulationtubing or reduced voltage.

4.5.6 Environmental conditioning and functioning. The Gas Generator assemblies-shall be tested as follows, in the sequence specified, using approved equipment:

a. Measure resistance between the shorted electrode and cup in accordance with 4.5.4.

b. Condition for two (2) hours minimum at -65 ± 5°F.

c. Remove from cold chamber and within 20 seconds transfer to a hot chamber at 165 ± 5°F.

d, Condition for two (2) hours minimum at +165 ± 5°F and 20% maximum relative humidity.

e. Remove from hot chamber.

f. Vibrate for 15 minutes, minimum in a sweep covering a frequency range of 25-500-25 cycles per second, parallel to the transverse orthogonal axis, with base charge down and a 2 ± 0.2 G's peak.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

g. Measure resistance between electrode and cup in accordance with 4.5.5.

h. The Gas Generators shall be functioned as specified in 4.5.7.

4.5.7 All-fire voltage of gas generator assembly. The Gas Generator assembly shall be subjected to the specified all-fire voltage impressed across the bridge, circuit. Observation shall be made to determine compliance with the requirement specified on the applicable drawing. A record of each firing shall be kept. Any sample tailing to comply with all of the specified requirements shall be classed defective. (Destructive test.)

4.5.8 Output pressure/time test of gas generator assembly lots l This test shall be performed for each gas generator assembly serial lot to be used in the Housing, Timing and Fuzing lot. The assemblies shall be assembled in a fixture in accordance with Dwg. 9295530 which is instrumented to provide a record of pressure versus time. The assemblies and fixture shall be conditioned at the required test temperature for two (2) hours minimum prior to test. The Gas Generator assembly shall be initiated using a suitable power source and the pressure/time results evaluated against the applicable requirements. If any Gas Generator assembly fails to function and/or more than one (1) pressure/time failure occurs, that combination of serial. lots shall be rejected for use in the Housing, Timing and Fuzing lot.

Care shall be taken during conditioning and handling of the assemblies to avoid contamination. The fixture shall be cleaned after each shot or, as required. Any assembly failing to comply with all of the specified requirements shall be classed defective. (Destructive test.).

4.5.9 Bridgewire resistance. The assembly shall be measured for the specified resistance using a Government approved ohmmeter with a current limiter of such a value so as not to cause any component degradation. Any sample failing to comply with all of the specified requirements shall be classed defective. (Non-destructive test.) .

4.5.10 Check test for deterioration of gas generator assemblies. The following test is designed to prevent Gas Generator assemblies that have deteriorated from being assembled into major ammunition items. The test shall be performed on Gas Generator assemblies from each lot which have been stored for more than two years, under adverse conditions for any perior of time, or at the request of the Contracting Officer. If the specification for the

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

ammunition item into which the Gas Generator assemblies are assembled does not require that the check test be performed, the Contracting Officer should insert in the a provision for the performance of the check test. The Contracting Officer will arrange for the contractor to be reimbursed for expense incurred in his performance of the check test for possible deterioration.

4.5.10.1 Functioning. Seventy (70) Gas Generator Assemblies shall be selected from each lot and subjected to the functioning test specified in 4.5.8. If two (2) or snore igniter assemblies fail to comply with the requirements specified on the applicable drawing, including duds, the lot shall be rejected. If any lot is rejected, all data generated shall be forwarded to Commander, ATTN: DRDAR-QAA-M, ARRADCOM, Dover, NJ 07801.

5. PACKAGING

5.1 Preservation and packaging

5.1.1 Level B

5.1.1.1 Gas generator assembly

a. Rosett wrap. A bundle of 25 Gas Generator assemblies shall be made, lead wires out straight, using the lead wire from one assembly to secure the bundle. Each bundle of Gas Generators shall be wrapped in a sheet of approximately 8 inches by 8 inches by .0015 inch thick aluminum foil complying with QQ-A-1876, so that all Gas Generators and lead wires in a bundle are completely encased by the foil. Five bundles of Gas Generators totaling 125, shall be packed in a folding carton, set-up box, or comparable container, made of material with a minimum board thickness of .03 inch.

b. Pocket assembly, alternate pack. The Gas Generators shall be packed in pocket assemblies manufactured in accordance with Figure 4 (as applicable) made of .0015 inch aluminum foil complying with QQ-A-1876. An adhesive seal shall be used to bond the faces of the aluminum foil together to form five pockets. The adhesive used for the sealing of the two faces of the aluminum foil shall be suitable for the application. The strength of the seal shall be sufficient to allow the insertion of the dowel (See Figure 4) without s eparation of the seal. The two faces of any seal shall not be misaligned by more ;than 1/16 inch when the pouch is formed. Each pocket shall be opened to form a cylinder using a smooth dowel with rounded end and similar to that shown on Figure 4. Each pocket may, however, be opened by other suitable methods whichwill result in providing a satisfactory pocket for insertion of the Gas Generator without injury to the material. One Gas Generator shall be inserted, output end down, in each pocket. The lip of the pocket

Source: http://assist.daps.mil - Downloaded: 2016-01-21T02:46
Check the source to verify that this is the current version before use.

pocket assemblies or a total of 125 Gas Generators, shall be packed in a folding carton, set-up box, or comparable container, made of a material with a minimum board thickness of .03 inch.

c. Marking. Each inner carton, set-up box, or comparable container, shall be marked: "PATENTED - U.S. PATENT 2,389,086."

5.2 Packing

5.2.1 Level B. The Gas Generator assembly, preserved and packaged as specifed in 5.1.1 shall be packed for shipment in accordance with Code of Federal Regulations, Title 40, parts 100-199.

5.3 Marking

5.3.1 Gas generator assembly. The cartons shall be marked in accordance with Dwg. 8796522. The DOT marking shall be: (QTY) ELECTRIC WASTING CAPS-HANDLE CAREFULLY.

NOTE: Insert number of blasting caps in the exterior container.

5.4 Shipping. When components from more than one lot are shipped at one time, such as in a carload, each lot shall be kept separate, and the division between lots clearly indicated to prevent mixing of the lots in transit.

6. Noms

6.1 Intended use. The components covered by this specification are intended for use with Housing, Timing and Fuzing.

6.2 Ordering data. See MIL-A-48078.

6.3 Submission of inspection equipment designs for approval. See MIL-A-48078. Submit equipment designs as required to: Commander, ARRADCOM, ATTN: DRDAR-QAA-I, Dover, New Jersey 07801. Letter of submittal should state contractor, contract number, specification number, item nomenclature and classification of defects or test paragraph.

6.4 Drawings. Drawings listed in Section 2 of this specification under the heading U.S. Army Armament Research and Development Command (ARRADCOM) may also include drawings prepared by and identified as Edgewood Arsenal, Frankford Arsenal, Rock Island Arsenal or Picatinny Arsenal drawings. Technical data originally prepared by these activities are now under the cognizance of ARRADCOM.

Custodian:
Army-AR

Preparing Activity:
Army-AR

Project No.: 1345-A111

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

INSTRUCTIONS This form is provided to solicit beneficial comments which may improve this document and enhance its use. DoD contractors, government activities, manufacturers, vendors, or other prospective users of the document are invited to submit comments to the government Fold on lines on reverse side, staple in corner, and send to preparing activity. Attach any pertinent data which may be of use in improving this document If there are additional papers, attach to form and place both in an envelope addressed to preparing activity. A response will be provided to the submitter, when name and address is provided, within 30 days indicating that the 1426 was received and when any appropriate action on it will be completed.

NOTE: This form shall not be used to submit requests for waivers, deviations or clarification of specification requirements on current contracts. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements.

DOCUMENT IDENTIFIER *(Number)* AND TITLE

MIL-G-63386 Gas Generator Assembly

NAME OF ORGANIZATION AND ADDRESS OF SUBMITTER

☐ VENDOR ☐ USER ☐ MANUFACTURER

1. ☐ HAS ANY PART OF THE DOCUMENT CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE? ☐ IS ANY PART OF IT TOO RIGID, RESTRICTIVE, LOOSE OR AMBIGUOUS? PLEASE EXPLAIN BELOW.

A. GIVE PARAGRAPH NUMBER AND WORDING

B. RECOMMENDED WORDING CHANGE

C. REASON FOR RECOMMENDED CHANGE(S)

2. REMARKS

SUBMITTED BY *(Printed or typed name and address — Optional)*

TELEPHONE NO

DATE

DD FORM 1426 1 OCT 76

EDITION OF 1 JAN 72 WILL BE USED UNTIL EXHAUSTED.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.

FOLD

DEPARTMENT OF THE ARMY

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BUSINESS REPLY CARD

FIRST CLASS PERMIT NO. 12062 WASHINGTON D. C.

POSTAGE WILL BE PAID BY THE DEPARTMENT OF THE ARMY

Commander
US Army Armament R&D Command
ATTN: DRDAR-QAA
Dover, New Jersey 07801

FOLD

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T02:46Z
Check the source to verify that this is the current version before use.