INCH-POUND

MIL-T-49305(CR)

17 February 1989

MILITARY SPECIFICATION

TEST SET, COUNTERMEASURE SET

TS-3609( )/ALQ-156(V)

This specification is approved for use by the Communications-Electronics Command, Department of the Army, and is available for use by all Departments and Agencies of the Department of Defense.

1. SCOPE.

1.1 Scope. This specification covers the requirements for the construction and testing of the Countermeasure Set TS-3609 AN/ALQ-156(V) Test Set, which is used to test and fault isolate the following units of the AN/ALQ-156(V):

Control Indicator C-10131( )/ALQ-156(V)
Receiver-Transmitter RT-1220( )ALQ-156(V)

2. APPLICABLE DOCUMENTS

2.1 Government document

2.1.1 Specifications and standards and handbooks. The following specifications and standards and handbooks form a part of this specification to the extent specified herein. Unless otherwise specified, the issues of these documents shall be those listed in the issue of the Department of Defense Index of Specifications and Standards (DODISS) and supplement thereto, cited in the solicitation.

Beneficial comments (recommendations, additions, deletions) and any pertinent data which may be of use in improving this document should be addressed to: Commander, US Army Communications-Electronics Command and Fort Monmouth, ATTN: AMSEL-ED-TO, Fort Monmouth, New Jersey 07703-5000, by using the self-addressed Standardization Document Improvement Proposal (DD Form 1426) appearing at the end of this document or by letter.

AMSC-N/A FSC 6625

DISTRIBUTION STATEMENT A. Approved for public release, distribution unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

SPECIFICATIONS

MILITARY

MIL-P-116	Preservation-Packaging, Method of
MIL-P-11268	Parts, Materials, and Processes Used in Electronic Equipment
MIL-M-13231	Marking of Electronic Items
MIL-F-14072	Finishes for Ground Signal Equipment
MIL-I-43553	Ink, Marking, Epoxy Base
MIL-E-55535	Electronic Equipment and Parts, Packaging

STANDARDS

FEDERAL

FED-STD-101	Preservation, Packaging and Packing Materials

MILITARY

MIL-STD-105	Sampling Procedures and Tables for inspection By Attributes
MIL-STD-130	Identification Marking of U.S. Military Property
MIL-STD-252	Wired Equipment, Classification of Visual and Mechanical Defects
MIL-STD-275	Printed Wiring for Electronics Equipment
MIL-STD-454	Standard General Requirements for Electronic Equipment
MIL-STD-461	Electromagnetic Interference Characteristics Requirements for Equipment Subsystem and System
MIL-STD-462	Electromagnetic Interference Characteristics, Measurement of
MIL-STD-810C	Environmental Test Methods
MIL-STD-1188	Commercial Packaging of Supplies and Equipment
MIL-STD-1472	Human Engineering Design Criteria for Military Systems, Equipment and Facilities
MIL-STD-2073-2	Packaging Requirements Codes

2.1.2 Other Government document, drawings, and publications. The following Government documents, drawings, and publications form a part of this specification to the extent specified herein. Unless otherwise specified, the issues shall be those in effect on the date of the solicitation.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the currentversion before use.

DRAWINGS

ELECTRONICS COMMAND

SM-A-920699	Coded Parameters and Requirements etc.
DL-SM-B-920797	Test Set, TS-3609/ALQ-156(V)
DL-SM-B-920844	Test Set Assembly
SM-A-951543	ATP, TS-3609/ALQ-156

(Copies for specifications, standards, handbooks, drawings and publications and other Government documents required by contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer. Both the title and number or symbol should be stipulated when requesting copies.)

2.2 Order of precedence. In the event of a conflict between the text of this specification and the references cited herein (except for associated detail specification, specification sheets or MS standards), the text of this specification shall take precedence. Nothing in this specification, however, shall supersede applicable laws and regulations unless a specific exemption has been obtained.

3. REQUIREMENTS

3.1 First article. When specified in the contract or purchase order, the contract shall furnish first article sets in accordance with the requirements of this specification (see para. 4.3 and 6.2).

3.2 Construction. The Test Set, Countermeasure Set TS-3609 AN/ALQ-156(V) shall be constructed in accordance with the requirements of this specification and the drawings listed in the CECOM Data Lists DL-SM-B-920979 and DL-SM-A-920844.

3.2.1 Weight. The equipment weight including the transit case with all components of the TS-3609/ALQ-156(V), shall be no greater than 95 pounds.

3.3 Parts, Materials and Process; General. In addition to the requirements of this specification, the requirements of MIL-P-11268, including the selection requirements therein shall apply.

3.3.1 Finish. The TS-3609/ALQ-156(V) shall be finished in accordance with MIL-F-14072 and the equipment drawings.

3.3.2 Marking.

3.3.2.1 General. The wire harness marking shall be in accordance with MIL-STD-681B, System IV. Wires will be identified by coding numbers on white wire.

3.3.2.2 Visibility. Wherever practical, parts shall be so mounted that their identification markings will be readily visible with minimum disassembly of the equipment.

Source: https://assist.dla.mil -- Downloaded: 202640-26T04:00Z
Check the source to verify that this is the current version before use.

3.3.2.3 Serial Numbers. The following items shall have serial numbers: Test Set, Countermeasure Set TS-3609/ALQ-156(V) and Case, Test Set CY-7766/ALQ-156(V).

3.4 Printed Wiring Assemblies. Printed wiring assemblies shall be fabricated and processed in accordance with MIL-STD-275C and the equipment drawings.

3.5 Cable Assemblies, Electrical. Cable assemblies W1, W2, W3, W4, W5, W6, W7, W8, W9 and W10 shall provide the interconnections between the TS-3609/ALQ-156(V) and AN/ALQ-156(V) during testing.

3.6 Performance. Unless otherwise specified, performance requirements shall apply under standard conditions, service input power conditions, and service environmental conditions.

3.6.1 System Compatibility. The Test Set Countermeasure Set TS-3609/ALQ-156(V) (hereafter referred to as the BTS) provides the capability to localize malfunctions contained within, and performs operational checkouts of the AN/ALQ-156(V) with a minimum of operator intervention during the execution of the test and diagnostic routines. The BTS shall exercise the operational functions of the AN/ALQ-156(V) and provide the capability of isolating faults within a major replacement assembly.

3.6.2 Input Power. The BTS shall operate from 115 ± 4 Vac, 400 ± 20 Hertz, Y configuration, three phase power.

3.6.3 Power Supplies. The BTS internal power supplies shall provide sufficient power to operate the receiver transmitter (RT) and control units being tested while meeting the load requirements of the other BTS circuitry.

3.6.3.1 Low Voltage Supplies. The BTS low voltage supplies shall provide the following outputs:

Power Supply	Voltage (DC)	Tolerance
PS 1	+15V	±.15
	-15V	±.15
	+24	±.24
	+5V	±.1
PS 2	+24	±1.0

3.6.4 RT-1220/ALQ-156(V) Inputs. The BTS shall provide AC and DC power and simulated RF signals to test the RT-1120/ALQ-156(V) and determine switch changes or logic levels in its operational status.

3.6.4.1 AC Power. The BTS shall provide filtered 115 ± 4 Vac, 400 ± 20 Hz, 3 phase AC power to the RT-1220/ALQ-156(V) under test via the front panel Power RT circuit breaker.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

3.6.4.2 DC Power. The BTS shall provide 24 ± .24 Vdc to the RT-1220/ALQ-156(V) under test.

3.6.4.3 RF Signals. The BTS shall utilize the RF output of the RT-1220/ALQ-156(V) under test to test that same RT unit. The BTS shall modulate or delay the RF signal to produce the signals specified in TABLE II of SM-A-920699.

3.6.4.4 Switch Closures/Logic Levels. The BTS shall provide the RT-1220/ALQ-156(V) under test with switch closures or logic levels to test or simulate the following items:

a. Channel Selection.

b. BITE

c. FMO Phase Code

d. Antenna Switching

e. XMTR Disabling

3.6.5 RT-1220/ALQ-156(V)Outputs. The BTS shall provide RF loads to the RT unit under test and monitor signals within that unit.

3.6.5.1 Test/Lamp Indicators. The BTS shall provide a current status of the following functions within the AN/ALQ-156(V) under test:

a. RT-1220 BITE (PWR AMPL, VSWR/SW, LOW PWR, SYNC, PROC, PWR SPLY) CI (CM, PA ON, STBY, WRM UP) ADVISORY (CM INOP, CM JAM)

b. C-10131 ADVISORY (CM INOP, CM JAM)

3.6.5.2 RF Power Output. The BTS shall terminate the RT-1220/ALQ-156(V) RF Power Output and provide a coupled output for external measurement of the RF signal.

3.6.5.3 Power Supply Outputs. The BTS shall monitor all of the RT-1220/ALQ-156(V) internal power supply voltages using the METER switch and associated test points.

3.6.5.4 Signals. The BTS shall permit monitoring of integral RT-1220/ALQ-156(V) signals through the front panel connectors, as shown in Tables I, II and III.

3.6.6 Control, C-10131/ALQ-156(V) Inputs. The BTS shall provide 24 ± .24 Vdc to the control indicator C/I to power the C/I internal circuitry and lights. 5 ± .1 Vdc shall also be applied to the C/I to illuminate the panel lighting. A logic level shall be provided by the front panel C/I push button switch to test the C/I DIML input command.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the current version before use.

3.6.7 C-10131/ALQ-156(V) Outputs. The BTS shall provide advisory indicators, switch closures, monitor the channel select BCD control lines and load and monitor the C/I CM command pulse.

3.6.8 Controls and Indicators. The front panel switches and indicators shall control the functions of the BTS as follows:

3.6.8.1 Power.

3.6.8.1.1 Test Set, ON/OFF. The circuit breaker switch shall apply three phase 400Hz, 115 Vac power to the BTS and RT switch. The associated amber lamp shall light when phase A is available.

3.6.8.1.2 RT, ON/OFF. The circuit breaker shall apply three phase, 400 Hz, 115 Vac power to the RT being tested plus 24 volts shall be applied to the FMO pre-heat circuit in the RT. The amber lamp shall light when the switch is on and phase A is available.

3.6.8.2 Control Indicator.

3.6.8.2.1 ON/STBY/OFF. The switch shall control the operating mode of the RT being tested, OFF shall remove the 24 Vdc from the RT, STBY shall apply 24 Vdc to the RT, but inhibit the transmitter and ON shall apply 24 Vdc to RT and enable transmitter and synchronizer with RDYH signal.

3.6.8.2.2 Channel Select. The switch shall select the operating frequency of RT being testing by applying appropriate BCD Command to the RT's FMO assembly. The preselect frequency shall be channel 13. Another position shall be "AUTOMATIC FREQUENCY SELECT" which allows normal automatic frequency selection of the radar The last position shall be "CM BITE" which duplicates flare test switch on the control indicator.

3.6.8.2.3 CM. The amber indicator lamp shall light when the RT processes a valid target signal.

3.6.8.2.4 PA ON. The amber indicator lamp shall light when the RT-1220 is radiating RF energy to the BTS and the level is within specified limits.

3.6.8.2.5 STBY. The amber indicator lamp shall light when the ON/STBY/OFF switch is in the STBY position.

3.6.8.2.6 Warm-Up. The amber indicator lamp shall light until the RT FMO assembly oven has reached operating temperature and the C/I mode switch is in the STBY or ON position.

3.6.8.3 BITE Fault.

3.6.8.3.1 PWR AMPL. The amber indicator shall light when the RT RF power amplifier is overheated.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

3.6.8.3.2 VSWR/SW. The amber indicator lamp shall flash for 1 second when RT VSWR BITE monitor indicates a fault. The lamp shall light when the RT duplexer switch BITE monitor indicates a fault.

3.6.8.3.3 LOW PWR. The amber indicator lamp shall light when the RT RF power output level BITE monitor indicates a fault.

3.6.8.3.4 SYNC. The amber indicator lamp shall light when the RT synchronizer BITE monitor indicates a fault.

3.6.8.3.5 PROC. The amber indicator lamp shall light when the RT processor BITE monitor indicates a fault.

3.6.8.3.6 PWR SPLY. The amber indicator lamp shall light when the RT power supply (+5V output) drops below 2.4 Vdc.

3.6.8.4 Indicators.

3.6.8.4.1 C/I DIM. Depression of the switch shall simulate the DIM command to the system Control Indicator and to the BTS Control Indicator section.

3.6.8.4.2 LAMP DRVR. Depression of the switch shall activate all lamp drivers in the test set.

3.6.8.5 Test.

3.6.8.5.1 BITE, Continuous/Norm/Off. The Continuous position shall enable the RT BITE cycle to repeat continuously, the Norm position shall allow normal RT synchronizer control of the RT BITE cycle and the Off position shall inhibit the RT BITE cycle.

3.6.8.5.2 PA, Test Set Ovrd/Normal. Test Set OVRD position shall keep the PA on the enable the Switch Fault circuit in the R/T.

3.6.8.5.3 FMO Phase Code, Test/Norm/Off. The TEST position shall inhibit the RT synchronizer from controlling the FMO phase code and inject a phase code test signal from the BTS to the RT FMO assembly. The NORM position shall allow the RT synchronizer assembly to control the phase code to the FMO assembly. The OFF position shall inhibit all phase code commands to the RT FMO assembly.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the current version before use.

3.6.8.5.4 Ant Cont. Normal /J3/J4/J5/J6. The Norm position shall allow the RT synchronizer to operate antenna switching. The J3/J4/J5/J6 position shall force the RT duplexer assembly RF switch to select the antenna position selected.

3.6.8.5.5 XMTR, Disable/Normal. The Disable position shall inhibit the RT synchronizer from enabling the RT transmitter and the Normal position shall permit the RT synchronizer to enable the transmitter as in normal operation.

3.6.8.5.6 Program, Reset/Normal. The program switch is spring loaded to the Normal position. In the RESET position the RT synchronizer assembly is forced to restart the microprocessor from Step 1 of the program.

3.6.8.6 SCOPE.

3.6.8.6.1 Scope A, Monitor/Syn. The Monitor test connector and switch shall permit monitoring of the analog and logic signals of the RT being tested. The Syn connector shall provide a signal (DMPL MON) for oscilloscope synchronization (See Table I).

3.6.8.6.2 Scope B, Monitor/Syn. The Monitor test connector shall permit monitoring of the similar signals as a Monitor plus additional logic signals. The Syn connector shall provide a logic signal (SYRSTL) for oscilloscope synchronization (See TABLE II).

3.6.8.7 Meter. The HIGH/LOW test points shall permit monitoring of the RT power supplies, BTS power supplies and logic levels in the control indicator under test. The LOW test point shall be at ground potential (See Table III).

3.6.8.8 RT Channel.

3.6.8.8.1 RT Channel display. The two digit channel display shall indicate the channel number that the RT-1220( ), connected to the BTS, is currently operating on. When no RT-1220( ) is connected to the BTS, the channel display will indicate channel 3.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the currentversion before use.

TABLE I. Scope A. Monitor/Syn.

SWITCH POSITION	SIGNAL
1	SYRSTL
2	BTOH
3	BRG1 ALARM L
4	BRG2 ALARM L
5	BRG3 ALARM L
6	CM
7	(NOT USED)
8	RF DET MON
9	MIL
10	(NOT USED)
11	VSWRFLTH
12	SWFLTH
13	PROFLTH
14	PAFLTL
15	BLLPWRH
16	BSYNFL
17	(NOT USED)
18	WRMUPL
19	JAMH
20	MBBLH
21	CM PULSEH
22	BDMPL
23	BDMPL MON
24	RT +5

TABLE II. Scope B. Monitor/Syn.

SWITCH POSITION	SIGNAL
1	XMTR PWRL
2	STE CM
3	LSDLL
4	ANT 1
5	ANT 2
6	ALOPWRH
7	SWFLTDISH
8	INHTX2L
9	INHTX1L
10	ECMIL
11	ECM2L
12	ECM3L

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

TABLE III. Meter

SWITCH POSITION	SIGNAL
1	+5
2	+15
3	+24
4	B+(+32)
5	-8
6	-15
7	-47
8	(NOT USED)
9	(NOT USED)
10	(NOT USED)
11	CI 8L
12	CI 16L
13	28V RTN
14	CI +24 VS
15	A/C 28V
16	PWM +15
17	(NOT USED)
18	(NOT USED)
19	PS1 +5
20	PS1 -15
21	PS1 -15
22	PS1 +24
23	PS2 +24

3.6.8.9 RF Modulation

3.6.8.9.1 Mode. The Mode switch shall control the RF circuits to select simulated return test signals to the RT.

3.6.8.9.1.1 Off. There shall be no test signals generated when the swtich is in the Off mode.

3.6.8.9.1.2 MDS. The MDS position shall select a simulated minimum discernable signal test target with a doppler frequency selected by the Frequency Select switch in accordance with SM-A-920699.

3.6.8.9.1.3 SCV. The switch position shall select a simulated maximum level subclutter visibility test return signal in accordance with SM-A-920699.

3.6.8.9.1.4 MDS/SCV. The switch position shall select a simulated MDS test target signal combined with a simulated maximum SCV return signal in accordance with SM-A-920699.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the current version before use.

3.6.8.9.1.5 Blades. The switch position shall select a modulated doppler signal that simulates rotor blade interference in accordance with SM-A-920699.

3.6.8.9.1.6 INTRF. The switch position selects a simulated interference signal in accordance with SM-A-920699.

3.6.8.9.1.7 ECM. The switch position shall select a simulated jamming signal in accordance with SM-A-920699.

3.6.8.9.2 MDS. The switches shall select fixed doppler frequencies for the MDS and Blades modes, and appropriate signal levels in accordance with SM-A-920699.

3.6.8.9 Advisory.

3.6.8.9.1 CM INOP. The amber indicator shall light when the RT BITE monitors a fault.

3.6.8.9.2 CM JAM. The amber indicator shall light when the RT outputs a CM JAM command.

3.7 Environmental Requirements. The equipment herein referred to as BTS, shall meet the following service conditions. Where a test is referenced, meeting the performance criteria shall be considered as compliance with the requirement.

3.7.1 Temperature - altitude. The BTS shall be operable without degradation in specified performance at altitudes up to 15,000 feet above sea level and shall withstand air transportation at altitudes up to 40,000 feet above sea level. The BTS shall be capable of continuous operation without degradation in specified performance at ambient temperatures as low as -17.7 ^{o}C and as high as +55 ^{o}C The equipment shall withstand exposure to ambient air temperature as low as -56 ^{o}C and as high as +71 ^{o}C. Testing shall be in conformance with the test requirements of 4.9.1.

3.7.2 Humidity. The BTS shall exhibit no physical damage such as corrosion, rust, blistering, swelling or deterioration of parts and materials, and shall meet the requirements of SM-A-951543 during the operating times specified in 4.9.2.

3.7.3 Mechanically Induced Stress.

3.7.3.1 Vibration. The BTS shall be capable of operation and shall sustain no physical damage after being subjected to the vibrations normally encountered by equipment transported by rail, sea, truck or semitrailer. Before and after testing as specified in 4.9.3 the BTS shall meet the performance specified in SM-A-951543.

3.7.3.2 Bench Handling. The BTS shall be capable of operation and shall sustain no physical damage after exposure to the shock intensities normally encountered

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

during servicing. Before and after testing as specified in 4.9.4 the BTS shall meet the performance specified in SM-A-951543.

3.7.4 Sand and Dust. The BTS shall withstand, in both operating and non-operating conditions, exposure to fine sand and dust particles with wind speeds of up to 300 ft/min. After testing as specified in 4.9.8, the equipment shall meet the specified performance requirements specified in SM-A-951543.

3.7.5 Salt Fog. The BTS shall withstand the effects of the salt fog exposure test of 4.9.6. Upon completion of test, the BTS when examined visually, shall show no evidence of degradation, such as flaking, pitting, blistering or lossening of finish or metal surfaces; or exfoliation of metal. There shall be no clogging or binding of controls or other moving parts after subjecting the BTS to the 48 hour salt fog exposure period or after subjection to the 48 hour drying period.

3.7.6 Fungus. After the fungus test of 4.9.7 the equipment shall be visually examined. The BTS shall show no more than six minute unrelated spots, each no greater than 0.015 square inch in area, of sparse microbial growth (see 6.3.2) as evidenced by growth colonization (see 6.3.1) which includes branching (see 6.3.5) and sporulation (see 6.3.3) on or within each cubic foot, or fraction thereof, of equipment assembly volume. Isolated instances of partial tubular germination (see 6.3.4) shall not be included in this evaluation.

3.7.7 Immersion. The transit case of the BTS shall withstand immersion in fresh water to a covering depth of three feet for not less than 2 hours and not greater than two and a quarter hours. Tests shall be as specified in 4.9.5.

3.8 Electromagnetic Interference (EMI). The BTS shall comply with the emission and susceptibility requirements of MIL-STD-461, Notice 4(EL) as follows when tested as specified in 4.10 with the exception of RS03.

CE04	CS-6	RE02	RS02
		RE02.1	RS03
		(1)	(2)

(1) The limits of MIL-STD-461 Notice 4 shall be relaxed 15 dB at the fundamental frequency and second harmonic of the AN/ALQ-156(V).

(2) The BTS shall not exhibit degraded performance, undesirable response or malfunction when immersed in electric fields of the following intensities using the modulation characteristics specified

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

3.8 Electromagnetic Interference, (EMI) Con't.

10kHz - 1.9MHz	1V/M	400Hz square wave, 50%
2MHz - 75.9MHz	5V/M	FM: ±8KHz deviation
76MHz - 399.9MHz	5V/M	AM: 50% 1000Hz tone
400MHz - 1999MHz	10V/M	Pulse: 0.1 us width, 400 PPs
2GHz - 12.4GHz	5V/M	Pulse: 0.1 us width, 400 pps

3.9 Burn-In. Each BTS on order shall be subjected to a 48 hour on time burn-in prior to any of the performance tests specified herein. The last 24 hours of the burn-in period shall be failure free (see 4.6).

3.10 Human Factors Engineering. Design changes affecting operation, maintainability and handling shall be maintained through compliance to the requirements of MIL-STD-1472.

3.11 System Safety Engineering.

3.11.1 Personnel Hazards. Personnel hazards shall be kept to a minimum through compliance of configuration changes and parts selection with Requirement 1 of MIL-STD-454. Compliance with these requirements will be verified through a visual inspection.

3.11.2 Edge Rounding Exposed. Exposed edges shall be rounded to a minimum radius of 0.04 inch (1mm) and exposed corners to a minimum of 0.05 inch (1.3mm).

3.11.3 Radioactive Materials. Radioactive materials shall not be used (e.g., luminour dials/markings, electron tubes, surge arrestors and lenses).

3.12 Interchangeability. Like units, assemblies, subassemblies, and replaceable parts shall be physically and functionally interchangeable without modification of such items or the system and shall conform to Requirement 7 of MIL-STD-454 (see 4.11). However, small variations in the A5 RF assembly insertion losses must be compensated on a test set assembly level. Individual items shall not be selected for fit or performance, however, matched pairs or sets when permitted, may be interchangeable as such. Reliance shall not be placed on any unspecified dimension, rating or characteristic.

3.13 Workmanship. The equipment shall be manufactured and assembled in accordance with Requirement 9 of MIL-STD-454 and the applicable portions of the following paragraphs:

a. In MIL-P-11268

General requirements for plastic material and plastic parts
Wiring and cable, including:
- Slack
- Clearance
- Protection
- Splicing

Process for soldering
Cleaning
Riveting
General requirements for securing of parts

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

a. In MIL-P-11268 (Cont.)

Connections, general
Grounding
Wire and cable shielding
Flux and cleaning agent for soldering
Cleaning after welding
Process for welding
Self-tapping screws
Mechanical operations of controls

b. In this specification.

3.3.1 Finish
3.3.2 Marking

4. Quality Assurance Provisions.

4.1 Responsibility for Inspection. Unless otherwise specified in the contract or purchase order, the contractor is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or purchase order, the contractor may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in this specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 Responsibility for Compliance. All items must meet all requirements of sections 3 and 5. The inspection setforth in this specification shall become a part of the contractor's overall inspection system or quality program. The absence of any inspection requirements in the specification shall not relieve the contractor of the responsibility of assuring that all products or supplies submitted to the Government for acceptance comply with all requirements of the contract. Sampling in quality conformance does not authorize submission of known defective material, either indicated or actual, nor does it commit the Government to acceptance of defective material.

4.3 First Article. Unless otherwise specified in the contract or purchase order (see 6.2), the first article inspection shall be performed by the contractor

4.3.1 First Article Units. When specified in the contract, the contractor shall furnish four (4) first article units of the complete TS-3609/ALQ-156(V).

4.3.2 First Article Inspection The first article inspection shall consist of the inspections specified in TABLE I and shall be performed in the order specified herein.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the current version before use.

4.3.3 First Article Data. The first article test plan and test report(s) shall be as required in the contract or purchase order.

4.4 Inspection Covered by Subsidiary Documents. The following shall be inspected under the applicable subsidiary documents as part of the inspection required by this specification and the inspection requirement specified in the contract or purchase order:

ITEM	WHERE REQUIRED
Parts, materials and processes - general	3.3
Finish	3.3.1
Marking	3.3.2
Printed wiring assemblies	3.4
Workmanship	3.13

4.5 Quality Conformance Inspection of Equipment. Each unit on contract shall be subjected to burn-in of 4.6. Prior to submission to quality conformance inspection, the contractor shall perform the inspection specified in 4.4 and 4.5. This does not relieve the contractor of his responsibility for performing any additional inspection which is necessary to control the quality of the product and to assure compliance with all specification requirements.

4.5.1 Group A Inspection. Each BTS on contract or purchase order shall be inspected for conformance to the inspections specified in TABLE V. Discrete lots shall be formed from the test sets that pass this inspection. Factors of lot composition not defined herein, or in the contract or purchase order, shall be in accordance with MIL-STD-105. Each lot shall be subject to sampling inspection utilizing the procedures of MIL-STD-105, using general inspection levels indicated in Table V.

4.5.1.1 Order of Inspection within Group A. Group A inspection shall be performed in an order satisfactory to the Government.

4.5.2 Group B Inspection. Group B inspection shall normally be performed on inspection lots that have passed Group A inspection and on samples selected from units that have been subjected to and met the Group A inspection, except inspection for the interchangeability requirement. Interchangeability test samples may be separate units whose modules and replaceable parts were randomly selected and assembled prior to Group A testing. This inspection shall conform to TABLE III.

4.5.2.1 Sampling for Group B Inspection. The Group B inspection level shall be S-4 of MIL-STD-105.

4.5.2.2 Order of Inspection within Group B. Group B inspection shall be performed in an order satisfactory to the Government.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

4.5.3 Group C Inspection. Group C inspection shall be performed on units that have passed Group A and Group B inspection. The inspection shall consist of the inspections specified in TABLE VII. Samples shall be selected in accordance with 4.5.3.1.

4.5.3.1 Sampling of Group C Inspection. Four samples of the equipment shall be selected at random from every 50 sets or fraction thereof produced. One sample shall be used for each sub-group inspection in Table VII. First article samples shall constitute the Group C requirement for the first 20 units produced.

4.5.3.2 Order of Inspection within Group C. Group C inspection shall be performed in the order specified in TABLE IV.

4.5.3.3 Group C Failures. Action required relative to Group C failures shall be as specified in the contract or purchase order.

4.5.4 Reinspection Of Conforming Group C Samples Units. Unless otherwise specified, sample units which have been subjected to and passed Group C inspection may be accepted on the contract provided all damage is repaired and the sample units are resubjected to and pass Group B and Group A inspection, in that order.

4.5.5 Noncompliance. If a sample fails to pass group C or D inspection, the manufacturer shall notify the qualifying activity and the cognizant inspection activity of such failure and take corrective action on the materials or processes, or both, as warranted, and on all units of product which can be corrected and which were manufactured with essentially the same materials and processes, and which are considered subject to the same failure. Acceptance and shipment of the product shall be discontinued until corrective action, acceptable to the qualifying activity has been taken. After the corrective action has been taken, group C or D inspection shall be repeated on additional sample units (all tests and examinations, or the test which the original sample failed, at the option of the qualifying activity). Groups A and B inspections may be reinstituted; however, final acceptance and shipment shall be withheld until the group C or D inspection has shown that the corrective action was successful. In the event of failure after reinspection, information concerning the failure shall be furnished to the cognizant inspection activity and the qualifying activity.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

TABLE IV. First Article Inspection

INSPECTIONS	REQ PARA	TEST PARA	UNIT 1	UNIT 2	UNIT 3	UNIT 4
1. Inspection covered by subsidiary documents	3.3 3.4	4.4	Inspections to be performed on all units.			
2. Burn-In	3.9	4.6				
3. Group A Inspection	See Table V		Inspections to be performed on all units			
4. Group B Inspection	See Table VI		Inspections to be performed on all units			
5. Group C Inspection						
EMI	3.8	4.10		1		
Environmental						
Temp/Altitude	3.7.1	4.9.1				2
Humidity	3.7.2	4.9.2	2			
Vibration	3.7.3.1	4.9.3	1			
Bench Handling	3.7.3.2	4.9.4			1	
Sand/Dust	3.7.4	4.9.8				3
Salt/Fog	3.7.5	4.9.6		2		
Fungus	3.7.6	4.9.7			2	
Immersion	3.7.7	4.9.5				1

NOTES: a. The inspections 1 through 4, in the order shown, shall be performed on all first article units before subjecting these units to any other inspection requirements specified in the table.

b. The numbers in the unit columns in the table covered by inspection 4 specify the order of inspections for the indicated unit.

c. The equipment shall be thoroughly washed, cleaned, dried and refurbished after the fungus and salt-fog tests before proceeding with subsequent inspection.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

TABLE V. Group A Inspection

INSPECTIONS	REQ PARA	TEST PARA
Visual & Mechanical	3.2, 3.3 3.4, 3.5 3.10, 3.11 3.13	4.4, 4.7
Electrical		
Input Power	3.6.2	4.8.1
Power Supplies	3.6.3	4.8.1
RT Inputs	3.6.4	4.8.1
RT Outputs	3.6.5	4.8.1
Control Inputs	3.6.6	4.8.1
Control Outputs	3.6.7	4.8.1
Controls/Indicators	3.6.8	4.8.1

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

TABLE VI. Group B Inspection

INSPECTIONS	REQ PARA	TEST PARA
Interchangeability	3.12	4.11

TABLE VII. Group C Inspection

INSPECTION	REQ. PARA.	INSP. PARA.
Subgroup I		
EMI	3.8	4.10
Salt Fog 1/ and 2/	3.7.5	4.9.6
Immersion	3.7.7	4.9.5
Subgroup II		
Bench Handling	3.7.3.2	4.9.4
Vibration	3.7.3.1	4.9.3
Fungus 1/ and 2/	3.7.6	4.9.7
Subgroup III		
Temp/Altitude	3.7.1	4.9.1
Sand/Dust	3.7.4	4.9.8
Humidity	3.7.2	4.9.2

1/ The equipment shall be thoroughly washed, cleaned, dried and refurbished after this inspection before proceeding with subsequent inspection.

2/ Subgroup I inspection (Salt Fog) and Subgroup II inspection (Fungus) shall be conducted on first article units only.

4.7 Visual and Mechanical Inspection. The equipment shall be visually and mechanically inspected to insure conformance to the following requirements:

3.2 The drawings listed on DLSM-B-920844.
3.3 Specified parts, materials and processes.
3.3.2 Marking, marking visibility and serial numbers.
3.10 Safety requirements, if required on contract.
3.11 Human engineering requirements, if required on contract.
3.13 Workmanship requirements.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

4.8 Performance Tests. Unless otherwise specified, the electrical tests shall be conducted under the following conditions:

a. Temperature and humidity.....room ambient
b. Input voltage.....114 ± 4 volts AC, 400 ± 20 Hz, 30
c. Warm-up time.....5 minutes

4.8.1 Performance. The BTS shall meet the requirements of 3.6 when tested in accordance with subparagraphs of SM-A-951543 as follows:

REQMT	PARA. NO.	TEST PROCEDURE PARA(S) SM-A-951543
Input Power	3.6.2	
Power Supplies	3.6.3	4.2.1
RT Inputs	3.6.4	4.3.11, 4.3.12
RT Outputs	3.6.5	4.4.3, 4.4.4, 4.4.5
Control Inputs	3.6.6	4.3.0
Control Outputs	3.6.7	4.2.6
Control/Indicators	3.6.8	4.2.0 thru 4.4.9

4.9 Environmental Tests. All environmental test methods, conditions and procedures given below are contained in MIL-STD-810. The equipment performance measurements shall be made under standard conditions as defined in MIL-STD-810. Successful completion of any particular test shall be considered evidence of meeting the corresponding service condition.

4.9.1 Temperature/Altitude. The BTS shall be tested in accordance with Method 504.1, Procedure I of MIL-STD-810. A non-operating test shall be performed for 1 hour at 40,000 feet. The BTS shall meet the requirements of 3.7.1 when tested at Steps 1, 2 and 4.

Equipment operating altitude	15,000 feet
Equipment non-operating altitude	40,000 feet

4.9.2 Humidity. The BTS shall be tested in accordance with Method 507.1, Procedure II of MIL-STD-810. The BTS shall be operated during the last 5 hours of the last cycle of Step 6, and shall meet the requirements of 3.7.2 when tested at Steps 4, 6 (last cycle only) and 8.

4.9.3 Vibration. The BTS as prepared for transit, shall be tested in accordance with Method 514.2, Procedure V of MIL-STD-810 and shall meet the requirements of 3.7.3.1.

Equipment category	g
Applicable table	514.2 - VII
Applicable figure	514.2 - 7
Test curve	AW

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

Make measurements before and after only. The frequency of applied vibration shall be swept logarithmically over the specified range.

4.9.4 Bench Handling. The BTS shall be tested in accordance with Method 516.2, Procedure V of MIL-STD-810, and shall meet the requirements of 3.7.3.2.

4.9.5 Immersion. The equipment in its transit case shall be tested in accordance with Method 512., Procedure I. If the equipment is in a transit case, it shall be removed and a mass of approximately the same size and weight shall be placed inside the case. The transit case with the dummy load shall then be tested in accordance with the above test procedure.

4.9.6 Salt Fog. The equipment shall be tested according to Method 509.1, Procedure I. No electronic operation shall be performed.

4.9.7 Fungus. The equipment shall be tested according to Method 508.1, Procedure. No electronic operations shall be performed.

4.9.8 Dust. The equipment shall be tested according to Method 510.1, Procedure I. The equipment shall be re-oriented in the test chamber every 1-1/2 hours during Step 1, so that all sides are exposed directly to the dust-laden air. The equipment shall not be operated during Steps 1 through 4. Step 3 of test procedure shall immediately follow temperature stabilization in Step 2. The dust velocity in Steps 1, 2 and 3 shall be 300 $\pm$ 200 feet per minute.

4.10 Electromagnetic Interference(EMI). The BTS shall be tested in accordance with the test set-ups and measurement techniques of MIL-STD-462, as implemented by a contractor prepared, Government approved EMI test plan, and shall meet the requirements of 3.8.

4.11 Interchangeability. The BTS shall be inspected to insure the physical and functional interchangeability requirements of 3.12.

4.11.1 Electrical Interchangeability. All like modules and replaceable parts shall be tested for functional interchangeability by assembly of randomly selected parts. The assembly shall be tested to and shall meet Group A acceptance requirements. Electrical retuning or realignment of modules during this production assembly may be expected and is permissible. Random selection for this assembly shall be supervised by the Government.

4.11.2 Machanical Interchangeability. The dimensions listed below shall be gaged or measured to determine conformance to the physical interchangeability requirements of 3.12. When a listed dimension is not within specified or design limits, it shall be considered a major defect.

a. External and internal dimension of case, cover and insertable assemblies, when such dimensions affect mating of parts.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

b. Dimensions of cavities, when such dimensions affect insertion of items.

c. Location of hinges and fasteners on separable parts or assemblies which must mate, such as case, covers and mountings.

d. Location of connectors, locking pins, fasteners, slides and mountings which receive mating parts, plug-in assemblies and major units; and location of mating parts on the plug-in assembly or major unit.

e. Size and form of special threads.

4.12 Packaging Inspection. Packaging inspection requirements specified herein are classified as follows

a. First Article Inspection of Packaging.

b. Quality Conformance Inspection of Packaging.

4.12.1 First Article Inpsection of Packaging. Unless otherwise specified in the contract, First Article Inspection of Packaging shall be in accordance with the Unit Pack Design Validation Requirements of MIL-P-116.

4.12.2 Quality Conformance Inspection of Packaging.

4.12.2.1 Materials Inspection. All materials to be used in packaging shall be inspected in accordance with the applicable material specification.

4.12.2.2 Preservation Inspection. Inspection of preservation and interior markings shall be in accordance with group A and B Quality Conformance Inspection Requirements of MIL-STD-116. Lot formation and sampling procedures shall be as specified therein.

4.12.2.3 Packing Inspection. Inspection of packing and the marking for shipment and storage shall consist of the examinations specified in Table VIII, "PACKAGING INSPECTION PROVISIONS." Lot formation shall consist of all packs made of the same materials during an identifiable period and submitted at one time for acceptance. Sampling procedures shall be in accordance with MIL-STD-105, using a single sampling plan.

Source: https://assist.dla.mil -- Downloaded: 202640-26T04:00Z
Check the source to verify that this is the current version before use.

TABLE VIII. PACKING INSPECTION PROVISIONS

NO.	CHARACTERISTICS	METHOD OF INSPECTION
101	Intermediate container not as specified	Visual
102	Improper closure of intermediate container	Visual
103	Shipping containers not in accordance with specification	Visual
104	Excessive cube	Visual
105	Improper blocking and bracing	Visual
106	Closure not in accordance with specification	Visual
107	Weight and size exceed container limitations	Weight and Measure
108	Strapping not in accordance with specification, incorrectly applied, omitted	Visual
109	Marking omitted, incorrect, or illegible	Visual

5. PACKAGING.

5.1 Preservation. Preservation shall be as specified in MIL-STD-2073-2, Tables I through VII, codes as follows: JR-1-00-00-NS-X-EI.

5.2 Packing and Marking. Packing and marking shall be in accordance with MIL-E-5585.

5.2.1 Level A. A multiple quantity of Test Set, TS-3609( )/ALQ-156(V), unit packed as specified in 5.1, shall be packed within a close-fitting box conforming to PPP-B-601, overseas type; PPP-B-621, style 4, class 2; or PPP-B-585, style 2 or 3, class 3. When the gross weight exceeds 200 pounds, or the container length and width is 48 X 24 inches or more and the weight exceeds 100 pounds, 3 X 4 skids, laid flat, shall be applied in accordance with the requirements of the container specification, or if not specified in the specification, in a manner which will adequately support the item and facilitate the use of material handling equipment. Closure and strapping shall be in accordance with the applicable container specification or appendix thereto except that metal strapping shall conform to QQ-S-781, type 1, finish A. When a single unit is shipped to a single destination, the unit shall be individually packed as specified above.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

5.2.1.1 Unitization. Palletization shall be required when: containers specified in 5.23.1 do not require skids; quantities per destination exceed either a total of 250 pounds (excluding the pallet) or volume of 20 cubic feet; and the container size permits use of one of the pallet patterns of MIL-STD-147. A quantity of containers, packed as specified in 5.2.1 except that container strapping may be omitted, shall be placed on a pallet, load type I, conforming to MIL-STD-147. The pallet shall conform to NN-P-71, type IV, group I or II woods. The load shall be "bonded" to the pallet by strapping conforming to QQ-S-781, type I, finish A, or shrink film conforming to L-P-378, type IV. Stretch wrap IAW MIL-STD-147 is authorized for shipments within continental U.S. and for containerized shipments.

5.2.2 Level B. A multiple quantity of Test Set,TS-3609( )/ALQ-156(V), unit packed as specified in 5.1, shall be packed within a close-fitting box conforming to PPP-B-640, class 2, style E or PPP-B-636, type CF, class weather-resistant. The gross weight of boxes conforming to PPP-B-640 shall not exceed 250 pounds. Closure shall be in accordance with the appendix of the applicable box specification. Reinforcing shall be by pressure-sensitive filament tape banding or non-metallic strapping conforming to PPP-T-97 and PPP-S-760, respectively; selection of the material and application shall be in accordance with the appendix of the applicable box specification. When the gross weight exceeds 200 pounds, or the container length and width is 48 X 24 inches or more and the weight exceeds 100 pounds, containers will be pallet-mounted on pallets conforming to NN-P-71, group I or II woods. The load shall be "bonded" to the pallet by strapping conforming to QQ-S-781, type I, finish A or shrink film conforming to L-P-378, type IV. When a single unit is shipped to a single destination, no packing is required, the unit container shall serve as the shipping container. Reinforcing shall be as specified above.

5.2.2.1 Unitization. Palletization shall be required when quantities per destination exceed either a total of 250 pounds (excluding the pallet) or a volume of 20 cubic feet, and the container size permits use of one of the pallet patterns of MIL-STD-147. A quantity of Test Set, TS--3609( )/ALQ-156(V) unit packed as specified in 5.1, shall be placed on a pallet, load type I, conforming to MIL-STD-147. The pallet shall conform to NN-P-71, type IV, group I or II woods. The load shall be "bonded" to the pallet by strapping conforming to QQ-S-781, type I, finish A, or shrink film conforming to L-P-378, type IV. Stretch wrap IAW MIL-STD-147 is authorized for shipments within the continental U.S. and for containerized shipments.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the currentversion before use.

5.3 Marking. In additional to any special marking required by the contract or order, interior packs and exterior shipping containers shall be marked in accordance with MIL-STD-129.

6. Notes.

6.1 Intended Use. The TS-3609( )/ALQ-156(V) Bench Test Set is used to test the operation of the AN/ALQ-156(V) Countermeasures Set at the direct support level of maintenance (AVIM).

6.2 Ordering Data.

6.2.1 Acquisition Requirements. Acquisition documents should specify the following.

a. Title, number, and date of this specification.

b. Issue of DODISS to be cited in the solicitation.

c. MIL-STD-461A, Notice 4 shall be used for EMI requirements in 3.__ and tests in 4.__.

d. MIL-STD-810C shall be used for environmental requirements and tests in 3.__, 3.__, 4.__ and 4.__.

6.3 Definitions.

6.3.1 Temperature Stabilization. Temperature stabilization will have been attained when the temperature of the part of the test item considered to have the longest thermal lag does not change more than 2.0 ^{o}C(3.6 ^{o}F) per hour.

6.3.2 Physical Damage. Physical damage is defined as corrosion, rust, blistering, swelling or other deterioration of parts and materials.

6.3.3 Fungus.

6.3.3.1 Growth Colonization. Growth colonization is a mass of individual plants, generally of one species living together, or a group of hyphae which is formed from one spore or cell and may be one individual plant. Colonization which completely covers the surface of the nutrient material constitutes abundant growth.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the current version before use.

6.3.3.2 Microbial Growth. Microbial growth is the growth of very minute organisms when present in large numbers may provide a colony visible to the naked eye.

6.3.3.3 Sporulation. Sporulation is the formation of minute unicellular reproductive or dormat bodies, called spores.

6.3.3.4 Tublar Germination. Tublar germination is partial growth by the production of hyphae, which are tubular shaped fungal filaments. Tublular germination constitutes restricted individual spore growth not preceeding to colonization.

6.3.5 Branching. Branching is a connected arrangement of filaments (hyhae) formed by shoots or secondary items growing from the main stem or filament (hyhae).

6.4 Details to be Specified by the Procuring Activity.

6.4.1 Acceptability Quality Levels (AQL). The following AQL's are recommended for use by the Procuring Activity in connection with the inspections outlined below.

6.4.1.1 Group A Inspection

Inspection		Major	Minor
Visual and Mechanical	(See Table V)	1%	4%
Electrical	(See Table V)	1% for the group	*

* All electrical defects are considered major.

6.4.1.2 Group B Inspection

Inspection	AQL
Interchageability (See Table VII)	6.5 dhu

6.4.1.3 Packing Inspection

Inspection	AQL
Packing and Marking (See Table VIII)	4%

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

6.6 Data Requirements. Deliverable data required by this specification is cited in 4.3.3 entitled First Article Data.

6.7 First Article. First articles are required for inspection and approval (see 3.1, 4.3 and 6.2).

6.8 Subject Term (Keyword) Listing

Countermeasure Set, Test Set
Countermeasure Set TS-3609( )/ALQ-156(V)
Control indicator C-10131( )/ALQ-156(V)
Receiver-transmitter RT-1220( )/ALQ-156(V)
FMO Phase Code
XMTR Disabling

Custodian:
Army-CR

Preparing Activity:
Army-CR
Project 6625-A907

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

(See Instructions – Reverse Side)

1 DOCUMENT NUMBER	2 DOCUMENT TITLE
MIL-T-49305-(CR)	Test Set, Countermeasure Set TS-3609() ALQ-156(V)

3a NAME OF SUBMITTING ORGANIZATION	4 TYPE OF ORGANIZATION *(Mark one)*
	☐ VENDOR
	☐ USER
b ADDRESS *(Street City State ZIP Code)*	☐ MANUFACTURER
	☐ OTHER *(Specify)* _____

5 PROBLEM AREAS

a Paragraph Number and Wording

b Recommended Wording

c Reason Rationale for Recommendation

6 REMARKS

7a NAME OF SUBMITTER *(Last First MI)* – Optional	b WORK TELEPHONE NUMBER *(Include Area Code)* – Optional
c MAILING ADDRESS *(Street City State ZIP Code)* – Optional	8 DATE OF SUBMISSION *(YYMMDD)*

DD FORM 82 MAR 1426 PREVIOUS EDITION IS OBSOLETE HISA-FM 149-85

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:00Z
Check the source to verify that this is the current version before use.

INSTRUCTIONS In a continuing effort to make our standardization documents better, the DoD provides this form for use in submitting comments and suggestions for improvements All users of military standardization documents are invited to provide suggestions. This form may be detached, folded along the lines indicated, taped along the loose edge *(DO NOT STAPLE)*, and mailed In block 5, be as specific as possible about particular problem areas such as wording which required interpretation, was too rigid, restrictive, loose, ambiguous, or was incompatible, and give proposed wording changes which would alleviate the problems Enter in block 6 any remarks not related to a specific paragraph of the document. If block 7 is filled out, an acknowledgement will be mailed to you within 30 days to let you know that your comments were received and are being considered

NOTE This form may not be used to request copies of documents, nor to request waivers, deviations, or clarification of specification requirements on current contracts Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements

(Fold along this line)

(Fold along this line)

Cdr, CECOM
ATTN AMSEL-ED-TO
Fort Monmouth, NJ 07703-9990

NO POSTAGE NECESSARY IF MAILED IN THE UNITED STATES

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

BUSINESS REPLY MAIL
FIRST CLASS PERMIT NO 4966 Alexandria, VA

POSTAGE WILL BE PAID BY

Commander
U.S. Army Communications-Electronics Command
and Fort Monmouth
ATTN: AMSEL-ED-TO
Fort Monmouth, NJ 07703-9990

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:00Z
Check the source to verify that this is the current version before use.