MILITARY SPECIFICATION

GENERATOR, HAND CRANK

1. SCOPE

1.1 This specification covers special requirements not included on the drawings, and provides the quality assurance provisions for the fabrication of parts, assembling, and the preparation for delivery for one type of Hand Crank Generator used on Test Set for Atomic Weapons and designated as Generator, Hand Crank.

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposals, form a part of this specification to the extent specified herein:

SPECIFICATIONS

MILITARY

MIL-P-116 - Preservation, Methods of
MIL-S-60902(MU) - Soldering Electrical Connections for Nuclear Weapons Systems, Procedure for

STANDARDS

MILITARY

MIL-STD-105 - Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-1168 - Lot Numbering of Ammunition
MIL-STD-1169(MU) - Packaging, Packing and Marking for Shipment of Inert Ammunition Components

DRAWINGS

ORDNANCE CORPS

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

8808362 - Packing and Marking for Storage and Shipments
8834301 - Generator, Hand Crank
8883534 - Bag, Packing for Repair Part
EL-8834301 - Equipment List

(Copies of specifications, standards, drawings, and publications required by contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer).

3. REQUIREMENTS

3.1 Materials. The contractor shall furnish objective evidence (see 6.2) that the material complies with the specifications listed on the applicable drawing.

3.2 Assembly. The Generator shall comply with all requirements specified on Drawing (dwg.) 8834301, with all requirements specified herein, and with the requirements of applicable specifications to the extent specified on the drawing and herein.

3.3 First article testing. Requirements for the submission of first article samples by the contractor shall be as specified in the contract (see 4.2).

3.4 Continuity and resistance. At ambient temperature, the generator shall have a resistance of 3000 plus or minus (±) 400 ohms. The resistance at high temperature shall be 3600 ± 400 ohms. The resistance at low temperature shall be 2130 ± 400 ohms. Testing shall be as specified in 4.4.1.

3.5 Dielectric strength. The generator shall withstand a potential of 650 ± 65 volts (v) root mean square (RMS) at 60 ± 5 cycles per second (CPS) between its electrically isolated circuits and between all circuits and chassis. Testing shall be as specified in 4.4.2.

3.6 Insulation resistance. The insulation resistance between all electrically isolated circuits and between ungrounded circuits and the chassis shall not be less than 30 megohms when tested as specified in 4.4.3.

3.7 Torque.

3.7.1 Ambient temperature. The generator, operating into a 12K ± 0.6 K ohm load and cranked at a minimum (min.) 3.5 revolutions per second (RPS), shall require torque no greater than 55 inch ounces at ambient temperature to deliver rated output as specified in 3.8. Testing shall be as specified in 4.4.4.1.

3.7.2 High temperature. The generator, operating into a 12K ± 0.6K ohm load and cranked at a min. 3.5 RPS, shall require torque no greater than 45 inch ounces at +160 ± 5 degrees fahrenheit (°F.) to deliver rated output as specified in 3.8. Testing shall be as specified in 4.4.4.2.

3.7.3 Low temperature. The generator, operating into a 12K ± 0.6 K ohm load and cranked at a min. 3.5 RPS, shall require torque no greater than 250 inch ounces at -65 ± 5°F. to deliver rated output as specified in 3.8. Testing shall be as specified in 4.4.4.3.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

3.8 Operation.

3.8.1 Watts and Voltage. When cranked at a maximum (max.) 3.5 RPS, the generator shall deliver a min. 1.17 watts with voltage of 135 ± 13.5 Volts Alternating Current (v.a.c.) at ambient temperature, 130 ± 13 v.a.c. at high temperature , and 143 ± 14.3 v.a.c. at low temperature. Testing shall be as specified in 4.4.5.1.

3.8.2 Regulation. The output current shall be measured under the the following conditions of load: 20K ± 1K ohms, 12.K ± 0.6K ohms, 50.0 ± 2.5 ohms. For acceptance testing, do not test with less than a 12K ohm load as this tends to demagnetize the generator rotor. Crank speed for testing shall be 4.5 ± .2 RPS. Generated current shall not exceed 20 m.a at 12K ohm load. Current produced at the 12K ohm load shall not exceed that produced at the 20K ohm load by more than 10 m.a. Current produced at the 50 ohm and the 1 ohm load shall not exceed the current produced at the 12K ohm load by more than 52 m.a. Testing shall be as specified in 4.4.5.2.

3.9 Shock. The generator shall withstand half sine wave shock pulses of 20 ± 2 g peak intensity, each shock having an 11 ± 2 millisecond duration. The generator shall withstand these shocks in each direction of each of 3 mutually perpendicular axes, one axis being in line with the crank shaft. The shocks shall not cause damage that would impair the operation of the generator. Testing shall be as specified in 4.4.6. Upon completion of the test shocks, the generator shall comply with 3.4, 3.5, 3.6, 3.7.1 and 3.8.

3.10 Vibration. The generator shall withstand vibrations as specified in Table I without evidence of damage that would impair its intended use. The generator shall withstand these vibrations in each of the 3 axes specified in 3.9. Testing shall be as specified in 4.4.7. Upon completion of the vibration test cycles, the generator shall comply with 3.4, 3.5, 3.6, 3.7.1 and 3.8.

Table I
Vibration schedule

Frequency -CPS-	Sweep Time -Minutes-	Double Amplitude -Inches-	Number of Sweeps
5-55-5	1 ± .2	.06 ± .006	15

3.11 High temperature. The generator shall withstand exposure to a 160 ± 5°F. and ambient humidity without evidence of damage that would impair its operation. While at this temperature, the generator shall comply with 3.4, 3.5, 3.6, 3.7.2 and 3.8. Testing shall be as specified in 4.4.8.

3.12 Low temperature. The generator shall withstand exposure to a -65 + 5°F. and ambient humidity without evidence of damage that would impair its operation. While at this temperature, the generator shall comply with 3.4, 3.5, 3.6, 3.7.3 and 3.8.1. Testing shall be as specified in 4.4.9.

3.13 Soldering. Soldering shall be in accordance with MIL-S-60902 (MU).

3.14 Workmanship.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

3.14.1 Plastic and metal characteristics. All components shall be free from cracks, splits, cold flow, shrinkage, cold shuts, inclusions, porosity, or any similar characteristics.

3.14.2 Threads. Threads shall be full and undamaged for the entire minimum length or depth as required on the applicable drawing.

3.14.3 Burrs. Parts shall be free from burrs.

3.14.4 Foreign matter. Parts shall be free from chips, dirt, grease, rust, corrosion, or any embedded foreign material.

3.14.5 Cleaning. The cleaning method shall not be injurious to any of the parts, nor shall the parts be contaminated by the cleaning agents.

3.14.6 Electrical. Cable assemblies and wires shall be dressed in such a manner as to prevent pinching or chafing of the wire insulation. Ends of wires shall be free from burrs, sharp edges, or points. All parts shall be free from flux, chips, dirt, grease, rust or foreign material.

4. QUALITY ASSURANCE PROVISIONS.

4.1 Responsibility for inspection. Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.2 First article inspection.

4.2.1 Quantity to be submitted. When the contractor requires first article inspection, the contractor shall submit 4 complete assemblies (see dwg 8834301) for first article testing to the testing facility designated in the invitation for bids or request for proposal.

4.2.2 Inspection and testing to be performed. The first article inspection sample shall be subjected to the inspections and tests specified in table II. Tests need not be conducted in order specified in table II.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

Table II

First article inspections and tests

Examination or test	Contractor's inspection before submission	Destruct.	Non Destruct.
1. Classification of characteristics (see 4.3.2.1)	X		X
2. Continuity and Resistance (see 3.4)	X		X
3. Dielectric strength (see 3.5)	X		X
4. Insulation resistance (see 3.6)	X		X
5. Torque (see 3.7)	X		X
6. Operation (see 3.8)		X	
7. Shock (see 3.9)	X		X
8. Vibration (see 3.10)	X		X
9. High temperature (see 3.11)	X		X
10. Low temperature (see 3.12)	X		X

4.2.3 Inspection equipment. The inspection and testing specified in 4.2.2 shall be accomplished by using the gages and test equipment specified in 4.3.4.1.

4.2.4 Rejection. If any item fails to comply with any of the applicable requirements, the first article sample shall be rejected.

4.3 Product acceptance inspection.

4.3.1 Lot formation. A lot shall consist of parts and assemblies produced by one manufacturer in one unchanged process, in accordance with the same drawing, same drawing revision, same specification and same specification revision. Drawing, specification and process changes not affecting safety, performance, storage, or interchangeability, as determined by the Government, shall not necessitate changing the lot interfix number. The criteria and procedures for the assignment of lot numbers shall be in accordance with MIL-STD-1168.

4.3.1.1 Inspection lot. An inspection lot shall be the quantity of parts, subassemblies, or assemblies from the same lot, which are submitted to inspection for Government acceptance.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

4.3.2 Product inspection examination. Critical characteristics shall require 100 percent inspection of all items in the inspection lot. A sample shall be selected at random from each inspection lot in accordance with the applicable major or minor characteristic table and inspected for all characteristics in the applicable classification. Any characteristic in the sample found to be defective shall reject the inspection lot. Sequence for the inspection of characteristics in each classification need not be followed as long as all characteristic inspections are performed.

Major characteristic table III

Lot size	Sample size
1- 155	100% inspection
156- 200	155
201- 250	175
251- 300	190
301- 350	200
351- 400	210
401- 450	220
451- 500	225
501- 550	230
551- 600	235
601- 650	240
651- 700	243
701- 750	247
751- 800	250
801- 900	254
901-1000	258
1001-1100	261
1101-1200	264
1201-1300	266
1301-1400	268
1401-1500	270
1501-1600	272

Minor characteristic table IV

Lot size	Sample size
1- 25	100% inspection
26- 30	25
31- 35	26
36- 40	27
41- 45	28
46- 50	29
51- 55	30
56- 60	31
61- 65	32
66- 70	33
71- 75	34
76- 85	35
86- 95	36
96- 110	37
111- 130	38
131- 156	39
157- 190	40
191- 240	41
241- 340	42
341- 520	43
521-1120	44
1121 and over	45

4.3.2.1 Classification of characteristics. Critical, major, and minor characteristics are defined in MIL-STD-105. Inspection shall be conducted as follows:

4.3.2.1.1 Generator, hand crank (see dwg 8834301).

Categories	Characteristics	Method of Inspection
Critical: None defined.		

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

Major:
101. Diameter over identification plate, max.....Gage
102. Length from terminal to mounting face, max.....Gage
103. Length from end of generator to mounting face, max.....Gage
104. Diameter left of mounting plate.....Gage
105. Length of flat on shaft, min.....Gage
106. Depth of flat on shaft, min.....Gage
107. Shaft diameter.....Gage
108. Diameter adjacent to shaft.....Gage
109. Location of 4 mounting holes.....Gage
110. Diameter of 4 mounting holes.....Gage
111. Length and width of mounting flange, max.....Gage
112. Thickness of mounting flange.....Gage
113. Length from mounting flange to shaft.....Gage
114. Length from left face of mounting flange to end of shaft.....Gage

Minor
201. Identification plate present and legible.....Visual
202. Workmanship (see 3.14).....Visual/Manual

4.3.2.1.2 Preparation for delivery (see 5.1)

Categories	Characteristics	Method of inspection
Critical: None defined.		
Major:		
101.	Packaging, packing and marking in accordance with MIL-STD-1169(MU)	Visual
Minor:		
201.	Workmanship (see 3.14)	Visual

4.3.2.1.3 Bag, Packing, for Repair Parts (see dwg. 8883534 covering dwg. part number 8883534-6 and 5.2).

Categories	Characteristics	Method of inspection
Critical: None defined.		
Major:		
101.	Material (see 3.1)	Visual
102.	Length before packing, min	*Measure
103.	Width before packing, min	*Measure
104.	Objective evidence (see 6.2 SQAP-Appendix I) available for heat seal test in accordance with MIL-P-116	Visual

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

105. Properly packed.....Visual
106. No tear, split, or crack in bag.....Visual

*Measure with suitable scale.

Minor:
201. Marking.....Visual
202. Workmanship (see 3.14).....Visual/Manual

4.3.2.1.4 Packing and Marking for Storage and Shipments (see dwg. 8808362 and 5.2).

Categories	Characteristics	Method of inspection

Critical: None defined.

Major:
101. Gross load weight, max.....*Measure
102. Contents tight in package.....Manual
103. Correctly packed.....Visual/Manual
104. Package material (see 3.1).....Visual

*Determine weight with a suitable scale.

Minor:
201. Marking.....Visual
202. Workmanship (see 3.14).....Visual/Manual

4.3.3 Testing. The contractor shall perform all the tests specified in this paragraph. Tests do not have to be performed in the order specified.

Test	Test Classification
a. Continuity and resistance	Major
b. Dielectric strength	Major
c. Insulation resistance	Major
d. Torque	Major
e. Operation	Major

None of these tests are destructive and samples so tested may be returned to the lot.

4.3.3.1 Continuity and resistance (see 3.4), Dielectric strength (see 3.5), Insulation resistance (see 3.6), Torque (see 3.7.1) and Operation (see 3.8). Each generator shall be subjected to these tests (see 4.4). If any generator fails to comply with the applicable requirement, it shall be classified defective and removed from the lot.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

4.3.4 Acceptance inspection equipment.

4.3.4.1 Critical and major characteristics and tests. Inspection and testing shall be performed with the acceptance inspection equipment, operating instructions, and calibration instructions specified on the Equipment List (EL-8834301). When either of the conditions listed below exist, the contractor shall design required equipment or specify suitable commercial equipment. The contractor shall obtain approval of such designs, operating instructions, and special calibration instructions as specified in 6.3 prior to use on the contract.

a. Any deviation from equipment or procedures specified on the EL is desired.
b. The code "CD" is listed in the "Part or Identifying Number" column on the EL.

4.3.4.2 Minor characteristics and tests. Acceptance inspection equipment for minor characteristics is not specified on EL's. The acceptance inspection equipment, operating instructions and calibration instructions used by the contractor for minor classification inspection shall be approved by the Government representative authorized by the procuring agency.

4.4 Test methods. The tolerances specified herein are absolute with no allowance for test equipment inaccuracy. The tolerances used by the manufacturer shall be equal to the absolute tolerances less the accuracy tolerances of the test equipment used.

4.4.1 Continuity and resistance (see 3.4). Measure continuity and resistance of the generator between terminals with a calibrated low resistance measuring instrument or by the voltammeter method with the current adjusted to 10 milliamperes (m.a.) max.

4.4.2 Dielectric strength (see 3.5). Connect a potential of 650 ± 65 v. RMS at 60 ± 5 CPS for a min. period of 15 seconds between one output lead and the chassis of the generator. Current shall be limited to 5 ma. so as to protect human life.

4.4.3 Insulation resistance (see 3.6). The insulation resistance shall be measured with a 500 ± 50 vdc megohm insulation tester -- the current limited to 5 ma, max. between one output and the generator chassis.

4.4.4 Torque (see 3.7).

4.4.4.1 Ambient temperature (see 3.7.1). With the generator operating into a 12K ± 0.6K ohm load at ambient temperature, measure the torque required to rotate the generator shaft at a min. 3.5 RPS with the generator case restrained.

4.4.4.2 High temperature (see 3.7.2). Conduct this test the same as in 4.4.4.1 except that the generator shall be heated to a stabilized 160 ± 5°F. temperature (see 6.4) or for a 4 hour period. The test shall be conducted with the generator at this temperature.

4.4.4.3 Low temperature (see 3.7.3). Conduct this test the same as in 4.4.4.1 except that the generator shall be cooled to a stabilized -65 ± 5°F. (see 6.4) or for a 4 hour period. The test shall be conducted with the generator at this temperature.

4.4.5 Operation (see 3.8).

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

4.4.5.1 Watts and Voltage (see 3.8.1). Using a load resistor of 12K ohm ± 0.6K, 2 watt, measure the output voltage and watts delivered by the generator with the hand crank rotating at a speed not exceeding 3.5 RPS.

4.4.5.2 Regulation. Measure the output current with a crank speed of 4.5 ± .2 RPS. for each load specified.

4.4.6 Shock (see 3.9). By means of its normal mounting holes and a fixture that simulates the actual mounting method, mount the generator in a suitable shock producing device and impose 3 half sine wave shock pulses in each direction of each of 3 mutually perpendicular axes, one axis being in line with the generator crank shaft. Each shock shall have a 20 ± 2 g peak intensity and an 11 ± 2 millisecond duration. Upon completion of all shocks, inspect the generator for damage and for compliance with 3.4, 3.5, 3.6, 3.7.1 and 3.8.

4.4.7 Vibration (see 3.10).

4.4.7.1 Shaker-Fixture-Component Resonance Test. Prior to performance of the Component Vibration Test, subject one component to vibration in each of its 3 major mutually perpendicular axes throughout the frequency range from 5-55 CPS unless this has already been done with an identical component and an identical fixture on the same machine to be used for the Component Vibration Test. Attach the component to test fixture by means of the attachment points used to mount the component in service in such a matter as to prevent additional stiffness or restraint to the component other than at the attachment points. Monitor the vibration response continuously during this test at one of the component-to-fixture points. Note: Resonant frequencies, band width and amplification of all resonances. Amplitude readings perpendicular to the direction of excitation shall be no greater than the max. level in the direction of excitation. Alter the component-fixture-shaker combination until these conditions are satisfied. Control frequency sweep manually to insure that all resonances observed are fully excited. Vary vibration amplitude with the frequency such that the max. amplitude at the attachment points does not exceed the following..

Frequency	Amplitude
5-55	.03 inch (peak to peak)

If any alterations are made to the machine, fixture or component, or if a different machine or fixture is used after the above test has been made, repeat this test, incorporating the new conditions, prior to component testing.

4.4.7.2 Component Test. Using the fixture developed for the Resonance Test (see 4.4.7.1), vibrate the generator in each of its 3 major mutually perpendicular axes (includes the axis parallel to the hand crank shaft) in accordance with the schedule in 3.10. The vibrations shall not cause damage that will impair the operation of the generator. Upon completion of the vibration runs, inspect the generator for compliance with 3.4, 3.5, 3.6, 3.7.1 and 3.8.

4.4.8 High temperature. Heat the generator in a temperature chamber at a temperature of 160 ± 5 F. at ambient humidity for a min, of 4 hours or

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

the temperature of the generator has stabilized (see 6.4). With the generator at this temperature, inspect it for compliance with 3.4, 3.5, 3.6, 3.7.2 and 3.8. Permit the generator to return to ambient temperature by natural cooling when testing is completed.

4.4.9 Low temperature. Conduct this test the same as in 4.4.8 . Except that temperature should be decreased to -65 ± 5 F. and torque requirement should be 3.7.3. Warming to ambient temperature after the test should not be accomplished forcibly.

5. PREPARATION FOR DELIVERY

5.1 Production items.

5.1.1 Preservation and packaging. Preservation and packaging shall be level A or C as specified (see 6.1).

5.1.1.1 Level A. The generator shall be preserved and packaged in accordance with instructions contained in MIL-STD-1169(MU).

5.1.1.2 Level C. The generator shall be preserved and packaged in accordance with instructions contained in MIL-STD-1169(MU).

5.1.2 Packing.

5.1.2.1 Levels A and C. The generator shall be packed in accordance with the applicable instructions contained in MIL-STD-1169(MU).

5.1.3 Marking. Marking shall be in accordance with MIL-STD-1169(MU).

5.2 Repair items only.

5.2.1 Preservation and packaging. Preservation and packaging shall be level A or C as specified (see 6.1).

5.2.1.1 Level A. The generator shall be packaged in accordance with dwgs 8883534 and 8808362 using the specified moisture barrier.

5.2.1.2 Level C. The generator shall be packaged in accordance with dwg 8808362 except that the moisture barrier may be omitted.

5.2.2 Packing.

5.2.2.1 Level A and C, The generator shall be packed in accordance with dwgs 8883534 and 8808362.

5.2.3 Marking. Marking shall be as specified in accordance with dwgs 8883534 and 8808362, as applicable.

6. NOTES

6.1 Ordering data. Procurement documents should specify the followings:

a. Title, number and date of this specification.
b. Selection of applicable level of packaging and packing required (see 5.1.1 and 5.2.1)

6.2 Objective evidence. Records of contractor quality control and inspections which can be verified.

6.3 Acceptance inspection equipment. The contractor shall obtain approval of equipment designs, operating instructions, and calibration instructions from the Commanding Officer, Picatinny Arsenal, Dover, New Jersey 07801, ATTN: SMUPA-NR4.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

6.4 Temperature Stabilization. The temperature is considered stabalized when the greatest peaks (both highest and lowest) continually observed over 5 minutes, min. do not exceed the nominal temperature plus the tolerance specified.

6.5 Supersession data. This specification includes the requirements of a Purchase Description PA-PD-1864 Generator, Hand Crank dated 18 April 1963.

Custodian:
Army - MU

Preparing activity:
Army - MU

Project No. 1190-A044

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 22-R255

INSTRUCTIONS: This sheet is to be filled out by personnel, either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments and suggestions submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or serve to amend contractual requirements.

SPECIFICATION

MIL-G-50229(MU) Generator, Hand Crank

ORGANIZATION

CITY AND STATE	CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

   A. GIVE PARAGRAPH NUMBER AND WORDING.

   B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

   ☐ YES ☐ NO *(If "yes", in what way?)*

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity)*

SUBMITTED BY *(Printed or typed name and activity - Optional)*	DATE

DD FORM 1 JAN 66 1426 REPLACES EDITION OF 1 OCT 64 WHICH MAY BE USED.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.

FOLD

DEPARTMENT OF THE ARMY

POSTAGE AND FEES PAID
DEPARTMENT OF THE ARMY

OFFICIAL BUSINESS

Commanding Officer
Picatinny Arsenal
ATTN: SMUPA-NR
Dover, New Jersey 07801

FOLD

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:17Z
Check the source to verify that this is the current version before use.