MIL-C-48814(PA)
9 June 1975
SUPERSEDING
See Section 6

MILITARY SPECIFICATION

CARTRIDGE ASSEMBLY,
for M74 WARHEAD SECTION

1. SCOPE

1.1 This specification covers requirements, quality assurance provisions, and the preparation for delivery criteria for one type of Cartridge Assembly which is used in the Nike Hercules warhead section.

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposals, form a part of this specification to the extent specified herein:

STANDARDS

MILITARY

MIL-STD-105	- Sampling Procedures and Tables for Inspection by Attributes.
MIL-STD-1168	- Lot Numbering of Ammunition.
MIL-STD-1169	- Packaging, Packing and Marking for Shipment of Inert Ammunition Components.
MIL-STD-1460	- Soldering of Electrical Connections and Printed Wiring Assemblies, Procedure For.

DRAWINGS

ORDNANCE CORPS

8846038	- Cartridge Assembly.
8846199	- Cartridge Support Assembly.
8846220	- Cartridge Shell Assembly.
EL-8855810	- Equipment List.

FSC 1135

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

(Copies of specifications, standards, drawings, and publications required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

3. REQUIREMENTS

3.1 Materials. The contractor shall furnish objective evidence (see 6.2) that the material complies with the specifications listed on the applicable drawing.

3.2 Assembly. The cartridge assembly shall comply with all requirements specified on the drawing (dwg) 8846038, with all requirements specified herein, and with the requirements of all applicable specifications to the extent specified on the drawing and herein.

3.3 First article testing. Requirements for the submission of first article samples by the contractor shall be as specified in the contract (see 4.2).

3.4 Continuity. The cartridge assembly shall exhibit point to point continuity in accordance with Table I when specified in 4.4.1.

Table I

From	To	From	To
J1-XW	J3-F	J6-l	J9-b
J1-EV	J3-O	J6-j	J9-T
J1-NP	J3-M	J6-P	J9-V
J1-D	J2-f	J7-e	J9-l
J1-a	J2-b	J7-f	J9-H
J1-S	J3-P	J7-d	J9-j
J1-GH	J3-E	J7-b	J9-A
J2-B	J3-K	J7-RC	Ground
J2-M	J6-a	J7-a	Relay-7
J2-U	Ground	J7-Z	J9-e
J3-G	J8-A	J7-h	J9-G
J3-A	J8-F	J7-G	J9-c
J3-M	Valve-1	J7-U	J9-C
J3-N	Ground	J7-V	Relay-1
J3-L	J9-N	J7-1	J9-j
J3-P	J9-d	J7-j	J9-E
J3-K	J7-a	J7-P	J9-W
J3-E	J9-B	J8-M	J9-F
J3-H	J6-a	J8-P	J9-0
J3-1	J9-M	J8-U	J9-g
J6-f	J9-Z	J8-D	J9-e
J6-Z	J9-g	J8-Y	J9-G
J6-RLE	Ground	J8-KCV	Ground
J6-U	J9-f	J9-Y	Valve-2

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

From	To
J6-V	Relay-1
J6-e	J9-L
J6-S	J9-R
J6-Y	J9-S
J6-b	J9-U
J6-d	J9-x
J6-h	J9-a
J9-k	Ground
J9-h	Relay-6
Relay-4	Ground

3.5 Insulation resistance. The insulation resistance between electrically isolated circuit and between ungrounded pins specified in Table II shall not be less than 50 megohms when subjected to a direct currect (dc) potential of 500 ± 50 volts when tested as specified in 4.4.2.

Table II

From	To	Except
Shells	All pins	
J1-XW	All other pins	J3-F
J1-EV	All other pins	J3-O
J1-NP	All other pins	J3-M
J1-D	All other pins	J2-f
J1-a	All other pins	J2-b
J1-S	All other pins	J3-P
J1-GH	All other pins	J3-E
J2-B	All other pins	J3-K
J2-M	All other pins	J6-a
J2-U	All other pins	Ground
J3-G	All other pins	J8-A
J3-A	All other pins	J8-F
J3-M	All other pins	Valve-1
J3-N	All other pins	Ground
J3-L	All other pins	J9-N
J3-P	All other pins	J9-d
J3-K	All other pins	J7-a
J3-E	All other pins	J9-B
J3-H	All other pins	J6-a
J3-I	All other pins	J9-M
J6-f	All other pins	J9-Z
J6-Z	All other pins	J9-g
J6-RLE	All other pins	Ground
J6-U	All other pins	J9-f
J6-V	All other pins	Relay-1
J6-e	All other pins	J9-L
J6-S	All other pins	J9-R
J6-Y	All other pins	J9-S
J6-b	All other pins	J9-U
J6-d	All other pins	J9-x
J6-h	All other pins	J9-a
J6-1	All other pins	J9-b
J6-j	All other pins	J9-T
J6-P	All other pins	J9-V
J7-e	All other pins	J9-I
J7-f	All other pins	J9-H
J7-d	All other pins	J9-j
J7-b	All other pins	J9-A
J7-RC	All other pins	Ground
J7-a	All other pins	Relay-7
J7-Z	All other pins	J9-e
J7-h	All other pins	J9-G
J7-G	All other pins	J9-c
J7-U	All other pins	J9-C
J7-V	All other pins	Relay-1
J7-1	All other pins	J9-j
J7-j	All other pins	J9-E
J7-P	All other pins	J9-W
J8-M	All other pins	J9-F
J8-P	All other pins	J9-O
J8-U	All other pins	J9-g
J8-D	All other pins	J9-e
J8-Y	All other pins	J9-G
J8-KCV	All other pins	Ground
J9-Y	All other pins	Valve-2
J9-k	All other pins	Ground
J9-h	All other pins	Relay-6
Relay-4	All other pins	Ground

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

3.6 Setting mechanism. The cartridge servoed synchros shall be capable of being set when tested as specified in 4.4.3.

3.7 Soldering. All soldering shall comply with the requirements specified in MIL-STD-1460.

3.8 Workmanship.

3.8.1 Plastic and metal characteristics. All components shall be free from cracks, splits, cold flow, shrinkage, cold shuts, inclusions, porosity, or any similar characteristic.

3.8.2 Threads. Threads shall be full and undamaged for the entire minimum length or depth as required on the applicable drawing.

3.8.3 Burrs. Parts shall be free from burrs.

3.8.4 Foreign matter. Parts shall be free from chips, dirt, grease, rust, corrosion, or any embedded foreign material.

3.8.5 Cleaning. The cleaning method shall not be injurious to any of the parts, nor shall the parts be contaminated by the cleaning agent.

3.8.6 Electrical. Cable assemblies and wires shall be dressed in such a manner as to prevent pinching or chafing of the wire insulation. Ends of wires shall be free from burrs, sharp edges, or points. All parts shall be free from flux, chips, dirt, grease, rust or foreign material.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.2 First article inspection.

4.2.1 Quantity to be submitted. When the contract requires first article inspection, the contractor shall submit 2 complete assemblies (see dwg 8846038) for first article testing to the testing facility designated in the invitation for bids or request for proposal.

4.2.2 Inspection and testing to be performed. The first article inspection sample shall be subjected to the inspections and tests specified in Table III. Tests shall be conducted in order specified in Table III.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

Table III

First article inspection and tests

Inspection or Test	Dest	Non-Dest
1. Classification of characteristics (see 4.3.2.1)		X
2. Continuity (see 3.4)		X
3. Insulation resistance (see 3.5)		X
4. Setting mechanism (see 3.6)		X

4.2.3 Inspection equipment. The inspection and testing specified in 4.2.2 shall be accomplished by using the gages and test equipment specified in 4.3.4.1.

4.2.4 Rejection. If any item fails to comply with any of the applicable requirements, the first article sample shall be rejected.

4.3 Quality conformance inspection.

4.3.1 Lot formation.

4.3.1.1 Production lot. A lot shall consist of parts and assemblies produced by one manufacturer in one unchanged process, in accordance with the same drawing, same drawing revision, same specification and same specification revision. Drawing, specification and process changes not affecting safety, performance, storage, or interchangeability, as determined by the Government, shall not necessitate changing the lot interfix number. The criteria and procedures for the assignment of lot numbers shall be in accordance with MIL-STD-1168.

4.3.1.2 Inspection lot. A lot or batch and its formation, size, and presentation is described in MIL-STD-105, Section 5. Accordingly, a lot shall mean an inspection lot and a batch shall mean an inspection batch for the purpose of this specification. The manner in which each inspection lot or batch is to be presented and identified by the contractor, shall be designated or approved by the Government representative.

4.3.2 Product inspection examination. A sample shall be selected at random from each inspection lot in accordance with the applicable major or minor characteristic table (see Table IV and Table V), and inspected for all characteristics in the applicable classification. Any characteristics in the sample found to be defective shall reject the inspection lot. Sequence for the inspection of characteristics in each classification need not be followed as long as all characteristic inspections are performed.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

Table IV
Major Characteristics

Lot Size	Sample Size	Lot Size	Sample Size	Lot Size	Sample Size	Lot Size	Sample Size
1-72	all	140-141	124	256-259	177	541-549	230
73	72	142	125	260-262	178	550-559	231
74	73	143-144	126	263-265	179	560-569	232
75	74	145	127	266-268	180	570-579	233
76	75	146-147	128	269-271	181	580-590	234
77	76	148-149	129	272-275	182	591-601	235
78	77	150	130	276-278	183	602-613	236
79	78	151-152	131	279-282	184	614-625	237
80	79	153-154	132	283-285	185	626-637	238
81-82	80	155-156	133	286-289	186	638-649	239
83	81	157	134	290-293	187	650-662	240
84	82	158-159	135	294-296	188	663-676	241
85	83	160-161	136	297-300	189	677-690	242
86	84	162-163	137	301-304	190	691-704	243
87	85	164-165	138	305-308	191	705-719	244
88-89	86	166-167	139	309-312	192	720-735	245
90	87	168	140	313-316	193	736-751	246
91	88	169-170	141	317-320	194	752-768	247
92	89	171-172	142	321-324	195	769-785	248
93	90	173-174	143	325-329	196	786-804	249
94-95	91	175-176	144	330-333	197	805-823	250
96	92	177-178	145	334-338	198	824-842	251
97	93	179-180	146	339-342	199	843-863	252
98	94	181-182	147	343-347	200	864-884	253
99-100	95	183-184	148	348-352	201	885-907	254
101	96	185-187	149	353-356	202	908-930	255
102	97	188-189	150	357-361	203	931-955	256
103	98	190-191	151	362-366	204	956-981	257
104-105	99	192-193	152	367-372	205	982-1008	258
106	100	194-195	153	373-377	206	1009-1036	259
107	101	196-197	154	378-382	207	1037-1066	260
108-109	102	198-200	155	383-388	208	1067-1098	261
110	103	201-202	156	389-393	209	1099-1131	262
111	104	203-204	157	394-399	210	1132-1166	263
112-113	105	205-207	158	400-405	211	1167-1204	264
114	106	208-209	159	406-411	212	1205-1243	265
115	107	210-212	160	412-417	213	1244-1285	266
116-117	108	213-214	161	418-424	214	1286-1330	267
118	109	215-217	162	425-430	215	1331-1378	268
119	110	218-219	163	431-437	216	1379-1429	269
120-121	111	220-222	164	438-443	217	1430-1483	270
122	112	223-224	165	444-450	218	1484-1542	271
123-124	113	225-227	166	451-457	219	1543-1605	272
125	114	228-230	167	458-465	220	1606-1673	273
126-127	115	231-232	168	466-472	221	1674-1747	274
128	116	233-235	169	473-480	222	1748-1827	275
129-130	117	236-238	170	481-488	223	1828-1914	276
131	118	239-241	171	489-496	224	1915-2010	277
132-133	119	242-243	172	497-504	225	2011-2115	278
134	120	244-246	173	505-513	226	2116-2232	279
135-136	121	247-249	174	514-521	227	2233-2361	280
137	122	250-252	175	522-530	228	over 2361	298
138-139	123	253-255	176	531-540	229		

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

Table V
Minor Characteristics

Lot Size	Sample Size	Lot Size	Sample Size	Lot Size	Sample Size	Lot Size	Sample Size
1-16	all	28-29	23	52-56	31	132-156	39
17	16	30-31	24	57-62	32	157-191	40
18	17	32-34	25	63-69	33	192-244	41
19-20	18	35-36	26	70-76	34	245-334	42
21	19	37-40	27	77-86	35	335-519	43
22-23	20	41-43	28	87-97	36	520-1120	44
24-25	21	44-47	29	98-112	37	over 1120	45
26-27	22	48-51	30	113-131	38		

4.3.2.1 Classification of characteristics (see 3.2). Critical, major and minor characteristics are defined in MIL-STD-105. Inspection shall be conducted as follows:

4.3.2.1.1 Cartridge support assembly (see dwg 8346199) prior to assembly with cartridge shell assembly.

Categories	Characteristics	Method of Inspection
Critical:	None defined.	
Major:		
101.	Servoed Synchro cover missing or not securely fastened to Cartridge Support	Visual
102.	Servoed Synchro Assemblies missing or not securely fastened to Cartridge Support	Visual
103.	Solenoid valve assembly missing	Visual
104.	Any operation missing	Visual
105.	Fuses missing or incorrect fuses in socket	Visual
106.	Evidence of poor workmanship (see 3.8)	Visual
107.	Insulation sleeving loose, torn or damaged	Visual
108.	Improper soldering (see 3.7)	Visual
109.	Servoed Synchro plugs not properly connected to cartridge harness receptacles	Visual
*110.	Height of pin(s) (pins of the same diameter must all appear to be within 1/16 inch in height relative to the adjacent pin)	Visual/Gage
**111.	Depth of socket(s) (female sockets of the same diameter must all appear to be within 1/16 inch in depth relative to the adjacent sockets	Visual/Gage

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

112. Connector loose in Cartridge Support or connector cracked.....Visual
113. Insulation missing from harness wire...Visual
114. Any wire broken.....Visual
115. Foreign matter in Cartridge Support unless removable.....Visual
116. Foreign matter on any pin unless removable.....Visual
117. Markings missing, misleading, or unidentifiable.....Visual
118. Painting defective to the extent it shows primer coat or bare metal.....Visual
119. Any pin bent or broken.....Visual
120. Relays missing or loose.....Visual
121. Capacitors missing or loose.....Visual
122. Connector deformed to extent it prevents subsequent assembly.....Visual

Minor: None defined.

4.3.2.1.2 Cartridge shell assembly (see dwg 8846220) prior to assembly with cartridge support assembly.

Categories	Characteristics	Method of Inspection

Critical: None defined.

Major:
101. Flexible tube missing, cracked or split.....Visual
102. Pressurizing Adapter Assembly missing or loose.....Visual
103. Tube to Housing Adapter missing, cracked or split.....Visual
104. Foreign matter in Cartridge Shell unless removable.....Visual
105. Markings missing, misleading, or unidentifiable.....Visual
106. Painting defective to the extent it shows primer coat or bare metal.....Visual
107. Mounting holes on Cartridge Shell Ring improperly located or tapped.....Gage
108. Mounting holes on Cartridge Shell Plate improperly located or drilled....Gage
109. Plug alignment bracket missing.....Visual
110. Evidence of poor workmanship (see 3.8).....Visual

Minor: None defined.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

4.3.2.1.3 Cartridge assembly (see dwg 8846038).

Categories	Characteristics	Method of Inspection
Critical:	None defined.	
Major:		
101.	Dust covers missing from connectors on cartridge	Visual
102.	Fuseholder guard missing	Visual
103.	Marking missing, misleading or unidentifiable	Visual
104.	Painting defective to the extent it shows primer coat or bare metal	Visual
105.	Assembly punctured or cracked	Visual
106.	Objective evidence relative to material missing or improper (see 3.1)	Visual
Minor:		
201.	Evidence of poor workmanship (see 3.8)	Visual

*In the event pin(s) do not appear to be within 1/16 inch in height relative to the adjacent pins, gage (see 4.3.4) shall be used to determine the variation from the normal height. Reject any pin that varies by more than 0.063 inch max. from the normal pin height of the individual connector. The normal height of the individual connector pins shall be determined by calculating the average height from measurements taken of pins adjacent to the pin that appears to be defective. The forward metal edge of the connector shall be utilized as the reference surface of all measurements of pin heights.

**In the event socket inserts do not appear to be within 1/16 inch in depth relative to the adjacent sockets, gage (see 4.3.4) shall be used to determine the variation from the normal depth. Reject any insert that varies by more than 0.063 inch max. from the normal socket insert depth of the individual connector. The normal depth of the individual connector sockets shall be determined by calculating the average depth from measurements taken of sockets adjacent to the socket that appears to be defective. The forward edge of the connector shall be utilized as the reference surface for all measurements of socket depths.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

4.3.2.1.4 Preparation for delivery (see 5).

Categories	Characteristics	Method of Inspection
Critical:	None defined.	
Major:		
	101. Preservation, packaging and packing not in accordance with MIL-STD-1169	Visual
	102. Marking not in accordance with MIL-STD-1169	Visual
Minor:		
	201. Evidence of poor workmanship (see 3.8)	Visual

4.3.3 Testing. All tests shall be performed. Tests shall be performed in the order specified below:

Test	Test Classification
a. Continuity	Major
b. Insulation resistance	Major
c. Setting mechanism	Major

None of these tests are considered destructive and samples so tested may be returned to the lot.

4.3.3.1 Continuity, insulation resistance, and setting mechanism. Each cartridge assembly shall be tested in accordance with 4.4.1 through 4.4.3. If any item fails to comply with 3.4 through 3.6, the item shall be rejected and removed from the lot.

4.3.4 Acceptance inspection equipment.

4.3.4.1 Major characteristics and tests. Inspection and testing shall be performed with the acceptance inspection equipment, operating instructions, and calibration instructions specified on the Equipment Lists (EL) (see EL-8855810). When either of the conditions listed below exist, the contractor shall design required equipment or specify suitable commercial equipment and obtain approval prior to use on the contract.

a. Any deviation from equipment or procedures specified on the EL is desired (see 6.3).
b. The code "CD" is listed in the "Part or Identifying Number" column on the EL (see 6.1.2).

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

4.3.4.2 Minor characteristics and tests. Acceptance inspection equipment for minor characteristics is not specified on ELs. The acceptance inspection equipment, operating instructions and calibration instructions used by the contractor for minor classification inspection shall be approved by the Government representative authorized by the procuring agency.

4.4 Test methods. The tolerances specified herein are absolute with no allowance for test equipment inaccuracy. The tolerances used by the manufacturer shall be equal to the absolute tolerances less the accuracy tolerances of the test equipment used.

4.4.1 Continuity. The point to point continuity as specified in Table I of the cartridge assembly shall be tested utilizing a commercial resistance meter.

4.4.2 Insulation resistance. The insulation resistance between circuits specified in Table II shall be tested with an insulation resistance tester with an output of 500 ± 50 vdc and a scale reading directly in megohms.

4.4.3 Setting mechanism. The setting mechanism of the Cartridge Assembly shall be tested in accordance with procedure in 4.4.3.1 through 4.4.3.3.4.

4.4.3.1 T-4014 Test.

4.4.3.1.1 Preparation for Test.

4.4.3.1.1.1 Connect W6H Test Cable from T-4014 (T-229) to the Cartridge in the following manner.

Connect P1 to J3 on the T-4014.
Connect P2 to J2 on the T-4014.
Connect P3 to J6 on the Cartridge.
Connect P4 to J7 on the Cartridge.

4.4.3.1.1.2 T-4014 AC PWR, Baro Set power, S1, S4, S5 and S6 shall be in the OFF position.

4.4.3.1.1.3 Connect from T-4014 GND to earth ground with the W13-C ground strap.

4.4.3.1.1.4 T-4014 shall be connected to a 115 ± 10 volt, 60 Hz ac power source by means of the W3-H power cable, from receptacle J1 on the T-4014 to the power source.

4.4.3.1.2 Upon operation of the AC PWR switch to the ON position, check that the AC PWR and DEFECTIVE lamps light and the test set motor starts.

4.4.3.1.3 Operate AC PWR switch to OFF position. Observe the following: AC PWR and DEFECTIVE lamps go out and test motor stops.

4.4.3.2 Baroswitch setting procedures and limit test. Remote setting of Simulated Baroswitches is done using the T-4014 Test Set. The operation is performed using the same ground power and test connections as were used previously on the T-4014 test. (see 4.4.2.1.1).

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

4.4.3.2.1 Upon operation of the AC power switch to the ON position, check that the AC power and DEFECTIVE lamps light and the test set motor starts.

CAUTION: Do not operate Baro Set PWR Switch to the ON position unless switch S1 is the OFF position.

4.4.3.2.2 Operate Baro Set PWR switch to the ON position. (S2 is normally in Fuse Baro position).

NOTE: If M-1 Baro Indicator operates, allow it to come to rest before proceeding.

4.4.3.2.2.1 Operate Switch, S-3 to the increase position until the indicator reads 25,000 ± 10 feet.

4.4.3.2.2.2 Operate Switch, S-3 to the decrease position until the indicator reads 10,000 ± 10 feet.

4.4.3.2.2.3 Operate Switch, S-3 to the decrease position until the indicator reads minus 3,000 ± 10 feet.

4.4.3.2.2.4 Operate switch, S-2 to the A.B. position and hold.

NOTE: If M-1 Baro Indicator operates, allow it to come to rest before proceeding.

4.4.3.2.2.5 Operate switch, S-3 to the decrease position until the indicator reads minus 3,000 ± 10 feet.

4.4.3.2.2.6 Operate switch, S-3 to the decrease position until the indicator reads 10,000 ± 10 feet.

4.4.3.2.2.7 Operate switch, S-3 to the increase position until the indicator reads 25,000 ± 10 feet.

4.4.3.2.2.8 Release all switches.

NOTE: If M-1 Baro Indicator operates, allow it to come to rest before proceeding.

4.4.3.2.2.9 Operate Baro Set power switch to the OFF position.

4.4.3.3 Fuse Baro Set.

4.4.3.3.1 Operate T-4014 power switch to the ON position.

4.4.3.3.2 Operate Baro Set power switch to the ON position.

NOTE: If M-1 Baro indicator operates, allow it to come to rest before proceeding.

4.4.3.3.2.1 Operate switch, S-3 to the increase position until the indicator reads 1,000 ± 10 feet.

4.4.3.3.2.2 Operate switch, S-3 to the decrease position until the indicator reads minus 3,000 ± 10 feet.

4.4.3.3.2.3 Operate Baro set power switch to the OFF position.

4.4.3.3.2.4 Operate the T-4014 AC power switch to the OFF position.

4.4.3.3.2.5 Disconnect W6H Cable.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.

5. PREPARATION FOR DELIVERY

5.1 Preservation and packaging. Preservation and packaging shall be level A or C as specified (see 6.1).

5.1.1 Level A. The cartridge assembly shall be preserved and packaged in accordance with instructions contained in MIL-STD-1169.

5.1.2 Level C. The cartridge assembly shall be preserved and packaged in accordance with instructions contained in MIL-STD-1169.

5.2 Packing.

5.2.1 Levels A and C. The cartridge assembly shall be packed in accordance with the applicable instructions contained in MIL-STD-1169.

5.3 Marking. Marking shall be in accordance with MIL-STD-1169.

6. NOTES

6.1 Ordering data. Procurement documents should specify the following:

6.1.1 Procurement requirements.

a. Title, number, and date of this specification.

b. Selection of applicable level of packaging and packing required (see 5.1 and 5.2).

6.1.2 Contract data requirements (see 4.3.4.1). Data specified in 4.3.4.1 will be delivered as identified on a numbered DD Form 1664 when required on a DD Form 1423 incorporated in the contract.

6.2 Objective evidence. Records of contractor quality control and inspections which can be verified.

6.3 Acceptance inspection equipment (see 4.3.4.1). The contractor shall obtain approval from the Commander, Picatinny Arsenal, Dover, New Jersey 07801, ATTN: SARPA-QA-T.

6.4 Supersession data. This specification supersedes the requirements of Purchase Description PA-PD-2133 dated 7 March 1962.

Custodian:
Army - PA

Preparing activity:
Army - PA

Project No. 1135-A200

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:40Z
Check the source to verify that this is the current version before use.