INCH-POUND

MIL-P-53124/8(ME)
9 April 1992
SUPERSEDING
MIL-P-52854A(ME)
9 April 1979

MILITARY SPECIFICATION SHEET

POWER PLANT, ELECTRIC,

30 KW, 50/60 HERTZ, AN/MJQ-10A

The requirements for acquiring the product described herein shall consist of this specification sheet and the issue of the following specification listed in that issue of the Department of Defense Index of Specifications and Standards (DODISS) specified in the solicitation: MIL-P-53124.

1. APPLICABLE DOCUMENTS

1.1 Government drawings. The following Government drawings form a part of this document to the extent specified herein. Unless otherwise specified, the issues are those cited in the solicitation.

DRAWINGS

ME

TA13220E6335 - Power Plant, Electric, AN/MJQ-10A.

(Copies of drawings required by contractors in connection with specific acquisition functions should be obtained from the USA Belvoir Research, Development and Engineering Center, ATTN: STRBE-FG, Fort Belvoir, VA 22060-5606.)

2. REQUIREMENTS

2.1 Description. The power plant, AN/MJQ-10A, shall be in accordance with TA13220E6335, MIL-P-53124 and as specified herein.

FSC 6115

AMSC N/A

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T22:09Z
Check the source to verify that this is the current version before use.

2.2 Government-furnished property. The following property in the quantities indicated will be furnished by the Government:

Item No.	Description	Identification	Quantity for each AN/MJQ-10A
1	Chassis, trailer, 2-1/2 ton, 2 wheel, Model M200A1.	NSN 2330-00-331-2307	2
2	Generator set, diesel-engine-driven, 30 kw, 50/60 hertz, DOD Model MEP-005A.	NSN 6115-00-118-1240	2

2.3 Switch box. Provisioning shall be made for switching load from one generator set to the other, while both sets are running. To accommodate the generator set 5 wire systems the switch box shall have a 5th terminal that is connected via a low impedance connection to the box. This 5th terminal, in addition to the (4) load terminals, shall be of sufficient size (may be multiple terminals) to accept the 5th wire from each generator set and from the load and to accept a ground rod cable.

3. QUALITY ASSURANCE PROVISIONS

3.1 Test conditions. The following preparations shall be made prior to testing the switch box assembly:

a. Power input cables shall be connected to the switch box assembly.
b. The free ends of the power input cables shall be attached to the generator sets as follows:

1. Cable wires marked L1 shall be attached to Phase A.
2. Cable wires marked L2 shall be attached to Phase B.
3. Cable wires marked L3 shall be attached to Phase C.
4. Cable wires marked L0 shall be attached to neutral.

c. A 3-phase, 4-wire, 30 kw resistive load shall be connected to the output of the switch box.
d. Provide ground to ground terminal of switch box.

Custodian:
Army - ME

Preparing activity:
Army - ME

Project 6115-A558

Source: https://assist.dla.mil -- Downloaded: 202610-22T22:09Z
Check the source to verify that this is the currentversion before use.