MIL-T-21451(NOrd)

15 July 1958
SUPERSEDING
NAVORD OS 5867A
26 August 1954

MILITARY SPECIFICATION

TEST SET MARK 77 MOD 0

1. SCOPE

1.1 This specification establishes the requirements for the procurement of the Test Set Mark 77 Mod 0. This test set is used during the acceptance testing of the Terminal Board TB-19 Mod 0 with Terminal Board TB-20 Mod 0 attached.

2. APPLICABLE DOCUMENTS.

2.1 The following specifications, standards, drawings, and publications of the issue in effect an date of invitation for bids, form a part of this specification.

SPECIFICATIONS

FEDERAL

PPP-B-601	Boxes, Wood, Cleated-Plywood.
PPP-B-621	Boxes, Wood, Nailed and Lock-corner.
PPP-B-636	Boxes, Fiber.

MILITARY

JAN-P-100	Packaging and Packing-for Overseas Shipment, General Specification. for.
MIL-P-116	Preservation, Methods of.
MIL-B-131	Barrier Material; Water Vaporproof, Flexible.
MIL-V-173	Varnish, Moisture and Fungus resistant for the Treatment of Communications, Electronic and Associated Electrical Equipment.
MIL-D-3464	Desiccants, Activated, Bagged, Packaging Use and Static Dehumidification.
MIL-S-6872	Soldering Processes, General Specifications for.

FSC 4925

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

STANDARDS

MILITARY

MIL-STD-105	Sampling Procedures and Tables for Inspection by Attributes.
MIL-STD-129	Marking for Shipment and Storage.

DRAWINGS

BUREAU OF ORDNANCE

LD 274823	Test Set Mark 77 Mod 0.
LD 284866	Preparation for Delivery for Test Set Cable Assemblies.
1476194	Marking Instructions for Storage and Shipping Containers.

And all documents listed in the above LD's and drawings.

PUBLICATIONS

BUREAU OF ORDNANCE

NAVORD OP 400	General Instructions for the Design, Manufacture and Inspection of Naval Ordnance Equipment.

(Copies of specifications, standards, drawings, and publications required by contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer).

3. REQUIREMENTS

3.1 General requirements.

3.1.1 Test Set Mark 77 Mod 0 shall be manufactured in accordance with LD 274823 and all documents listed thereon.

3.1.2 The requirements and procedures established in OP 400 shall be complied with as applicable.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

3.1.3 Preproduction sample. - Unless otherwise specified in the contract or order, a preproduction sample shall be manufactured by the same procedures and processes and at the same location as proposed for full production. This sample will be tested for the purpose of determining compliance with the requirements of this specification, the drawings, and the contract. See 4.1.2.

3.1.4 Interchangeability. - Component parts of assembled units (unless otherwise specified on the applicable drawings) fabricated in strict agreement with their applicable drawings, shall be interchangeable and shall assemble with mating components of the unit without selection or fitting. If, during assembly of the fabricated parts of a unit, selection or fitting is required and changes in dimensions are necessary, no changes in the parts as delineated on applicable drawings shall be made without prior approval of the Bureau of Ordnance.

3.2 Moisture-and fungus-resistant treatment. - Materials and parts of this test set which are not moisture and fungus resistant shall be treated, before assembly, with a varnish conforming to Military Specification MIL-V-173.

3.3 Requests for deviation. - Requests for deviation from this specification, applicable drawings, specifications publications, materials and processes specified herein, shall be as set forth in OP 400.

3.4 Conflicting requirements. - Conflicting requirements arising between this specification or any specifications, publications, or drawings listed herein, shall be referred in writing to the procuring agency or appointed agent for interpretation and clarification.

3.5 Soldering. - Unless otherwise specified, soldering processes shall conform to the requirements specified in Military Specification MIL-S-6872. Only non-corrosive and non-volatile fluxes shall be used. Rosin shall be used when soldering wires to contacts and terminals. The use of rosin core solder is permitted. Electrical connections shall be mechanically secure and electrically continuous before soldering. Sufficient heat shall be applied during the soldering process to avoid "cold" solder joints.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

3.6 Wiring. - All internal wiring shall be cabled wherever possible.

3.7 **Performance requirements and product characteristics.** The test set covered by this specification shall meet the following performance requirements and product characteristics.

3.7.1 Insulation resistance. - The insulation resistance between electrical circuits and between each circuit and the chassis shall be not less than 500 megohms when tested in accordance with 4.5.3.

3.7.2 Calibration. - The calibration circuitry shall be properly connected as verified by testing as specified in 4.5.4.

3.7.3 Continuity circuits. - The continuity circuitry shall be properly connected as verified by testing as specified in 4.5.5.

3.7.4 Leakage circuits. - The leakage circuitry shall be properly connected as verified by testing as specified in 4.5.6.

3.7.5 Leakage value. - The leakage values of the test set shall be checked by connecting resistors across adapter terminals and testing as specified in 4.5.7.

3.7.6 Omitted leakage circuits. - The test set shall be tested to determine that no leakage circuits are omitted. When the circuitry is shorted out and tested as specified in 4.5.8, the test set shall cycle to home position.

3.8 Workmanship and cleanliness. - The test set shall be free from dust, dirt, metal filings, moisture, solder splashes, chips, and other foreign matter. Necessary precautions shall be taken during manufacture and assembly to insure these conditions.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

4. QUALITY ASSURANCE PROVISIONS AND TEST REQUIREMENTS.

4.1 Government inspection. - The Government inspector will make such inspections as are necessary to determine t all components and assemblies are in accordance with the r quirements of the contract, pertinent specifications and drawings. Unless otherwise specified, these inspections w be conducted in accordance with instructions contained in OP 400.

4.1.1 Sampling. - Unless otherwise specified, and when applicable, the sampling plans and procedures used by the Government. inspector in the determination of the acceptabi of products submitted by a supplier for Government inspect will be in accordance with the provisions of MIL-STD-105.

4.1.2 Preproduction sample. - Unless otherwise specifi for each contract or order, a representative sample of one test set shall be manufactured using the methods and proce proposed for full production. The Government inspector sh perform, witness, or participate in such inspections and t on the sample as are required for full production. Upon c ditional acceptance by the inspector, the preproduction sa shall be forwarded, together with a report of inspection, an activity designated in the contract or by the procuring agency, for the purpose of determining compliance with the quirements of the contract, specifications and drawings. Further production of the item by the contractor prior to approval of the contracting activity or the completion of tests on preproduction samples shall be at the contractor's risk. Preproduction samples accepted will be applied as pa of the quantity specified by the contract or order.

4.1.2.1 Preproduction sample for a subsequent contract The necessity for a preproduction sample will be determined by the procuring agency when production under a new contra by the same contractor at the same location follows the manufacture of satisfactory material as covered by this doc ment.

4.1.3 Lot. - As applied to the Government inspection of units of product, the term “lot” shall mean “inspection lot i.e. a collection of units of the product used as a basis f Government inspection. Unless otherwise specified, the number of units of product in “inspection lots” shall be as

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

determined by the Government inspector, and may differ from the quantity designated in the contract or order as a lot for production, shipment, or other purpose.

4.2 Contractor's inspection. - Contractor's inspection shall be conducted in accordance with provisions of "Inspection by Contractor" as contained in OP 400.

4.3 Classification of tests. - The inspection and testing of mechanisms covered by this document shall be classified as follows:

(a) acceptance tests

(b) preproduction tests

4.3.1 Acceptance tests. - Acceptance tests for acceptance of the test set covered by this specification shall consist of tests to determine compliance with all requirements specified in this documents.

4.3.2 Preproduction tests. - Preproduction tests are those performed on samples submitted in accordance with 4.1.2 to determine that the lot and production meet all the requirements of this specification. Acceptance shall be based on no defects in a sample.

4.4 Test equipment.

4.4.1 Test and inspection equipment and facilities. - Unless otherwise specified, the manufacturer shall furnish and maintain all necessary-test equipment, facilities and personnel for performing all acceptance tests under the supervision of the Government inspector. The test equipment shall be adequate in quantity, and unless definite requirements are specified, they shall be of sufficient accuracy and quality to permit performance of the required acceptance tests.

4.4.1.1 Equipment required for performing these tests is as follows:

(a) One resistor, 55 megohms, 1 watt, accuracy within ± 5 percent.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

(b) One resistor, 60 megohms, 1 watt, accuracy within ± 5 percent.

(c) One 3.3 megohm resistor, 1 watt, accuracy within ± 5 percent.

(d) 8 volt d-c power supply, ±5 percent regulation, ±2 percent ripple voltage capable of delivering 4 amperes.

(e) 115-volt, 60 cycle a-c supply.

(f) Megohmmeter capable of measuring 500 megohms to an accuracy of ± 10 percent with a minimum applied potential of 500 volts d-c.

4.5 Tests.

4.5.1 Test conditions. - Unless otherwise specified, tests shall be performed at 80° ±10°F and ambient relative humidity.

4.5.2 Visual inspection. -The test set and its component parts shall be inspected to verify that the materials, design, construction, physical dimensions, soldering and workmanship are in accordance with this document and the drawings.

4.5.3 Insulation resistance. - The test set shall be subjected to a conditioning period of 24 hours at a temperature of 77° ±2°F, and a relative humidity of 75 ± 5 percent. A minimum test potential of 500 volts d-c is then applied as specified in 3.7.1, using test item 4.4.1.1 (f). The insulation resistance shall be not less than 500 megohms.

4.5.4 Calibration test.

(a) Set POWER SWITCH at OFF.

(b) Set J-N JUMPERS switch to IN.

(c) Connect adapter cables and CA-811, CA-812, and CA-813 cables to test set connectors.

(d) Connect test set to 8-volt d-c (test item 4.4.1.1 (d)) and 115-volt a-c (test item 4.4.1.1(e)) supplies. Polarity is unimportant.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

(e) Set POWER SWITCH at ON and allow test set to warm up for about 7 minutes.

(f) Lift CALIBRATION SWITCH. CALIBRATION INDICATION lamp shall light. If lamp does not light, it shall be possible to turn CALIBRATION ADJUSTMENT until lamp lights.

(g) Depress CALIBRATION SWITCH. CALIBRATION INDICATION lamp shall not light. If lamp does light, it shall be possible to turn CALIBRATION ADJUSTMENT until lamp goes out. (If any adjustment is made, repeat step (f)).

(h) Set CALIBRATION SWITCH in mid-position.

NOTE

Where lamp panel designations consist of more than one, row of letters and/or symbols, the lamp is herein referred to by the uppermost row, only.

4.5.5 Continuity circuits test.

(a) With test set energized and ready to operate, depress and release OPERATION SWITCH until set is in home position. Test set is in home position when A_1F_4 and left CONTINUITY lamps, only are lit.

(b) Depress and release OPERATION SWITCH. T_1 -(minus) lamp shall light. A_1F_4 and left CONTINUITY lamps shall remain lit.

(c) Jumper adapter and/or cable terminals listed in sequence 1 of table 1. Test set shall step and A_1F_4 and indicated lamps shall light.

(d) Remove jumper.

(e) Repeat steps (c) and (d) for all sequences in table. Lamps shall light or set shall operate as indicated in table.

Source: https://assist.dla.mil -- Downloaded: 202610-19T09:37Z
Check the source to verify that this is the current version before use.

TABLE 1

Sequence	Adapter		Jumpered Terminals CA-811	CA-812	CA-813	Lighted Lamps
1	38	11	-	-	-	left CONTINUITY, T_1G_5
2	38	-	G	-	-	left CONTINUITY, T_1G_4
3	38	-	-	-	G	left CONTINUITY , Q_1C_2
4	37	22	-	-	-	left CONTINUITY, Q_1B_4
5	37	-	-	-	B	left CONTINUITY, Q_1B_5
6	37	-	B	-	-	left CONTINUITY, D_1D_4
7	34	1	-	-	-	left CONTINUITY, D_1E_2
8	34	-	-	-	E	left CONTINUITY, D_1E_3
9	34	-	E	-	-	left CONTINUITY, G_1G_2
10	35	26	-	-	-	left CONTINUITY, G_1H_2
11	35	-	-	-	H	left CONTINUITY, C_1H_1
12	33	23	-	-	-	left CONTINUITY, C_1L_4
13	33	-	-	-	L	left CONTINUITY, C_1L_5
14	33	-	L	-	-	left CONTINUITY, B_1B_3
15	32	3	-	-	-	left CONTINUITY , B_1K_1
16	32	-	-	-	K	left CONTINUITY, B_1K_2
17	32	-	K	-	-	left CONTINUITY, C_3D_5
18	-	-	-	C	D	left CONTINUITY, C_3D_6
19	-	-	D	C	-	left CONTINUITY, A_1A_3
20	30	5	-	-	-	right CONTINUITY,

Source: https://assist.dla.mil -- Downloaded: 202610-19T09:37Z
Check the source to verify that this is the current version before use.

Sequence	Adapter		Jumpered Terminals CA-811	CA-812	CA-813	Lighted Lamps
21	30	-	-	-	F	right CONTINUITY, T_1--
22	30	-	F	-	-	right CONTINUITY, T_1G_5
23	16	5	-	-	-	right CONTINUITY, T_1G_4
24	16	19	-	-	-	right CONTINUITY, Q_1C_2
25	29	-	-	B	-	right CONTINUITY, Q_1B_4
26	29	-	-	-	J	right CONTINUITY, Q_1B_5
27	29	-	J	-	-	right CONTINUITY, D_1D_4
28	25	20	-	-	-	right CONTINUITY, D_1E_2
29	21	12	-	-	-	right CONTINUITY, D_1E_3
30	24	-	-	D	-	right CONTINUITY, G_1G_2
31	24	10	-	-	-	right CONTINUITY, G_1H_2
32	4	-	-	A	-	right CONTINUITY, C_1H_1
33	9	15	-	-	-	right CONTINUITY, C_1L_4
34	8	14	-	-	-	right CONTINUITY, C_1L_5
35	17	18	-	-	-	right CONTINUITY, B_1B_3
36	-	-	H	-	C	right CONTINUITY, B_1K_1
37	-	-	M	-	M	right CONTINUITY, B_1K_2
38	-	-	C	-	M	right CONTINUITY, C3D5
39	36	2	-	-	-	right CONTINUITY, C3D6
40	36	-	-	-	N	right CONTINUITY, A_1A_3
41	36	-	N	-	-	set cycles home

Source: https://assist.dla.mil -- Downloaded: 20261O-19T09:37Z
Check the source to verify that this is the current version before use.

(f) Remove jumper.

4.5.6 Leakage circuits test.

(a) Turn Power Switch to OFF.

(b) Solder a 3.3M resistor (test item 4.4.1.1 (c)) between pin 5 of V2 and the wiper of REL Y1.

(c) Set Power Switch. to ON and allow test set to warm up for about 7 min.

(d) With set energized and ready for use, repeatedly depress and release OPERATION SWITCH until A_1F_4, A_1A_3, and right CONTINUITY lamps are lit.

(e) CAUTION - 405 VOLTS. Jumper adapter and/or cable terminals listed in sequence 1 of table 2.

(f) Depress and release OPERATION SWITCH. Test set shall stop with A_1F_4 lamp and lamps indicated in sequence 1 lit.

(g) CAUTION - 405 VOLTS Jumper terminals listed in sequence 2 and then remove jumper listed in preceding sequence. Test set shall step and then stop with A_1F_4 lamp and lamps listed in sequence 2 lit.

(h) Repeat step (d) for all sequences.

TABLE 2

Sequence	Adapter	Jumpered Terminals CA-811	CA-812	CA-813	Lighted Lamps
1	37 11	-	-	-	Q_1
2	37 2	-	-	-	Q_1, T_1G5
3	37 26	-	-	-	Q_1, T_1G_4
4	37 1	-	-	-	Q_1, Q_1C_2
5	37 23	-	-	-	Q_1, Q_1B_4

Source: https://assist.dla.mil -- Downloaded: 202640-19T09:37Z
Check the source to verify that this is the current version before use.

Sequence	Adapter	Jumpered Terminals CA-811	CA-812	CA-813	Lighted Lamps
6	37	3	-	-	-	Q_1, Q_1B_5
7	37	-	-	-	D	Q_1, D_1D_4
8	37	5	-	-	-	Q_1, D_1E_2
9	37	-	-	-	J	Q_1, D_1E_3
10	37	20	-	-	-	Q_1, G_1G_2
11	37	12	-	-	-	Q_1, G_1H_2
12	37	-	-	D	-	Q_1, C_1H_1
13	37	4	-	-	-	Q_1, C_1L_4
14	37	15	-	-	-	Q_1, C_1L_5
15	37	14	-	-	-	Q_1, B_1B_3
16	37	17	-	-	-	Q_1, B_1K_1
17	37	-	H	-	-	Q_1, B_1K_2
18	37	-	M	-	-	Q_1, $C_3D_5^2$
19	28	11	-	-	-	GND
20	28	22	-	-	-	GND, T_1--
21	28	2	-	-	-	GND, T_1G_5
22	28	26	-	-	-	GND, T_1G_4
23	28	1	-	-	-	GND, Q_1C_2
24	28	23	-	-	-	GND, Q_1B_4
25	28	3	-	-	-	GND, Q_1B_5
26	28	-	-	-	D	GND, D_1D_4

Source: https://assist.dla.mil -- Downloaded: 202610-19T09:37Z
Check the source to verify that this is the current version before use.

Sequence	Adapter	Jumpered Terminals				Lighted Lamps
			CA-811	CA-812	CA-813	
27	28	5	-	-	-	GND, D_1E_2
28	28	-	-	-	J	GND, D_1E_3
29	28	20	-	-	-	GND, G_1G_2
30	28	12	-	-	-	GND, G_1H_2
31	28	-	-	D	-	GND, C_1H_1
32	28	4	-	-	-	GND, C_1L_4
33	28	15	-	-	-	GND, C_1L_5
34	28	14	-	-	-	GND, B_1B_3
35	28	17	-	-	-	GND, B_1K_1
36	28	-	H	-	-	GND, B_1K_2
37	28	-	M	-	-	GND, C_3D_5

(i) Remove jumper. Test set shall cycle to home position.

(j) Turn Power Switch to OFF.

(k) Remove 3.3M resistor and replace original connection as shown on the schematic.

4.5.7 Leakage Value Tests.

(a) Turn Power Switch to ON. Allow test set to warm up about 7 minutes.

(b) With set energized and ready for use, repeatedly depress and release OPERATION SWITCH until A_1F_4, A_1A_3, and right CONTINUITY lamps are lit.

Source: https://assist.dla.mil -- Downloaded: 202610-19T09:37Z
Check the source to verify that this is the current version before use.

(c) Connect 55-megohm resistor (test item 4.4.1.1 (a)) across adapter terminals 2 and 37.

(d) Connect 60M resistor (test item 4.4.1.1 (b)) across adapter terminals 36 and 22.

(e) Depress and release OPERATION SWITCH. Test set shall step and then stop with A_1F_4, Q_1, and T_1G_5 lamps lit.

(f) Depress and release OPERATION SWITCH. Stepper switches shall cycle to home positions.

(g) Remove 55 and 60 megohm resistors.

4.5.8 Omitted leakage circuits test.

(a) With test set energized and ready for use, repeatedly depress and release OPERATION SWITCH until A_1F_4, A_1A_3, and right CONTINUITY lamps are lit.

(b) Jumper the following adapter and/or cable terminals:

Adapter		CA-811	CA-812	CA-813
38	11	-	-	-
37	22	-	-	-
34	1	-	-	-
35	26	-	-	-
33	23	-	-	-
32	3	-	-	-
--	--	-	C	D
30	5	-	-	-
29	--	-	B	-

Source: https://assist.dla.mil -- Downloaded: 20260-19T09:37Z
Check the source to verify that this is the current version before use.

Adapter		CA-811	CA-812	CA-813
25	20	-	-	-
21	12	-	-	-
24	--	-	D	-
4	--	-	A	-
9	15	-	-	-
8	14	-	-	-
17	18	-	-	-
--	--	H	-	C
--	--	M	-	M
36	2	-	-	-

(c) Depress and release OPERATION SWITCH. Test set shall cycle to home position.

(d) Remove jumpers.

(e) Set POWER SWITCH at OFF and disconnect newer supplies, cables, and adapter.

4.5.9 Acceptance criteria. - Failure of any test set to meet any of the requirements and tests of this specification shall result in rejection of the test set. If the number of failing test sets exceeds the number permitted by the associated criteria, the lot represented will be rejected.

5. PREPARATION FOR DELIVERY.

5.1. Preservation and Packaging.

5.1.1 Level A. - In addition to the following, Level A packaging shall be in accordance with JAN-P-100.

Source: https://assist.dla.mil -- Downloaded: 202610-19T09:37Z
Check the source to verify that this is the current version before use.

5.1.1.1 Cleaning and drying. - Unless otherwise specified, accessory components within the test set case, shall be cleaned in accordance with Method C-1 of Military Specification MIL-P-116 and dried in accordance with one or more of the procedures given in Military Specification MIL-P-116, provided the selected procedure is not injurious to the item.

5.1.1.2 Preservative application. - (Not applicable).

5.1.1.3 Unit packaging. - Prior to unit packaging, test set cables and adapter shall be packaged in accordance with Bureau of Ordnance List of Drawings LD 284866 and positioned in cable well of test set. Each test set shall be initially packaged in a Style RSC fiberboard box fabricated from Class 1, Type I or Type II board, having 275 lb. minimum bursting strength, conforming to the requirements of Federal Specification PPP-B-636. Sufficient fillers and folded corner pads, of the same box material, shall be utilized within the carton to provide a tight pack and to prevent direct contact between protrusions of the test set case and the walls of the fiberboard box.

5.1.1.3.1 Each test set, prepared as specified above, shall be further packaged Method IIb conforming to the requirements of Military Specification MIL-P-116. The inner carton, containing the packaged test set, shall be inserted into a water-vaporproof bag, fabricated from Class I barrier-material conforming to requirements of Military Specification MIL-B-131, and closure heat sealed.

5.1.1.3.2 A Style RSC fiberboard box, Class 2, W5c or W5s compliance symbol, conforming to the requirements of Federal Specification PPP-B-636, shall be employed for the outer carton and designed to snugly enclose the barrier-sealed inner container. The required desiccant shall be suitably positioned within the test set case. For conformance and quantity required see Military Specification MIL-D-3464.

5.1.2 Level B. - (Not applicable)

5.1.3 Level C.

5.1.3.1 Test set units shall be packaged in a manner which will afford adequate protection from deterioration and physical damage during shipment from the contractor or supply source to the first receiving activity for immediate use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

5.2 Packing.

5.2.1 Level A. - In addition to the following, Level A packing shall be in accordance with JAN-P-100.

5.2.1.1 Exterior containers. - Each test set, individually packaged as specified under 5.1.1, shall be packed in an overseas type wood-cleated plywood box or a Class 2, Style 2, 2 1/2, 3 or 4 nailed wood box conforming to the requirements of Federal Specification PPP-B-601 or PPP-B-621, respectively.

5.2.2 Level B. - (Not applicable).

5.2.3 Level C.

5.2.3.1 Test set units shall be packed in a manner which will provide protection from damage during direct shipment from the contractor or supply source to the first receiving activity for immediate use. The type of containers used shall conform to applicable carrier rules and regulations.

5.3 Marking.

5.3.1 Normal markings. - In addition to any special marking required by the contract or order, all marking shall be in accordance with Military Standard MIL-STD-129.

5.3.1.1 For details on marking requirements, see Bureau of Ordnance Drawing Number 1476194.

5.3.1.2 Special markings. - The following special marking shall appear on the top, one (1) side and one (1) end of each shipping container:

DELICATE INSTRUMENT
HANDLE WITH CARE

6. NOTES

6.1 Ordering data. - Procurement documents should specify the title, number and date of this specification, and exceptions to this specification, applicable drawings and other documents. Procurement documents should also specify the desired level of packaging and packing. Level C should not be selected unless it is definitely known that the equipment will be used immediately upon receipt.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

Notice. - When Government drawings, specifications, or other data are used for any purpose other than in connection with a definitely related Government procurement operation, the United States Government thereby incurs no responsibility nor any obligation whatsoever: and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use, or sell any invention that may in any way be related thereto.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T09:37Z
Check the source to verify that this is the current version before use.