MILITARY SPECIFICATION

INVERTER, POWER, STATIC: 10516412

This amendment forms a part of Military Specification MIL-I-60166(MU), dated 14 May 1964.

Paragraph 2.1: Delete the following Military Specification:

"MIL-I-26600 Interference Control Requirements, Aeronautical Equipment"

and substitute the following Military Standards:

"MIL-STD-461 Electromagnetic Interference Characteristics, Requirements for Equipment
MIL-STD-462 Electromagnetic Interference Characteristics, Measurement of"

Paragraph 3.4: Add "(see 6.2(d))".

Paragraph 3.5.2: Delete last sentence and substitute:

"The inverter shall meet the requirements of 3.7 before and after vibration."

Paragraph 3.5.2.1: Add the following new paragraph:

"Monitoring during vibration.- The inverter input voltage shall be 24 vdc. A load of 150 volt amperes at unit power factor shall be applied. The characteristics to be monitored are as follows: input current, voltage output, output current, frequency of output voltage, and the harmonic content of the output waveform. All monitored values shall meet the requirements of 3.7."

Paragraph 3.7: Delete first sentence and substitute the following:

"Before and after vibration (see 3.5.2) the inverter shall meet the requirements of 3.7.1 thru 3.7.6 without spasmodic or intermittent operation, with input voltages of 18 vdc, 24 vdc and 30 vdc."

Paragraph 3.7.5: Delete and substitute the following:

"3.7.5 Harmonic distortion.- The total peak to peak output voltage of the inverter shall not exceed 1.25 times the peak to peak output voltage

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:14Z
Check the source to verify that this is the current version before use.

specified in 3.7.2 and 3.7.3. Duration of transients at the output shall diminish to 1.10 times the peak to peak output voltage, or less, within three cycles. The above requirement shall apply during energizing and deenergizing the inverter under all conditions of output load. The inverter shall have a harmonic distortion of less than 4% for all loads and all power factor ranges between 0.8 leading and 0.6 lagging. With a unity power factor and at a load of 75 VA, the maximum variation of harmonic distortion shall be 1.5%.

Paragraph 3.10: Delete and substitute the following:

* "3.10 Radio interference.- The inverter shall meet the following requirements of MIL-STD-461, Class IC, CE03, CS01, RE02, (T)RE04. Tests are to be performed for broadband interference only.

3.11 Continuity.- The outside case shall be constructed in such a manner that it will provide one conductance path between any two points on the case."

Paragraph 4.3.2, Table II: Delete the following:

"115.	Radio interference	3.10	4.6.11"

and substitute:

"115.	Continuity	3.11	4.6.12"

Paragraph 4.4.1: Add the following control test:

"Radio interference	3.10	4.6.11"

Paragraph 4.4.3, Reliability: Delete in its entirety.

Paragraph 4.6.5: Add the following sentence:

"This test shall only be conducted for Qualification (QPL) (see 4.2.1.2) and as otherwise specified in the contract (see 6.2(d))."

Paragraph 4.6.6.2: Delete the second sentence and substitute the following:

"Before and after vibration, the inverter shall be tested at inputs 18 vdc, 24 vdc and 30 vdc in accordance with 4.6.8 to 4.6.8.6, inclusive to determine compliance with 3.7. During vibration in each of the three mutually perpendicular planes (see 3.5.2), the inverter shall be monitored when energized at 24 vdc with a unity power factor load of 150 VA to determine compliance with 3.5.2.1."

Paragraph 4.6.8.5: Delete last sentence and add the following:

"4.6.8.5 Harmonic distortion.- All measurements shall be made with standard measuring equipment, utilizing a Tektronic #564 storage oscilliscope with a No. 3A1 plug-in module or equivalent test equipment for measuring

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:14Z
Check the source to verify that this is the current version before use.

voltage spikes during switching between loads as specified in 3.7.5."

Paragraph 4.6.8.6, third sentence: Delete "for a minimum of one hour" and substitute "and be stabilized for a period of five minutes."

Paragraph 4.6.11: Delete "MIL-I-26600" and substitute "MIL-STD-462".

Add paragraph 4.6.12 Continuity.- The test for continuity shall be conducted as an inprocess test prior to application of paint finish on the exterior surfaces, to insure that the case mating surfaces have metal to metal contact. This test shall be conducted by placing a potential of 100 milli-volts at one point on the case while isolating the case from ground. Using standard measuring equipment, measure the potential between the other five sides and ground potential. Measured values of this potential should be at least 90 ± 5 milli-volts to insure proper continuity as specified in 3.11.

Paragraph 6.2: Add the following sub-paragraph:

"(d) Compliance with the Reliability requirement and test (see 3.4 and 4.6.5)."

*The outside margins have been marked to indicate where additions to the previous amendment have been made. This has been done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in these notations. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content as written irrespective of the marginal notations and relationship to the last previous issue.

Custodian:

Army - MU

Preparing activity:

Army - MU

Project No. 1220-A126

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:14Z
Check the source to verify that this is the current version before use.