7 April 1975
SUPERSEDING
MIL-B-3694B
25 February 1963

MILITARY SPECIFICATION

BRIDGE, CAPACITANCE-INDUCTANCE-RESISTANCE

AN/URM-90( )

This specification is approved for use by all Departments and Agencies of the Department of Defense

1. SCOPE.

1.1 This specification covers one type of Bridge, Capacitance-Inductance Resistance, hereinafter referred to as "the equipment", that is capable of measuring resistance, capacitance, inductance, the storage factor (Q) of inductors, and the dissipation factor (D) of capacitors.

2. APPLICABLE DOCUMENTS.

2.1 Documents. The following documents of the issue in effect at date of invitation for bids or request for proposal, form a part of the specification to the extent specified herein.

SPECIFICATIONS

FEDERAL

NN-P-71	Pallet, Material Handling, Wood (General Construction Requirements)
PPP-B-585	Box, Wood, Wirewound
PPP-B-601	Boxes, Wood, Cleated-Plywood
PPP-B-621	Box, Wood, Nailed and Lock Corner
PPP-B-636	Box, Fiberboard
PPP-B-640	Box, Fiberboard, Corrugated, Triple-wall
PPP-F-320	Fiberboard; Corrugated and Solid, Steel Stock (Container Grade), and Cut Shapes
PPP-P-291	Paperboard, Wrapping, Cushioning

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

SPECIFICATIONS

FEDERAL

PPP-S-760	Strapping, Non-metallic, (And Connectors)
PPP-T-45	Tape, Gummed, Paper, Reinforced and Plain, for Sealing and Securing
PPP-T-76	Tape, Pressure-Sensitive Adhesive Paper, Water Resistant (For Carton Sealing)
PPP-T-97	Tape, Pressure Sensitive Adhesive, Filament Reinforced
T-T-871	Twine, Cotton, Wrapping
QQ-S-781	Strapping, Steel, Flat and Seals

MILITARY

MIL-E-75	Electron Tube, Preparation for Delivery of
MIL-P-116	Preservation-packaging, Methods of
MIL-P-11268	Parts, Materials, and Processes Used in Electronic Equipment
MIL-M-13231	Marking of Electronic Items
MIL-F-14072	Finish for Ground Signal Equipment

STANDARDS

MILITARY

MIL-STD-105	Sampling Procedures and Tables for Inspections by Attributes
MIL-STD-129	Marking for Shipment and Storage
MIL-STD-147	Palletized and Containerized Unit Loads 40" x 48" 4-Way (Partial) Pallet Skids, Runners, or Pallet-Type Base
MIL-STD-252	Wired Equipment; Classification of Visual and Mechanical Defects
MIL-STD-454	Standard General Requirements for Electronic Equipment
MIL-STD-781	Reliability Tests, Exponential Distribution
MIL-STD-810	Environmental Test Methods

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

DRAWINGS

ELECTRONICS COMMAND

SC-DL-60008	Test Set AN/URM-90 Drawing and Data List
SC-C-82761	Prod, Test
SC-A-46439	List of Accessories for Package Tester

(Copies of specifications, standards and drawings required by contractors in connection with specific procurement functions should be obtained from the procuring activity, or as directed by the contracting officer. Both the title and number or symbol should be stipulated when requesting copies).

3. REQUIREMENTS

3.1 First article. When specified in the contract or purchase order, the contractor shall furnish first article units in accordance with 4.3.

3.2 Construction. The equipment shall be constructed in accordance with SC-DL-60008 and SC-C-82761 and all the requirements specified herein.

3.3 Parts, materials and processes-general. In addition to the requirements of this specification and on the drawings specified in 3.2, the requirements of MIL-P-11268 shall apply.

3.3.1 Cleaning. The equipment shall be cleaned prior to subjection to any first article or quality conformance inspection, and all equipment on contract or purchase order shall be cleaned in the same manner. The cleaning procedure and cleaning agents shall have no deleterious effect on the performance requirements of the equipment. The cleaning process shall remove such contaminants as corrosion products, dust, fingerprints, excess lubricating oils, mold release agents, sand, solder flux residues, outgassing products and any other contaminant which could contribute to corrosion, fungus growth or loss of moisture resistance.

3.4 Finish, protective. The equipment shall be finished in accordance with MIL-F-14072. This includes finish of hardware; such as screws, etc., and necessary touch-up after mounting. The final paint film of type I surfaces shall be final Film E, semigloss, light gray enamel, conforming to MIL-F-14072.

3.5 Marking. The marking shall conform to MIL-M-13231.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

3.5.1 Visibility. Wherever practicable, parts and assemblies shall be so mounted that their identification markings shall be readily visible with a minimum disassembly of the equipment.

3.5.2 Serial numbers. Serial numbers are required on each nomenclatured (item name and type designation) item, except cords and cables.

3.6 Preconditioning.

3.6.1 Bounce preconditioning. Each equipment produced and first article shall be subjected to the bounce preconditoning of 4.6.1. After bounce preconditioning, the equipment shall be inspected for loose or broken parts or controls. If a failure occurs, the loose or broken part or control shall be repaired or replaced and the test repeated. Bounce preconditioning shall be performed prior to electrical preconditioning and Group A inspection.

3.6.2 Electrical preconditioning. Each equipment produced and first article shall be subjected to the electrical preconditioning of 4.6.2. Electrical preconditioning shall be performed after bounce preconditioning and prior to Group A inspection. The equipment shall be monitored for requirements and tests of 3.7.7 and 4.7.7 during period of test.

3.7 Electrical.

3.7.1 DC Resistance range and accuracy. The equipment shall measure resistance values over the range of 1 milliohm to 11 megohms. The accuracies for the indicated LRC DIAL MULTIPLIER ranges are given in the list below:

Range	Accuracy
0.1 ohm	± (0.35% + 1 div on inner LRC dial)
100k ohm	± (0.2% + 1 div on inner LRC dial)
other ranges	± (0.15% + 1 div on inner LRC dial)

The equipment shall be tested in accordance with 4.7.1.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

3.7.2 AC Resistance range and accuracy. The AC resistance range of the equipment is from 1 milliohn to 11 megohms. The accuracies for the indicated values of resistance are given in the list below:

Resistance	Accuracy
less than 1 ohm	± (1% + 1 div on the inner LRC dial)
1.0 to 100k ohms	± (0.5% + 1 div on inner LRC dial)
greater than 100,000 ohms	± (1% + 1 div on the inner LRC dial)

The equipment shall be tested in accordance with 4.7.2.

3.7.3 Capacitance range and accuracy. The equipment shall measure capacitance values over the range of 1 picofarad to 1,100 microfarads. The accuracies for the indicated values of capacitance are given in the list below:

Capacitance	Accuracy
less than 100pF	± (2pF)
100pF to 100uF	± (0.5% + 1 div on inner LRC dial)
greater than 100uF	± (2%)

The equipment shall be tested in accordance with 4.7.3.

3.7.4 Inductance range and accuracy. The equipment shall measure inductance values over the range from one microhenry to 1100 henries. The accuracies for the indicated values of inductance are given in the list below:

Inductance	Accuracy
greater than 10 henries	± 10%
less than 100 uh	± 2 uh
100 uh to 10 henries	± (1.0% + 1 div of inner LRC dial)
* 100 uh to 10 henries	± (1.5% + 1 div of inner LRC dial)

* For CIRCUIT SELECTOR on L and Qx100 position and for inductors with Q < 15.

The equipment shall be tested in accordance with 4.7.4.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

3.7.5 Storage factor (Q) and accuracy. The equipment shall measure storage factors (Q) of inductors over the range from 0.05 to 1,000. The accuracy of the storage factor readings expressed in terms of their reciprocals, dissipation factors (D), are given in the list below:

Inductance	Storage Factor (Q) Accuracy
less than 10 henries	± (5% + 0.0025)
10 henries to 100 henries	± (5% + 0.015)
100 henries to 1000 henries	± (5% + 0.055)

The equipment shall be tested in accordance with 4.7.5.

3.7.6 Dissipation factor (D) range and accuracy. The equipment shall measure the dissipation factors (D) of capacitors over the range from 0.001 to 1.0. The maximum error of the dissipation factor measurement shall be plus or minus (5 percent plus 0.0025) for capacitance values greater than 0.01 microfarad. The equipment shall be tested in accordance with 4.7.6.

3.7.7 Oscillator frequency. The frequency of the equipment's internal oscillator shall be 1,000 Hz ± 10 Hz when tested in accordance with 4.7.7.

3.7.8 Oscillator output voltage. The open circuit output voltage of the equipment's internal oscillator shall be continuously adjustable to a maximum of not less than 12 volts. The equipment shall be tested in accordance with 4.7.8.

3.7.9 Frequency range - External AC generator. The equipment when used in conjunction with an external audio oscillator shall meet the inductance accuracy requirements of 3.7.4 throughout the range of 100 hertz to 10 kilohertz. The equipment shall be tested in accordance with 4.7.9.

3.7.10 High voltage DC bridge excitation. The high voltage DC bridge excitation current required for the resistance measurement function of the equipment shall be not less than 10 milliamperes when tested in accordance with 4.7.10.

3.7.11 Low voltage DC bridge excitation. The low voltage DC bridge excitation current required for the resistance measurement function of the equipment shall be not less than 250 milliamperes when tested in accordance with 4.7.11.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

3.7.12 Noise output. The noise output at the equipment's phone jacks shall not exceed 6 millivolts when tested in accordance with 4.7.12.

3.8 Environmental conditions. The equipment shall be constructed so that no fixed part shall become loose, cracked, flaked, pitted or blistered, no movable part or control shall be shifted in setting, position or adjustment, and no permanent degradation shall be caused in performance below that specified in the following environmental conditions.

3.8.1 Fungus. The equipment, after 28 days of exposure, shall be visually examined, using a 10 power magnifier. The equipment shall show no more than 6 minute unrelated areas, no greater than 0.125 inch in diameter of sparse microbial growth (see 6.5.3) as evidenced by growth colonization (see 6.5.2), which includes branching (see 6.5.1) and sporulation (see 6.5.4), on or within each cubic foot of equipment assembly volume. Isolated instances of partial tubular germination (see 6.5.5) shall not be included in this evaluation. The equipment shall be tested in accordance with 4.8.1.

3.8.2 Low temperature. The equipment shall meet the electrical requirements of 3.7.7 at times specified when tested in accordance with 4.8.2.

3.8.3 High temperature. The equipment shall meet the electrical requirements of 3.7.7 at time specified when tested in accordance with 4.8.3.

3.8.4 Altitude. The equipment shall meet the electrical requirements of 3.7.7 at times specified when tested in accordance with 4.8.4.

3.8.5 Humidity. The equipment shall exhibit no physical damage of parts and material, such as corrosion, rust, blistering, swelling, deterioration, etc., or electrical degradation, and shall meet the electrical requirements of 3.7.7 at times specified, when tested in accordance with 4.8.5.

3.8.6 Vibration. The equipment shall show no evidence of breakage or loosening of parts when tested in accordance with 4.8.6.

3.8.7 Shock, bench handling. The equipment shall show no evidence of physical damage except minor surface abrasion and shall meet the electrical requirements of 3.7.7 at times specified, when tested in accordance with 4.8.7.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

3.9 Interchangeability. Like units, assemblies, subassemblies and replaceable parts shall meet Requirement 7 of MIL-STD-454. Inspection shall be in accordance with 4.9.

3.10 Workmanship. The equipment shall be manufactured and assembled in accordance with Requirement 9 of MIL-STD-454, and with the applicable portions of MIL-P-11268 as follows:

a. Adhesives
b. Cables, cords, and wires, electrical
c. Wire (harnessing)
d. Lubricants
e. Plastic material and parts
f. Rubber
g. Tropicalization of material and parts
h. Wiring and cabling
i. Printed wiring assemblies
k. Screws, other threaded devices, and related parts
l. Tightening of threaded parts
m. Riveting
n. Brazing, soldering, and welding
o. Welding

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. Unless otherwise specified in the contract or purchase order, the contractor is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or purchase order, the contractor may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies, and services conform to prescribed requirements.

4.2 Classifications of inspections. The inspection requirements specified herein are classified as follows:

a. First article inspection (see 4.3). Does not include preparation for delivery.

b. Inspections covered by subsidiary documents (see 4.4).

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

c. Quality conformance inspections.

(1) Quality conformance inspection of equipment before preparation for delivery. (See 4.5)

(2) Quality conformance inspection of preparation for delivery. (See 4.11)

4.3 First article. Unless otherwise specified in the contract or purchase order, the first article inspection shall be performed by the contractor.

4.3.1 First article inspection. The first article inspection shall consist of the inspections specified in subsidiary documents covering the items listed in 4.4, preconditioning specified in 4.6, and the inspections specified for Group A, Group B and Group C (See Tables I, II and III respectively). The inspection shall be performed in the following order: 4.4, 4.6, Group A and Group B for all equipments; and designated equipments for specific subgroups within Group C. After completion of Group C environmental tests, conforming equipments shall be reinspected and shall pass all Group A inspection.

4.3.2 First article data. The first article test plan and test report(s) shall be as required in the contract or purchase order.

4.4 Inspections covered by subsidiary documents. The following shall be inspected under the applicable subsidiary documents as part of the inspection required by this specification, and the inspection requirement specified in the contract or purchase order.

Item	Where required
Parts, materials, and processes-general	3.3
Finish, protective	3.4
Marking	3.5
Workmanship	3.10

4.5 Quality conformance inspection of equipment before preparation for delivery. The contractor shall perform the inspections specified in 4.4, 4.6 and 4.5.1 through 4.5.4. This does not relieve the contractor of his responsibility for performing any additional inspection which is necessary to control the quality of the product and to assure compliance with all specification requirements.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

4.5.1 Group A inspection. Each equipment contract or purchase order shall be inspected for conformance to the inspections specified in Table I. Discrete lots shall be formed from equipments that pass this inspection. Factors of lot composition not defined herein, or in the contract or purchase order shall be in accordance with MIL-STD-105. Each lot shall be subjected to sampling inspection, utilizing the procedures of MIL-STD-105, using the general inspection levels, and AQL's indicated in Table I.

4.5.1.1 Order of inspection within Group A. Group A inspection shall be performed in an order satisfactory to the Government.

Table I Group A inspection

Inspection	Req. Para.	Test Para.	AQL Major	AQL Minor
Visual and Mechanical Workmanship	3.10	4.10	1 dphu*	4 dphu
Electrical				
DC Resistance Range and Accuracy	3.7.1	4.7.1		
AC Resistance Range and Accuracy	3.7.2	4.7.2		
Capacitance Range and Accuracy	3.7.3	4.7.3	2.5 dphu for the group	**
Inductance Range and Accuracy	3.7.4	4.7.4		
Storage factor (Q) and Accuracy	3.7.5	4.7.5		
Dissipation factor (D) range and Accuracy	3.7.6	4.7.6		
Oscillator frequency	3.7.7	4.7.7		
Oscillator output voltage	3.7.8	4.7.8		
Frequency range-External AC Generator	3.7.9	4.7.9		
High voltage DC bridge excitation	3.7.10	4.7.10		
Low voltage DC bridge excitation	3.7.11	4.7.11		
Noise output	3.7.12	4.7.12		

* Defects per hundred units
** All electrical tests are major

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

4.5.2 Group B inspection. Group B inspection shall normally be performed on inspection lots that have passed Group A inspection and on samples selected from equipments that have been subjected to and met the Group A inspection. This inspection shall conform to Table II and to the special inspection levels of Table I of MIL-STD-105.

Table II Group B inspection

Inspection	Req Para.	Test Para.	AQL
Interchangeability	3.9	4.9	6.5 dphu *

* Defects per hundred units

4.5.2.1 Group B sampling plans. The Group B AQL shall be 6.5 percent defective and the inspection level shall be S-4.

4.5.2.2 Order of inspection within Group B. Group B inspection shall be performed in an order satisfactory to the Government.

4.5.3 Group C inspection. Group C inspection shall be performed on equipments that have passed Group A and Group B inspection. The inspection shall consist of the inspections specified in Table III. Samples shall be selected in accordance with 4.5.3.1.

4.5.3.1 Sampling for Group C inspection. Three (3) samples of the complete equipment shall be selected at random, one (1) sample for each Subgroup 1 through Subgroup 3 in Table III. The samples shall be selected at the start of the contract from the first quality conformance inspection lot. These samples shall constitute the Group C requirements for the first 100 units produced.

4.5.3.1.1 Thereafter, two (2) samples of the complete equipment shall be selected at random, one (1) sample for each Subgroup 2 and Subgroup 3 in Table III from every 100 units and fraction thereof produced.

4.5.3.2 Order of inspection within Group C. Group C inspection shall be performed in an order which is satisfactory to the Government.

4.5.3.3 Group C failures. Actions required relative to Group C failures shall be as specified in the contract or purchase order.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

Table III Group C inspection

Inspection	Req Para.	Test Para.
Subgroup 1		
Fungus	3.8.1	4.8.1
Subgroup 2		
Low temperature	3.8.2	4.8.2
High temperature	3.8.3	4.8.3
Altitude	3.8.4	4.8.4
Humidity	3.8.5	4.8.5
Subgroup 3		
Vibration	3.8.6	4.8.6
Shock-bench handling	3.8.7	4.8.7

4.5.4 Reinspection of conforming Group B and C sample equipments. Unless otherwise specified, sample equipments which have been subjected to and passed both Group B and Group C inspection may be accepted on the contract provided all damage is repaired and the sample equipments are resubjected to and pass Group A inspection.

4.5.5 Disposition of Group C sample equipments. Unless otherwise specified, sample equipments which have been subjected to and passed Group C inspection may be delivered on the contract or purchase order, provided sample equipments meet requirements of 4.5.4.

4.6 Preconditioning.

4.6.1 Bounce preconditioning. Each equipment produced and first article shall be placed in its normal operating position on the table of a package tester of suitable capacity as made by the L.A.B. Corporation, Skaneatales, New York with accessories as per Model 10005C and SC-A-46439, or equal. The package tester, shafts in phase, shall have a

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

speed such that it is just possible to insert a 1/32 inch strip of material under one corner or edge of the equipment under test to a distance of 3 inches as the equipment bounces. The equipment shall be subjected to this preconditioning for 1 minute and shall meet the requirements of 3.6.1.

4.6.2 Electrical preconditioning. Each equipment produced and first article shall be placed in its normal operating position on a test table or in a test rack with room temperature at 77° ± 5° F, with specified operating voltage applied from a suitable power source. With all controls in the normal operating position, the equipment shall be turned on and remain on for a continuous 24 hour period and monitored. In case of failure, the equipment shall be repaired, recalibrated, and the electrical preconditioning test repeated for the failed equipment. A failed item analysis report shall be submitted on each failure with contents of report in accordance with 5.10.5 of MIL-STD-781. Each equipment shall meet the requirements of 3.6.2.

4.7 Electrical. The tolerance of the components used in performing the following electrical tests shall be not less than 5 times the accuracy prescribed for each function of the test set. For the following electrical tests, the EXT D-Q binding posts shall be shorted unless indicated otherwise.

4.7.1 DC resistance range and accuracy. Connect the equipment line cord to a power source capable of supplying 115 VAC at 60 Hz.

a. Turn the GENERATOR switch to the INTERNAL POWER OFF position and the POWER switch to ON. Set the DETECTOR switch to the METER position.

b. Connect a decade resistor box to the binding posts marked L and R.

c. Release the galvanometer movement.

d. Position the controls according to the first row of Table IV below, in an order from left to right:

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

TABLE IV Control Positions

DECADE RESISTOR BOX	CIRCUIT SELECTOR	LRC DIAL MULTIPLIER	GENERATOR
.1	R RX1	.1 Ω	DC LO
1	R RX1	1 Ω	DC LO
10	R RX1	10 Ω	DC LO
100	R RX1	100 Ω	DC LO
1,000	R RX1	1,000 Ω	DC LO
10,000	R RX1	10,000 Ω	DC LO
100,000	R RX1	100,000 Ω	DC LO
1,000,000	R RX10	100,000 Ω	DC HI

e. Beginning with the LRC DIAL set at 1.00, adjust the outer dial and then the middle dial until the galvanometer needle is as close to zero as possible.

f. Push in the METER SHUNT button and adjust the inner dial of LRC DIAL until a zero reading is obtained on the galvanometer.

g. Use the formula below to find the value of the decade standard resistor.

R = CIRCUIT SELECTOR reading x LRC DIAL MULTIPLIER reading x LRC DIAL reading.

Record this value.

h. Turn the GENERATOR switch to the INTERNAL POWER OFF position.

i. Repeat steps d. through h. until the remaining rows of settings in Table IV have been completed.

j. The equipment shall meet the requirements of 3.7.1

4.7.2 AC resistance range and accuracy.

a. Turn the GENERATOR switch to the INTERNAL POWER OFF position and the POWER switch to ON. Turn the AMP. RESPONSE to FLAT.

b. Connect a decade resistor box to the binding posts marked L and R.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

c. Set the DETECTOR switch to the INTERNAL position and turn the OSC GAIN control clockwise from the OFF position approximately 1/4 turn.

d. Position the controls according to the first row of Table V below, in an order from left to right:

TABLE V Control Positions

DECADE RESISTOR BOX	CIRCUIT SELECTOR	LRC DIAL MULTIPLIER	GENERATOR
.1	R RX1	.1 Ω	INTERNAL
1	R RX1	1 Ω	INTERNAL
10	R RX1	10 Ω	INTERNAL
100	R RX1	100 Ω	INTERNAL
1,000	R RX1	1,000 Ω	INTERNAL
10,000	R RX1	10,000 Ω	INTERNAL
100,000	R RX1	100,000 Ω	INTERNAL
1,000,000	R RX10	100,000 Ω	INTERNAL

e. Adjust the AMP. GAIN control for minimum shadow width on the electron ray tube.

f. Adjust the OSC. GAIN control toward the HI position to increase the sensitivity of the null indication.

g. Starting with the LRC DIAL set at 1.00, adjust the outer, middle, and inner dial for minimum signal(widest shadow) on the electron ray tube.

h. Use the formula below to find the value of the decade standard resistor.

R = CIRCUIT SELECTOR reading X LRC DIAL MULTIPLIER reading X LRC DIAL reading.

Record this value.

i. Turn the GENERATOR switch to the INTERNAL POWER OFF position.

j. Repeat steps e. through i. until the remaining rows of settings in Table V have been completed.

k. The equipment shall meet the requirements of 3.7.2.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

4.7.3 Capacitance range and accuracy.

a. Set the AMP RESPONSE switch to PEAK.

b. Turn the GENERATOR switch to the INTERNAL POWER OFF position and the POWER switch to ON.

c. Connect a decade capacitor box or standard capacitor to the binding posts marked C. Turn the OSC. GAIN control clockwise from the OFF position approximately 1/4 turn.

d. Set the DETECTOR switch to the INTERNAL position.

e. Position the controls according to the first row of Table VI below, in an order from left to right:

TABLE VI Control Positions

DECADE CAPACITOR BOX	CIRCUIT SELECTOR	LRC DIAL MULTIPLIER	GENERATOR
.00001 uf	C D-Q X .01	.0001 uf	INTERNAL
.0001 uf	C D-Q X .01	.0001 uf	INTERNAL
.001 uf	C D-Q X .01	.001 uf	INTERNAL
.01 uf	C D-Q X .01	.01 uf	INTERNAL
.1 uf	C D-Q X .01	.1 uf	INTERNAL
1 uf	C D-Q X .01	1 uf	INTERNAL
10 uf	C D-Q X .01	10 uf	INTERNAL
100 uf	C D-Q X .01	100 uf	INTERNAL

f. Adjust the LRC DIAL and the D-Q DIAL alternately until the best null indication is obtained. If a sharp null cannot be obtained, operate alternately in small increments the AMP. GAIN and OSC. GAIN controls toward their HI positions until a sharp null is indicated on the electron ray tube.

g. If a wide shadow cannot be obtained on the electron ray tube, repeat step f. with the CIRCUIT SELECTOR switch in the D-Q X.1 position. The CIRCUIT SELECTOR setting which gives the best null indication (widest shadow) is the correct setting.

h. Use the formula below to find the value of the decade capacitor.

C = LRC DIAL reading X LRC DIAL MULTIPLIER reading.

Record this value.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

i. Turn the GENERATOR switch to the INTERNAL POWER OFF position.

j. Repeat steps e. through i. until the remaining rows of setting in Table IV have been completed.

k. The equipment shall meet the requirements of 3.7.3.

4.7.4 Inductance ranges and accuracy.

a. Set the AMP RESPONSE switch to PEAK.

b. Turn the GENERATOR switch to the INTERNAL POWER OFF position and the POWER switch to ON.

c. Connect a decade inductor box or standard inductor to the binding posts marked L and R. Turn the OSC. GAIN control clockwise from the OFF position approximately 1/4 turn.

d. Set the DETECTOR switch to the INTERNAL position.

e. Position the controls according to the first row of Table VII below in an order from left to right:

TABLE VII Control Positions

DECADE INDUCTOR BOX	CIRCUIT SELECTOR	LRC DIAL MULTIPLIER	GENERATOR
.1 mh	L Q X 1	.1 mh	INTERNAL
1 mh	L Q X 1	1 mh	INTERNAL
10 mh	L Q X 1	10 mh	INTERNAL
100 mh	L Q X 1	100 mh	INTERNAL
1 h	L Q X 1	1 h	INTERNAL
10 h	L Q X 1	10 h	INTERNAL
100 h	L Q X 1	100 h	INTERNAL

f. Adjust the LRC DIAL and the D-Q DIAL alternately until the best null indication is obtained. If a sharp null cannot be obtained, operate alternately in small increments the AMP. GAIN and OSC. GAIN controls toward their HI positions until a sharp null is indicated on the electron ray tube.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

g. If a wide shadow cannot be obtained on the electron ray tube, repeat step f. with the CIRCUIT SELECTOR switch in the QX100 position. The CIRCUIT SELECTOR setting which gives the best null indication (widest shadow) is the correct setting.

h. Use the formula below to find the value of the standard measured inductor:

L = LRC DIAL reading X LRC DIAL MULTIPLIER reading.

Record this value.

i. Turn the GENERATOR switch to the INTERNAL POWER OFF position.

j. Repeat steps e. through i. until the remaining rows of settings in Table VII have been completed.

k. The equipment shall meet the requirements of 3.7.4.

4.7.5 Storage factor (Q) and accuracy.

a. Set the AMP RESPONSE switch to PEAK.

b. Turn the GENERATOR switch to the INTERNAL POWER OFF position and POWER switch to ON.

c. Turn the OSC. GAIN control clockwise from the OFF position approximately 1/4 turn.

d. Set the DETECTOR switch to the INTERNAL position.

e. Connect an inductor with a Q as indicated in Table VIII to the binding posts marked L and R, and position the controls according to the first row of Table VIII below in an order from left to right:

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

TABLE VIII Control Positions

INDUCTOR CONNECTED TO L AND R BINDING POSTS * (See Note below)	CIRCUIT SELECTOR	LRC DIAL MULTIPLIER	GENERATOR
100 mh, Q = .1	L D-Q X 1	100 mh	INTERNAL
100 mh, Q = 1	L D-Q X 1	100 mh	INTERNAL
100 mh, Q = 10	L D-Q X 1	100 mh	INTERNAL
100 mh, Q = 100	L Q X 100	100 mh	INTERNAL
100 mh, Q = 1000	L Q X 100	100 mh	INTERNAL

* The inductor must have the indicated Q at 1000 Hz.

f. Adjust the LRC DIAL and the D-Q DIAL alternately until the best null indication is obtained, operate alternately in small increments the AMP GAIN and OSC. GAIN controls toward their HI positions until a sharp null is defined on the electron ray tube.

g. Use the formula below to find the measured Q of the inductor:

Q = Q and D-Q DIAL reading X CIRCUIT SELECTOR reading.

Record this value.

h. Turn the GENERATOR switch to the INTERNAL POWER OFF position.

i. Repeat steps e. through h. until the remaining rows of setting in Table VIII have been completed.

j. The equipment shall meet the requirements of 3.7.5.

4.7.6 Dissipation factor (D) range and accuracy.

a. Set the AMP RESPONSE switch to PEAK.

b. Turn the GENERATOR switch to the INTERNAL POWER OFF position and POWER switch to ON.

c. Turn the OSC. GAIN control clockwise from the OFF position approximately 1/4 turn.

d. Set the DETECTOR switch to the INTERNAL position.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

e. Connect a capacitor with a dissipation factor (D) as indicated in Table IX to the binding posts marked C, and position the controls according to the first row of Table IX below in an order from left to right:

TABLE IX Control Positions

CAPACITOR CONNECTED TO C BINDING POSTS *	CIRCUIT SELECTOR	LRC DIAL MULTIPLIER	GENERATOR
.1 uF, D = .01	C D-Q X .01	.1 uF	INTERNAL
.1 uF, D = .1	C D-Q X .1	.1 uF	INTERNAL
.1 uF, D = 1	C D-Q X .1	.1 uF	INTERNAL

*The capacitor must have the indicated D at 1000 Hz.

f. Adjust the LRC DIAL and the D-Q DIAL alternately until the best null indication is obtained. If a sharp null cannot be obtained, operate alternately in small increments the AMP. GAIN and OSC. GAIN controls toward their HI positions until a sharp null is indicated on the electron ray tube.

g. Use the formula below to find the measured value of the dissipation factor of the capacitor:

D = Q and D-Q DIAL reading X CIRCUIT SELECTOR reading.

Record this value.

h. Turn the GENERATOR switch to the INTERNAL POWER OFF position.

i. Repeat steps e. through h. until the remaining rows of settings in Table IX have been completed.

j. The equipment shall meet the requirements of 3.7.6.

4.7.7 Oscillator frequency.

a. Turn the CIRCUIT SELECTOR switch to the C and D-Q X 0.1 position.

b. Turn the LRC DIAL MULTIPLIER to the 100 uF position on the C scale.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

c. Remove the shorting bar from the EXT. D-Q binding posts and set the DETECTOR switch to the EXTERNAL position.

d. Move the OSC. GAIN control clockwise to the ON position.

e. Connect an electronic frequency counter to the red L and R (high) and the red C (high) binding posts.

f. Turn the GENERATOR switch to the INTERNAL position and the POWER switch to ON. Record the counter frequency.

g. The equipment shall meet the requirements of 3.7.7.

4.7.8 Oscillator output voltage.

a. Turn the CIRCUIT SELECTOR switch to the C and D-Q X .1 position.

b. Turn the LRC DIAL MULTIPLIER to the .1 uF position on the C scale.

c. Remove the shorting bar from the EXT. D-Q binding posts and set the DETECTOR switch to the EXTERNAL position.

d. Move the OSC. GAIN control clockwise to the ON position.

e. Connect a vacuum tube voltmeter to the red L and R (high) and the red C (high) binding posts.

f. Turn the GENERATOR switch to the INTERNAL position and the POWER switch to ON. Record voltage reading.

g. The equipment shall meet the requirements of 3.7.8.

4.7.9 Frequency range - External AC Generator.

a. Connect the OUTPUT ground terminal of an audio generator to EXT. GEN. binding post marked LO. Connect the other OUTPUT terminal of the audio generator to the red EXT. GEN. binding post.

b. Perform test 4.7.4 at 100 Hz, and 10,000 Hz with the following changes in control settings:

(a) Set the AMP RESPONSE to FLAT when PEAK is specified.

(b) Set the GENERATOR switch to EXTERNAL when INTERNAL is specified.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

c. Make sure the chassis of the equipment and the chassis of the audio generator remain electrically isolated, or improper readings on the equipment will result. Do not connect a common ground between the cases of the two units.

d. The equipment shall meet the requirements of 3.7.9.

4.7.10 High voltage DC bridge excitation.

a. Turn the CIRCUIT SELECTOR switch to the R and R X 1 position.

b. Turn the LRC DIAL MULTIPLIER to the 100 position on the R scale.

c. Remove the shorting bar from the EXT. D-Q binding posts and set the DETECTOR switch to the EXTERNAL position.

d. Connect an ammeter between the red L and R (high) and the red C (high) binding posts.

e. Turn the GENERATOR switch to the DC HI position and the POWER switch to ON. Record the current value.

f. The equipment shall meet the requirements of 3.7.10.

4.7.11 Low voltage DC bridge excitation.

a. Turn the CIRCUIT SELECTOR switch to the R and R X 1 position.

b. Turn the LRC DIAL MULTIPLIER to 100 position on the R scale.

c. Remove the shorting bar from the EXT. D-Q binding posts and set the DETECTOR switch to the EXT. position.

d. Connect an ammeter between the red L and R (high) and the red C (high) binding posts.

e. Turn the GENERATOR switch to the DC LO position and the POWER switch to ON. Record the current value.

f. The equipment shall meet the requirements of 3.7.11.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

4.7.12 Noise output.

a. Turn the GENERATOR switch to the EXTERNAL position.

b. Set the DETECTOR switch to the EXTERNAL position.

c. Turn the OSC. GAIN counterclockwise to the OFF position.

d. Set the AMP RESPONSE to PEAK and AMP GAIN on LO.

e. Connect a vacuum tube voltmeter to the phone jacks.

f. Turn the POWER switch to ON. Record the voltage.

g. The equipment shall meet the requirements of 3.7.12.

4.8 Environmental. The equipment shall be tested in accordance with the following environmental conditions.

4.8.1 Fungus. The equipment in its normal operating configuration shall be subjected to the fungus test specified in Method 508, Procedure I of MIL-STD-810. There shall be abundant growth colonization (See 6.5.2) on 50 percent or more of the area of the control item after 14 and 28 days. No cleaning of the equipment is permitted for 72 hours prior to the fungus test. Inability of the equipment to meet the requirements of 3.8.1 shall constitute failure of this test.

4.8.2 Low temperature. The equipment in its normal operating configuration shall be subjected to the low temperature test specified in Procedure I, Method 502 of MIL-STD-810, with temperatures in Step 2 held for 24 hours and in Step 4 held for 4 hours, and shall meet the requirements of 3.8.2. The low temperature extremes for this test are -4° operating and -65° F storage.

4.8.3 High temperature. The equipment in its normal operating configuration shall be subjected to the high temperature test specified in Procedure I, Method 501 of MIL-STD-810, with temperature in Step 3 held for 24 hours instead of 48 hours and in Step 4 held for 4 hours, and shall meet the requirements of 3.8.3. The high temperature extremes for this test are 125° F operating and 160° F storage.

4.8.4 Altitude. The equipment in its normal operating configuration shall be subjected to the altitude test specified in Procedure I, Method 500 of MIL-STD-810. with altitude in Step 3 held for 1 hour, and shall meet the requirements of 3.8.4.

4.8.5 Humidity. The equipment shall be subjected to the humidity test specified in Method 507, Procedure II of MIL-STD-810, with test measurements during the 24 to 28 hour period and last 5 hour period of each cycle. Failure of the equipment to meet the requirements of 3.8.5 shall constitute failure of test.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

4.8.6 Vibration. The equipment shall be subjected to the vibration test specified in Part I, Procedure IX, Method 514 of MIL-STD-810, in a horizontal plane parallel to the major horizontal axis of the equipment; horizontal, at right angles to the major horizontal axis of the equipment; and vertical to the major axis of the equipment; and shall meet the requirements of 3.8.6.

4.8.7 Shock, bench handling. The equipment shall be subjected to the bench handling shock test specified in Procedure V, Method 516 of MIL-STD-810, and shall meet the requirements of 3.8.7.

4.9 Interchangeability. The dimensions listed below shall be gaged or measured to determine conformance to the physical interchangeability requirements of 3.9. When a listed dimension is not within specified or design limits, it shall be considered a major defect.

a. External and internal dimensions of case, cover and insertable assemblies, when such dimensions affect mating of parts.

b. Dimensions of cavities, when such dimensions affect insertion of items.

c. Location of hinges and fasteners on separable parts or assemblies which must mate, such as case, covers and mountings.

d. Location of crystal test holders, battery holder and terminals.

e. Location of switches, sockets and fasteners.

f. Location of covers and fasteners on carrying case which must mate.

g. Location of panel mounting screw holes on basic unit for mating with case.

h. Location of connectors, locking pins, fasteners, slides, and mountings which receive mating parts or plug-in assemblies and major units; and location of the mating parts on the plug-in assembly or major unit.

i. Size and form of special threads.

4.10 Visual and Mechanical. The equipment shall be subjected to a thorough visual and mechanical inspection. The defects shall be classified in accordance with MIL-STD-252.

4.11 Quality conformance inspection of preparation for delivery. Preparation for delivery shall be inspected in accordance with MIL-P-116 to determine conformance to the requirements of Section 5.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

5. PREPARATION FOR DELIVERY.

5.1 Preservation and packaging. Preservation and packaging shall be level A or C, as specified. (See 6.2(b)).

5.1.1 Level A.

5.1.1.1 Cleaning. The equipment shall be cleaned in accordance with process C-1 of MIL-P-116.

5.1.1.2 Drying. The equipment shall be dried in accordance with the applicable procedure of MIL-P-116.

5.1.1.3 Preservative application. None required.

5.1.1.4 Unit Packaging. Unit packaging shall be in accordance with the methods prescribed in MIL-P-116 as specified herein.

5.1.1.4.1 Technical manuals. Each technical manual shall be packaged method 1C-1.

5.1.1.4.2 Electron tubes (spares). Spare tubes shall be packaged individually in accordance with MIL-E-75.

5.1.1.4.3 Fuses and lamps (spares). Each spare fuse and lamp shall be packaged individually method III. Cushion by wrapping in paperboard conforming to PPP-P-291 and secure with tape conforming to PPP-T-45.

5.1.1.4.4 Test leads CX-3644/U and CX-3645. Each test lead shall be packaged method III. Coil each lead into a coil of proportionate dimensions and tie in three places with cotton twine conforming to T-T-871.

5.1.1.4.5 Equipment, AN/URM-90( ). Each equipment shall be packaged method III. Place the spare parts, packaged as specified in 5.1.1.4.2 through 5.1.1.4.4, within the compartment provided in the case cover. Close the case and secure all fastenings. Cushion the case on all surfaces with cells or pads or both fabricated of fiberboard conforming to PPP-F-320, type CF, class weather-resistant designed to protect all projections and absorb the shock of impact in handling and transit. Place the cushioned case within a close-fitting fiberboard box conforming to PPP-B-636, W5c. Place the technical literature, packaged as specified in 5.1.1.4.1, on top of the contents, directly under the lid of the box. Close the box in accordance with the appendix of the box specification.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

5.1.2 Level C. Each clean and dry equipment shall be individually packaged in a manner that will afford adequate protection against corrosion, deterioration and physical damage during shipment from supply source to the first receiving activity.

5.2 Packing. Packing shall be level A, B or C, as specified. (See 6.2(b)).

5.2.1 Level A.

5.2.1.1 Palletized load. A quantity of equipments, packaged as specified in 5.1, shall be placed on pallets in conformance with MIL-STD-147, load type 1, with a weather-resistant fiberboard cap (storage aid 4) positioned over the load.

5.2.1.2 Less than palletized load. When quantities per destination are less than a pallet load a quantity of equipment, packaged as specified in 5.1, shall be packed within a close-fitting fiberboard box conforming to PPP-B-640, class 2. Closure shall be in accordance with the appendix of the box specification.

5.2.2 Level B.

5.2.2.1 Palletized load. A quantity of equipments, packaged as specified in 5.1, be palletized as specified in 5.2.1.1, except that the fiberboard caps shall be class domestic.

5.2.2.2 Less than palletized load. When quantities per destination are less than a pallet load, a quantity of equipments, packaged as specified in 5.1, shall be packed within a close-fitting fiberboard box conforming to PPP-B-640, class 1. Closure shall be in accordance with the appendix of the box specification.

5.2.3 Level C.

5.2.3.1 Palletized load. A quantity of equipments, packaged as specified in 5.1, shall be palletized with pallets and caps of the type, size and kind commonly used for the purpose and shall conform to the applicable carrier rules and regulations.

5.2.3.2 Less than palletized load. Equipments, packaged as specified in 5.1, shall be packed in shipping containers in a manner that will afford adequate protection against damage during direct shipment from the supply source to the first receiving activity. These packs shall conform to the applicable carrier rules and regulations.

5.3 Marking. In addition to any special marking required by the contract or order, each unit package, interior container and palletized load shall be marked in accordance with MIL-STD-129.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

5.4 General.

5.4.1 Army procurements (see 5.2.1, 5.2.2 and 5.2.3).

5.4.1.1 Level A packing shall be as follows:

5.4.1.1.1 Palletized load. A quantity of equipments, packaged as specified in 5.1, shall be placed on a pallet, load type 1, conforming to MIL-STD-147 except that the pallet shall be softwood conforming to NN-P-71, type IV, size 2. A fiberboard cap shall be employed over the load having two sides extending down the stacked load at least 12 inches to accommodate marking requirements. The cap shall be fabricated of fiberboard conforming to PPP-F-320, class weather-resistant, W5s or V3c. The load shall be "bonded" to the pallet by strapping conforming to QQ-S-781, Type I, finish A or shrink film.

5.4.1.1.2 Less than palletized load. When quantities per destination are less than a pallet load, the item packaged as specified in 5.1, shall be waterproofed, with tape conforming to PPP-T-76, in accordance with the taping requirements of the appendix of the box specification. A quantity of the waterproofed containers shall be packed within a close-fitting box conforming to PPP-B-601, overseas type; PPP-B-621, style 4, class 2; or PPP-B-585, style 2 or 3, class 3. When the gross weight exceeds 200 pounds, or the container length and width is 48 x 24 inches or more and the weight exceeds 100 pounds, 3 x 4 inch skids, laid flat, shall be applied in accordance with the requirements of the container specification, or if not specified in the specification, in a manner which will adequately support the item and facilitate the use of material handling equipment. Closure and strapping shall be in accordance with the applicable container specification, or appendix thereto except that metal strapping shall conform to QQ-S-781, type 1, finish A.

5.4.1.2 Level B packing shall be as follows:

5.4.1.2.1 Palletized load. A quantity of equipments, packaged as specified in 5.1, shall be palletized as specified in 5.4.1.1.1.

5.4.1.2.2 Less than palletized load. When quantities per destination are less than a pallet load, a quantity of equipments, packaged as specified in 5.1, shall be packed within a close-fitting fiberboard box conforming to PPP-B-640, class 2, style E, or PPP-B-636, type CF, class weather-resistant, variety DW. The gross weight of boxes conforming to PPP-B-640 shall not exceed 250 pounds. When the gross weight exceeds 200 pounds, or the container length and width is 48 x 24 inches or more and the weight exceeds 100 pounds, containers will be pallet-mounted on pallets conforming to NN-P-71, type IV. Closure shall be in accordance with the appendix of the applicable box specification. Reinforcing shall be by pressure-sensitive filament tape banding or non-metallic strapping conforming to PPP-T-97, type IV and PPP-S-760, type II, respectively; selection of the material and application shall be in accordance with the appendix of the applicable box specification.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

5.4.1.3 Level C packing shall be as follows:

5.4.1.3.1 Palletized load. A quantity of equipments, packaged as specified in 5.1, shall be palletized as specified in 5.4.1.1.1, except that the fiberboard caps shall be class domestic.

5.4.1.3.2 Less than palletized load. When quantities per destination are less than a pallet load, a quantity of equipments, packaged as specified in 5.1, shall be packed as specified in 5.4.1.2.2, except that the fiberboard boxes shall conform to PPP-B-640 and PPP-B-636, class 1 and class domestic, respectively, and reinforcing shall not be required for boxes conforming to PPP-B-636.

5.4.2 Navy procurements. For Navy procurements, the use of polystyrene loose fill material (such as strips, strands and beads) is prohibited for packaging and packing applications.

6. NOTES

6.1 Intended use. The equipment is useful for any general purpose testing of components. It is best suited for use at the fourth or fifth echelon level of maintenance.

6.2 Ordering data. Procurement documents should specify the following:

a. Title, number and date of this specification and any amendment thereto.

b. Level of preservation and packaging and packing (see Section 5).

c. When rough handling and functional tests are required.

d. Quantity of first articles required.

e. Place of final inspection.

f. Technical literature required.

g. Quantity of tools and running spare parts required.

h. Marking for shipment and shipping containers.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

6.3 Nomenclature. The contractor should apply the nomenclature (item name and type designation) in accordance with the applicable clause in the contract. The parenthesis in the type designation will be deleted or replaced by a letter identifying the particular design, for example: AN/URM-73( ) to AN/URM-73C.

6.4 Group C inspection. Approval to ship may be withheld at the discretion of the Government, pending the decision from the contracting officer on the adequacy of corrective action. (see 4.5.3.3)

6.5 Definitions.

6.5.1 Branching. Branching is a connected arrangement of filaments, formed by shoots or secondary stems growing from the main stem or filament (hypha).

6.5.2 Growth colonization. Growth colonization is a mass of individual plants generally of one species, living together; or a group of hyphne which is formed from one spore or cell and may be one individual plant. Colonization which completely covers the surface of the nutrient material, constitutes abundant growth.

6.5.3 Microbial growth. Microbial growth is the growth of very minute organisms. Such organisms when present in large numbers may provide a colony visible to the naked eye.

6.5.4 Sporulation. Sporulation is the formation of minute unicellular reproductive or dormant bodies, called spores.

6.5.5 Tubular germination. Tubular germination is partial growth by the production of hyphne, which are tubular shaped individual spores. Tubular germination constitutes restricted growth not proceeding to colonization.

6.6 Sampling inspection. Sampling inspection by the Government will be limited to the amount deemed necessary to determine compliance with the contract or purchase order and will be limited in severity to the definitive quality assurance provisions established in this specification and the contract. The amount of sampling inspection by the Government will be adjusted to make maximum utilization of the contractor's quality control system and the quality history of the product.

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

Custodians:
Army - EL
Navy - SH
Air Force -

Preparing Activity:
Army - EL

Review activities:
Army - AT, ME, AV
Navy - AS
Air Force -

User Activities:
Army - MU
Navy - OS, MC, SH
Air Force -

Project number: 6625-0554

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 22-R255

INSTRUCTIONS: This sheet is to be filled out by personnel, either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments and suggestions submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or serve to amend contractual requirements.

SPECIFICATION MIL-B-3694C BRIDGE, CAPACITANCE-INDUCTANCE-RESISTANCE AN/URM-90( )

ORGANIZATION

CITY AND STATE

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

   A. GIVE PARAGRAPH NUMBER AND WORDING.

   B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

   ☐ YES ☐ NO *(If "yes", in what way?)*

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity)*

SUBMITTED BY *(Printed or typed name and activity - Optional)*

DATE

DD, FORM 1 JAN 66 1426 REPLACES EDITION OF 1 OCT 64 WHICH MAY BE USED.

ESC-FM 1068-68

To detach this form, cut along this line

Source: https://assist.dla.mil -- Downloaded: 2026-10-16T21:15Z
Check the source to verify that this is the current version before use.