MIL-T-48291 (PA)
5 FEBRUARY 1974
SUPERSESSION DATA
(See 6.4)

MILITARY SPECIFICATION

TEST SET, ELECTRICAL CIRCUIT, BOMB DISPENSER A/E 24T-80

This Specification is approved for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 This Specification covers the metal parts for one type of test set designated as Test Set, Electrical Circuit, Bomb Dispenser A/E 24T-80.

2. APPLICABLE DOCUMENTS

2.1 The following documents of the issue in effect on date of invitation for bids or request for proposals, form a part of this specification to the extent specified herein.

SPECIFICATIONS

MILITARY

MIL-A-2550	-	Ammunition and Special Weapons; General Specification For.
MIL-A-8625	-	Anodic Coatings for Aluminum and Aluminum Alloys

STANDARDS

MILITARY

MIL-STD-105	-	Sampling Procedures and Tables for Inspection by Attributes (ABC-STD-105)

FSC: 4925

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

MIL-STD-109 - Quality Assurance Terms and Definitions
MIL-STD-202 - Test Methods for Electronic and Electrical Component Parts
MIL-STD-1168 - Lot Numbering of Ammunition
MIL-STD-1235 - Single and Multilevel Continuous Sampling Procedures and Tables for Inspection by Attributes

DRAWINGS

U.S. ARMY PICATINNY ARSENAL

PRODUCT AND PACKAGING DRAWINGS

9209945 or 9280146 as applicable - Test Set, Electrical Circuit, Bomb Dispenser A/E 24T-80
9218792 - Drum, Metal Shipping for Test Set, Electrical Circuit, Bomb, Dispenser: A/E 24T-80

(Copies of specifications, standards, drawings and publications required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the Contracting Officer.)

3. REQUIREMENTS

3.1 Material.-Materials shall be in accordance with the applicable drawings and specifications.

3.2 Assembly.-The assembly shall comply with all requirements specified on Drawing (dwg.) 9209945 or 9280146 as applicable (see 6.1), and with all requirements specified in applicable specifications.

3.3 Continuity and resistance of the electrical circuits of the cable assemblies.

3.3.1 Power cable No. 1 assembly.-The power cable No. 1 assembly shall show evidence of continuity from pin "A" of the connector plug to the red banana plug and from pin "B" of the connector plug to the black banana plug and shall exhibit no more than 0.25 ohms resistance.

3.3.2 Power cable No. 2 assembly.-The power cable No. 2 assembly shall show evidence of continuity from pins "t", "x" and

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

"y" of the male connector to pin "A" of the female connector and from pin "BB" of the male connector to pin "B" of the female connector and shall exhibit no more than 0.25 ohms resistance.

3.3.3 Continuity. - All cables shall have a maximum resistance of two hundred (200) milliohms between all connected pins on the cable.

3.4 Insulation Resistance. - All cables shall not indicate a current leakage greater than two (2) microamperes between all pins on the cable when it is tested at five hundred plus fifty (500 + 50) volts direct current for a minimum of ten (10) seconds.

3.5 Functioning of the test, set, electrical circuit, bomb dispenser, A/E 24T-80.

3.5.1 External power source circuit.-The external power source circuit shall show evidence of functioning when tested as specified in 4.4.3.1.

3.5.2 Press to test lamp assemblies.-Each press to test lamp shall light when tested as specified in 4.4.3.2.

3.5.3 Safe - safe check circuits.-The safe circuit and the safe check circuit shall show evidence of functioning when tested as specified in 4.4.3.3.

3.5.4 Fire circuit.-The fire circuit shall show evidence of functioning when tested as specified in 4.4.3.4.

3.5.5 Manual advance circuit.-The manual advance circuit shall show evidence of functioning when tested as specified in 4.4.3.5.

3.5.6 "35 - 39" and "40" lamp circuits.-The "35 - 39" lamp circuit and the "40" lamp circuit shall show evidence of functioning when tested as specified in 4.4.3.6.

3.5.7 1 - 40 indicator circuits.-Each indicator circuit shall show evidence of functioning when tested as specified in 4.4.3.7.

3.6 Workmanship.-All parts and assemblies shall be fabricated and finished in a thorough workmanlike manner. They shall be free of burrs, chips, sharp edges, cracks, unblended radii, surface defects, dirt, grease, rust, corrosion productions, and other

Source: https://assist.dla.mil -- Downloaded: 202640-26T03:55Z
Check the source to verify that this is the current version before use.

foreign matter. The cleaning method used shall not be injurious to any parts, nor shall the parts be contaminated by the cleaning agents. All markings and stampings shall be neat and sharply defined.

3.7 First article inspection.-This specification contains technical provisions for first article inspection. Requirements for submission of first article samples by the contractor shall be as specified in the contract.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for Inspection.-Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements. Reference shall be made to MIL-STD-109 to define terms used herein. The provisions of MIL-A-2550 shall apply.

4.1.1 Submission of Product.-At the time each completed lot of items deliverable under the contract is submitted to the Government for acceptance, the contractor shall supply the following information accompanied by a certificate which attests that the information provided is correct and applicable to the product being submitted.

a. A statement that the lot complies with all of the quality assurance provisions specified in this specification.
b. Drawing and specification number and date, together with identification and date of changes thereto.
c. A statement that all material purchased by the contractor meets requirements, when such material is controlled by Government or commercial specifications referenced in any of the contractual documents, and that certificates of conformance are on file and available for review.
d. Number of items in the lot.
e. Date submitted.

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the currentversion before use.

The certificate shall be signed by a responsible agent of the certifying organization. The initial certificate submitted shall be substantiated by evidence of the agent's authority to bind his principal. Substantiation of the agents authority will not be required with subsequent certificates unless, during the course of the contract, this authority is vested in another agent of the certifying organization.

4.2 First Article Inspection

4.2.1 Submission.-Prior to the start of regular production the contractor shall submit a first article sample (see 6.1c) to a Government approved facility as designated by the contracting officer for evaluation in accordance with the provisions of 4.2.2 and 4.2.3. The first article sample shall consist of the following:

Component	Quantity
a. Test Set, Electrical Circuit, Bomb Dispenser A/E 24T-80 (9209945 or 9280146, as applicable	1
b. Power Cable No. 1 Assembly (9209961)	2
c. Power Cable No. 2 Assembly (9209963)	2
d. Test Cable Assembly (9219850 or 9280149, as applicable	2
e. Cable, Assembly - Switch, Electrical (8860162)	2

In addition, panels or coupons of each coating process, of the size and number as specified in the applicable finish specifications for the following items shall be submitted:

a. Plate, Relay Mounting (9219844)

b. Panel (9219841)

All parts and completed assemblies shall have been produced by the contractor or furnished by a supplier and which have been manufactured using the same production processes, procedures and equipment which will be used in fulfilling the contract. All parts and materials including packaging and packing shall be obtained from the same source of supply as will be used in regular production.

performed as specified in [illegible]

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

Prior to submission, the contractor shall inspect the sample to the degress necessary to assure that it conforms to the requirements of the contract and submit a record of this inspection with the sample. including a certificate of conformance for materials. A sample containing known defects will not be submitted unless specifically authorized by the Contracting Officer. A first article sample, or portion thereof, as directed by the Contracting Officer, shall also be submitted whenever there is a lapse in production for a period in excess of 90 days or whenever a change occurs in manufacturing process, material used, drawing or specification such as to significantly affect product uniformity as determined by the Government.

4.2.2 Inspections to be performed.-Assemblies and components will be subjected by the Government to any or all of the examinations and tests specified in this specification and any or all requirements of the applicable drawings.

4.2.2.1 Salt Spray. - The panels or coupons of each part specified in 4.2.1 shall be subjected to this test after classification of defects and other inspections have been performed as specified in 4.2.2. This test shall be performed as specified in MIL-A-8625 except that exposure time shall be 96 hours. Rejection criteria shall be as specified in the finish specification.

4.2.3 Rejection. - If any component or subassembly fails to comply with any or all of the applicable requirements, the first article sample shall be rejected. The Government reserves the right to terminate its inspection upon any failure of an inert component or subassembly to comply with any of the stated requirements.

4.3 Inspection provisions

4.3.1 Lot formation.-The term "inspection lot" as used in this specification is defined as an essentially homogeneous collection of units of product from which a representative sample is drawn and inspected to determine conformance with applicable requirements. The sample selected shall represent only that quantity of units from which the sample was drawn and shall not be construed to represent any prior or subsequent quantities presented for inspection. Homogeneity shall be considered to exist

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

provided the inspection lot has been produced by one manufacturer in one unchanged process using the same materials and methods in accordance with the same drawings, same drawing revisions, same specifications and same specification revisions and complies with the provisions for submission of product as specified in MIL-STD-105. Changes to the process, specifications, or drawings not affecting safety, performance, interchangeability, or storage, as determined by the Government, shall not be deemed to alter the homogeneity of an inspection lot. All material submitted for inspection in accordance with this specification shall comply with the homogeneity criteria specified herein regardless of the type of sampling procedure which is being applied to determine conformance with requirements. Lot numbering, as required, shall be in accordance with MIL-STD-1168.

4.3.2 Examination.-The examinations listed in the following subparagraphs shall be performed on inspection lots (see 4.3.1) of the components or assemblies designated in the applicable paragraph headings. Inspection for critical defects (and major defects, when so specified) shall be 100 percent. Sampling plans for major and minor defects shall be in accordance with MIL-STD-105 except that continuous sampling plans in accordance with MIL-STD-1235 may be used if approved by the Government. Instead of applying the AQL's designated herein to the groups of major and minor defects listed, the contractor may elect to apply an AQL of 0.40 percent for each major defect and an AQL of 0.65 percent for each minor defect. When this method is elected, it shall be applied to all of the major and minor defects listed in the applicable sub-paragraph of this section, except where 100 percent inspection is specified, and be documented as part of the contractor's inspection system. Equipment necessary for the performance of the inspections listed shall be in accordance with 4.3.4.

4.3.2.1 Panel assembly (see Dwg. 9219840 covering a detail of Dwg. 9209945).

Categories	Defects	Method of Inspection	Code No. (see 6.2)
Critical:	None defined.		
Major:	AQL 0.65 percent		
101.	Any component missing, damaged or improperly assembled.....	Visual	01001

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

102.	Wiring incorrect and/or not laced	Visual	01002
103.	Soldering improper	Visual	01003
Minor:	AQL 1.00 percent		
201.	Marking on panel misleading, misoriented or unidentifiable	Visual	01004
202.	Evidence of poor workmanship (see 3.6)	Visual	01005

4.3.2.2 Power cable No. 1 assembly (see Dwg. 9209961 covering a detail of dwg. 9209945).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined.		
Major:	AQL 0.40 percent		
101.	Improper wiring between pin "A" of the connector and the red banana plug, or pin "B" of the connector and the black banana plug (prior to assembling connector clamp)	Visual	02001
102.	Any component missing or damaged	Visual	02002
Minor:	AQL 1.50 percent		
201.	Length of cable incorrect	Gage	02003
202.	Length of banana plug leads incorrect	Gage	02004
203.	Evidence of poor workmanship (see 3.6)	Visual	02005

4.3.2.3 Power cable No. 2 assembly (see Dwg. 9209963 covering a detail of dwg. 9209945).

Categories	Defects	Method of Inspection	Code No.
Major:	AQL 0.65 percent		
101.	Improper wiring between connectors (prior to assembling connector backshells)	Visual	03001

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

102.	Incorrect color coded wires between connectors (prior to assembling connector backshells)	Visual	03002
103.	Evidence of more than four (4) pins, as shown on drawing, in male connector (prior to assembling connector backshell)	Visual	03003
104.	Any component missing or damaged	Visual	03004

Minor: AQL 1.00 percent

201.	Length of cable incorrect	Gage	03005
202.	Evidence of poor workmanship (see 3.6)	Visual	03006

4.3.2.4 Test cable assembly (see Dwg. 9219850 covering a detail of dwg. 9209945 or 9280149 covering a detail of dwg. 9280146, as applicable).

Categories	Defects	Method of Inspection	Code No.

Critical: None defined.

Major: AQL 0.40 percent

101.	Improper wiring between connectors (prior to securing connectors)	Visual	04001
102.	Any component missing or damaged	Visual	04002

Minor: AQL 1.00 percent

201.	Length of cable incorrect	Gage	04003
202.	Evidence of poor workmanship (see 3.6)	Visual	04004

4.3.2.5 Cable Assembly - Switch Electrical (see dwg. 8860162 covering a detail of dwg. 9209945.)

Categories	Defects	Method of Inspection	Code No.

Critical: None defined

Major: AQL 0.40 percent

101.	Potting not flush	Visual	12001

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

102.	Any component missing or damaged	Visual	12002
Minor:	AQL 1.00 percent		
201.	Length of cable incorrect	Gage	12003
202.	Evidence of poor workmanship	Visual	12004

4.3.2.6 Test set, electrical circuit, bomb dispenser A/E 24T-80 (see Dwg. 9209945 or 9280146, as applicable).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined.		
Major:	AQL 0.40 percent		
101.	Any cable missing.....	Visual	05001
102.	Decal missing.....	Visual	05002
Minor:	AQL 1.00 percent		
201.	Any mounting screw missing.....	Visual	05003
202.	Evidence of poor workmanship (see 3.6).....	Visual	05004

4.3.2.7 Drum, metal, shipping (before closing) (see Dwg. 9218792).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined.		
Major:	AQL 0.40 percent		
101.	Contents loose.....	Visual-Manual	06001
102.	Any cushion missing.....	Visual	06002
Minor:	AQL 0.65 percent		
201.	Carton missing or damaged.....	Visual	06003

4.3.2.8 Drum, metal shipping (see Dwg. 9218792).

Categories	Defects	Method of Inspection	Code No.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

Critical: None defined.

Major:	AQL 0.40 percent		
101.	Cover loose or improperly sealed	Visual-Manual	07001
Minor:	AQL 1.00 percent		
201.	Marking improper, misleading or unidentifiable	Visual	07002
202.	Evidence of poor workmanship (see 3.6)	Visual	07003

4.3.3 Testing

4.3.3.1 Continuity and resistance of the electrical circuits of cable assemblies (see 3.3) - Major defect - Power cable No. 1, Code No. 08001. Switch cable code no. 08004. -Power cable No. 2, Code No. 08002.-Test cable Code No. 08003.-Each cable assembly shall be subjected to this test. The test shall be performed in accordance with 4.4.1. Any cable assembly which fails to comply with the applicable requirements shall be classed defective and removed from the lot.

4.3.3.2 Insulation Resistance Test of the Cable Assemblies (see 3.4). - Major Defect - Power Cable No. 1, Code No. 09001. - Power Cable No. 2, Code No. 09002. - Test cable, code No. 09003. - Switch cable, code no. 09004. - Each cable assembly shall be subjected to this test. This test shall be performed as specified in 4.4.2. Any cable assembly that fails to comply with the requirement shall be classified defective and removed from the lot.

4.3.3.3 Salt spray (panel, see Dwg. 9219841) (Relay Mounting Plate, see Dwg. 9219844) - Major defect - Panel, Code No. 10001 - Relay Mounting Plate, Code No. 10002.-Panels or coupons of each coating process of panels and mounting plates of the size and number as specified in finish specification MIL-A-8625 shall be subjected to this test. This test shall be performed as specified in MIL-A-8625 except, the exposure time shall be 96 hours. Rejection criteria shall be as specified in the finish specification.

4.3.3.4 Functioning.-Each test set shall be subjected to this test and observed for any evidence of failure to comply with the requirements, as classified in Table 1. The test shall be performed as specified in 4.4.3. Any test set that

Source: https://assist.dla.mil -- Downloaded: 202640-26T03:55Z
Check the source to verify that this is the current version before use.

fails to comply with the applicable requirements shall be classified defective and removed from the lot.

TABLE 1

Defect	Classification	Code No.
External power source circuit (see 3.5.1)	Major	11001
Press to test lamp assemblies (see 3.5.2)	Major	11002
Safe-safe check circuits (see 3.5.3)	Major	11003
Fire circuit (see 3.5.4)	Major	11004
Manual advance circuit (see 3.5.5)	Major	11005
"35-39" and "40" lamp circuits (see 3.5.6)	Major	11006
1-40 indicator circuits (see 3.5.7)	Major	11007

4.3.3.5 Electrical Cable Assembly Switch - Diode Test (see dwg. 8860162), Major Defect, Code No. 12005. - Each cable shall be tested 100 percent for the specified requirement in accordance with 4.4.4. Any cable classed defective shall be removed from the lot. (Non-destructive test).

4.3.4 Inspection Equipment.-Inspection equipment required to perform the inspections prescribed in this specification is identified in the Examination (4.3.2) and Test Method (4.4) paragraphs herein. See 6.3 for details concerning responsibilities for inspection design and approval.

4.4 Test methods and procedures

4.4.1 Continuity and Resistance of cable assemblies. - Cable assemblies shall be tested for the applicable requirements using a Government approved test fixture and operating procedures. Any cable failing to comply with the requirements shall be classed defective and removed from the lot.

4.4.2 Current leakage test of the power cable assemblies.- The power cables shall be tested in accordance with MIL-STD-202,

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

Method 302, Test Condition B, between each wire and each wire and ground. Non-destructive test. Cables so tested may be returned to the lot.

4.4.3 Functioning test (non-destructive test)

4.4.3.1 External power source circuit.-The test set shall be connected to 28 ± 1 volt DC power source using the power cable No. 1 assembly. Set the power "OFF-ON" switch to the "ON" position. The amber "POWER ON" lamp shall light. No other lamp shall light.

4.4.3.2 Press to test lamp circuits.-Under conditions as stated in paragraph 4.4.3.1, depress each press to test lamp assembly. Each lamp shall light when depressed.

4.4.3.3 Safe-safe check circuits.-Short terminals J2 - t and J2 - CC. Under conditions stated in paragraph 4.4.3.1, flip the "safe check" switch down. The green "safe" lamp shall light.

4.4.3.4 Fire circuit.-Using the equipment listed on the Equipment List, there shall be evidence of continuity from pin J1 - A to pins J2 - x, J2 - y and J2 - t when the power switch is in the "ON" position and the fire button is depressed. There shall be no continuity when the "fire" button is released. (Safe-check switch in open (up) position).

4.4.3.5 Manual advance circuit.-Short terminal J2 - w to ground (J2 - BB). Under conditions as stated in paragraph 4.4.3.1, depress the "manual advance" button. Using equipment as listed on the Equipment List, check for voltage across terminal J2 - DD (positive) and J2 - EE (negative). Check for voltage from J2 - z to ground (J2 - BB). There shall be an indication of approximately 28 VDC across these terminals. Release the "manual advance" button and again check for voltage across these terminals. There shall be no voltage present.

4.4.3.6 "35 - 39" and "40" Lamp Circuits. - Short terminals u and v to ground (J2 - BB). Under condition as stated in paragraph 4.4.3.1, the "35-39" and "40" lamps shall light.

4.4.3.7 "1-40" Indicator Relay Circuits. - Under conditions as stated in paragraph 4.4.3.1, depress the "tester reset" button. All indicators shall appear red. Momentarily apply 28 ± 1 VDC to each pair of terminals indicated below and observe the corresponding indicator turn white. The test shall be per-

Source: https://assist.dla.mil -- Downloaded: 20260-26T03:55Z
Check the source to verify that this is the current version before use.

formed in the sequence given.

J2 Terminals (+)	J2 Terminals (-)	Indicator
A	BB	1
B	BB	2
C	BB	3
D	BB	4
E	BB	5
F	BB	6
G	BB	7
H	BB	8
J	BB	9
K	BB	10
L	BB	11
M	BB	12
N	BB	13
P	BB	14
R	BB	15
S	BB	16
T	BB	17
U	BB	18
V	BB	19
W	BB	20
X	BB	21
Y	BB	22
Z	BB	23
a	BB	24
b	BB	25
c	BB	26
d	BB	27
e	BB	28
f	BB	29
g	BB	30
h	BB	31
i	BB	32
j	BB	33
k	BB	34
m	BB	35
n	BB	36
p	BB	37
q	BB	38
r	BB	39
s	BB	40

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

All indicators shall be white. Depress the "tester reset" button. All indicators shall return to red.

4.4.4 Electrical Cable Assembly Switch - Diode Test. - The toggle switch shall be placed in the closed position and a direct current voltage applied between the clip leads. The red lead shall be used as the positive voltage input reference from the voltage source. The voltage drop shall be monitored between pin "E" of the connector and the black clip lead. The positive voltmeter lead shall be connected to pin "E" of the connector. A maximum current of ten (10) amperes shall be driven through the cable assembly and the voltage drop measured by the voltmeter shall not exceed 1.00 volts. The input power shall be turned off after the measurement and the toggle switch shall then be opened. The power shall be re-applied from the voltage source and the voltmeter shall not indicate any reading.

5. PREPARATION FOR DELIVERY

5.1 Preservation and packaging

5.1.1 Level A. - The test set shall be preserved and packaged in accordance with dwg. 9218792.

5.2 Packing

5.2.1 Level A. - The test set shall be packed in accordance with dwg. 9218792.

5.3 Marking. - Marking shall be in accordance with dwg. 9218792.

5.4 Shipping. - When shipments from more than one lot are shipped as a carload, each lot shall be kept separate, and the division between lots clearly indicated to prevent mixing in transit.

6. NOTES

6.1 Ordering data.-Procurement documents shall specify the following:

a. Title, number and date of this specification.
b. Data cards. - Data cards shall be prepared for each

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

lot in accordance with the information specified in Standard MIL-STD-1167.

c. Provisions for submission of first article samples.

d. Test cable assembly dwg. no. 9219850 will be purchased with test set dwg. 9209945; and test cable assembly dwg. 9280149 will be purchased with test set dwg. 9280146.

6.2 Inspection code numbers.-The five digit code numbers assigned to the inspections herein are to facilitate future data collection and analysis by the Government. They should be cited as references on drawings of equipment designs submitted by the contractor to the Government for approval (see 6.3.3).

6.3 Inspection Equipment Designs.-Inspection equipment designs are of two types - Government Special Inspection Equipment (SIE) designs and contractor designs. SIE designs are designated by drawing numbers under the "Method of Inspection" headings in Section 4. Design responsibility for all other inspection equipment is assigned to the contractor. The contractor need not furnish any design when a complete Government SIE design is provided. Unless otherwise specified, however, the contractor may submit alternate or modified contractor designs of SIE in accordance with 6.3.2 and 6.3.3 should he elect to do so.

6.3.1 SIE designs.-SIE designs may consist of any of the following:

a. Detailed drawings which completely depict all information necessary for the fabrication and use of the item of inspection equipment.

b. A source control drawing or a specification control drawing as defined in MIL-STD-100.

c. An envelope drawing, as defined in MIL-STD-100, which establishes the criteria which a detailed design shall meet. When envelope drawings are specified, the contractor shall prepare designs which comply with the criteria therein.

6.3.2 Contractor designs.-Contractor designs are required for all inspection equipment for which SIE designs are not specified and may include commercial equipment which the contractor proposes to use. (Commercial equipment is defined as unmodified equipment which is cataloged and available for purchase by the general public). Contractor designs shall include appropriate

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

operating instructions, calibration procedures and maintenance procedures. Commercial equipment shall be fully described by catalog listings or other means which provide sufficient information to permit identification and evaluation by the Government and may include illustrations and engineering data. Designs shall be prepared for any special fixture(s) required to be used with commercial equipment, or with SIE designs if not otherwise covered thereby (see 6.3.1c). Designs shall be of the category and form (per MIL-D-1000) specified in the Contract Data Requirements Lists (DD Form 1423). The contractor is referred to MIL-HDBK-204, "Inspection Equipment Design" for guidance. The specification number and the applicable five digit defect code number (or other specific identifying information) from Section 4 of this specification shall be referenced on each contractor design together with the component or assembly drawing number and revision letter to which the specific design applies.

6.3.3 Submission of Designs for Approval.-Contractor designs shall be approved by the Government prior to fabricating or procuring the equipment. Designs shall be submitted for approval to Picatinny Arsenal, ATTN: SARPA-QA-A-M, Dover, New Jersey 07801 in accordance with the stipulations, time frame and distribution specified in the Contract Data Requirements List (DD Form 1423) or in the contract. The contractor must include in his submission of designs a listing of any and all Government SIE designs which will be utilized. Partial submission of inspection designs is permissible and encouraged. However, the completion date for design review will be based on the date of the final submission of designs. Picatinny Arsenal design review will normally be accomplished within one month after receipt.

6.4 Supersession Data. - This specification includes the requirements of AEI-366 dated 20 October 1966.

Custodian:
Army-PA

Preparing Activity:
Army-PA

Project Number: 4925-A-019

Source: https://assist.dla.mil -- Downloaded: 202610-26T03:55Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

OMB Approval
No. 22-R255

INSTRUCTIONS: The purpose of this form is to solicit beneficial comments which will help achieve procurement of suitable products at reasonable cost and minimum delay, or will otherwise enhance use of the document. DoD contractors, government activities, or manufacturers/ vendors who are prospective suppliers of the product are invited to submit comments to the government. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements. Attach any pertinent data which may be of use in improving this document. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity.

DOCUMENT IDENTIFIER AND TITLE

NAME OF ORGANIZATION AND ADDRESS

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE DOCUMENT CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?
   A. GIVE PARAGRAPH NUMBER AND WORDING.

   B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY DOCUMENT REQUIREMENT CONSIDERED TOO RIGID

3. IS THE DOCUMENT RESTRICTIVE?

   ☐ YES ☐ NO *(If "Yes", in what way?)*

4. REMARKS

SUBMITTED BY *(Printed or typed name and address - Optional)*

TELEPHONE NO.

DATE

DD FORM 1 JAN 72 1426 REPLACES EDITION OF 1 JAN 66 WHICH MAY BE USED

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T03:55Z
Check the source to verify that this is the current version before use.

FOLD

DEPARTMENT OF THE ARMY
PICATINNY ARSENAL
DOVER, NEW JERSEY 07801

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

POSTAGE AND FEES PAID
DEPARTMENT OF THE ARMY
DOD – 314



COMMANDER
Picatinny Arsenal
ATTN: SARPA-QA-A
Dover, New Jersey 07801

FOLD

Source: https://assist.dla.mil -- Downloaded: 202640-26T03:55Z
Check the source to verify that this is the current version before use.