MILITARY SPECIFICATION

COMPUTER LOGIC UNIT: 8623272

This amendment forms a part of Military Specification MIL-C-60215(MU), dated 5 March 1965.

Paragraph 1.1: Delete "FLAT" and substitute "FALT".

Paragraph 2.1, under DRAWINGS: Add the following:

"C8213506	Power Cable
C8623423	Cable Assembly
F8623471	Wiring Harness Jumper"

Paragraph 3.4.1, first sentnece: Delete and substitute: "The FALT with Power Cable C8213506, Wiring Harness Jumper F8623471, and Cable Assemblies C8623423-1 through C8623423-5, enhoused within the FALT transit case, shall be capable of withstanding a circular motion of 1 ± 0.1 inch diameter at a frequency of 271 ± 2 cycles per minute for a total of 3 hours."

Paragraph 3.6.1: Delete in its entirety and substitute:

"3.6.1 Vibration.- The FALT, including the cables and wiring harness specified in 3.4.1 shall be capable of withstanding a simple harmonic motion with a single amplitude of 0.015 inch (0.03 inch total excursion) and a frequency varying uniformly between the limits of 10 and 55 cycles per second and return to 10 cycles per second in approximately one minute. The FALT shall be capable of withstanding this motion for a period of 10 minutes in each of the 3 mutually perpendicular axes (total 30 minutes)."

* Following paragraph 4.1.1: Add paragraphs 4.1.2, 4.1.2.1 and 4.1.2.2 as follows:

"4.1.2 First article (initial production) approval.- The requirement for first article approval and the responsibility (Government or contractor) for first article testing shall be as specified in the contract. The sample for first article tests shall consist of two (2) samples manufactured in the same manner using the same materials, equipment, processes, and procedures as used in regular production. All parts and materials, including packaging and packing, shall be obtained from the same source of supply as used in regular production.

* 4.1.2.1 Government testing.- When the Government is responsible for conducting first article approval tests, the contractor, prior to sub-

Source: https://assist.dla.mil -- Downloaded: 2026-05-23T10:21:10Z
Check the source to verify that this is the current version before use.

mitting the sample to the Government, shall inspect the sample to insure that it conforms to all the requirements of the contract and submit a record of this inspection with the sample, including certificates of conformance for materials.

* 4.1.2.2 Contractor testing.- When the contractor is responsible for conducting first article approval tests, the sample shall be inspected by the contractor for all the requirements of the contract. The sample and a record of this inspection, including certificates of conformance for materials, shall be submitted to the Government for approval. The Government reserves the right to witness the contractor's inspection."

Paragraph 4.2.4, Table A, Characteristic Column: Add to Characteristic "125. FALT run-in", the following: "(except items selected for tests specified in 4.3.2)".

* Paragraph 4.3.2, In the first sentence delete: "or from each months production, whichever occurs first."

Paragraph 4.5, first sentnece: Delete and substitute: "The FALT with Power Cable C8213506, Wiring Harness Jumper F8623471, and Cable Assemblies C8623423-1 through C8623423-5, enhoused within the FALT transit case, shall be placed on a test table, but not fastened to it".

Paragraph 4.9.2(e), Table II, Columns A, B and C, line 7: Delete "-1.5R 1.25, 12 watt 6.8, 1 watt" and substitute "-1.5R 13.75, 25 watt* 75, 5 watt*",; Add the following notation at bottom of Table II: "*Return -1.5R loads to -18R not to Gnd".

Paragraph 4.9.5(f)(2): Delete "-6.2 ± 0.2 volts" and substitute "-6.0 ± 1 volts".

Paragraph 4.9.6.2, Table VII, under Nominal Voltage, line 4: Delete "+6" and substitute "+6(z)"; line 14: Delete "+6(z)" and substitute "+6".

Paragraph 4.9.9: Delete Step 18(c) and (d) in their entirety and substitute the following:

"Step 18(c) Manual Control Lamp 7 shall go out. Release hand sprocket switch.

Step 18(d) Operate clock key two times."

Table XI, CTO Voltage on Pin J10-GG Column: Delete "+5.58" and "+6.1" and substitute "+5.0" and "+7.0". Make the same changes in Tables XII through XIX.

Paragraph 4.9.10, Step 4: Delete "Table VIII" and substitute "Table XIII".

Paragraph 4.9.10, Step 10(h): Delete "E5, E5" and substitute "E5".

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:18Z
Check the source to verify that this is the current version before use.

Paragraph 4.9.12, Step 3(d): Delete: "#123" and substitute "123".

Table XXII: Delete the values in the last two columns and substitute the following values:

"Max.	Min.
15.0	12.5
34.4	28.6
18.2	15.2
17.6	14.8
49.2	40.9
12.4	10.4
24.2	20.3
196.9	167.4
196.9	167.4
27.3	22.8
23.3	19.3
17.5	14.5"

After paragraph 4.9.28 add new paragraph:

"4.9.29 Falt to Falt test.- F tape, Part No. 8213330-25 may be substituted for paragraphs 4.9.5 and 4.9.9 through 4.9.27 except 4.9.25. This test shall be performed using F tape, Signal Data Reproducer and Control Box, Computer Logic Unit Test Set C-4020/GSM-70, in accordance with instructions in TM-9-4931-204-34/5. This test and the self-test (4.9.28) shall be performed with the Falt front and rear covers removed."

Paragraph 4.10.1: Delete in its entirety and substitute:

"4.10.1 Vibration test.- The Falt shall be tested as outlined in MIL-F-13926, Procedure II, Condition B except the frequency, amplitude, direction and duration shall be as specified in 3.6.1. Subsequent to this test, the unit shall be visually inspected for physical damage then tested as outlined in 4.10.2."

Figure 3: Delete "D1520 or equivalent" and substitute "D152 or equivalent".

The outside margins have been marked to indicate where additions to the previous amendment have been made. This has been done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in this notation. Bidders anc contractors are cautioned to evaluate the requirements of this document based on the entire content as written irrespective of the marginal notation and relationship to the last previous amendment.

Custodian:

Army - MU

Preparing activity:

Army - MU

Project No. 1220-A136

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:18Z
Check the source to verify that this is the current version before use.