MILITARY SPECIFICATION

GUIDED MISSILE LAUNCHER TEST SET, AN/ASM-464A,

This specification is approved for use within the Naval Air Systems Command,Department of the Navy and is available for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 Scope. This specification establishes the performance, design, and test requirements for the Guided Missile Launcher Test Set, AN/ASM-464A hereinafter referred to as the test set. The test set is used on the flight line to perform operational tests on the SIDEWINDER missile launcher circuits associated with the Guided Missile Launcher LAU-7A.

2. APPLICABLE DOCUMENTS

2.1 Government documents.

2.1.1 Specifications and standards. The following specifications and standards form a part of this specification to the extent specified herein. Unless otherwise specified, the issues of these documents shall be those listed in the issue of the Department of Defense Index of Specifications and Standards (DODISS) and supplement thereto, cited in the solicitation.

Beneficial comments (recommendations, additions, deletions) and any pertinent data which may be of use in improving this document should be addressed to: Commanding Officer, Naval Air Engineering Center, Systems Engineering and Standardization Department (SESD) Code 93, Lakehurst, NJ 08733-5100, by using the self-addressed Standardization Document Improvement Proposal (DD Form 1426) appearing at the end of this document or by letter.

AMSC N/A

FSC 4935

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

SPECIFICATIONS

MILITARY

MIL-P-116	Preservation Packaging Methods of
MIL-E-5400	Electronic Equipment, Aerospace, General Specification for
MIL-E-17555	Electronic and Electrical Equipment, Accessories, and Repair Parts; Packaging and Packing of
MIL-T-28800	Test Equipment for Use with Electrical and Electronic Equipment, General Specification for

STANDARDS

MILITARY

MIL-STD-129	Marking for Shipment and Storage
MIL-STD-130	Identification Marking of US Military Property
MIL-STD-454	Standard General Requirements for Electronic Equipment
MIL-STD-461	Electromagnetic Emission and Susceptibility Requirements for the Control of Electromagnetic Interference
MIL-STD-462	Electromagnetic Interference Requirements, Measurements of
MIL-STD-781	Reliability Design Qualification and Production Acceptance Tests; Exponential Distribution
MIL-STD-794	Parts and Equipment Procedures for Packaging and Packing of
MIL-STD-965	Parts Control Program

2.1.2 Other Government drawings. The following other Government drawings form a part of this specification to the extent specified herein. Unless otherwise specified, the issues shall be those in effect on the date of the solicitation.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

DRAWINGS

Naval Ordnance Systems Command

2412395	Sheet, Technical Frequency Specifications

Naval Air Systems Command

DL 1058AS11OO	Guided Missile Launcher Test Set, AN/ASM-464A
60A89C217	Circuit, Resonant Tuned

(Copies of specifications, standards and drawings required by contractors in connection with specific acquisition functions should be obtained from the contracting activity or as directed by the contracting activity,)

2.1.3 Order of precedence. In the event of a conflict between the text of this specification and the references cited herein (except for associated detail specifications, specification sheets or MS standards), the text of this specification shall take precedence. Nothing in this specification, however, shall supersede applicable laws and regulations unless a specific exemption has been obtained.

3. REQUIREMENTS

3.1 Item description. The test set shall test the aircraft launcher (LAU-7A) for the AIM-9D/G/H/L/M weapon systems at the organizational maintenance level. The test set shall be capable of determining that all required voltages and signals are available to the launcher system, and shall monitor critical functions continuously for stray electrical energy. The test set shall perform multiple functional tests simultaneously and indicate failure of a tested function by lighting a FUNCTION SELECT NO-GO indicator. If a NO-GO indication occurs, the operator must be able to troubleshoot the individual interface circuits by selecting the appropriate line with a LINE SELECT switch and read voltages on a digital voltmeter (DVM). Stray electrical energy on critical functions shall be monitored continuously with results indicated on separate GO/NO-GO indicators. Stray electrical energy NO-GO results are not required to be line selectable. Internal self test circuitry continuously monitors test set condition and shall indicate an unserviceable test set by causing the SELECTED FUNCTION NO-GO indicator to continuously flash ON and OFF.

3.1.1 General. The test set shall be comprised of a front panel with permanently attached chassis and a card cage assembly attached to the chassis. The card cage shall contain 12 printed circuit cards. The chassis and card cage shall be hinged together at one side to allow the card cage to be opened, away from the chassis, to expose the chassis mounted and front panel mounted omponents. The chassis and card cage shall be retained together, at the side opposite the hinge, by spring loaded detent fasteners.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

3.1.1.1 Missile simulation. The test set shall not test the SIDEWINDER missile, but shall simulate the missile to test the capability of the aircraft to supply required launcher inputs, and shall test the launcher capability to supply required missile inputs. The test results shall be indicated on a front-panel mounted GO, or NO-GO indicator.

3.1.1.2 Stray energy tests. The test set shall indicate a GO condition on the front panel mounted STRAY ENERGY GO indicator as long as safe limits are not exceeded. The STRAY ENERGY NO-GO indicator lamp shall light when stray energy is in excess of safe limits.

3.1.1,3 Test set, launcher/pylon interface. The test set shall connect to launcher via the igniter contact block of Cable Assembly W1. The W1P1 of the W1 cable shall connect to the test set. The W1P2 connector interfaces with adapter W2 for the pylon connection.

3.1.2 Major components. Table I lists the major components that comprise the test set.

TABLE I. Major components of Guided Missile Launcher Test Set AN/ASM-464A.

Quantity	Description	Part Number
1	Test Set Assembly (1A1)	1058AS1110
	(a) Front Panel (1A1A1)	1058AS1105
	(b) Card Cage Assembly (1A1A2)	1058AS125
	(1) Circuit Card (1A1A2A1)	1058AS160
	(2) Circuit Card (1A1A2A2)	1058AS165
	(3) Circuit Card (1A1A2A3)	1058AS170
	(4) Circuit Card (1A1A2A4)	1058AS175
	(5) Circuit Card (1A1A2A5)	1058AS180
	(6) Circuit Card (1A1A2A6)	1058AS185
	(7) Circuit Card (1A1A2A7)	1058AS190
	(8) Circuit Card (1A1A2A8)	1058AS195
	(9) Circuit Card (1A1A2A9)	1058AS200
	(10) Circuit Card (1A1A2A10)	1058AS205
	(11) Circuit Card (1A1A2A11)	1058AS265
	(12) Circuit Card (1A1A2A12)	1058AS210
1	Cable Assembly W1 (connects test set to the umbilical connector and igniter contact of Launcher, LAU-7A)	1058AS275
1	Pylon Adapter W2 (used with W1 to connect test set to pylon connector)	1058AS290
1	Detect Wrench (used to raise igniter contact to mount W1 into launcher rails)	67A274C391
1	Case and Cover Assembly	1058AS1103

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

3.2 First article. When specified in the contract or purchase order, a sample shall be subjected to first article inspection (see 4.4 and 6.3).

3.3 Parts and materials.

3.3.1 General requirements. Parts and materials used in the test set shall conform to the requirements of DL 1058AS110O, except insofar as errors on the drawings may be incompatible with the requirements of this specification and related specifications.

3.3.2 Nonstandard parts approval. Approval for the use of nonstandard parts shall be obtained by the contractor as specified in MIL-STD-965.

3.3.3 Supplemental requirements. In the event that the contractor proposes to alter the equipment delineated by this specification and applicable drawings, the supplemental requirements specified in 3.3.3.1 and 3.3.3.2 for the selection of parts and materials shall be applicable.

3.3.3.1 Basic conformance. Parts and materials selected for use in the equipment shall be as specified in MIL-T-28800. Parts shall be selected from those conforming to MIL-E-5400, unless the parts selected will not perform as required in the intended applications and environments specified herein, in which case 3.3.2 applies.

3.3.3.2 Interchangeability. All parts and materials shall meet the interchangeability requirements as specified in MIL-T-28800. The drawings conforming to DL 1058AS11OO shall be the standard for measuring interchangeability of all applicable units, assemblies, subassemblies and parts.

3.4 Design and construction. The test set shall be manufactured in accordance with DL 1058AS11OO, except that errors of omission or commission on the drawings may be incompatible with the requirements of this specification. In any case, it is a condition of final acceptance that the equipment manufactured shall meet all the design, construction, and workmanship requirements of this specification.

3.4.1 Reliability.

3.4.1.1 Operational stability. The test set shall operate as required continuously or intermittently, for a period of at least eight hours. During this time, it shall not be necessary to readjust any controls.

3.4.1.2 Operating life. The test set shall have a minimum total operating life of 10,000 hours with minimal servicing and replacement of parts.

3.4.1.3 Reliability in mean-time-between-failures (MTBF). The test set shall have a lower mean- (operating) time-between-failures of 250 hours (θ_1) as specified in MIL-STD-781 when tested in accordance with 4.5.3.

3.4.2 Standard conditions. The following conditions shall be used to establish the normal performance characteristics under standard conditions for performing laboratory-bench tests:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

a.	Temperature	25 ± 5°C
b.	Altitude	Normal ground (28 to 32 inches of mercury)
c.	Vibration	None
d.	Humidity	Up to 90 percent relative humidity
e.	Input Operating Voltage	115 ± 1.5v, single phase, 400 ± 5 Hz ac

3.4.2.1 Service conditions. The test set shall meet the operating test requirements of this specification under any environment service condition or combination of conditions specified in MIL-T-28800 for Type I, Class 2 equipment.

3.4.2.1.1 Interference. The test set shall comply with all electromagnetic radiation and susceptibility requirements of MIL-STD-461, Class 1C except as specified in table II.

TABLE II. Radiation and susceptibility limits.

-- Test method	Limits	Frequency range
CE01 Narrowband Conducted	17 db 1/	30 Hz to 20 KHz
CE01 Broadband Conducted	42 db 1/	30 Hz to 20 KHz
CE03 Broadband Conducted	64 db 1/	20 KHz to 50 MHz
CE04 Broadband Conducted	52 db 1/	20 KHz to 50 MHz
RE01 Radiated Emission	17 db 1/	30 Hz to 30 KHz
RE02 Narrowband Radiated	36 db 1/	14 KHz to 10 GHz
CS06 Powerline Spike	65 volts in lieu of 100 volts peak	

1/ Above the limits that are specified in MIL-STD-461, Class 1C.

3.4.3 Performance characteristics. Unless otherwise specified herein, the performance characteristics shall apply under both standard and environmental conditions as specified in 3.4.2 and 3.4,2.1. Performance of the test set shall be as specified in DL 1058AS1100 and 3.4.3.1 through 3.4.5.

3.4.3.1 External power. The test set shall meet performance characteristics when powered from an external source, applied to the test set through cable W1 as follows: (Input power shall be not greater than 200 volt-ampere: under any operating conditions.)

a. W1P2-1 (phase A)

b. W1P2-21 (neutral)

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

3.4.3.2 Warm-up time. Warm-up time shall be from 1.5 to 25 seconds as indicated by the SELECTED FUNCTION GO/NO-GO lights in the FUNCTION SELECT TD position.

3.4.3.3 Lamp test. A lamp test of the SELECTED FUNCTION GO/NO-GO and STRAY ENERGY GO/NO-GO lamps shall be performed in the FUNCTION SELECT switch TD position.

3.4.4 Interface requirements. The test set shall be capable of physical and electrical interface to the launcher LAU-7A or to the aircraft pylon for performance of tests. Table III lists the tests and the electrical interface required to perform launcher tests. Table IV specifies interface requirements for pylon tests. Tables IV and V contain the accept and reject limits for launcher and pylon interface requirements. The ranges specified for the upper and lower voltage limits are the transition regions between the illumination of the GO and NO-GO lamps. When a signal being tested is between the transition regions, the GO lamp shall illuminate. When a signal being tested is within a transition region either the GO or the NO-GO lamp may illuminate. When a signal being tested is beyond the minimum lower limit or the maximum upper limit, the NO-GO lamp shall illuminate. The test set shall be connected to the launcher by cable W1 or to the pylon connector using pylon adapter W2 and cable W1. All requirements and limits shall be specified at the cable W1, P2 interface for both launcher and pylon functions.

TABLE III. Launcher interface test limits.

Pin (W1-P2)	Function	Voltage Limits		
		Lower	Nominal	Upper
18	Heater Filament	22.5 ± 0.4 vdc	28 vdc	30.0 ± 0.4 vdc
22	Missile Filament	24.0 ± 0.15 vdc	25.2 vdc	26.4 ± 0.15 vdc
33	Missile B+	160 ± 1.5 vdc	175 vdc	190 ± 1.5 vdc
3	Launch Latch	19.6 ± 0.4 vdc	24.8 vdc	27.2 ± 0.4 vdc
13	Gas Grain	11.8 ± 0.2 vdc	14.7 vdc	15.9 ± 0.2 vdc
19	Fuze/PCO	12.5 ± 0.25 vdc	15.9 vdc	17.5 ± 0.25 vdc
-	Motor Fire	2.68 ± 0.15 vdc	4.5 vdc	7.0 vdc, min.

3.4.4.1 Stray energy requirements. Critical circuits (Fuze/PCO, Gas Grain, and Motor Fire) shall be continuously monitored for stray electrical energy. A front panel mounted STRAY ENERGY GO indicator lamp shall be illuminated as long as no stray energy in excess of safe limits is detected. Measurement of stray energy shall be inhibited when a functional test is being performed on the line in question. Stray energy in excess of safe limits shall light the STRAY ENERGY NO-GO indicator lamp. (Stray energy criteria is specified in table V.)

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

TABLE IV. Pylon interface test limits.

Pin (W2-P2)	Function	Voltage Limits		
		Lower	Nominal	Upper
15	28v Bus	22.5 ± 0.4 vdc	28 vdc	30.0 ± 0.4 vdc
6	Master Arm	22.5 ± 0.4 vdc	28 vdc	30.0 ± 0.4 vdc
20	Cool Control	22.5 ± 0.4 vdc	28 vdc	30.0 ± 0.4 vdc
9	115 v, Phase A	105 ± 0.85 vac	115 vac	122 ± 0.85 vac
1	Fire Pulse	22.5 ± 0.4 vdc	28 vdc	30.0 ± 0.4 vdc
25	Manual Uncage	22.5 ± 0.4 vdc	28 vdc	30.0 ± 0.4 vdc

3.4.4.2 Test set, launcher/pylon interface requirements. The test set shall be connected to test the launcher by installing the igniter contact block of Cable Assembly W1 in the launcher rails; and connecting one connector of Cable Assembly W1 to the launcher interface, and the other connector to J1 of the test set. Connection to the pylon interface shall require connection of adapter W2 between the pylon connector and W1P2 of Cable Assembly W1. The igniter contact block shall be a lug support part of Cable Assembly W1 that mounts on the launcher rail and provides the electrical connections between the test set and motor igniter circuits in the aircraft/launcher.

3.4.5 Functional requirements.

3.4.5.1 Ground interface requirements, LAU-7 and pylon test modes.

a. Ground return

(1) Launcher - W1, P2-21

(2) Pylon - W2, P2-18

(3) Description: Ground return line for all test set ac and dc inputs and outputs.

b. Power interlock ground

(1) Launcher - W1, P2-14

(2) Pylon - W2, P2-26

(3) Description: Provides switch contact closure (not greater than 10 ohms) to power ground in all positions of the test set FUNCTION SELECT switch except the OFF position. OFF position resistance to ground shall be not less than 100K ohms.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

c. 115 v, 400 Hz, phase A power

(1) Launcher - W1, P2-1

(2) Pylon - W2, P2-9

(3) Description: Input power for test set, 105 to 122 vat, 380 to 420 Hz, 120 volt-amperes; fused at two amperes.

d. Missile identification output, 28 vdc

(1) Launcher - W1, P2-17

(a) Output switched ON/OFF by front panel MISSILE ID switch.

(b) Output voltage shall be the greater of the input Heater Filament voltage (W1, P2-18) minus a maximum of one volt dc, or the input Missile Filament voltage (W1, P2-22) minus a maximum of one volt dc.

(c) External load resistance shall be not less than 1K ohms.

(2) Pylon - W2, P2-13

(a) Output switched ON/OFF by front panel MISSILE ID switch.

(b) Output voltage shall be equal to the 28v bus (W2, P2-15) input voltage minus not greater than one volt dc.

(c) External load resistance shall be not less than 1K ohms.

e. All signals - capacitance from interface pin to ground shall be not greater than 0.6 uf unless otherwise stated.

f. When between detent positions of the FUNCTION SELECT switch, the STRAY ENERGY GO lamp shall illuminate and the STRAY ENERGY NO-GO lamp shall not illuminate.

3.4.5.2 Launcher interface requirements.

a. FUNCTION SELECT test one.

(1) Missile B+, W1, P2-33, 175 volts dc.

(a) A 14K ± 5 percent ohms resistive load shall be continuously applied between ground and the input pin (W1, P2-33).

(b) A 1.4K + 5 percent ohms resistive load shall be applied between ground and the input pin (W1, P2-33) for a single nonrepetitive 2.0 + 0.5 second period, after placing the FUNCTION SELECT switch to position one.

Source: https://assist.dla.mil - Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

(c) The input pin shall be monitored for correct voltage (for limits see table III), starting 5.0 ± 1.0 seconds after application of the resistive load specified in 3.4.5.2.a.(1)(b). An accept/reject decision shall be updated at a one Hertz rate after the five-second delay is over.

(2) Heater filament, W1, P2-18, 28 volts dc.

(a) A 78 + 5 percent ohms resistive load shall be continuously applied between ground and the input pin (W1, P2-18).

(b) A 7.9 + 5 percent ohms resistive load shall be applied between ground-and the input pin (W1, P2-18) as specified in 3.4.5.2.a.(1)(b).

(c) The input pin shall be monitored for correct voltage as specified in 3.4.5.2.a.(1)(c).

(d) Capacitance from the input pin (W1, P2-18) to ground shall be not greater than 1.2 µf.

(3) Missile filament, W1, P2-22, 25.2 volts dc.

(a) A 250 + 5 percent ohms resistive load shall be continuously applied between ground and the input pin (W1, P2-22).

(b) A 24.8 + 5 percent ohms resistive load shall be applied between–ground and the input pin (W1, P2-22) as specified in 3.4.5.2.a.(1)(b).

(c) The input pin shall be monitored for correct voltage as specified in 3.4.5.2.a.(1)(c).

(4) Ground, W1, P2-9. Continuity test to power ground pin. Accept/reject limits: accept for not greater than 800 ohms; reject for greater than 2,500 ohms. Accept/reject decision shall be updated at a one Hertz rate after an initial five-second delay.

(5) Electrical cage, W1, P2-30. Continuity test to pin W1, P2-23, electrical cage return. Accept/reject limits: accept for not greater than 8.OK ohms; reject for greater than 90K ohms. Accept/reject decision shall be updated at a one Hertz rate after an initial five-second delay.

(6) Electrical cage return, W1, P2-23. Continuity test to pin W1, P2-30, electrical cage as specified in 3.4.5.2.a.(5).

(7) Gas grain squib, W1, P2-13.

(a) A 1.5 ± 5 percent ohms resistive load shall be fused with a 1.5 ampere slowblow fuse, and shall be continuously applied from ground to pin W1, P2-13.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

(b) The input pin shall be continuously monitored for a stray energy accept/reject decision in accordance with the limits of table V. A reject decision shall be latched and displayed on STRAY ENERGY GO/NO-GO lamps until both an acceptable input is monitored and the latch has been reset by the PRESS TO READ DVM/RESET pushbutton or changing the position of the FUNCTION SELECT switch.

(8) Power changeover, W1, P2-19.

(a) A load shall be applied from ground to pin W1, P2-19 as specified in 3.4.5.2.a.(7)(a).

(b) The input shall be monitored as specified in 3.4.5.2.a.(7)(b).

(9) Motor fire squib, W1, aft striker contact.

(a) A load shall be applied from ground to the aft striker block electrical contact as specified in 3.4.5.2.a.(7)(a).

(b) The input shall be monitored as specified in 3.4.5.2.a.(7)(b).

(10) Missile audio, W1, P2-15.

(a) The output shall be an ac signal of frequency F2 + 300 Hz, in accordance with Drawing 2412395. Output amplitude shall be selectable by the test set AUDIO switch: OFF equal to not greater than 0.1 volt ac; LO equal to 1.00 ± 0.25 volt ac; and HI equal to 3.00 ± 0.25 volts ac. output impedance shall be not greater than 400 ohms.

(b) Load impedance shall be not less than 1,000 ohms.

(c) Capacitance to ground shall be not greater than 0,04 µf.

b. FUNCTION SELECT test two.

(1) Launch latch, W1, P2-3,

(a) A 30.3 + 5 percent ohms resistive load shall be applied between-ground and the input pin (W1, P2-3) for 20 milliseconds out of each second.

(b) The input pin shall be monitored for correct voltage in accordance with the accept/reject limits specified in table III. The accept/reject decision shall be updated at a one Hertz rate at a point 14 milliseconds after the application of the 20 millisecond resistive load pulse.

(c) Capacitance from pin W1, P2-3 to ground shall be not greater than 0.3 µf.

(2) Power changeover, W1, P2-19.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

TABLE V. Stray energy test limits.

Input Condition	Lamp	
	GO	NO-GO
0 to ± 50 mv dc	X	
± 75 mv to ± 2.0 vdc		X
0 to 55 mv rms, 100 Hz to 100 KHz	X	
85 mv to 1.5 v rms, 100 Hz to 10 KHz		X
200 mv to 1.5 v rms, 10 KHz to 100 KHz		X
0 to ± 6.1 v, 10 ± 0.2 microsec. pulse	X	
± 10.6 to ± 150 v, 10 ± 0.2 microsec. pulse		X
0 to ± 1.8 v 100 ± 2 microsec. pulse	X	
± 3.4 to ± 50 v 100 ± 2 microsec. pulse		X
0 to ± 0.5 v 1 ± 0.02 ms pulse	X	
± 1.1 to ± 15 v 1 ± 0.02 ms pulse		X
0 to ± 90 mv, 10 ± 0.2 ms pulse	X	
± 500 mv to ± 4.5 v, 10 ± 0.2 ms pulse		X

(a) A 6.9 + 5 percent ohms resistive load shall be applied to the input pin (W1, P2-19) as specified in 3.4.5.2.b.(1)(a). The load pulses for the power changeover input and the launch latch input shall be applied simultaneously.

(b) The input shall be monitored for correct voltage as specified in 3.4.5.2.b.(1)(b).

(3) Gas grain squib, W1, P2-13.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

(a) A3.8 + 5 percent ohms resistive load shall be applied between ground-and the input pin (W1, P2-13) for a single, non-repetitive 69 ± 10 millisecond period. The load pulse shall be initiated by application of an input voltage with a slope not less than 5 v/millisecond to the input pin. Application of the load pulse shall follow the input voltage rise by not greater than one millisecond.

(b) The input pin is monitored for correct voltage in accordance with the accept/reject limits specified in table III. The accept/reject decision shall be made at a point 39 ± 6 milliseconds after application of the resistive load pulse. The input voltage accept/reject decision shall be latched until reset by the PRESS TO READ DVM/RESET pushbutton or changing the position of the FUNCTION SELECT switch.

(c) The input pin shall be monitored for the presence of voltage in accordance with the limits of table III. The accept criteria are met only when the latch of 3.4.5.2.b.(3)(b) is set and voltage has subsequently been removed from the input pin.

(4) Missile filament, W1, P2-22. The input pin shall be loaded by the test set regulator load output amplifier circuitry. Current load shall be not greater than 1.5 amperes.

(5) Regulator load, WI, P2-32.

(a) The test set output shall be an ac signal of 45 + 5 volts ac amplitude at a frequency of 5,700 ± 300 Hz.

(b) The load circuit shall be the tuned resonant circuit as specified in Drawing 60A89C217.

(c) Capacitance to ground shall be not greater than 0.04 µf.

(6) Electrical cage, W1, P2-30. Continuity test to pin W1, P2-23, electrical cage return. Accept/reject limits:

(a) Accept for greater than 90K ohms, reject for less than 8.OK ohms.

(b) Accept/reject decision shall be updated at a one Hertz rate.

(7) Electrical cage return, W1, P2-23. Continuity test to pin W1, P2-30, electrical cage as specified in 3.4.5.2.b(6).

(8) Motor fire squib, W1, aft striker contact.

(a) A 1.5 ± 5 percent ohms resistive load, fused with a 1.5 ampere slow-blow fuse shall be continuously applied from ground to the aft striker contact.

(b) The aft striker contact shall be continuously monitored for a stray energy accept/reject decision in accordance with limits of table VI. A reject decision shall be latched and displayed

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

on the STRAY ENERGY GO/NO-GO lamps until both an acceptable input is monitored, and the latch has been reset by the PRESS TO READ DVM/RESET push-button or by changing the position of the FUNCTION SELECT switch.

(9) Missile audio, W1, P2-15. The output signal shall be as specified in 3.4.5.2.a.(10)

c. FUNCTION SELECT test three.

(1) Launch latch, W1, P2-3. This input function shall be as specified in 3.4.5.2.b.(1).

(2) Power changeover, W1, P2-19. This input function shall be as specified in 3.4.5.2.b.(2).

(3) Motor fire squib, W1, aft strike contact.

(a) A 0.97 + 5 percent ohm resistive load shall be applied between ground and the aft striker contact for 20 milliseconds out of each second. The load pulses for the motor fire squib shall be applied simultaneously with those for the launch latch and power changeover inputs.

(b) The input pin shall monitored for correct voltage in accordance with the accept/reject limits as specified in table III. The accept/reject decision shall be updated at a one Hertz rate, at a point 14 milliseconds after application of the 20 millisecond resistive load pulse.

(4) Missile filament, W1, P2-22, 25.2 volts dc. The test set shall provide a direct switched current path from the input pin W1, P2-22 to auxiliary fire output pin, W1, P2-27. Resistance of the circuit path shall be not greater than one ohm.

(5) Auxiliary Fire, W1, P2-27.

(a) The test set shall provide a direct circuit path as specified in 3.4.5.2.c.(4)

(b) The external load shall be not less than 950 ohms.

(6) Electrical cage, W1, P2-30. Performance shall be as specified in 3.4.5.2.b.(6).

(7) Electrical cage return, W1, P2-23. Performance shall be as specified in 3.4.5.2.b.(7).

(8) Missile audio, W1, P2-15. Performance shall be as specified in 3.4.5.2.a.(10).

d. FUNCTION SELECT test four.

(1) Left-right reference, W1, P2-34.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

(a) The output shall be a continuous ac signal of frequency F1 ± 3 Hertz in accordance with Drawing 2412395. Output amplitude shall be 1.8 ± 0.8 volts ac, with a total harmonic distortion of not greater than 10 percent.

(b) Load impedance shall be not less than 9.5K ohms.

(2) Acquisition lambda, W1, P2-5.

(a) The output of pin W1, P2-5 shall be not greater than 0.1 volt ac, with either the STATION switch in the OFF position or with the ACQA switch in the OFF, two, or three position.

(b) With the ACQA switch in position one or four, and the STATION switch in either the LI/RO or LO/RI position, the output shall be 2.2 ± 0.1 0.1 volts ac, at a frequency of F1 ± 3 Hertz in accordance with Drawing 2412395. Total harmonic distortion shall be not greater than 10 percent.

(c) With the ACQA switch in position 5 and the STATION switch in either the LI/RO or LO/RI position, the output amplitude shall be 0.24 to 0.30 volt ac. Frequency and distortion shall be as specified in 3.4.5.2.d.(2)(b).

(d) With the STATION switch in the LI/RO position, the left-right reference output shall have a phase shift of 25 ± 3° with respect to the acquisition lambda signal. For the LO/RI position of the STATION switch, the output shall have a phase shift of -155 ± 3° with respect to the acquisition lambda signal.

(e) External load impedance shall be not less than 9.5K ohms.

(3) Electrical cage return, W1, P2-23.

(a) The input impedance for positions one through five of the front panel ACQA switch shall be not less than 102K ohms in parallel with not greater than 0.02 µf.

(b) The amplitude of the input signal shall be monitored by a frequency sensitive (low pass) threshold detector. Accept/reject criteria for the various ACQA switch positions are shown in table VI.

(c) For ACQA switch positions three and four, the output of the threshold detector shall enable or disable the missile audio output, W1, P2-15. In either of the above switch positions, an accept status shall disable the missile audio output (0.1 volt ac maximum output voltage). A reject status shall enable the missile audio output in accordance with the setting of the front panel AUDIO switch (see 3.4.5.2.d.(4)).

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

TABLE VI. Electrical cage voltage limits.

ACQA Switch Position	Accept Level	Reject Level
OFF	--	--
1 and 2	150 mv ac	250 mv ac
3 and 4	20 mv ac	30 mv ac
5	90 mv ac	150 mv ac

(4) Missile audio, W1, P2-15. The missile audio requirements shall be as specified in 3.4.5.2.a.(10) except that the output shall be disabled by an accept status of the electrical cage return threshold detector in ACQA switch positions three and four. Disabled output level shall be not greater than 0.1 volt ac, see 3.4.5.2.d(3).

(5) Electrical cage, W1, P2-30. The output signal requirements shall be the same as those for the Acquisition Lambda signal, as specified in 3.4,5.2.d.(2), except that the output impedance shall be 15K $\pm$ 15 percent ohms.

(6) Gas grain squib, W1, P2-13. Requirements are as specified in 3.4.5.2.a.(7).

(7) Power changeover, W1, P2-19. Requirements are as specified in 3.4.5.2.a.(8).

(8) Motor fire squib, W1, aft striker contact. Requirements are as specified in 3.4.5.2.a. (9).

3.4.5.3 Pylon interface requirements.

a. FUNCTION SELECT test one.

(1) 28 volt dc BUS, W1, P2-18 (W2, P2-15).

(a) A 7.87 + 5 percent ohms resistive load shall be applied between ground and W1, P2-18 for 20 milliseconds out of each second.

(b) The input pin shall be monitored for correct voltage in accordance with the accept/reject limits of table IV. The accept/reject decision shall be updated at a one Hertz rate at a point 14 milliseconds after application of the 20 millisecond resistive load pulse.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

(2) Master arm, W1, P2-20 (W2, P2-6).

(a) A 13.0 + 5 percent ohms resistive load shall be applied between ground and input pin W1, P2-20 for 20 milliseconds out of each second. The master arm load pulse shall be applied simultaneously with the 28 volt BUS load pulse of 3.4.5.3.a.(1)(a).

(b) The input pin shall be monitored for correct voltage as specified in 3.4.5.3.a(1)(b).

(c) Capacitance from pin W1, P2-20 to ground shall be not greater than 1.2 µf.

(3) Cool control, W1, P2-12 (W2, P2-20).

(a) A 200 + 5 percent ohms resistive load shall be continuously applied between ground and input pin W1, P2-12.

(b) The input pin shall be monitored for correct voltage in accordance with the accept/reject limits of table IV.

(4) 115 v, 400 Hz, phase A, W1, P2-1 (W2, P2-9).

(a) A 98K ohms minimum resistive load shall be continuously applied between ground and input pin W1, P2-1.

(b) The input pin shall be monitored for correct voltage in accordance with the accept/reject limits of table IV.

(5) Ground, W1, P2-9 (W2, P2-16).

(a) Continuity test shall be conducted to the power ground pin, W1, P2-21 (W2, P2-18). Accept/reject limits: accept for not greater than 800 ohms; reject for greater than 2,500 ohms. Accept/reject decision shall be updated at a one Hertz rate simultaneously with the updating of the signals of 3.4.5.3.a.(1) through (4).

(6) Fire signal, W1, P2-13 (W2, P2-1).

(a) A 1.5 + 5 percent ohms resistive load, fused with a 1.5 ampere slowblow fuse, shall be continuously applied from ground to pin W1, P2-13.

(b) The input pin shall be continuously monitored for a stray energy accept/reject decision as specified in 3.4.5.2.a.(7)(b).

(7) Missile audio, W1, P2-15 (W2, P2-19). The requirements are as specified in 3.4.5.2.a.(10).

b. FUNCTION SELECT test two.

(1) Fire signal, W1, P2-13 (W2, P2-1). The requirements are as specified in 3.4.5.2.b.(3).

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

(2) Missile audio, W1, P2-15 (W2, P2-19). The requirements are as specified in 3.4.5.2.a.(10).

c. FUNCTION SELECT test three. No test shall be performed in this operating mode.

d. FUNCTION SELECT test four.

(1) Manual uncage, W1, P2-25 (W2, P2-25).

(a) A 620 + 5 percent ohms resistive load shall be continuously applied between ground and input pin W1, P2-25.

(b) The input pin is monitored for correct voltage in accordance with the accept/reject limits of table IV. The accept/reject decision is updated at a one Hertz rate.

(2) Left-right reference, W1, P2-34 (W2, P2-23). The requirements are as specified in 3.4.5.2.d.(1).

(3) Acquisition lambda, W1, P2-5 (W2, P2-21). The requirements are as specified in 3.4.5.2.d.(2).

(4) Electrical cage return, W1, P2-23 (W2, P2-22). The requirements are as specified in 3.4.5.2.d.(3).

(5) Missile audio, W1, P2-15 (W2, P2-19). The requirements are as specified in 3.4.5.2.d.(4).

(6) Fire signal, W1, P2-13 (W2, P2-1). The requirements are as specified in 3.4.5.2.a.(7).

3.4.5.4 Built-in-test requirements.

a. Common requirements.

(1) Built-in-test (BIT) reject status shall be indicated by the flashing of the SELECTED FUNCTION NO-GO front panel lamp at a rate of 0.5 to 1.3 Hertz.

(2) BIT reject status indication shall be overridden when the FUNCTION SELECT switch is in the TD position.

(3) All BIT accept/reject limits shall be as specified in Drawing 1058AS1100.

b. Power supply BIT.

(1) For FUNCTION SELECT positions one through four, the BIT shall check all internal regulated power supply voltages and the DVM reference voltage against the +10 volt reference.

(2) For FUNCTION SELECT position four, the amplitude of the acquisition lambda signal shall also be checked.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

c. Frequency BIT.

(1) The audio oscillator frequency shall be checked against the master crystal oscillator in FUNCTION SELECT positions one through four.

(2) In FUNCTION SELECT position four, the acquisition lambda signal frequency shall be checked.

(3) The regulator load signal frequency shall be checked with the PROGRAM switch set to the LAU-7 position and the FUNCTION SELECT switch in position two.

d. Phase BIT. The phase relationship between the acquisition lambda signal and the left-right reference signal shall be tested when the FUNCTION SELECT switch is in position four.

e. Stray energy BIT. In FUNCTION SELECT position three, the one millisecond pulse response of all three stray energy detector hybrid circuits shall be tested.

f. Load circuit BIT. In FUNCTION SELECT Positions one through three, the operation of all pulse load transistors shall be tested whenever they are operating. The voltage waveforms at the transistor collector shall be compared with the waveform of the pulse which shall drive the transistor.

3.4.5.5 Digital voltmeter.

a. The test set shall have a built-in digital voltmeter capable of measuring both ac and dc voltages. The meter shall have full scale ranges of 4.99, 49.9 and 499 volts. The display shall be blanked except when the PRESS TO TEST DVM/RESET push-button is depressed.

b. For ac voltage measurement, the meter shall be rms calibrated and average responding. The accuracy of the reading shall be three percent of full scale $\pm$ one digit for frequencies of 100 Hertz to six kilohertz.

c. For dc voltage measurements, the reading shall be an instantaneous value stored by a sample and hold circuit. Updating of measurement shall occur at a one Hertz rate. Updating shall be between the 14th and 18th milliseconds of the 20 milliseconds, one Hertz, repetitive load pulses, where applicable. The accuracy of the readings shall be + two percent of full scale + one digit of the instantaneous interface voltage.

d. The voltmeter input shall be connected to the various input and output lines by the use of the LINE SELECT switch. The relationships of the LINE SELECT switch positions and the input and output pins shall be as specified in table VII. For LINE SELECT positions four through eight, and 11 through 24, the input impedance of the selected interface pin shall be modified by an additional 100K ohms resistance in parallel to ground.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

3.4.6 Major components performance. Unless otherwise specified herein, these requirements apply under both standard and environmental conditions specified in 3.4.2 and 3.4.2.1.

TABLE VII. Line select switch.

Switch Position	Function Name	Interface Pin No.	
		W1-P2	W2-P2
1	115v, Phase A	1	9
3	Regulator Load	32	--
4	Missile Audio	15	19
5	L-R Reference	34	23
6	Acquisition Lambda	5	21
7	ECA, Amplified	23	22
8	ECA, Direct	23	22
9	--	--	--
10	Missile B+	33	--
11	Heater Filament	18	15
12	Missile Filament	22	--
13	Power Changeover	19	--
14	Launch Latch	3	--
15	Gas Grain Squib/Fire	13	1
16	Motor Fire Squib	1/	--
17	Auxiliary Fire	27	--
18	Master Arm	--	6
19	Cool Control	--	20
20	Manual Uncage	--	25
21	Electrical Cage Return	23	22
22	Electrical Cage	30	--
23	Missile ID	17	13
24	ECA Detector Output	--	--

1/ Connected to Striker Block contact of W1 cable.

Source: https://assist.dla.mil - Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

3.4.6.1 Electronic circuit cards. The performance characteristics for the test set circuit cards (1A1A2A1 - 1A1A2A11) shall be in accordance with the respective drawings listed in table VIII.

TABLE VIII. Electronic circuit card drawing list.

Card Name (Function)	Reference Designation	30003 Performance Requirements Drawing	30003 Assembly Drawing
Stray Energy Detection	1A1A2A1	1058AS164	1058AS160
Regulator Load Acquisition Lambda Signal R-L Reference, DVM Amp., ac/dc Converter Circuitry	1A1A2A2	1058AS169	1058AS165
Voltage Regulators, Precision References	1A1A2A3	1058AS174	1058AS170
Load Comparators (Pylon tests 2 and 3)	1A1A2A4	1058AS179	1058AS175
Load Comparators (Pylon tests 1 and 4)	1A1A2A5	1058AS184	1058AS180
GO/NO-GO, Audio and Electronic Caging Amplifier (ECA) Detector Circuitry	1A1A2A6	1058AS189	1058AS185
Load Drivers, Master Timing	1A1A2A7	1058AS194	1058AS190
Digital Voltmeter	1A1A2A8	1058AS199	1058AS195
Frequency and Phase Detector	1A1A2A9	1058AS204	1058AS200
Load Circuit Built-In-Test (BIT) and BIT Output	1A1A2A10	1058AS209	1058AS205
Power Supply BIT	1A1A2A11	1058AS270	1058AS265

3.4.6.2 Cable W1. The performance characteristics for cable assembly W1 shall be in accordance with Drawing 1058AS275.

3.4.6.3 Pylon adapter W2. The performance characteristics for the pylon adapter shall be in accordance with Drawing 1058AS290.

3.4.7 Weight. The total weight of the test set shall be not greater than 48 pounds.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

3.4.8 Identification plate and markings. Nomenclature and identification marking shall be in accordance with MIL-STD-130.

3.5 Soldering. All electrical soldered connections shall be in accordance with MIL-STD-454, Requirement 5.

3.6 Workmanship. Workmanship shall be in accordance with MIL-STD-454, Requirement 9.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. Unless otherwise specified in the contract or purchase order, the contractor is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or purchase order, the contractor may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 Responsibility of compliance. All items must meet all requirements of Sections 3 and 5. The inspection set forth in this specification shall become a part of the contractor's overall inspection system or quality program. The absence of any inspection requirements in the specification shall not relieve the contractor of the responsibility of assuring that all products or supplies submitted to the Government for acceptance comply with all requirements of the contract. Sample tests of quality conformance does not authorize submission of known defective material, either indicated or actual, nor does it commit the Government to acceptance of defective material.

4.2 Classification of inspections. The inspection requirements specified herein are classified as follows:

a. First article inspection (see 4.4).

b. Quality conformance inspection (see 4.5).

4.3 Inspection conditions. Unless otherwise specified herein, all inspections shall be performed in accordance with the conditions specified in 3.4.3.

4.3.1 Performance characteristics.

4.3.1.1 Before tests. The test set shall be in accordance with the requirements for interference control (see 3.4.2.1.1) and warm-up time (see 3.4.3.2).

4.3.1.2 During inspection acceptance tests. The test set shall be in accordance with the requirements of Section 3.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

4.4 First article inspection.

4.4.1 First article samples. First article tests shall be made on a test set representative of the production test sets to be supplied under the contract. First article test performance shall be the responsibility of the contractor and shall be performed in accordance with approved test procedures (see 4.6). No first article inspections shall be conducted prior to acceptance of the first article test procedure by the contracting officer.

4.4.2 Scope of first article tests. First article tests shall include all tests deemed necessary by the procuring activity to determine that the test set meets all the requirements of this specification and the contract. These shall include environmental and interference tests as specified in MIL-T-28800. Environmental test methods shall be in accordance with MIL-T-28800 except as modified by this specification. Electromagnetic interference test methods shall be in accordance with MIL-STD-462.

4.4.3 First article acceptance. Acceptance of the first article will be by the procuring activity upon the contractor meeting the requirements of all tests.

4.4.4 Production equipments. Test sets supplied under the contract shall, in all respects including design, construction, workmanship, performance and quality, be equal to the accepted first article sample. Each test set shall be capable of successfully completing the same tests as imposed on the first article sample. Evidence-of non-compliance with the above shall constitute cause for rejection of a test set and of a test set already accepted by the Government. The contractor shall make necessary corrections as authorized by the procuring activity.

4.5 Quality conformance inspection. The contractor shall furnish all samples and shall be responsible for accomplishing the quality conformance tests. All inspection and testing shall be to the accepted quality conformance test procedures under the supervision of the Government inspector. Quality conformance or acceptance of material during the course of manufacture shall not be construed as a guarantee of the acceptance of the finished product. Tests shall consist of the following:

a. Individual tests (see 4.5.1)

b. Sample tests (see 4.5.2) or reliability assurance tests (see 4.5.3)

c. Special tests (see 4.5.4)

d. Life tests (see 4.5.6)

4.5.1 Individual tests. Each test set made available for acceptance shall be subjected to the individual tests. These tests shall be adequate to determine compliance with the requirements of material, workmanship, operational adequacy and reliability. As a minimum, each test set accepted shall have passed the following tests:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

a. Examination of product (see 4.5.1.1)

b. Operational test (see 4.5.1.2)

c. Manufacturing run-in test (see 4.5.1.3)

4.5.1.1 Examination of product. Each test set shall be examined carefully to determine that the material and workmanship requirements have been met.

4.5.1.2 Operational test. Each test set shall be operated not less than 10 minutes to permit the temperature to stabilize and to check sufficient characteristics and record adequate data to assure required test set operation.

4.5.1.3 Environmental burn-in. Each test set shall be operated under the conditions specified herein for a period of 48 operational hours without failure. A failure shall be specified as anything which causes malfunctioning of the test set. Only those adjustments will be permitted which can be made using controls that are accessible to the operator during normal use of the test set. The test time shall be comprised of nine 8-hour environmental test cycles consisting of three hours (test set non-operational) at -40°C and five hours (test set operational) at +55°C. The unit shall be energized during the -40°C performance test just prior to transition from cold to hot, the transition from cold to hot, and the entire hot soak. The performance tests shall be conducted once daily after stabilization at each temperature. The test set shall be checked for compliance with performance requirements. Should repetitive failures occur, corrective action shall be taken to eliminate this defect from future test sets. A record shall be kept of all failures.

4.5.2 Sample tests. Test sets selected for sample tests shall first have passed the individual tests. Test sets will be selected for sample tests by the Government inspector in accordance with table IX.

TABLE IX. Sample test sample selection.

Quantity of Equipments Offered for Acceptance	Quantity to be Selected for Sampling Test
First 10	1
Next 50	1
Next 75	1
Next 100	1
	1 for each additional 200 or fraction thereof

4.5.2.1 Scope of tests. As a minimum, each test set selected for sample tests shall be subjected to the following:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

a. Complete operational test at standard laboratory room conditions, making all necessary measurements to assure that all applicable specification requirements have been met.

b. Operational test at certain environmental conditions. The conditions may vary for each test set tested and should be based on results of the first article, individual and special tests.

c. Environmental burn-in test specified in 4.5.1.3.

4.5.3 Reliability assurance tests. Reliability assurance tests shall be conducted in accordance with the requirements of MIL-STD-781. Tests shall be conducted as required for both the qualification phase and the production acceptance (sample) phase.

4.5.3.1 Reliability qualification phase. Prior to acceptance of test sets under the contract or purchase order, a contractually specified quantity of test sets (or not less than three if not specified) shall be tested in accordance with MIL-STD-781. For the qualification base, the test set shall be preconditioned at a test temperature level of -54 to +55°C (temperature cycling with the unit off during the cold portion of the cycle and temperature cycling with the unit on during the hot portion of the cycle), The accept/reject criteria for Test Plan IVC shall be used.

4.5.3.2 Reliability acceptance phase. Production lot samples of the test sets shall be tested in accordance with MIL-STD-781. For the sample phase. MIL-STD-781 shall be used. The accept/reject criteria for Test Plan IVC shall be used to determine the length of the tests (until an accept or reject decision is reached).

4.5.3.2.1 Acceptance phase sample size. The test sets constructed during a six month period shall be one lot. The accept/reject criteria for MIL-STD-781, Test Plan IV shall be used to determine the length of the tests in each lot. When specified in the contract or purchase order, no test sets shall be shipped until an accept decision is reached under each lot (see 6.2.1).

4.5.3.3 Test details. The test details such as the length of the test cycle, the length of the heat portion of the cycle, the performance characteristics to be measured, special failure criteria, and preventive maintenance to be allowed during the test, shall be part of the test procedures.

4.5.4 Special tests. Special tests shall be conducted for the purpose of checking the effect of any design or material change on the performance of the test set and to assure adequate quality control, The test set selected for special tests shall be selected from test sets previously subjected to the sample or reliability assurance tests.

4.5.4.1 Special test schedule. Selection of test sets for special tests shall be made as follows:

a. On early test sets after an engineering or material change.

b. Whenever failure reports or other evidences indicate that additional tests are required. (This will be determined by the procuring activity.)

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

4.5.4.2 Scope of tests. Special tests shall consist of such tests as are acceptable to the procuring activity. Test procedures previously approved for the first article tests may be used where applicable.

4.5.5 Equipment failure. Should a failure occur during either the sample, reliability assurance or special tests, the following action shall be taken:

a, Determine the cause of failure.

b. Determine if the failure is an isolated case or a repetitive failure.

c. Where practical, include a test (in the individual test) to check all test sets for this requirement until assurance is forthcoming that the defect has been corrected.

4.6 Methods of examination and test. The procedures used for conducting first article tests and quality conformance tests are subject to Government modification or additional testing deemed necessary to determine compliance with the requirements of this specification and the contract. When approved test procedures are available from previous contracts, such procedures will be provided and may be used when their use is authorized by the procuring activity (subject to modification or additional tests when deemed necessary.

4.7 Pre-submission tests. No item, part, or complete equipment shall be delivered by the contractor until it has been previously tested and inspected by the contractor and found to comply with all-applicable requirements.

5. PACKAGING

5.1 Guided Missile Launcher Test Set AN/ASM-464A. The test set shall be preserved, packaged, and packed in accordance with the requirements of DL 1058AS11OO and MIL-P-116, Method II, Level A. The outer container shall be marked for shipment in accordance with MIL-STD-129.

5.2 Major components and parts. All major components and all parts, that are ordered as end items, shall be preserved, packaged, packed and marked for the level of shipment specified in the contract or purchase order in accordance with MIL-E-17555. If the component or part is not covered in MIL-E-17555, the method of preservation for Level A shall be determined in accordance with the selection chart in Appendix D of MIL-STD-794.

6. NOTES

6.1 Intended use. The test set specified herein is used to perform operational checks of the Sidewinder launching circuits and aircraft circuitry associated with the Guided Missile Launcher, LAU-7A. The test set is used to simulate the Sidewinder missile during Visual Target Acquisition System (VTAS) and Sidewinder Expanded Acquisition Mode (SEAM).

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

6.2 Ordering data.

6.2.1 Acquisition requirements.

a. Title, number, and date of this specification.

b. If first article inspection is required (see 3.2, 6.3).

c. Acceptance, if other than specified in 4.5.3.2.1.

6.2.2 Data requirements. When this specification is used in an acquisition and data are required to be delivered, the data requirements identified below shall be developed as specified by an approved Data Item Description (DD Form 1664) and delivered in accordance with the approved Contract Data Requirements List (CDRL), incorporated into the contract. When the provisions of DOD FAR Supplement, Part 27, Sub-Part 27.410-6 (DD Form 1423) are invoked and the DD Form 1423 is not used, the data specified below shall be delivered by the contractor in accordance with the contract or purchase order requirements, Deliverable data required by this specification are cited in the following paragraphs.

Paragraph no.	Data requirement title	Applicable DID no.	Options
4.4.1, 4.6	Procedure, First Article Inspection	DI-T-4901	---
4.4.4	Report, First Article Inspection	DI-T-4902	---
4.5.1.2, 4.5.1.3	Reports, Production Inspection	DI-T-4904	---
4.5.3.3	Procedures, Reliability Tests	DI-R-7035	---
4.5.4.2, 4.6	Procedures, Production/Acceptance Inspection	DI-T-4903	---

(Data item descriptions related to this specification, and identified in section 6 will be approved and listed as such in DOD 5010.12-L, AMSDL. Copies of data item descriptions required by the contractors in connection with specific acquisition functions should be obtained from the Naval Publications and Forms Center or as directed by the contracting officer.)

6.3 First article. When a first article inspection is required, the item should be a first article sample. The first article should consist of one test set. The contracting officer should included specific instructions in acquisition documents regarding arrangements for examinations, approval of first article test results and disposition of first articles. Invitations for bids should provide that the Government reserves the right to waive the requirement for samples for first article inspection to those bidders offering a product which has been previously acquired or tested by the Government, and that bidders offering such products, who wish to rely on such production or test, must furnish evidence with the bid that prior Government approval is presently appropriate for the pending contract.

6.4 Changes from previous issue. Asterisks are not used in this revision to identify changes with respect to the previous issue due to the extensiveness of the changes.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

6.5 Subject term (keyword) listing

Aircraft launcher
Card cage assembly
Detent fasteners
Igniter contract block
Launcher system
Printed circuit cards
Pylon
Self test circuitry
Test set
Weapon system

Preparing Activity
Navy-AS

(Project 4935-N064)

Source: https://assist.dla.mil/ -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

INSTRUCTIONS: In a continuing effort to make our standardization documents better, the DoD provides this form for use in submitting comments and suggestions for improvements. All users of military standardization documents are invited to provide suggestions. This form may be detached, folded along the lines indicated, taped along the loose edge *(DO NOT STAPLE)*, and mailed. In block 5, be as specific as possible about particular problem areas such as wording which required interpretation, was too rigid, restrictive, loose, ambiguous, or was incompatible, and give proposed wording changes which would alleviate the problems. Enter in block 6 any remarks not related to a specific paragraph of the document. If block 7 is filled out, an acknowledgement will be mailed to you within 30 days to let you know that your comments were received and are being considered.

NOTE. This form may not be used to request copies of documents, nor to request waivers, deviations, or clarification of specification requirements on current contracts. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements.

(Fold along this line)

(Fold along this line)

DEPARTMENT OF THE NAVY
Commanding Officer
Naval Air Engineering Center
Systems Engineering and Standardization Department
(SESD) Code 93
Lakehurst, NJ 08733-5100

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES

BUSINESS REPLY MAIL
FIRST CLASS PERMIT NO. 12503 WASHINGTON, D.C.

POSTAGE WILL BE PAID BY THE DEPARTMENT OF THE NAVY

Commanding Officer
Naval Air Engineering Center
Systems Engineering and Standardization Department
(SESD) Code 93
Lakehurst, NJ 08733-5100

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T10:37Z
Check the source to verify that this is the current version before use.