MIL-T-48297 (PA)
7 February 1974

MILITARY SPECIFICATION

TEST SET ASSEMBLY, DISPENSER CONTROL PANEL
FOR M56 AIRCRAFT SUBSYSTEM

This specification is approved for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 This specification covers the inspections and tests for a test set used to test aircraft panel controls for the M56 Aircraft Subsystem.

2. APPLICABLE DOCUMENTS

2.1 The following documents of the issue in effect on date of invitation for bids or request for proposals, form a part of this specification to the extent specified herein.

SPECIFICATIONS

MILITARY

MIL-A-2550 - Ammunition, General Specification for

STANDARDS

MILITARY

MIL-STD-105 - Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-109 - Quality Assurance Terms and Definitions
MIL-STD-1168 - Lot Numbering of Ammunition
MIL-STD-1235 - Single and Multilevel Continuous Sampling Procedures and Tables for Inspection by Attributes

FSC: 1345

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:21Z
Check the source to verify that this is the current version before use.

DRAWINGS

U.S. ARMY PICATINNY ARSENAL

PRODUCT AND PACKAGING DRAWINGS

9280143 - Dispenser Control Panel Test Set Assembly
9280144 - Cable, Test, Control Panel
9280145 - Bench Power Cord
9287748 - Packing and Marking for Drum, Metal, Shipping for Test Set Dispenser Control Panel.

(Copies of specifications, standards, and drawings required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the Contracting Officer).

3. REQUIREMENTS

3.1 Material. - Materials shall be in accordance with the applicable drawings and specifications.

3.2 Assembly. - The assembly shall comply with all requirements specified on Drawing (dwg.) 9280143 and with all requirements specified in applicable specifications.

3.3 Control Panel, Test Cable

3.3.1 Continuity. - The maximum resistance between all wired corresponding pins on the connectors shall be one hundred (100) milliohms.

3.3.2 Insulation Resistance. - The maximum leakage current between all pins and the shell shall be two (2) microamperes when measured at five hundred plus fifty (500 + 50) volts direct current (V.D.C.) for a minimum time of ten (10) seconds.

3.4 Bench Power Cord

3.4.1 Continuity. - The maximum resistance between the two connectors shall be one hundred (100) milliohms.

3.4.2 Insulation Resistance. - The maximum leakage current between the pins and the shell shall be two (2) microamperes when

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the currentversion before use.

measured at five hundred plus fifty (500 + 50) V.D.C., for a minimum time of ten (10) seconds.

3.5 Input Power Circuit Functioning. - The "EXTERNAL POWER" pilot light shall lightup when twenty eight plus or minus one volt direct current (28.0 ± 1.0 V.D.C.) is applied to connector "EXTERNAL POWER" (J3) with the "EXTERNAL POWER" (S1) switch in the "ON" position. The plus twenty eight (+28) V.D.C. shall be applied to pin number "A" of J3 and the input ground shall be connected to pin number "B" of J3. This twenty eight (28) V.D.C. input shall be present within one tenth (0.1) V.D.C. at the "PANEL TEST" (J4) Socket between pins "D and M", "K and M" and "N and M". Pin "M" shall be the ground reference.

3.6 "EXTERNAL POWER" Pilot Light Manual Functioning. - The "EXTERNAL POWER" pilot light shall function after twenty eight plus or minus one (28.0 ± 1.0) V.D.C. is applied as in 3.5 to connector "EXTERNAL POWER", J3 and the "PRESS TO TEST" switch of DS3 is pressed downward and held for a minimum of ten (10) seconds.

3.7 Left Jettison Power Manual Switch. - The "LEFT JETTISON POWER" pilot light shall function when twenty eight plus or minus one (28.0 ± 1.0) V.D.C. is applied as in 3.5 to connector "EXTERNAL POWER" (J3) and the "PRESS TO TEST" switch of "LEFT JETTISON POWER" while (DSI) is pressed downward and held for a minimum of ten (10) seconds.

3.8 Left Jettison Power Function - The "LEFT JETTISON POWER" pilot light shall function when twenty eight plus or minus one V.D.C. (28.0 ± 1.0) is applied to connector J4, "PANEL TEST". Pin "J" shall be the plus voltage reference and pin "M" shall be at ground potential. This twenty eight (28) V.D.C. input shall be present within one tenth (0.1) V.D.C. at connector J1, "LEFT JETTISON POWER" with pin "A" used as the plus voltage reference.

3.9 Right Jettison Power Manual Switch. - The "RIGHT JETTISON POWER" pilot light shall function when twenty eight plus or minus one (28.0 ± 1.0) V.D.C. is applied as in 3.5 to connector "EXTERNAL POWER" (J3) and the "PRESS TO TEST" switch of "RIGHT JETTISON POWER" while (DS2) is pressed downward and held for a minimum of ten (10) seconds.

3.10 Right Jettison Power Function - The "RIGHT JETTISON POWER" pilot light shall function when twenty eight plus or minus one V.D.C. (28.0 ± 1.0) is applied to connector J4, "PANEL TEST".

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

Pin "H" shall be the plus voltage reference and pin "M" shall be at ground potential. This twenty eight (28) V.D.C. input shall be present within one tenth (0.1) V.D.C. at connector J6, "RIGHT JETTISON POWER" with pin "A" used as the plus voltage reference.

3.11 Empty Test Function - Continuity shall only be present between pin G of connector J4, "PANEL TEST" and pin "A" of connector J2, "LEFT DISPENSER" when switch S2 is in the "EMPTY TEST" position. Continuity shall only be present between pin "F" of J4, "PANEL TEST" and pin "A" of connector J5, "RIGHT DISPENSER" when switch S2 is in the "EMPTY TEST" position. Continuity shall be present between pins "G" and "U" of connector J4, "PANEL TEST" and pin "A" of connector J2, "LEFT DISPENSER" when switch S2 is in the "TEST" position. Continuity shall be present between pins "F" and "V" of connector J4, "PANEL TEST" and pin "A" of connector J5, "RIGHT DISPENSER" when switch S2 is in the "TEST" position.

3.12 Left Solenoid Step Aircraft Panel Pulsing. - The test set shall be pulsed through pin "E" of connector J4, "PANEL TEST" in accordance with Table No. 1.

TABLE NO. 1

PULSE INPUTS

Series	No. of Pulses	Pulse Length (Milliseconds) (MS)	Pulse Height (Volts)	Time Between Pulses (MS)	Time Between Series (Sec)
1	6	25 ± 1.0	26.0 ± 1.0	25 ± 1.0	10 ± 1
2	10	25 ± 1.0	26.0 ± 1.0	25 ± 1.0	10 ± 1
3	40	25 ± 1.0	26.0 ± 1.0	25 ± 1.0	10 ± 1

The pulses shall register on the counter, M1, "LEFT SOLENOID STEP" in the sequence described in Table No. 1.

3.13 Left Solenoid Step Test Set Panel Pulsing. - The Test Set shall be pulsed through connector J7 and Switch S3 in the "LEFT SOLENOID STEP" position and into Counter M1, "LEFT SOLENOID STEP". Pul-

Source: https://assist.dla.mil -- Downloaded: 20260-22T19:21Z
Check the source to verify that this is the current version before use.

sing shall be in accordance with Table No. 1 of 3.12. The pulses shall be registered on counter M1 in the sequence described in Table No. 1.

3.14 Right Solenoid Step Aircraft Panel Pulsing. - The test set shall be pulsed through pin "L" of connector J4, "PANEL TEST" in accordance with Table No. 2.

TABLE NO. 2

PULSE INPUTS

Series	No. of Pulses	Pulse Length (Milliseconds) (MS)	Pulse Height (Volts)	Time Between Pulses (MS)	Time Between Series (sec)
1	6	25 ± 1.0	26.0 ± 1.0	25 ± 1.0	10 ± 1
2	10	25 ± 1.0	26.0 ± 1.0	25 ± 1.0	10 ± 1
3	40	25 ± 1.0	26.0 ± 1.0	25 ± 1.0	10 ± 1

The pulses shall register on the counter, M2, "RIGHT SOLENOID STEP" in the sequence described in Table No. 2.

3.15 Right Solenoid Step Test Set Panel Pulsing. - The Test Set shall be pulsed through connector J7 and Switch S3 in the "RIGHT SOLENOID STEP" position and into counter M2, "RIGHT SOLENOID STEP". Pulsing shall be in accordance with Table No. 2 of 3.14. The pulses shall be registered on counter M2 in the sequence described in Table No. 2.

3.16 Left Canister Fire Aircraft Panel Pulsing. - The test set shall be pulsed through pin "P" of connector J4, "PANEL TEST" in accordance with Table No. 3

TABLE NO. 3

PULSE INPUTS

Series	No. of Pulses	Pulse Length (Milliseconds) (MS)	Pulse Height (Volts)	Time Between Pulses (MS)	Time Between Series (Sec)
1	6	12 ± 1.0	26 ± 1.0	12 ± 1.0	10 ± 1
2	10	12 ± 1.0	26 ± 1.0	12 ± 1.0	10 ± 1
3	40	12 ± 1.0	26 ± 1.0	12 ± 1.0	10 ± 1

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

The pulses shall be registered on the counter, M3, "LEFT CANISTER FIRE" in the sequence described in Table No. 3.

3.17 Left Canister Fire Test Set Panel Pulsing. - The test set shall be pulsed through connector J7 and switch S3 in the "LEFT CANISTER FIRE" position and into counter M3, "LEFT CANISTER FIRE". Pulsing shall be in accordance with Table No. 3 of 3.16. The pulses shall be registered on counter M3 in the sequence described in Table No. 3.

3.18 Right Canister Fire Aircraft Panel Pulsing. - The test set shall be pulsed through pin "R" of connector J4, "PANEL TEST" in accordance with Table No. 4.

TABLE NO. 4

PULSE INPUTS

Series	No. of Pulses	Pulse Length (Milliseconds) (MS)	Pulse Height (Volts)	Time Between Pulses (MS)	Time Between Series (Sec
1	6	12 ± 1.0	26 ± 1.0	12 ± 1.0	10 ± 1
2	10	12 ± 1.0	26 ± 1.0	12 ± 1.0	10 ± 1
3	40	12 ± 1.0	26 ± 1.0	12 ± 1.0	10 ± 1

The pulses shall be registered on the counter, M4, "RIGHT CANISTER FIRE" in the sequence described in Table No. 4.

3.19 Right Canister Fire Test Set Panel Pulsing. - The test set shall be pulsed through connector J7 and Switch S3 in the "RIGHT CANISTER FIRE" position and into counter M4, "RIGHT CANISTER FIRE". Pulsing shall be in accordance with Table No. 4 of 3.18. The pulses shall be registered on counter M4 in the sequence described in Table No. 4.

3.20 Workmanship. - All parts and assemblies shall be fabricated and finished in a thorough, workmanlike manner. They shall be free of burrs, chips, sharp edges, cracks, unblended radii, surface defects, dirt, grease, rust, corrosion products, and other

Source: https://assist.dla.mil -- Downloaded: 20261O-22T19:21Z
Check the source to verify that this is the current version before use.

foreign matter. The cleaning agent or method used shall not be injurious to any part, nor shall the part be contaminated by the cleaning agents. All required markings shall be neat, legible and sharply defined.

3.21 Submission of Results of Contractor-conducted Examinations and Tests. - The contractor shall forward copies of the results as required by the contract. Results shall be submitted within thirty (30) days at the completion of each lot tested (see 6.4).

3.22 First Article Inspection. - This specification makes provisions for first article inspection. Requirement for the submission of first article samples by the contractor shall be as specified in the contract.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for Inspection.-Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements. Reference shall be made to MIL-STD-109 to define terms used herein. The provisions of MIL-A-2550 shall apply.

4.1.1 Submission of Product.-At the time each completed lot of items deliverable under the contract is submitted to the Government for acceptance, the contractor shall supply the following information accompanied by a certificate which attests that the information provided is correct and applicable to the product being submitted.

a. A statement that the lot complies with all of the quality assurance provisions specified in this specification.
b. Drawing and specification number and date, together with identification and date of changes thereto.
c. A statement that all material purchased by the contractor meets requirements, when such material is controlled by Government or commercial specifications referenced in any of the

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:21Z
Check the source to verify that this is the current version before use.

contractual documents, and that certificates of conformance are on file and available for review.

d. Number of items in the lot.

e. Date submitted.

The certificate shall be signed by a responsible agent of the certifying organization. The initial certificate submitted shall be substantiated by evidence of the agent's authority to bind his principal. Substantiation of the agents authority will not be required with subsequent certificates unless, during the course of the contract, this authority is vested in another agent of the certifying organization.

4.2 First Article Inspection

4.2.1 Submission.-Prior to the start of regular production the contractor shall submit a first article sample (see 6.1c) to a Government approved facility as designated by the contracting officer for evaluation in accordance with the provisions of 4.2.2 and 4.2.3. The first article sample shall consist of five (5) sets of parts and five (5) complete test set assemblies which have been produced by the contractor or furnished by a supplier and which have been manufactured using the same production processes, procedures and equipment which will be used in fulfilling the contract. All parts and materials including packaging and packing shall be obtained from the same source of supply as will be used in regular production. Prior to submission, the contractor shall inspect the sample to the degree necessary to assure that it conforms to the requirements of the contract and submit a record of this inspection with the sample, including a certificate of conformance for materials. A sample containing known defects will not be submitted unless specifically authorized by the Contracting Officer. A first article sample, or portion thereof, as directed by the Contracting Officer, shall also be submitted whenever there is a lapse in production for a period in excess of 90 days or whenever a change occurs in manufacturing process, material used, drawing or specification such as to significantly affect product uniformity as determined by the Government.

4.2.2 Inspections to be performed.-Assemblies and components will be subjected by the Government to any or all of the examinations and tests specified in this specification and any or all requirements of the applicable drawings.

4.2.3 Rejection. - If any component or assembly fails to comply with any or all of the applicable requirements, the

Source: https://assist.dla.mil -- Downloaded: 202640-22T19:21Z
Check the source to verify that this is the currentversion before use.

first article sample shall be rejected. The Government reserves the right to terminate its inspection upon any failure of an inert component or subassembly to comply with any of the stated requirements.

4.3 Inspection provisions

4.3.1 Lot formation.-The term "inspection lot" as used in this specification is defined as an essentially homogeneous collection of units of product from which a representative sample is drawn and inspected to determine conformance with applicable requirements. The sample selected shall represent only that quantity of units from which the sample was drawn and shall not be construed to represent any prior or subsequent quantities presented for inspection. Homogeneity shall be considered to exist provided the inspection lot has been produced by one manufacturer in one unchanged process using the same materials and methods in accordance with the same drawings, same drawing revisions, same specifications and same specification revisions and complies with the provisions for submission of product as specified in MIL-STD-105. Changes to the process, specifications, or drawings not affecting safety, performance, interchangeability, or storage, as determined by the Government, shall not be deemed to alter the homogeneity of an inspection lot. All material submitted for inspection in accordance with this specification shall comply with the homogeneity criteria specified herein regardless of the type of sampling procedure which is being applied to determine conformance with requirements. Lot numbering, as required, shall be in accordance with MIL-STD-1168.

4.3.2 Examination.-The examinations listed in the following subparagraphs shall be performed on inspection lots (see 4.3.1) of the components or assemblies designated in the applicable paragraph headings. Inspection for critical defects (and major defects, when so specified) shall be 100 percent. Sampling plans for major and minor defects shall be in accordance with MIL-STD-105 except that continuous sampling plans in accordance with MIL-STD-1235 may be used if approved by the Government. Instead of applying the AQL's designated herein to the groups of major and minor defects listed, the contractor may elect to apply an AQL of 0.40 percent for each major defect and an AQL of 0.65 percent for each minor defect. When this method is elected, it shall be applied to all of the major and minor defects listed in the applicable sub-paragraph of this section, except where 100 percent inspection is specified, and be documented as part of the contractor's inspection system. Equipment necessary for the performance of the inspections listed shall be in accordance with 4.3.4.

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

4.3.2.1 Cable, Test, Control Panel, prior to sealing connectors (see dwg. 9280144).

Categories	Defects	Method of Inspection	Code No. (see 6.2)
Critical:	None defined		
Major:	AQL 0.40 percent		
101.	Loose wires at solder joints ..	Visual/ Manual	01001
102.	Sleeving does not extend into bushing	Visual	01002
Minor:	AQL 0.65 percent		
201.	Evidence of poor workmanship (see 3.20)	Visual	01003

4.3.2.2 Cable, Test, Control Panel (see dwg. 9280144).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined		
Major:	AQL 0.65 percent		
101.	Sleeving or bushing not in place	Visual	02001
102.	Connectors not secured	Manual	02002
103.	Overall Length	Gage	02003
Minor:	AQL 0.65 percent		
201.	Evidence of poor workmanship (see 3.20)	Visual	02004

4.3.2.3 Bench Power Cord, prior to sealing connectors (see dwg. 9280145).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined		
Major:	AQL 0.40 percent		
101.	Loose wires at connector or alligator clip connections ...	Visual/	

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:21Z
Check the source to verify that this is the current version before use.

		Manual	03001
102.	Bushing does not extend to connector	Visual	03002
Minor:	AQL 0.65 percent		
201.	Evidence of poor workmanship (see 3.20)	Visual	03003

4.3.2.4 Bench Power Cord (see dwg. 9280145).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined		
Major:	AQL 0.65 percent		
101.	Clip(s) or wire(s) improperly color coded	Visual	04001
102.	Connector or strap(s) not secured	Manual	04002
103.	Length of loose leads	Gage	04003
104.	Length of solid cable	Gage	04004
Minor:	AQL 0.65 percent		
201.	Evidence of poor workmanship (see 3.20)	Visual	04005

4.3.2.5 Dispenser Control Panel Test Set Assembly, prior to securing test panel (see dwg. 9280143).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined		
Major:	AQL 0.40 percent		
101.	Loose or bunched-up leads	Visual	05001
102.	Any part(s) loose, missing or insecure	Visual/ Manual	05002
Minor:	AQL 0.65 percent		
201.	Evidence of poor workmanship (see 3.20)	Visual	05003

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

4.3.2.6 Dispenser Control Panel Test Set Assembly (see dwg. 9280143).

Categories	Defects	Method of Inspection	Code No.
Critical:	None defined		
Major:	AQL 0.65 percent		
101.	Missing component on test panel	Visual	06001
102.	Missing hardware	Visual	06002
103.	Misaligned latches	Visual/ Manual	06003
104.	Missing, incomplete or distorted marking	Visual	06004
Minor:	AQL 0.65 percent		
201.	Evidence of poor workmanship (see 3.20)	Visual	06005

4.3.3 TESTING

4.3.3.1 Control Panel Test Cable.

4.3.3.1.1 Continuity Test, (see 3.3.1). - Major Defect Code No. 02005. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.1. Any cable classed defective shall be removed from the lot. (Non-destructive test).

4.3.3.1.2 Insulation Resistance (see 3.3.2) Major Defect - Code No. 02006. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.2. Any cable classed defective shall be removed from the lot. (Non-destructive Test)

4.3.3.2 Bench Power Cord.

4.3.3.2.1 Continuity Test (see 3.4.1) - Major Defect - Code No. 04006. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.3. Any cord classed defective shall be removed from the lot (Non-destructive test)

4.3.3.2.2 Insulation Resistance (see 3.4.2).- Major Defect - Code No. 04007. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.4. Any cord classed defective shall be removed from the lot (Non-destructive test).

Source: https://assist.dla.mil -- Downloaded: 20260-22T19:21Z
Check the source to verify that this is the current version before use.

4.3.3.3 Ground Circuit Continuity (see dwg. 9281122). - Major Defect - Code No. 07001. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.5. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.4 Input Power Circuit Continuity (see dwg. 9281122) - Major Defect - Code No. 07002. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.6. Any test set classed defective shall be removed from the lot. (Non-destructive test).

4.3.3.5 Input Power Circuit Functioning (see 3.5). - Major Defect - Code No. 07003. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.7. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.6 "EXTERNAL POWER" Pilot Light Manual Test (See 3.6) Major Defect - Code No. 07004. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.8. Any test set classed defective shall be removed from the lot. (Non-destructive test).

4.3.3.7 Left Jettison Power Manual Switch. (see 3.7) - Major Defect - Code No. 07005. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.9. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.8 Left Jettison Power Functioning (see 3.8). - Major Defect - Code No. 07006. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.10. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.9 Right Jettison Power Manual Switch (see 3.9) - Major Defect - Code No. 07007. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.11. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.10 Right Jettison Power Functioning (see 3.10) - Major Defect - Code No. 07008. - The lot shall be tested 100

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the currentversion before use.

percent for the specified requirement in accordance with 4.4.12. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.11 Empty Test Function (see 3.11) - Major Defect - Code No. 07009. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.13. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.12 Left Solenoid Step Continuity (see dwg. 9281122) - Major Defect - Code No. 07010. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.14. Any test set classed defective shall be removed from the lot. (Non-destructive test).

4.3.3.13 Left Solenoid Aircraft Panel Pulsing (see 3.12) Major Defect - Code No. 07011. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.15. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.14 Left Solenoid Test Set Panel Pulsing (see 3.13) Major Defect - Code No. 07012. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.16. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.15 Right Solenoid Step Continuity (see dwg. 9281122) Major Defect - Code No. 07013. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.17. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.16 Right Solenoid Aircraft Panel Pulsing (see 3.14) Major Defect - Code No. 07014. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.18. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.17 Right Solenoid Test Set Panel Pulsing. - (see 3.15) Major Defect - Code No. 07015. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.19. Any test set classed defective shall be removed from the lot. (Non-Destructive test)

Source: https://assist.dla.mil -- Downloaded: 20261O-22T19:21Z
Check the source to verify that this is the current version before use.

4.3.3.18 Left Canister Fire Continuity (see dwg. 9281122) Major Defect - Code No. 07016. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.20. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.19 Left Canister Fire Aircraft Panel Pulsing (see 3.16) - Major Defect - Code No. 07017. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.21. Any test set classed defective shall be removed from the lot (Non-Destructive test).

4.3.3.20 Left Canister Fire Test Set Panel Pulsing (see 3.17). - Major Defect - Code No. 07018. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.22. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.21 Right Canister Fire Continuity (see dwg. 9281122) Major Defect - Code No. 07019. - The lot shall be tested 100 percent for the specified requirement in accordance with 4.4.23. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.3.22 Right Canister Fire Aircraft Panel Pulsing (see 3.18). - Major Defect - Code No. 07020. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.24. Any test set classed defective shall be removed from the lot (Non-destructive test).

4.3.3.23 Right Canister Fire Test Set Panel Pulsing. (see 3.19) - Major Defect - Code No. 07021. - The lot shall be tested 100 percent for the specified requirements in accordance with 4.4.25. Any test set classed defective shall be removed from the lot. (Non-destructive test)

4.3.4 Inspection Equipment. - Inspection equipment required to perform the inspection prescribed in this specification is identified in the examination (4.3.2) paragraph herein. See 6.3 for details concerning responsibilities for inspection equipment design and approval.

4.4 TEST METHODS AND PROCEDURES

Source: https://assist.dla.mil -- Downloaded: 202640-22T19:21Z
Check the source to verify that this is the currentversion before use.

4.4.1 Control Panel Test Cable Continuity Test. - The cable shall be tested in an approved test fixture with plugs having corresponding pin numbers relating to those on the cable connector. The cable shall be inserted into the plugs and the test made for continuity by measuring at the plugs on pins A, B,C, D, E, F, G, H, J, K, L, M, N, P, R, S, T, U and V. Any cable failing to comply with all of the specified continuity requirements shall be classed defective.

4.4.2 Control Panel Test Cable Insulation Resistance. - The cable shall be tested in an approved test fixture that shorts together all of the pins and ground except one. The voltage shall be applied between the open pin and the tied together pins while the leakage current is continuously monitored for the specified time. After this test, the procedure shall be repeated for each pin in the cable. Any cable failing to comply with all of the specified requirements shall be classed defective.

4.4.3 Bench Power Cord Continuity Test. - The cord shall be tested for the specified resistance using a digital readout ohmmeter. Any cord failing to comply with all of the specified requirements shall be classed defective.

4.4.4 Bench Power Cord Insulation Resistance Test. - The cord shall be tested for the specified requirement using an approved megohmmeter. The leakage current shall be continuously monitored during the specified time. Any cord failing to comply with all of the specified requirements shall be classed defective.

4.4.5 Ground Circuit Continuity Test. - The test set shall be tested for the specified requirement using a digital readout ohmmeter on the front panel between the test points specified in Table No. 5. Any test set failing to conform with the applicable requirement shall be classed defective.

TABLE NO. 5

GROUND CIRCUIT CONTINUITY TEST POINTS

Connector	J1	J2	J3	J4	J5	J6	J7
Pin(s)	D	E	B	M U V	E	D	CASE

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

4.4.6 Input Power Circuit Continuity Test. - The test set shall be tested for the specified requirements using a digital readout ohmmeter on the front panel between pins "D", "K" and "N" of connector J4. Any test set failing to conform with the applicable requirement shall be classed defective.

4.4.7 Input Power Circuit Functioning. - The required voltage shall be applied as specified to connector J3 and the "EXTERNAL POWER" light shall be visually tested for functioning. After this, a digital readout voltmeter shall be used to measure the specified voltages on connectors J3 and J4. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.8 "EXTERNAL POWER" Pilot Light Manual Functioning Test. - The specified voltage shall be applied to connector J3 and the "EXTERNAL POWER" switch (DS-3) shall be pressed and held for the specified time while a visual observation is made to ascertain that the bulb functions. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.9 Left Jettison Power Manual Switch Test. - The specified voltage shall be applied to connector J3 and the "LEFT JETTISON POWER SWITCH" (DSI) shall be pressed and held for the specified time while a visual observation is made to ascertain that the bulb functions. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.10 Left Jettison Power Function Test. - The specified voltage shall be applied to connector J3 and a visual observation made to ascertain that the pilot light functions. Also, a digital readout voltmeter shall be used to measure the specified voltages on J4 and J1. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.11 Right Jettison Power Manual Switch Test. - The specified voltage shall be applied to connector J3 and the "LEFT JETTISON POWER SWITCH" (DSI) shall be pressed and held for the specified time while a visual observation is made to ascertain that the bulb functions. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.12 Right Jettison Power Function Test. - The specified voltage shall be applied to connector J3 and a visual observation

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

made to ascertain that the pilot light functions. Also, a digital readout voltmeter shall be used to measure the specified voltages on J4 and J1. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.13 Empty Test Function Tests. - The test set shall be tested for the specified continuity requirements when switch, S2, is in the "EMPTY TEST" position by suing a digital ohmmeter to make the measurements. Switch, S2, shall be placed in the "TEST" position and the digital ohmmeter shall be used to measure the continuity between the specified connectors. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.14 Left Solenoid Step Continuity. - The test set shall be tested for the specified requirement between connector J4, pin "E" and connector J2, pin "B" using a digital readout ohmmeter. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.15 Left Solenoid Aircraft Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of pulse tests. The counter shall register from zero (0) the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.16 Left Solenoid Test Set Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of tests. The selector switch shall be positioned before the pulsing starts and the counter shall be set to zero (0). The counter shall register the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.17 Right Solenoid Step Continuity. - The test set shall be tested for the specified requirement between connector J4, pin "L" and connector J5, pin "B" using a digital readout ohmmeter. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.18 Right Solenoid Aircraft Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of pulse tests. The counter shall register from zerio (0) the proper amount of pulses during each sequence.

Source: https://assist.dla.mil -- Downloaded: 20260-22T19:21Z
Check the source to verify that this is the current version before use.

Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.19 Right Solenoid Test Set Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of tests. The selector switch shall be positioned before the pulsing starts and the counter shall be set to zerio (0). The counter shall register the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.20 Left Canister Fire Continuity. - The test set shall be tested for the specified requirement between connector J4, pin "P" and connector J2, pin "D" using a digital readout ohmmeter. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.21 Left Canister Fire Aircraft Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of pulse tests. The counter shall register from zero (0) the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.22 Left Canister Fire Test Set Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of tests. The selector switch shall be positioned before the pulsing starts and the counter shall be set to zero (0). The counter shall register the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.23 Right Canister Fire Step Continuity. - The test set shall be tested for the specified requirement between connector J4, pin "R" and connector J5, pin "D" using a digital readout ohmmeter. Any test set failing to comply with all of the specified requirements shall be classed defective.

4.4.24 Right Canister Fire Aircraft Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of pulse tests. The counter shall register from zero (0) the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

Source: https://assist.dla.mil -- Downloaded: 20261O-22T19:21Z
Check the source to verify that this is the current version before use.

4.4.25 Right Canister Fire Test Set Panel Pulsing Test. - The test set shall be pulsed as specified using an approved pulse generator for the three (3) series of tests. The selector switch shall be positioned before the pulsing starts and the counter shall be set to zero (0). The counter shall register the proper amount of pulses during each sequence. Any test set failing to comply with all of the specified requirements shall be classed defective.

5. PREPARATIONS FOR DELIVERY

5.1 Preservation and Packaging.

5.1.1 Level A. - The test set and cables shall be packaged in accordance with dwg. 9287748.

5.2 Packing

5.2.1 Level A. - The test sets and cables shall be packed for shipment in accordance with dwg. 9287748.

5.3 Marking. - Marking of the carton shall comply with dwg. 9287748.

5.4 Shipping. - When test sets and cables of more than one lot are shipped together each lot shall be kept separate and the division between lots clearly indicated to prevent mixing of the lots in transit.

6. NOTES

6.1 Ordering data.-Procurement documents shall specify the following:

a. Title, number and date of this specification.
b. Data cards. - Data cards shall be prepared for each lot in accordance with the information specified in Standard MIL-STD-1167.
c. Provisions for submission of first article samples.

6.2 Inspection code numbers.-The five digit code numbers assigned to the inspections herein are to facilitate future data collection and analysis by the Government. They should be cited as references on drawings of equipment designs submitted by the contractor to the Government for approval (see

Source: https://assist.dla.mil -- Downloaded: 202610-22T19:21Z
Check the source to verify that this is the current version before use.

6.3.3).

6.3 Inspection Equipment Designs.-Inspection equipment designs are of two types - Government Special Inspection Equipment (SIE) designs and contractor designs. SIE designs are designated by drawing numbers under the "Method of Inspection" headings in Section 4. Design responsibility for all other inspection equipment is assigned to the contractor. The contractor need not furnish any design when a complete Government SIE design is provided. Unless otherwise specified, however, the contractor may submit alternate or modified contractor designs of SIE in accordance with 6.3.2 and 6.3.3 should he elect to do so.

6.3.1 SIE designs.-SIE designs may consist of any of the following:

a. Detailed drawings which completely depict all information necessary for the fabrication and use of the item of inspection equipment.

b. A source control drawing or a specification control drawing as defined in MIL-STD-100.

c. An envelope drawing, as defined in MIL-STD-100, which establishes the criteria which a detailed design shall meet. When envelope drawings are specified, the contractor shall prepare designs which comply with the criteria therein.

6.3.2 Contractor designs.-Contractor designs are required for all inspection equipment for which SIE designs are not specified and may include commercial equipment which the contractor proposes to use. (Commercial equipment is defined as unmodified equipment which is cataloged and available for purchase by the general public). Contractor designs shall include appropriate operating instructions, calibration procedures and maintenance procedures. Commercial equipment shall be fully described by catalog listings or other means which provide sufficient information to permit identification and evaluation by the Government and may include illustrations and engineering data. Designs shall be prepared for any special fixture(s) required to be used with commercial equipment, or with SIE designs if not otherwise covered thereby (see 6.3.1c). Designs shall be of the category and form (per MIL-D-1000) specified in the Contract Data Requirements Lists (DD Form 1423). The contractor is referred to MIL-HDBK-204, "Inspection Equipment Design" for guidance. The specification number and the applicable five digit defect code number (or

Source: https://assist.dla.mil -- Downloaded: 202640-22T19:21Z
Check the source to verify that this is the currentversion before use.

other specific identifying information) from Section 4 of this specification shall be referenced on each contractor design together with the component or assembly drawing number and revision letter to which the specific design applies.

6.3.3 Submission of Designs for Approval.-Contractor designs shall be approved by the Government prior to fabricating or procuring the equipment. Designs shall be submitted for approval to Picatinny Arsenal, ATTN: SARPA-QA-A-M, Dover, New Jersey 07801 in accordance with the stipulations, time frame and distribution specified in the Contract Data Requirements List (DD Form 1423) or in the contract. The contractor must include in his submission of designs a listing of any and all Government SIE designs which will be utilized. Partial submission of inspection designs is permissible and encouraged. However, the completion date for design review will be based on the date of the final submission of designs. Picatinny Arsenal design review will normally be accomplished within one month after receipt.

6.4 Submission of results of contractor conducted examinations and tests (see 3.21). - The contractor shall send his results to:

Commander
Picatinny Arsenal
ATTN: SARPA-QA-A-M
Dover, New Jersey 07801

Custodian:
Army-PA

Preparing Activity:
Army-PA

Project Number: 1345-A-046

Source: https://assist.dla.mil -- Downloaded: 202640-22T19:21Z
Check the source to verify that this is the current version before use.

FOLD

DEPARTMENT OF THE ARMY
PICATINNY ARSENAL
DOVER, NEW JERSEY 07801

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

POSTAGE AND FEES PAID
DEPARTMENT OF THE ARMY
DOD – 314

U.S.MAIL

COMMANDER
Picatinny Arsenal
ATTN: SARPA-QA-A
Dover, New Jersey 07801

FOLD

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:21Z
Check the source to verify that this is the current version before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

OMB Approval
No. 22-R255

INSTRUCTIONS: The purpose of this form is to solicit beneficial comments which will help achieve procurement of suitable products at reasonable cost and minimum delay, or will otherwise enhance use of the document. DoD contractors, government activities, or manufacturers / vendors who are prospective suppliers of the product are invited to submit comments to the government. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements. Attach any pertinent data which may be of use in improving this document. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity.

DOCUMENT IDENTIFIER AND TITLE

NAME OF ORGANIZATION AND ADDRESS

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE DOCUMENT CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY DOCUMENT REQUIREMENT CONSIDERED TOO RIGID

3. IS THE DOCUMENT RESTRICTIVE?

☐ YES ☐ NO *(If "Yes", in what way?)*

4. REMARKS

SUBMITTED BY *(Printed or typed name and address - Optional)*

TELEPHONE NO.

DATE

DD FORM 1 JAN 72 1426

REPLACES EDITION OF 1 JAN 66 WHICH MAY BE USED

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T19:21Z
Check the source to verify that this is the current version before use.