MILITARY SPECIFICATION

VOLTAGE REGULATOR SUBASSEMBLY: 10525750

This amendment forms a part of Military Specification MIL-V-60216(MU), dated 3 March 1965.

Table II, Variable inputs: Delete all of the columns under Variable inputs and substitute:

"NAME	LOW LINE (volts)	NOMINAL LINE (volts)	HIGH LINE (volts)
+6V main DC	+13.5 ± 1.4	+17.1	+20.0
-10V main DC	-14.5 ± 1.2	-17.9	-21.5
+20V	+17.0 ± 1.5	+21.0	+25.0
-32V	-26.0	-32.0	-37.5
-12V	-11.0 ± 0.2	-12.0 ± 0.2	13.0 ± 0.2"

Table II, under Trip load: Delete "1.5 ± 0.2" and "2.4 ± 0.2" and substitute "1.5 $\pm \begin{smallmatrix} 0.30 \\ 0.0 \end{smallmatrix}$" and "2.4 $\pm \begin{smallmatrix} 0.30 \\ 0.0 \end{smallmatrix}$".

Table II, under Loads: Add new column:

"Extreme Temperature Trip Loads

-10V Load	1.5 + 0.70 amperes
+6V Load	2.4 + 0.40 amperes - 0.20

Table II, Tripped output: Delete "(+10 percent)" and substitute "(±10 percent)".

Table III, Characteristic 107, Requirement Column: Delete "3.4.7" and substitute "3.5".

* Following paragraph 4.1.1: Add paragraphs 4.1.2, 4.1.2.1 and 4.1.2.2 as follows:

"4.1.2 First article (initial production) approval.- The requirement for first article approval and the responsibility (Government or contractor) for first article testing shall be as specified in the contract. The sample for first article approval tests shall consist of three (3) voltage regulators manufactured in the same manner using the same materials, equipment, processes, and procedures as used in regular production. All parts and materials, including packaging and packing, shall be obtained from the same source of supply as used in regular production.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:19Z
Check the source to verify that this is the current version before use.

4.1.2.1 Government testing.- When the Government is responsible for conducting first article approval tests, the contractor, prior to submitting the sample to the Government, shall inspect the sample to insure that it conforms to all the requirements of the contract and submit a record of this inspection with the sample, including certificates of performance for materials.

4.1.2.2 Contractor testing.- When the contractor is responsible for conducting first article approval tests, the sample shall be inspected by the contractor for all the requirements of the contract. The sample and a record of this inspection, including certificates of conformance for materials, shall be submitted to the Government for approval. The Government reserves the right to witness the contractor's inspection."

* Paragraph 4.3.2: Change first sentence of paragraph to read as follows:

"Voltage regulator units shall be selected at random by a Government representative as control samples from each three (3) months production or portion thereof as follows:

3 units per first 100 produced
5 units per 200
7 units per 300
9 units per 400
10 units per 500
12 units per 700
15 units per 1000
and 2 units for each 100 items produced in excess of 1000."

Paragraph 4.5.1.3.2: Delete in its entirety and substitute:

"4.5.1.3.2 Operating.- This test shall be conducted in accordance with the humidity test defined in Procedure III of MIL-F-13926, except that the humidity shall be maintained at 92 to 97 percent for the 24-hour period, and the test shall cease at the end of that period (Method 106 of MIL-STD-202 shall be excluded). Throughout the test period, the board shall be capable of performing the test of 4.5.2.4. In order to demonstrate this capability, the tests of 4.5.2.4 shall be performed a minimum of once each 6 hours of the period. The final test shall be conducted during the final portion of the 24-hour period. Between tests, the board shall be electrically energized as described in 4.5.2.4.1."

Paragraph 4.5.1.4: Delete in its entirety and substitute:

"4.5.1.4 Salt spray.- This test shall be conducted in accordance with the salt spray test defined in Method 101, Condition B of MIL-STD-202 using a 5 percent salt solution. At the end of the exposure period, salt deposits shall be removed from the board by a gentle wash, not exceeding 30 minutes, in running water not warmer than 100°F, using a soft-hair brush or plastic-bristle brush. The board shall be air dried in a controlled

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:19Z
Check the source to verify that this is the current version before use.

environment at 72°F ± 5°F and a relative humidity of 30 to 50 percent for a period of 24 hours. The board shall be inspected visually for any physical damage, then tested in accordance with 4.5.2.2 to 4.5.2.4.2.2 inclusive."

Paragraph 4.5.2: Delete in its entirety and substitute:

"4.5.2 Performance.- To determine compliance with 3.4.1, the voltage regulator shall be visually inspected to insure that all components are physically present and conform to ordnance drawing No. 10525753. If resistors R8, R9, R21, R23, R25, R26, R43, R52, R58, R66, R69 and R74 are missing, they shall be selected and installed using procedure indicated in 4.5.3.1 to 4.5.3.5 inclusive. If the voltage regulator conforms to ordnance drawing No. 10525753, it shall be electrically tested as indicated in 4.5.4.1 to 4.5.8 inclusive."

Paragraph 4.5.3.2: Delete "Table V" and substitute "Table II".

* Paragraph 4.5.3.3, first sentence: Delete "1.5 amperes" and substitute "1.8 amperes". Delete "Table V" and substitute "Table II".

* Paragraph 4.5.3.5: Add to end of paragraph "except for the trip current resistors. For the +6 volt trip resistor values shall be those determined by selecting the ratio of resistors (R52 to R43) that causes tripping at a current nearest to but $\geq$ 2.4 amperes. For the -10 volt trip resistor values shall be those determined by selecting the ratio of resistors (R8 to R9) that causes tripping at a current nearest to but $\leq$ 1.8 amperes".

Paragraph 4.5.4.3: Delete "1.75" and substitute "1.79".

Paragraph 4.5.4.4: Delete "2.65" and substitute "2.8".

Figure 5, line 8: Delete "R4: 10526600" and substitute "R4: 10526660".

*The outside margins have been marked to indicate where additions to the previous amendment have been made. This has been done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in this notation. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content as written irrespective of the marginal notations and relationship to the last previous amendment.

Custodian:

Army - MU

Preparing activity:

Army - MU

Project No. 1220-A100

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T00:19Z
Check the source to verify that this is the current version before use.