MILITARY SPECIFICATION

POWER PLANT, DIESEL ENGINE, TRAILER MOUNTED

200 KW, 60 HERTZ, AN/MJQ-11A

This specification is approved for use within the USA Belvoir Research, Development, and Engineering Center, Department of the Army, and is available for use by all Departments and Agencies of the Department of Defense.

1. SCOPE

1.1 Scope. This specification covers a trailer mounted generator set (hereinafter referred to as a power plant) designated AN/MJQ-11A. The power plant consists of a Department of Defense design, diesel-engine-driven, 200 kW, 60-Hertz generator set, various auxiliary equipment, brackets, and hardware mounted on 15 ton commercial fixed gooseneck, dropdeck, flatbed, trailer chassis.

2. APPLICABLE DOCUMENTS

2.1 Government documents.

2.1.1 Specifications and standards. Unless otherwise specified (see 6.2), the following specifications and standards of the issue listed in that issue of the Department of Defense Index of Specifications and Standards (DoDISS) specified in the solicitation, form a part of this specification to the extent specified herein.

SPECIFICATIONS

FEDERAL

UU-T-81	- Tags, Shipping and Stock.
PPP-B-601	- Boxes, Wood, Cleated-Plywood.
PPP-B-636	- Boxes, Shipping, Fiberboard.
PPP-T-97	- Tape, Pressure-Sensitive Adhesive, Filament Reinforced.

Beneficial comments (recommendations, additions, deletions) and any pertinent data which may be of use in improving this document should be addressed to: USA Belvoir Research, Development, and Engineering Center, ATTN: STRBE-TSE, Fort Belvoir, VA 22060-5606 by using the self-addressed Standardization Document Improvement Proposal (DD Form 1426) appearing at the end of this document or by letter.

AMSC N/A FSC 6115

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:57Z
Check the source to verify that this is the current version before use.

MILITARY

MIL-P-116	- Preservation, Methods of.
MIL-E-10062	- Engines: Preservation for Shipment and Storage of.
MIL-G-28554	- Generator Sets, Mobile Electric Power; Packaging of.

STANDARDS

MILITARY

MIL-STD-105	- Sampling Procedures and Tables for Inspection by Attributes.
MIL-STD-129	- Marking for Shipment and Storage.
MIL-STD-281	- Automobiles, Trucks, Truck-Tractors, Trailers and Trailer Dollies; Preservation and Packaging of.
MIL-STD-642	- Identification Marking of Combat and Tactical Transport Vehicles.
MIL-STD-705	- Generator Sets, Engine and Driven, Methods of Tests and Instructions.
MIL-STD-889	- Dissimilar metals.

2.1.2 Other Government drawings. The following other Government drawings, form a part of this specification to the extent specified herein. Unless otherwise specified, the issues shall be those in effect on the date of the solicitation.

DRAWINGS

ME

TA13220E6338	- Generator Set, Diesel Engine, Trailer Mounted, 200 KW, 60 Hertz AN/MJQ-11A.

(Copies of specifications, standards, and drawings required by contractors in connection with specific acquisition functions should be obtained from the contracting activity or as directed by the contracting officer.)

2.3 Order of precedence. In the event of a conflict between the text of this specification and the references cited herein, the text of this specification shall take precedence. Nothing in this specification, however, shall supersede applicable laws and regulations unless a specific exemption has been obtained.

3. REQUIREMENTS

3.1 Description. The AN/MJQ-11A shall be in accordance with TA13220E6338 and as specified herein.

3.1.1 Drawings. The drawings forming a part of this specification are end product drawings. No deviation from the prescribed dimensions or tolerances is

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:57Z
Check the source to verify that this is the currentversion before use.

permissible without prior approval of the contracting officer. Any data (e.g. shop drawings, layouts, flow sheets, processing procedures, etc.) prepared by the contractor or obtained from a vendor to support fabrication and manufacture of the production item shall be made available, upon request, for inspection by the contracting officer or his designated representative.

3.1.1.1 Vehicle marking. Registration numbers and other marking of the trailer shall be in accordance with MIL-STD-642 (see 6.7).

3.2 First article. When specified (see 6.2), a sample shall be subjected to first article inspection (see 4.3 and 6.3). Any changes or deviations of power plants from the approved first article during production will be subject to the approval of the contracting officer. Approval of the first article will not relieve the contractor of his obligation to furnish power plants conforming to this specification.

3.3 Material. Material shall be as specified herein and as shown on the applicable drawings. Materials not specified shall be selected by the contractor and shall be subject to all provisions in 3.3.1, 3.3.2, 3.3.3 and 3.3.4 of this specification.

3.3.1 Material deterioration and control. The item(s) shall be fabricated from compatible materials, inherently corrosion resistant or treated to provide protection against the various forms of corrosion and deterioration that may be encountered in any of the applicable operation and storage enviroments to which the item may be exposed.

3.3.2 Dissimilar metals. Dissimilar metals shall not be used in intimate contact with each other unless protected against galvanic corrosion. Dissimilar metals and methods of protection are defined and detailed in MIL-STD-889.

3.3.3 Identification of materials and finishes. The contractor shall identify the specific material, material finish or treatment for use with component and subcomponent, and shall make information available upon request to the contracting officer or designated representative.

3.3.4 Recovered materials. For the purpose of this requirement, recovered materials are those materials which have been collected from solid waste and reprocessed to become a source of raw materials, as distinguished from virgin raw materials. The components, pieces and parts incorporated in the generator set may be newly fabricated from recovered materials to the maximum extent practicable, provided the generator set produced meets all other requirements of this specification. Used, rebuilt or remanufactured components, pieces and parts shall not be incorporated in the generator set.

3.4 Government-furnished property. The following property in the quantities indicated will be furnished by the Government (see 6.4):

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:57Z
Check the source to verify that this is the currentversion before use.

Item No.	Description	Identification	Quantity for each AN/MJQ-11A
1	Chassis, Trailer, 15 ton commercial fixed goose-neck, drop neck.	NSN 2330-01-090-7868	2
2	Generator set, diesel-engine-driven, 200 kW, 60 Hertz DOD Model MEP-009A.	NSN 6115-00-133-9104	2

3.5 Workmanship. Workmanship shall be of a quality to assure that the power units are free from defects resulting from defective material, incorrect manufacturing or assembly practices, incorrect treatment and painting, incomplete welds, rust, cracks, and other defects that could impair its operation or serviceability. External surfaces shall be free from burrs, sharp edges, and corners except when sharp edges and corners are specified on the applicable drawing.

3.6 Safety. All changes, deviations, and waivers to TA13220E6338 shall be in accordance with the following requirements. All rotating or reciprocating parts and other parts subject to high operational temperatures that are of such a nature or are so located as to be a hazard to operating personnel, shall be guarded or insulated to the extent necessary to eliminate the hazard. Electrical equipment shall be effectively guarded and grounded to protect all persons and objects from electrical shock hazard.

3.7 Power plant component tests. The power plant switch box assembly and components shall be prepared for testing as specified in 4.5.2.1. The test shall be conducted as outlined in 4.5.2.2 unless otherwise specified in the contract.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. Unless otherwise specified in the contract, the contractor is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract, the contractor may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform or repeat any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 Disassembly inspection. Failure of the examination by the first article model shall be cause for disassembly in the presence of a Government representative of the first article model to the extent necessary to determine the cause of the failure. Each disassembled part shall be examined in detail for compliance with this specification and referenced drawings in regard to materials, dimensions, tolerances, and workmanship. Parts not complying with such requirements shall be rejected. Reassembly with accepted parts and reexamination shall be the responsibility of the contractor. Government-furnished property shall be excluded from the requirements of this paragraph.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:57Z
Check the source to verify that this is the current version before use.

4.1.2 Component and material inspection. The contractor is responsible for insuring that components and materials used are manufactured, examined, and tested in accordance with referenced specifications and standards.

4.1.3 Acceptability criteria. Power plants which conform to all requirements in sections 3 and 5 of this specification and pass all applicable examinations in section 4 of this specification will be considered acceptable by the Government.

4.2 Classification of inspections. The inspection requirements specified herein are classified as follows:

a. First article inspection (see 4.3).
b. Quality conformance inspection (see 4.4).
c. Inspection of packaging (see 4.6).

4.3 First article inspection.

4.3.1 Examination. The first article power plant shall be examined as specified in 4.5.1. Presence of one or more defects shall be cause for rejection.

4.3.2 Tests. The first article power plant components shall be tested as specified in 4.5.2. Failure of any test shall be cause for rejection or for performing the disassembly inspection specified in 4.1.1.

4.4 Quality conformance inspection.

4.4.1 Examination. Each power plant shall be examined for the defects specified in 4.5.1. Presence of one or more defects shall be cause for rejection.

4.4.2 Tests. Power plant components shall be tested as specified in 4.5.2. Failure of any test shall be cause for rejection.

4.5 Inspection procedure.

4.5.1 Examination. The power plant shall be examined for the following defects:

101. Materials not as specified.
102. Materials are resistant to corrosion or deterioration or treated to be made resistant to corrosion or deterioration for the applicable storage and operating environment.
103. Dissimilar metals as defined in MIL-STD-889 are not effectively insulated from each other.
104. Contractor does not have documentation available for identification of material, material finishes or treatments.
105. Used, rebuilt, or remanufactured components, pieces or parts incorporated in the generator sets.
106. Treatment and painting not as specified.
107. Dimensions not as shown on drawings.
108. Components missing or not as specified.
109. Assembly not as shown on the drawings.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:57Z
Check the source to verify that this is the current version before use.

110. Workmanship not as specified.
111. Safety not as specified.

4.5.2 Tests.

4.5.2.1 Test conditions. The following preparations shall be made prior to testing the switch box assembly:

a. Power input cables shall be connected to the switch box assembly.
b. The free ends of the power input cables shall be attached to the generator sets as follows:

1. Cable wire marked L_1 shall be attached to Phase A.
2. Cable wire marked L_2 shall be attached to Phase B.
3. Cable wire marked L_3 shall be attached to Phase C.
4. Cable wire marked L_0 shall be attached to neutral.

c. Paralleling cables shall be connected to the switch box assembly.
d. A 3 phase, 4 wire, 200KW resistive load shall be connected to the output of the switch box.

4.5.2.2 Test procedure. Tests shall be conducted in accordance with MIL-STD-705 and as specified herein. Test instruments shall be of the laboratory type and shall have been calibrated within 30 days prior to the start of testing and at intervals not more than 6 months thereafter.

1. Set all Circuit Breakers in the "OFF" Position.
2. Set Switch S2 INPUT VOLTAGE SELECTION for 120/208 VOLT INPUT.
3. Set Switch S1 COMMERCIAL POWER LOCKOUT to GENERATOR A Input Position.
4. Apply 120/208 Volts, 3-Phase voltage to GENERATOR UNIT A, POWER INPUT PANEL.
5. Indicator Light for GENERATOR UNIT A should be on.
6. Energize GENERATOR UNIT A Circuit Breaker.
7. Indicator Light for Power Output should be on.
8. Energize OUTPUT CIRCUIT BREAKER. Voltage should appear on output terminals.
9. COMMERCIAL POWER CIRCUIT BREAKER should be locked out and will not close.
   Reset Breaker.
10. Reduce voltage on GENERATOR A Input. OUTPUT CIRCUIT BREAKER should trip. Record input voltage.
11. Increase voltage on GENERATOR A INPUT to 120/208 VOLT. OUTPUT CIRCUIT BREAKER shall be capable of being re-energized after being reset.
12. Open GENERATOR A CIRCUIT BREAKER, OUTPUT CIRCUIT BREAKER should trip. Reset Circuit Breaker.
13. Disconnect input power to SWITCH BOX.
14. Set Switch S1 to GENERATOR UNIT B operation.
15. Apply 120/208, 3-pase voltage to GENERATOR UNIT B INPUT TERMINALS. Repeat steps 5 through 13, except that all references will be to GENERATOR UNIT B.
16. Disconnect input power to SWITCH BOX.
17. Apply voltage to COMMERCIAL POWER INPUT TERMINALS.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:57Z
Check the source to verify that this is the current version before use.

18. Indicator light for Commercial Power should be on.
19. Energize COMMERCIAL POWER CIRCUIT BREAKER.
20. Both GENERATOR CIRCUIT BREAKERS will be locked out and will not close. Reset both GENERATOR CIRCUIT BREAKERS.
21. Energize OUTPUT CIRCUIT BREAKER. Voltage should appear on Load Terminals.
22. Perform Steps 10, 11 and 12 using COMMERCIAL POWER INPUT as the control. Record data as 22/10, 22/11 and 22/12.
23. Disconnect power to SWITCH BOX.
24. Repeat all steps except that Switch S2 will be set for 240/416 Volt, 3-phase operation. Input and output indicator lights shall operate during tests. Inability of the switch box assembly to maintain and transfer rated load shall constitute failure of this test. With the paralleling cables connected to the switch box assembly, a continuity test of connector pins at cable ends shall confirm proper assembly; absence of continuity shall constitute failure of this test. Failure of the GFE generators to operate in accordance with the operator's manual shall not constitute failure of this test. The contracting officer shall be notified immediately of any such failure.

4.6 Inspection of packaging.

4.6.1 First article pack inspection. The first article pack shall be examined for defects specified in 4.6.2.3. Presence of one or more defects shall be cause for rejection. Any defect(s) shall be corrected and the first article re-examined.

4.6.2 Quality conformance inspection of pack.

4.6.2.1 Unit of product. For the purpose of inspection, a completed pack prepared for shipment shall be considered a unit of product.

4.6.2.2 Sampling. Sampling for examination shall be in accordance with MIL-STD-105.

4.6.2.3 Examination. Samples selected in accordance with 4.6.2.2 shall be examined for the following defects. AQL shall be 1.0 percent defective.

112. Generator sets not preserved as specified for levels A and B.
113. Engine and engine accessories not preserved as specified for level A and B.
114. Fire extinguisher not removed from bracket and preserved as specified for levels A and B.
115. Power and ground cable not disconnected and secured as specified for levels A and B. Cable and terminals not matchmarked as specified.
116. Hammer, fuel can adapters, oil drain line and ground rods not secured as specified.
117. Technical publications not preserved as specified for all levels.
118. Trailer chassis components not preserved as specified for levels A and B.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:57Z
Check the source to verify that this is the current version before use.

119. Packing not as specified for all levels.
120. Marking illegible, incomplete, incorrect, or missing.
121. Depreservation guides not prepared and attached to the power unit as specified.

5. PACKAGING

5.1 First article pack. The contractor shall furnish a first article pack for examination within the time frame specified (see 6.2) to prove prior to starting production packaging that the applied preservation, packing, and marking comply with the packaging requirements of this specification. Examination shall be as specified in Section 4 and shall be subject to surveillance and approval by the Government (see 6.5). The first article pack may be accomplished utilizing either the first article power plant or a production power plant. If the first article power plant is utilized, any preservation, and packing shall be removed by the contractor at no expense to the Government, when requested by the Government to facilitate comparison between the first article power plant and production power plant.

5.2 Preservation. Preservation shall be level A, B, or C, as specified (see 6.2).

5.2.1 Level A.

5.2.1.1 Generator sets. The generator set shall be preserved in accordance with MIL-P-116, method IIa. The generator set shall be secured directly through the barrier material to the trailer chassis, using the required mounting bolts. Before positioning the barrier material over the generator, the generator shall be covered with a half slotted container constructed in accordance with PPP-B-636, without cover, type CF, class-domestic, variety SW, grade-200 minimum. The container shall be sealed in accordance with method I of the appendix thereto. All sharp edges of the container that can damage the barrier material shall be covered with non abrasive pressure sensitive tape. The top corners of the container shall be rounded to prevent them from puncturing the barrier material. Additionally, the bottom corners and the bottom portion of the forward and aft panels shall be trimmed to receive the wood wedges. The barrier shall be protected by a box-type cover consisting of ends, sides, and top constructed in accordance with PPP-B-601, for an overseas type, style I box. Sides and ends shall be 1/4-inch-thick plywood. The top shall be one piece 1/2- inch-thick plywood and shall completely cover all edges. The humidity indicator and inspection port shall be installed on an end or side in a location convenient for inspection of the humidity indicator. The cover shall be secured using wood wedges and lag screws. The wedges shall be cut to fit the angle of the ends of the generator skids and shall be of sufficient length and width to provide a snug fit to the inside of the cover. The angle surface of the wedge shall be cushioned with fiberboard where contact with the barrier is required. Lag screws shall be the minimum length required to secure the cover to prevent puncture of the barrier. Before inclosing the generator set in the Method IIa barrier, the following preservation shall be accomplished.

Source: https://assist.dla.mil -- Downloaded: 20261O-22T21:57Z
Check the source to verify that this is the currentversion before use.

5.2.1.1.1 Engine. The engine and engine accessories shall be preserved in accordance with MIL-E-10062, level A, type II, method II. Drivebelts shall be relieved from tension and tagged and battery cables shall be disconnected and secured as specified therein.

5.2.1.1.2 Fire extinguisher. The fire extinguisher shall be removed from the bracket and preserved in a box conforming to PPP-B-636, type CF, class domestic, variety SW, grade 125, style optional and shall be secured to the generator set with tape conforming to PPP-T-97, type IV.

5.2.1.1.3 Cable. The ground cable shall be disconnected and the terminals on the generator set and cable ends shall be matchmarked with tags conforming to UU-T-81, type A. The cable shall be coiled, the coil secured. The coiled cable shall be secured to the generator set with tape conforming to PPP-T-97, type IV.

5.2.1.1.4 Hammer, fuel can adapters, oil drain line, and ground rods. The hammer, fuel can adapters, oil drain line, and ground rods shall be secured in the accessory box with tape conforming to PPP-T-97, type IV.

5.2.1.2 Chassis. The trailer chassis components shall be preserved in accordance with MIL-STD-281, level A, as specified for mobile vehicles.

5.2.1.3 Technical publications. Technical publications shall be preserved in accordance with MIL-P-116, method IC-1 and shall be secured to the generator set outside the method II barrier.

5.2.2 Level B. The generator set shall be preserved as specified for level A except for the following.

5.2.2.1 Box-type cover. The box-type cover specified in 5.2.1.1 shall be domestic type.

5.2.2.2 Engine. The engine and engine accessories shall be preserved in accordance with MIL-E-10062, level A, type II, method I.

5.2.2.3 Trailer chassis. The trailer chassis components shall be preserved in accordance with MIL-STD-281, level B, as specified for mobile units.

5.2.3 Level C. Power units including all components and surfaces requiring it, shall be preserved to provide protection against deterioration and damage during shipment and handling from the contractor to the initial destination. Cables shall be disconnected and match marked. All loose components shall be placed in the accessory box or secured in their disignated brackets. Technical publications shall be placed in a waterproof bag and placed in the accessory box.

5.3 Packing. Packing shall be level A, B, or C as specified (see 6.2).

5.3.1 Level A or B. Packing shall be in accordance with MIL-G-28554 and as specified herein. The humidity indicator and inspection port shall be installed on an end or side in a location convenient for inspection of the humidity indicator.

Source: https://assist.dla.mil -- Downloaded: 20261O-22T21:57Z
Check the source to verify that this is the current version before use.

5.3.2 Level C. Power units shall be completely mobile. Any components not placed in secure brackets shall be removed from them and placed in an out of the way area and secured to prevent loss or damage during shipment.

5.4 Marking. Marking for all levels shall be in accordance with MIL-STD-129.

5.5 Depreservation guides. Two copies of depreservation guides shall be prepared and placed in waterproof envelopes marked "Depreservation Guide". One copy shall be secured on the generator set and a second copy shall be secured in a conspicuous location on the power unit. Unless otherwise specified (see 6.2), DA Form 2258 "Depreservation Guide for Vehicles and Equipment" shall be used (see 6.6).

5.6 Preparation of Government-furnished property. Government-furnished property shall be preserved, packaged, and packed as specified herein, regardless of the preservation, packaging, and packing provided at the time of receipt by the contractor.

6. NOTES

6.1 Intended use. The power plant is intended for use by the armed services to supply electrical power for military operations.

6.2 Ordering data. Procurement documents should specify the following:

a. Title, number, and date of this specification.
b. Date of issue of DoDISS applicable and exceptions thereto (see 2.1.1).
c. Time frame required for submission of the first article model (see 3.2).
d. Time frame required for submission of the first article pack (see 5.1).
e. Degree of preservation and of packing required (see 5.2 and 5.3).
f. When other than DA Form 2258 is to be used (see 5.5).

6.3 First article. When a first article inspection is required, the items should be a first article model. The first article should consist of one or more units. The contracting officer should include specific instructions in acquisition documents regarding arrangements for examinations, tests and approval of the first test results and disposition of the first articles.

6.4 Government-furnished property. The contracting officer should arrange to furnish the property specified in 3.4.

6.5 First article pack. Any changes or deviations of production packs from the approved first article pack will be subject to the approval of the contracting officer. Approval of the first article pack will not relieve the contractor of his obligation to preserve, pack, and mark the power units in accordance with this specification.

6.6 Depreservation guide. The contracting officer should arrange to furnish the necessary copies of DA Form 2258, when requested by the contractor (see 5.5).

Source: https://assist.dla.mil -- Downloaded: 20260-22T21:57Z
Check the source to verify that this is the current version before use.

6.7 Registration numbers. The contracting officer should arrange to furnish a list of registration numbers to be applied to the trailer (see 3.1.1.1).

6.8 Subject term (key word) listing.

Diesel engine
Power unit
Power plant
Trailer mounted

Custodian:
Army - ME

Preparing activity:
Army - ME

Project 6115-A502

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T21:57Z
Check the source to verify that this is the current version before use.

INSTRUCTIONS: In a continuing effort to make our standardization documents better, the DoD provides this form for use in submitting comments and suggestions for improvements. All users of military standardization documents are invited to provide suggestions. This form may be detached, folded along the lines indicated, taped along the loose edge *(DO NOT STAPLE)*, and mailed. In block 5, be as specific as possible about particular problem areas such as wording which required interpretation, was too rigid, restrictive, loose, ambiguous, or was incompatible, and give proposed wording changes which would alleviate the problems. Enter in block 6 any remarks not related to a specific paragraph of the document. If block 7 is filled out, an acknowledgement will be mailed to you within 30 days to let you know that your comments were received and are being considered.

NOTE: This form may not be used to request copies of documents, nor to request waivers, deviations, or clarification of specification requirements on current contracts. Comments submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or to amend contractual requirements.

(Fold along this line)

(Fold along this line)

DEPARTMENT OF THE ARMY

NO POSTAGE NECESSARY IF MAILED IN THE UNITED STATE

OFFICIAL BUSINESS
PENALTY FOR PRIVATE USE $300

BUSINESS REPLY MAIL
FIRST CLASS PERMIT NO. 12062 WASHINGTON D. C.

POSTAGE WILL BE PAID BY THE DEPARTMENT OF THE ARMY

Commaneer
USA Belvoir RDE Center
STRBE-TSE
Fort Belvoir, VA 22060-5606

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:57Z
Check the source to verify that this is the currentversion before use.

STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

(See Instructions – Reverse Side)

1. DOCUMENT NUMBER	2. DOCUMENT TITLE
MIL-P-53069(ME)	Power Plant, Diesel Engine, Trailer Mounted 200 KW, 60 Hertz, AN/MJQ-11A

3a. NAME OF SUBMITTING ORGANIZATION	4. TYPE OF ORGANIZATION *(Mark one)*
	☐ VENDOR
b. ADDRESS *(Street, City, State, ZIP Code)*	☐ USER
	☐ MANUFACTURER
	☐ OTHER *(Specify)*: _____

5. PROBLEM AREAS

a. Paragraph Number and Wording:

b. Recommended Wording:

c. Reason/Rationale for Recommendation:

6. REMARKS

7a. NAME OF SUBMITTER *(Last, First, MI)* – Optional	b. WORK TELEPHONE NUMBER *(Include Area Code)* – Optional
c. MAILING ADDRESS *(Street, City, State, ZIP Code)* – Optional	8. DATE OF SUBMISSION *(YYMMDD)*

(TO DETACH THIS I, CUT ALONG THIS LINE.)

DD FORM 82 MAR 1426 PREVIOUS EDITION IS OBSOLETE.

Source: https://assist.dla.mil -- Downloaded: 202610-22T21:57Z
Check the source to verify that this is the current version before use.