MILITARY SPECIFICATION

TEST SET, COMPUTER, WEAPONS RELEASE AN/ASM-150

This specification has been approved by the Naval Air Systems Command, Department of the Navy

1. SCOPE

1.1 Scope - The test equipment covered by this specification shall be for shop and flight line use and shall perform operational tests on Weapons Release Computer CP-741(V)/A and related cockpit controls.

1.2 Classification - The Test Set, Computer, Weapons Release AN/ASM-150 shall consist of the following items:

Items	Type Designation	Appl. Para.
Test Set, Computer, Weapons Release	TS-2187/ASM-150	3.6.1
Cover, Test Set Unit	CW-769/ASM-150	3.6.2
Simulator, Module, Computer	SM-404/ASM-150	3.6.3
Case, Simulator and Cable	CY-4557/ASM-150	3.6.4
Cover, Simulator and Cable Case	CW-770/ASM-150	3.6.5
Cable Assembly, Special Purpose, Electrical	CX-10158/ASM-150	3.6.6
Cable Assembly, Power, Electrical, Branched	CS-10159/ASM-150	3.6.7
Tool, Module Puller and Disconnect	63A25D24	3.6.8
Wrench, Hex	58A5A294	3.6.9
Simplified Test Instructions	63A25D11	3.6.10

2. APPLICABLE DOCUMENTS

2.1 General - The following documents of the issue in effect on the date of invitation for bids form a part of this specification to the extent specified herein:

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

SPECIFICATIONS

Military

MIL-T-5422	Testing, Environmental, Aircraft Electronic Equipment
MIL-I-6181	Interference Control Requirements, Aircraft Equipment
MIL-E-17555	Electronic and Electrical Equipment and Associated Repair Parts, Preparation for Delivery of
MIL-T-18303	Test Procedures; Preproduction and Inspection, for Aircraft Electronic Equipment, Format for
MIL-T-21200	Test Equipment for Use with Electronic and Fire Control Systems, General Specifications for
MIL-W-27076	Workmanship Standards for Ground Electronics and Associated Equipment
MIL-P-24014	Preclusion of Hazards from Electromagnetic Radiation to Ordnance, General Requirements for
MIL-C-81233	Computer, Weapons Release CP-741(V)/A

STANDARDS

Military

MIL-STD-454	Standard Requirements for Electronic Equipment
MIL-STD-470	Maintainability Program Requirements for Systems and Equipments Prediction
MIL-STD-471	Maintainability Demonstrations
MIL-HDBK-472	Military Standardization Handbook, Maintainability Predictions
MIL-STD-781	Test Level and Accept/Reject Criteria for Reliability of Non-Expendable Electronic Equipment

BULLETINS

ANA Bulletin No. 400	Air Force-Navy Aeronautical Bulletin Electronic Equipment: Aircraft and Guided Missiles, Applicable Documents

DRAWINGS

Naval Air Systems Command

List of Drawings DL-63A25E1 for Test Set, Computer, Weapons Release AN/ASM-150. All drawings listed in this specification are a part of

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

DL-63A25E1 except the following:

64A6A100 (NASC)	Quality Assurance Information Requirements
64A7A100 (NASC)	Quality Assurance Information Requirements

2.1.1 Availability of Documents -

(1) Contractors requesting documents required in connection with specific procurement functions shall, on the application, refer to the documents by both title and number.

(2) Copies of this specification and specifications, standards, and publications referenced herein and in DL 63A25E1 may be obtained upon application to the Commanding Officer, Naval Supply Depot, Code 105, 5801 Tabor Avenue, Philadelphia, Pennsylvania 19120.

(3) Copies of DL 63A25E1 and the drawings listed therein may be obtained upon application to the Commanding Officer, Naval Air Technical Services Facility, 700 Robbins Avenue, Philadelphia, Pennsylvania 19111.

3. REQUIREMENTS

3.1 Preproduction - This specification makes provision for preproduction testing.

3.2 Parts and Materials - Parts and materials shall be as specified in DL 63A25E1. Any deviation by the contractor from the use of these specified parts and materials necessarily places both the burden of proof of the acceptability of the change, and the cost associated therewith, upon the contractor. Approval for deviations must be requested from the procuring activity by the contractor and granted by the procuring activity prior to submission of equipments for preproduction tests. A request for approval shall include, as supporting evidence, the data specified in 3.3. Approval of parts and material deviations shall not be construed by the contractor to constitute a waiver of any other requirement specified in this specification or in the applicable drawings of DL 63A25E1.

3.2.1 Quality of Parts Requirements - The contractor shall be responsible for assuring that all electrical, electromechanical and electronic parts meet the requirements of the "Preferred" or "Qualified" category as defined herein (see 6.4). Any information obtained from a component parts vendor by any other company or government activity for placing the parts in the "Preferred" or "Qualified" category shall not be applicable. (Exceptions to this are parts manufactured to conventional "MIL", "MS", or "AN" Specifications having Qualification Approval (QPL) requirements.) The lots of any parts meeting only the requirements of the "Preliminary" category, as defined herein (see 6.4), must be qualified individually by passing such tests as necessary to determine conformance to critical requirements. Data required to classify a part shall be made available to the procuring activity upon request.

3.3 Supplemental Requirements - The following supplemental requirements for the selection of parts and materials are applicable only in the event that the contractor proposes to alter the equipment design delineated by the drawings of DL 63A25E1.

3.3.1 Conformance to MIL-T-21200 - Parts and materials selected for use in the equipment shall conform to the requirements of MIL-T-21200. Parts shall be selected

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

from those parts included in ANA Bulletin No. 400, unless the parts listed therein will not perform adequately in the applications and environments specified herein.

3.3.2 Nonstandard Parts and Material Approval - Approval for the use of nonstandard parts and materials shall be obtained by the contractor as outlined in MIL-T-21200 (see 6.3).

3.4 Design and Construction - The equipment shall be manufactured in accordance with the drawings and subsidiary specifications listed in DL 63A25E1, except insofar as errors of omission or commission on the drawings may be incompatible with the requirements of this and related specifications. In any case, it is a condition of final acceptance that the equipment meet all the performance requirements specified herein and such acceptance test documents that shall be applicable. Proposed changes, either to correct errors in the design disclosure or to effect improvements, shall be specifically approved in writing by the procuring activity unless otherwise specified.

3.4.1 Reliability -

3.4.1.1 Operational Stability - The equipment shall operate with satisfactory performance, continuously or intermittently, for a period of at least 125 hours without the necessity for readjustment of any controls which are inaccessible to the operator during normal use.

3.4.1.2 Operating Life - The equipment shall have a minimum total operating life of 10,000 hours with reasonable servicing and replacement of parts. Parts requiring scheduled replacement due to wear during the life of the equipment, and the wearout life of such parts, shall be determined by the contractor and submitted to the procuring agency (see 6.3).

3.4.1.3 Reliability in Mean-Time-Between-Failure - The equipment shall have a minimum of 317 hours of mean- (operating) time-between-failures when tested and accepted as outlined under the requirements of 4.4.3.

3.4.2 Interchangeability - If the contractor proposes to alter the equipment design as described in 3.3, the drawings listed on DL 63A25E1 shall be the standard for measuring interchangeability of all replaceable assemblies, subassemblies, and parts.

3.4.3 Interference Control - The generation of radio interference by the equipment shall not exceed the limits of MIL-I-6181 by more than 60 db above one microvolt/mc. The equipment shall not malfunction while being exposed to radio interference as specified in MIL-P-24014.

3.4.4 Mean-Time-To-Repair (MTTR) - The mean-time-to-repair (MTTR) of the equipment shall be not greater than 2.5 hours when replacing circuit modules, plug-ins, assemblies and parts that are intended for replacement at the organizational level. Only where design changes shall cause significant deviations from procuring activity drawings, a prediction of MTTR shall be made in accordance with MIL-STD-470 and MIL-HDBK-472, PROCEDURE II, and shall be demonstrated in accordance with 4.2.2.1.

3.4.5 Standard Conditions - The following conditions shall be used to establish normal performance characteristics under standard conditions and for making laboratory bench tests.

Temperature	Room ambient (30 ± 10°C)
Altitude	Normal ground

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

Vibration	None
Humidity	Room ambient
Input Power	115 ± 11.5 V AC 400 ± 20 cps and 27.0 ± 2.0 V DC

3.4.6 Service Conditions - The equipment shall operate within the specified tolerance limits of 3.6 under any of the environmental service conditions or reasonable combination of these conditions as specified in MIL-T-21200 for Class 2 equipment except as specified below.

3.4.6.1 Shock - In addition to the shock requirements of MIL-T-21200 the test equipment, when stored in its respective transit case and combination case, shall operate as specified in 3.5 after subjection to 2 half sine wave, 70g shocks, each of 7 milliseconds duration applied upward along the vertical axis of the test equipment cases. Physical damage to the equipment is permissible provided the electrical operational requirements of 3.5 are maintained.

3.4.7 Warm-Up Time - The equipment shall require a maximum of 15 seconds warm-up time above +10°C, and a maximum of 2 minutes below +10° Centigrade.

3.4.8 Primary Input Power Requirements - The power required shall be of the following types and shall not exceed the specified amounts.

AC Power, Single Phase, 115 V, 400 cps, 200 VA

DC Power, 28 V, 160 watts

3.5 Performance - The performance of the equipment shall be as set forth below. Unless otherwise specified, these requirements shall apply under both standard and extreme service conditions. When reduced performance requirements for service conditions are acceptable, such variation will be specified.

3.6 Detail Requirements -

(1) Normal Operating Position - The normal operating position of the test set shall be with the front panel in a horizontal position.

(2) Measuring Equipment - Electrical requirements specified herein shall be measured with equipment having the following capabilities as a minimum.

a. DC voltage measurements - Measurement to 5 significant figures with an accuracy of ±0.01 percent of reading ±1 digit in the fifth significant figure.

b. AC voltage measurements - Measurement to 4 significant figures with an accuracy of ±0.1 percent of reading, ±2 digits in the fourth significant figure.

c. Resistance measurement - Measurement to 5 significant figures with an accuracy as follows:

0 to 999.99 ohms ± (0.01 percent of reading ± 2 digits)
1.0000 K to 99.999 K ohms ± (0.01 percent of reading ± 1 digit).
100 K to 999.99 K ohms ± (0.03 percent of reading ± 1 digit).

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

d. Voltage output - Adjustable to the nearest fifth significant figure with an accuracy of ±0.01 percent of setting or ±100 μv, whichever is greater.

e. Time measurement - Measurement to 4 significant figures with an accuracy of ±0.01 percent of reading.

(3) Computer Test Outputs - When Test Set TS-2187/ASM-150, Computer Module Simulator SM-404/ASM-150, and Special Purpose Electrical Cable CX-10158/ASM-150 are properly connected to Weapons Release Computer CP-741(V)/A built to MIL-C-81233 the integrate time and light indication for each TEST switch position shall be as specified in the applicable drawing of DL 63A25E1.

3.6.1 Test Set, TS-2187/ASM-150 - The test set unit shall be manufactured in accordance with the applicable drawings of DL 63A25E1 and shall meet the following requirements.

3.6.1.1 Function - The test set unit shall generate eight attack problems for testing Weapons Release Computer CP-741(V)/A and shall provide a means for indicating computer performance.

3.6.1.2 *Electrical Requirements - The test set shall meet the following electrical* requirements:

3.6.1.2.1 Ground Resistance - A resistance of not more then 1 ohm shall be obtained from pin 5 of the SHOP POWER connector to the chassis.

3.6.1.2.2 AC Voltage Adjust - The AC VOLTAGE SELECT switch (S101), AC VOLTAGE ADJUST autotransformer (T101), AC VOLTAGE meter (M102) and associated wiring operating in conjunction shall meet the following requirements when 115.0 volts a-c is applied between SHOP POWER connector J101-1 and J101-4 (neutral):

3.6.1.2.2.1 When the AC VOLTAGE SELECT switch is set to the NOM. position, the AC VOLTAGE ADJUST transformer may be adjusted until the AC VOLTAGE meter reads 115 volts a-c.

3.6.1.2.2.2 Without readjusting the transformer, the AC VOLTAGE SELECT switch shall be placed in the LOW and the HIGH positions. This shall cause the AC VOLTAGE meter to read 107.5 ± 2.0 volts a-c and 119.5 ± 2.0 volts a-c respectively.

3.6.1.2.2.3 The above performance shall be repeated, when the voltage applied between J101-1 and J101-4 is either 103.5 volts a-c or 126.5 volts a-c instead of 115 volts a-c.

3.6.1.2.2.4 The above performance shall be repeated with loads from 0 to 120 VA between J102-F and J102-s.

3.6.1.2.3 Attack Problem Voltage Outputs - The test set unit shall provide the following attack problem voltage outputs at SIMULATOR connector J102 when +10.0 volts d-c ± 0.01 percent is applied between SIMULATOR connector J102-c (+) and J102-e (common); and -10.0 volts d-c ± 0.01 percent between J102-d (-) and J102-e (common), and the TEST switch rotated through the indicated positions.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE I

Test Switch Position	DC Voltage Obtained from J102-e (common) to			
	J102-n	J102-p	J102-q	J102-W
OFF	0	0	0	0
1	-4.5884 ± 0.0116	8.0030 ± 0.0080	-3.7231 ± 0.0109	0
2	-4.1010 ± 0.0124	8.0030 ± 0.0080	-3.7231 ± 0.0109	0
3	-2.2984 ± 0.0090	3.0011 ± 0.0097	-3.7231 ± 0.0019	0
4	-7.5444 ± 0.0091	4.0015 ± 0.0112	-5.5846 ± 0.0116	0
5	-10.000 ± 0.001	7.0026 ± 0.0101	-5.5846 ± 0.0116	0
6	-1.6426 ± 0.0063	4.6417 ± 0.0128	-3.7231 ± 0.0109	2.3579 ± 0.0075
7	-1.6426 ± 0.0063	5.4420 ± 0.0128	-3.7231 ± 0.0109	2.3579 ± 0.0075
8	-10.000 ± 0.001	5.4420 ± 0.0128	-0.9308 ± 0.0039	0

3.6.1.2.4 Operating Voltage Outputs - The test set unit shall provide the following operating voltage outputs at SIMULATOR connector J102 when 115 volts, 400 cps is applied between SHOP POWER connector J101-1 and J101-4 (neutral); and +28 volts d-c between J101-7 (+) and J101-6 (common), and the TEST switch rotated through the indicated positions.

NOTE: POWER switch must be ON.

TABLE II

Test Switch Position	Voltage Obtained from J102-F and J102-									
	M	b	Z	K*	J*	H*	G*	r*	t	s
OFF	0	0	0	0	0	0	0	28 d-c	28 d-c	0
1	0	0	0	0	0	0	28 d-c	28 d-c	28 d-c	115 a-c
2	0	0	28 d-c	0	28 d-c	0	0	28 d-c	28 d-c	115 a-c
3	28 d-c	0	0	0	0	0	28 d-c	28 d-c	28 d-c	115 a-c
4	0	0	0	0	0	28 d-c	0	28 d-c	28 d-c	115 a-c
5	0	0	0	28 d-c	0	0	0	28 d-c	28 d-c	115 a-c
6	28 d-c	28 d-c	0	0	0	28 d-c	0	28 d-c	28 d-c	115 a-c
7	28 d-c	28 d-c	0	0	0	0	28 d-c	28 d-c	28 d-c	115 a-c
8	0	0	0	0	0	0	28 d-c	28 d-c	28 d-c	115 a-c

* PCM SELECT switch shall be in INT position to obtain indicated voltages. Zero volts shall be obtained at these pins when PCM SELECT switch is in ACFT position for all positions of TEST switch.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

3.6.1.2.5 Warning Lamps - The test set unit warning lamps shall operate as indicated in the following table when the voltages specified in 3.6.1.2.4 are applied to SHOP POWER connector J101.

NOTE: POWER switch must be ON.

TABLE III

Connect Jumper Between SIMULATOR Connector Pins		Warning Lamp Lights
From	To	
J102-i	J102-F	IN RANGE
J102-k	J102-F	SET RANGE
J102-j	J102-F	DIVE
J102-h	J102-F	BREAK
J102-g	J102-F	PULL UP
J102-t	J102-m	FIRING READY

3.6.1.2.6 Warning Lamp Self-Test - The IN RANGE, SET RANGE, DIVE, BREAK, PULL UP, and FIRING READY warning lamps shall illuminate when LAMP TEST switch is set to TEST position with the voltages specified in 3.6.1.2.4 applied to SHOP POWER connector J101.

3.6.1.2.7 Integrate Time - The integrate time circuit in the test set unit shall operate as indicated in the following table with the voltages specified in 3.6.1.2.4 applied to SHOP POWER connector J101.

NOTE: POWER switch must be ON.

TABLE IV

Procedure	Test Set Unit Performance
POWER switch to ON	
Jumper connected momentarily between J102-N and J102-t	INTEGRATE TIME meter starts
Jumper connected momentarily between J102-f and J102-t	INTEGRATE TIME meter stops
PCM SELECT switch to INT	
INTEGRATE switch momentarily to START	INTEGRATE TIME meter does not start
Connect Jumper from J102-t to J102-L	
INTEGRATE switch momentarily to START	INTEGRATE TIME meter starts

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE IV (CONT'D.)

Procedure	Test Set Unit Performance
INTEGRATE switch momentarily to RESET	INTEGRATE TIME meter resets
PCM SELECT to ACFT	
INTEGRATE switch momentarily to START	INTEGRATE TIME meter does not start
Connect Jumper between J102-r and J102-t	
INTEGRATE switch momentarily to START	INTEGRATE TIME meter starts
INTEGRATE switch momentarily to RESET	INTEGRATE TIME meter resets

3.6.1.2.8 Vertical Pitch Synchro Outputs - The test set unit shall provide the synchro (CX) outputs indicated in the following table. Synchro outputs shall be obtained at SIMULATOR connector J102 and shall be as follows: J102-S (S1), J102-T (S2), J102-U (S3), J102-P (R1), J102-F (R2). These synchro outputs shall be obtained when a voltage of 115 volts a-c is applied between J102-P and J102-F (neutral) or when the voltages of 3.6.1.2.4 are applied to SHOP POWER Connector J101.

NOTE: POWER switch must be ON and TEST switch must be in a position indicated in the following chart.

TABLE V

Test Switch Position	Synchro Output Signals* (degrees)
OFF	None
1	10
2	10**
3	30
4	30
5	10
6	45
7	45
8	30

*All synchro outputs shall be within a tolerance of 0.03° of the indicated value.

**Reverse rotor (J102-P and J102-F) and stator (J102-S and J102-U) leads of test equipment connected to test synchro output of test set unit in position 2 of TEST switch only.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

3.6.1.2.9 Power Change-Over - The SHOP POWER to aircraft power change-over circuit shall provide the voltage outputs indicated below at SIMULATOR connector J102 when the specified input voltages are supplied.

NOTE: POWER switch must be ON and TEST switch must be in a position other than OFF.

TABLE VI

Input Voltage	Input		Output Voltage	Output	
	From	To		From	To
115 v a-c 400 cps	J102-P	J102-F	115 v a-c 400 cps	J102-s	J102-F
28 v d-c	J102-X	J102-F	28 v d-c	J102-t	J102-F

3.6.1.2.10 Ballistic Correction Factor Resistance Loads - The test set unit shall provide the following ballistic correction factor resistance loads at SIMULATOR connector J102.

CAUTION

All external power connections must be removed from the test set unit.

TABLE VII

Test Switch Position	Resistance Obtained Between*				
	J102-A and J102-e	J102-B and J102-e	J102-C and J102-e	J102-D and J102-e	J102-E and J102-d
OFF	∞	∞	∞	∞	∞
1	5.6481 K	2.5803 K	78.770 K	7.1048 K	∞
2	6.5934 K	2.5188 K	∞	9.1271 K	∞
3	∞	∞	∞	∞	13.698 K
4	∞	20.950 K	∞	3.2444 K	∞
5	1.8591 K	6.3158 K	5.4194 K	1.6714 K	∞
6	∞	∞	∞	∞	5.7343 K
7	∞	∞	∞	∞	6.6022 K
8	53.962 K	6.0776 K	∞	1.6664 K	∞

*NOTE: All resistance readings obtained shall be within a tolerance of ±0.21 percent of the indicated value.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

3.6.2 Cover, Test Set Unit CW-769/ASM-150 - The test set unit shall be provided with a combination case cover manufactured in accordance with the applicable drawings of DL 63A25E1.

3.6.2.1 Function - The test set unit cover shall be used to house the test set handbook, simplified test instructions and hex wrench and to provide a cover for the test set unit.

3.6.3 Simulator, Module, Computer SM-404/ASM-150 - The computer module simulator shall be manufactured in accordance with the applicable drawings of DL 63A25E1 and shall meet the following requirements:

3.6.3.1 Function - The computer module simulator shall simulate the weapon adapters, aircraft adapter, and switch modules that are used in Weapons Release Computer CP-741(V)/A and shall provide a means for switching the computer outputs between the controls and indicators in the cockpit of the aircraft or those on the test set unit.

3.6.3.2 Electrical Requirements: The computer module simulator shall meet the following electrical requirements:

3.6.3.2.1 Connector P903 Module Simulator Resistance Loads - The computer module simulator shall provide the following resistance loads at P903.

TABLE VIII

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P903-8	P903-33	5,333.3	±10.8
-8	-34	1,777.8	±5.0
-8	-42	1,333.3	±3.7
-12	-42	1,200.0	±3.4
-12	-10	2,000.0	±4.0
-19	-43	2,500.0	±7.0
-35	-39	1,000.0	±3.5
-44	-47	0	0 to 1
-48	-46	1,739.1	±4.9
-48	-29	4,913.2	±9.9
-48	-23	1,739.1	±4.9
-49	-16	8,177.9	±16.5
-49	-30	44,197.0	±89.1
-49	-36	11,144.0	±23.0
-49	-38	6,000.0	±12.1
-49	-45	10,000.0	±20.0
-50	-1	1,531.2	±5.3

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE VIII (CONT'D.)

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P903-50	P903-2	0	0 to 1
-50	-3	1,031.2	±3.6
-50	-4	1,832.6	±6.3
-50	-5	4,946.5	±17.1
-50	-6	2,155.9	±7.4
-50	-7	669.45	±2.30
-50	-9	500.00	±1.01
-50	-11	0	0 to 1
-50	-13	1,088.9	±3.8
-50	-14	1,114.3	±2.3
-50	-15	2,141.0	±4.7
-50	-20	2,000.0	±5.6
-50	-21	1,273.2	±4.4
-50	-22	1,112.6	±3.8
-50	-24	1,591.9	±5.5
-50	-25	1,128.4	±3.9
-50	-26	779.10	±2.69
-50	-27	1,111.1	±3.8
-50	-28	0	0 to 1
-50	-32	1,458.5	±5.0
-50	-38	5,077.6	±10.1

3.6.3.2.2 Connector P904 Module Simulator Resistance Loads - The computer module simulator shall provide the following resistive loads at P904.

TABLE IX

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P904-32	P904-28	10,000.0	±20.0
-32	-30	43,956.0	±89.0
-32	-31	57,581.0	±116.0
-35	-36	48,840.0	±99.0
-40	-18	0	0 to 1

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE IX (CONT'D.)

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P904-41	P904-1	8,400.0	±17.0
-42	-8	555.56	±1.92
-42	-12	500.00	±1.01
-43	-19	9,500.0	±19.2
-48	-29	2,718.4	±7.6
-48	-34	2,500.0	±7.0
-48	-45	1,000.0	±3.5
-48	-46	13,605.0	±27.5
-49	-16	3,000.0	±8.4
-49	-20	6,000.0	±16.8
-49	-21	4,000.0	±8.1
-49	-30	19,845.0	±41.0
-49	-37	4,000.0	±8.1
-49	-38	2,914.6	±5.9
-50	-2	0	0 to 1
-50	-4	1,000.0	±3.5
-50	-6	1,000.0	±3.5
-50	-7	1,000.0	±3.5
-50	-9	500.0	±1.73
-50	-15	6,000.0	±12.1
-50	-22	1,000.0	±3.5
-50	-23	0	0 to 1
-50	-27	0	0 to 1
-50	-35	1,020.9	±3.5
-50	-38	9,000.0	±18.2

3.6.3.2.3 Connector P905 Module Simulator Resistance Loads - The computer module simulator shall provide the following resistance loads at connector P905.

TABLE X

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P905-3	P905-4	0	0 to 1
-8	-11	8,000.0	±16.2

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE X (CONT'D.)

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P905-8	P905-19	27,575.0	±56.0
-8	-49	21,075.0	±43.0
-9	-10	497.04	±1.71
-24	-25	544.67	±1.88
-26	-21	7,504.1	±15.2
-26	-39	7,504.1	±15.2
-28	-29	0	0 to 1
-30	-31	0	0 to 1
-48	-38	1,711.4	±4.8
-48	-6	2,431.1	±6.8
-50	-8	2,720.1	±7.6
-50	-10	2,487.2	±7.0
-50	-12	3,888.9	±10.9
-50	-14	6,955.3	±19.5
-50	-15	2,562.5	±7.2
-50	-16	12,171.0	±42.0
-50	-17	166.14	±0.57
-50	-22	1,416.7	±4.9
-50	-23	1,000.0	±2.0
-50	-26	731.68	±2.52
-50	-32	1,116.5	±3.2
-50	-34	1,120.4	±3.1
-50	-35	10,429.0	±29.0
-50	-36	1,111.1	±3.1
-50	-37	11,111.0	±31.0

3.6.3.2.4 Connector P906 Module Simulator Resistance Loads - The computer module simulator shall provide the following resistance loads at connector P906:

TABLE XI

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P906-5	P906-6	6,728.0	±13.6
-8	-1	901.50	±3.11

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE XI (CONT'D.)

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P906-8	P906-10	0	0 to 1
-8	-11	0	0 to 1
-8	-25	900.00	±3.11
-9	-14	0	0 to 1
-13	-3	12,480.0	±25.0
-13	-4	12,480.0	±25.0

3.6.3.2.5 Input/Output Resistances - The computer module simulator shall provide the following input/output resistances:

TABLE XII

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P906-2	P904-17	1,666.7	±4.7
J2001-A	P905-22	0	0 to 1
-B	P903-26	0	0 to 1
-C	P903-31	0	0 to 1
-D	P903-22	0	0 to 1
-E	P904-32	0	0 to 1
-p	P905-40	0	0 to 1
J2002-B	J2001-F	0	0 to 1
-B	P901-B	0	0 to 1
-C	P901-C	0	0 to 1
-C	J2001-G	0	0 to 1
-D	J2001-H	0	0 to 1
-D	P901-D	0	0 to 1
-E	P901-E	0	0 to 1
-E	J2001-J	0	0 to 1
-F	J2001-K	0	0 to 1
-F	P901-F	0	0 to 1
-H	P901-H	0	0 to 1
-J	P901-J	0	0 to 1
-J	J2001-N	0	0 to 1

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE XII (CONT'D.)

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
J2002-K	J2001-P	0	0 to 1
-L	P901-L	0	0 to 1
-V	P901-V	0	0 to 1
-U	J2001-X	0	0 to 1
J2003-A	P902-A	0	0 to 1
-A	J2001-c	0	0 to 1
-B	J2001-d	0	0 to 1
-B	P902-B	0	0 to 1
-C	P902-C	0	0 to 1
-C	P902-P	1,000.0	±2.0
-C	P902-U	666.67	±1.35
-C	P901-S	0	0 to 1
-C	J2001-e	0	0 to 1
-D	J2001-f	0	0 to 1
-D	P902-D	0	0 to 1
-E	P902-E	0	0 to 1
-F	P902-F	0	0 to 1
-G	P902-G	0	0 to 1
-H	P901-b	0	0 to 1
-J	P902-N	0	0 to 1
-M	P902-M	0	0 to 1
-R	P902-R	0	0 to 1
-V	P902-V	0	0 to 1
-W	P902-W	0	0 to 1
P901-G	J2001-b	0	0 to 1
-K	J2001-s	0	0 to 1
-M	J2001-S	0	0 to 1
-N	J2001-T	0	0 to 1
-P	J2001-U	0	0 to 1
-T	J2001-W	0	0 to 1
-U	J2001-t	0	0 to 1
-W	J2001-Z	0	0 to 1
-c	P902-H	0	0 to 1

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

TABLE XII (CONT'D.)

Resistance Obtained			
From	To	Resistance (ohms)	Tolerance (ohms)
P902-K	P902-L	0	0 to 1
-J	P902-b	0	0 to 1
-Y	P902-c	0	0 to 1
J2001-r (-)	J2001-F (+)	Less than 150	---
P902-T	J2003-T	0	0 to 1
P902-X	J2001-n	0	0 to 1
P902-Z	J2001-q	0	0 to 1
P901-V	J2001-L	0	0 to 1
With +28 volts applied between J2001-r and P901-B the following resistances shall be obtained.			
J2001-F	P901-L	0	0 to 1
-g	P902-E	0	0 to 1
-h	P902-F	0	0 to 1
-i	P902-G	0	0 to 1
-j	P901-b	0	0 to 1
-k	P902-N	0	0 to 1
-M	P901-H	0	0 to 1
P902-M	P902-C	2,850.7	±8.0
-R	P902-C	1,235.3	±3.5
-V	P902-B	10,000.0	±20.0
-W	P902-B	10,000.0	±20.0
J2003-D	P902-D	∞	-
J2002-J	J2001-N	∞	-
P902-T	J2001-m	0	0 to 1

3.6.3.2.6 Time Totalizing Meter - The time totalizing meter in the computer module simulator shall operate when 115 volts a-c, 400 cps is applied between P901-K and P901-B.

3.6.4 Case, Simulator and Cable CY-4557/ASM-150 - The simulator and cable case shall be manufactured in accordance with the applicable drawings of DL 63A25E1.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

3.6.4.1 Function - The simulator and cable case is used to house the computer module simulator and the module puller and disconnect tool.

3.6.5 Cover, Simulator and Cable Case CW-770/ASM-150 - The cover for the simulator and cable case CW-770/ASM-150 shall be manufactured in accordance with the applicable drawings of DL 63A25E1.

3.6.5.1 Function - The cover for the simulator and cable case shall be used to house the electrical special purpose cable assembly and the electrical power cable assembly.

3.6.6 Cable Assembly, Special Purpose, Electrical CX-10158/ASM-150 - The cable assembly shall be manufactured in accordance with the applicable drawings of DL 63A25E1.

3.6.6.1 Function - The special purpose cable assembly shall be used to connect the test set unit to the computer module simulator.

3.6.7 Cable Assembly, Power, Electrical, Branched CX-10159/ASM-150 - The cable assembly shall be manufactured in accordance with the applicable drawings of DL 63A25E1.

3.6.7.1 Function - The power cable assembly shall be used to provide power to the test set when the test set is used in the shop.

3.6.8 Tool, Module Puller and Disconnect - The module puller and disconnect tool shall be manufactured in accordance with the applicable drawings of DL 63A25E1.

3.6.8.1 Function - The module puller and disconnect tool shall be used as an aid in the removal of the Computer CP-741(V)/A modules, to carry the computer CP-741(V)/A and to mount the computer module simulator to the Computer CP-741(V)/A.

3.6.9 Wrench, Hex - The hex wrench shall be manufactured in accordance with the applicable drawings of DL 63A25E1.

3.6.9.1 Function - The hex wrench shall be used to loosen the set screws in all front panel knobs.

3.6.10 Simplified Test Instructions - Simplified test instructions shall be made in accordance with the applicable drawings of DL 63A25E1.

3.6.10.1 Function - The simplified test instructions shall be used to specify test procedures and results when the test set is used to test a Computer CP-741(V)/A on the flight line and in the shop.

3.7 Workmanship - General workmanship shall be in accordance with MIL-W-27076 and MIL-STD-454, requirement 9. Soldering shall be in accordance with MIL-STD-454, requirement 5.

3.8 Design Data - No data are required by this specification (other than reports accompanying samples submitted for testing) or by applicable documents, unless specified in the contract or order (see 6.3).

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for Inspection - Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

requirements as specified herein. Except as otherwise specified, the supplier may utilize his own facilities or any commercial laboratory acceptable to the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 Classification of Tests - Items covered by this specification shall be subjected to the following tests to determine compliance with all applicable requirements:

(1) Preproduction Tests
(2) Initial Production Tests
(3) Acceptance Tests
(4) Life Test

4.2 Preproduction Tests - Preproduction tests shall be made on an equipment representative of the production equipments to be supplied under the contract. Preproduction tests shall be accomplished under the responsibility of the contractor and shall be conducted in accordance with the approved test procedure of 4.6. The government inspector and the procuring activity shall be advised when tests are to be conducted so that a representative may be designated to witness or supervise the tests when so desired. Contractors not having adequate facilities to conduct all required tests shall obtain the services of a commercial testing laboratory acceptable to the Government.

4.2.1 Preproduction Test Data - The contractor shall submit all data collected in conducting these tests to the procuring agency for review and approval (see 6.3).

4.2.2 Scope of Tests - Preproduction tests shall include all tests deemed necessary by the procuring activity to determine that the equipment meets all the requirements of this specification and the contract.

4.2.2.1 Preproduction Tests shall include the following environmental tests in accordance with the requirements of MIL-T-5422 to the limits specified in MIL-T-21200 except as modified by 3.4.6.1.

(1) Temperature
(2) Altitude
(3) Vibration
(4) Shock
(5) Humidity
(6) Salt Spray
(7) Explosion-Proof
(8) Sand and Dust
(9) Fungus

In addition preproduction tests shall include interference tests in accordance with MIL-I-6181, tests to assure operational capability in environments specified by MIL-P-24014, and drop and watertightness tests in accordance with MIL-T-21200. When required (see 3.4.4) Maintainability Demonstration tests shall be in accordance with MIL-STD-471.

4.2.3 Preproduction Approval - Approval of the preproduction sample shall be by the procuring activity upon satisfactory completion of all tests. No production equipments

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

shall be delivered prior to the approval of the preproduction sample. Prefabrication of production equipment prior to the approval of the preproduction sample is at the contractor's own risk. The approved preproduction sample shall be retained by the contractor for his use in the fabrication and testing of equipment to be submitted for acceptance. The preproduction sample shall not be considered as one of the equipments under the contract.

4.2.4 Production Equipments - Equipments supplied under the contract shall in all respects, including design, construction, workmanship, performance and quality, be equivalent to the approved preproduction sample. Each equipment shall be capable of successfully passing the same tests as imposed on the preproduction sample. Evidence of noncompliance with the above shall constitute cause for rejection and for equipment already accepted by the Government, it shall be the obligation of the contractor to make necessary corrections as approved by the procuring activity.

4.3 Initial Production Tests - One of the first ten production equipment shall be selected and sent at the contractor's expense to a designated Government laboratory for tests. This equipment shall be selected by the procuring activity after the equipment has successfully passed all individual tests. The preproduction sample shall not be selected for this test.

4.3.1 Scope of Tests - This equipment may be subjected to any and all tests the procuring activity deems necessary to assure that the production equipment is equivalent to the previously approved preproduction sample in design, construction, workmanship, performance and quality and that it meets all applicable requirements.

4.3.2 Accessory Material - In addition to the complete equipment submitted for Initial Production Tests the contractor shall also submit such accessory material and data necessary to test the equipment (see 6.3).

4.3.3 Initial Production Sample Approval - Approval of the Initial Production Sample shall be by the procuring activity upon satisfactory completion of all tests. Any design, material or performance defect made evident during this test shall be corrected by the contractor to the satisfaction of the procuring activity. Failure of the Initial Production Sample to pass any of the tests shall be cause for deliveries of equipment under the contract to cease until proper corrective action is approved and accomplished. Corrective action shall also be accomplished on equipment previously accepted when requested by the procuring activity.

4.3.4 Reconditioning of Initial Production Test Sample - On completion of the initial production test the equipment shall be reworked by the contractor by replacing all worn and damaged items. After reworking, the contractor shall resubmit the equipment for acceptance.

4.4 Acceptance Tests - The contractor shall furnish all samples and shall be responsible for accomplishing the acceptance tests. All inspection and testing shall be under the supervision of the government inspector. Contractors not having testing facilities satisfactory to the procuring activity shall engage the service of a commercial testing laboratory acceptable to the procuring activity. The contractor shall furnish test reports showing quantitative results for all acceptance tests (see 6.3). Such reports shall be signed by an authorized representative of the contractor or laboratory, as applicable. Acceptance or approval of material during the course of manufacture shall not be construed as a guarantee of the acceptance of the finished product. Acceptance tests shall consist of the following.

(1) Individual Tests

(2) Sampling Tests

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

(3) Reliability Assurance Tests

(4) Special Tests

4.4.1 Individual Tests - Each equipment submitted for acceptance shall be subjected to the individual tests. These tests shall be adequate to determine compliance with the requirements of material, workmanship, operational adequacy and relaibility. As a minimum, each equipment accepted shall have passed the following tests:

(1) Examination of Product

(2) Operational Test

(3) Manufacturing Run-In Test

4.4.1.1 Examination of Product - Each equipment shall be examined carefully to determine that the material and workmanship requirements have been met.

4.4.1.2 Operational Test - Each equipment shall be operated long enough to permit the equipment temperature to stabilize and to check sufficient characteristics and record adequate data to assure satisfactory equipment operation (see 6.3).

4.4.1.3 Manufacturing Run-In Test - Each equipment shall be operated under the conditions specified herein for a period of 6 hours without failure. A failure shall be defined as anything which causes malfunctioning of the equipment. Only those adjustments will be permitted which can be made by using such controls and adjustments that are accessible to the operator during the normal use of the equipment.

Temperature	Ambient room
Humidity	Ambient room
Vibration	Any selected frequency within the range of 20 to 30 cps (excluding resonant points) and a minimum amplitude of ±3g's

The equipment shall be vibrated (without vibration isolators) for a period of 10 minutes prior to the beginning of the 6-hour period of operation. Where feasible, the equipment shall be operated during this vibration period for the purpose of detecting flaws and imperfect workmanship. The direction of vibration should be vertical to the normal mounting plane for 5 minutes and lateral to the plane for 5 minutes. Where it is not feasible to vibrate the equipment in two directions the vertical direction shall be used. During the 6-hour period of operation following the 10-minute vibration period, the equipment shall be mechanically cycled periodically through its various phases of operation. Should a failure occur it should be repaired and the test started over, except that the 10-minute vibration period need not be repeated when it is certain the failure was not a result of the vibration. Should repetitive failures occur, corrective action shall be taken to eliminate this defect from future equipment. A record shall be kept of all failures. The 6-hour period specified above may be composed of two 3-hour periods to conform with standard working hours.

4.4.2 Sampling Tests - Equipment selected for sampling tests shall first have passed the individual tests. Equipments shall be selected for sampling tests by the government inspector in accordance with the following. (Sampling tests shall not be conducted unless Reliability Assurance Tests of 4.4.3 are deleted by contractual action.)

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

Quantity of Equipments Offered for Acceptance	Quantity to be Selected for Sampling Tests
First 10	0*
Next 50	1
Next 75	1
Next 100	1
	1 for each additional 200 or fraction thereof

*NOTE: If by contract action the Initial Production Test (4.3) is deleted, then a Sample Test shall be conducted on one equipment from the first ten produced.

4.4.2.1 Scope of Tests - As a minimum, each equipment selected for sampling tests shall be subjected to the following tests:

(1) Complete operational test at ambient room conditions, making all necessary measurements to assure that all applicable specification requirements have been met.

(2) Operational test at certain environmental conditions. The conditions may vary for each equipment tested and should be based on results of the preproduction, initial production, individual and previous special tests.

(3) Manufacturing run-in tests specified in 4.4.1.3 except that test duration shall be 120 hours with no restriction on the number of failures. However, each failure shall be analyzed as to cause and remedial action necessary to reduce the possibility of its recurrence in future equipment.

4.4.3 Reliability Assurance Tests - Reliability Assurance Tests shall be conducted using MIL-STD-781. Tests shall be conducted as required by both the Qualification Phase and Sampling Phase.

4.4.3.1 Qualification Phase - Prior to the acceptance of equipments under the contract or order, a minimum of three (3) equipments shall be tested as outlined in MIL-STD-781, under the section entitled "Qualification Phase of Production Reliability Tests". The maximum number of equipments to be used shall be those listed in table 5 of MIL-STD-781. For the Qualification Phase Test Level E shall be used. The Accept-Reject Criteria for Test Plan V shall be used.

4.4.3.2 Reliability Sampling Phase Tests - Samples of the equipment shall be tested as outlined in MIL-STD-781, under the Section entitled "Sampling Phase of Production Reliability Tests". For the Sampling Phase Test Level E shall be used. The Accept-Reject Criteria for Test Plan V shall be used to determine the length of the tests (until an accept or reject decision is reached).

4.4.3.2.1 Lot Size for Sampling Phase - The entire contract quantity (with the exception of those equipments used in the Qualification Phase) shall be considered one lot. The test program shall start the first month after the Qualification Phase has been completed. Samples shall be selected and placed on test in the same manner as though 1 month's production was a lot. The samples shall be tested until an accept or reject decision is reached.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

In the meantime other equipments constructed shall be shipped. The test results shall be summarized monthly for the procuring activity (see 6.3). The procuring activity reserves the right to stop the acceptance of equipment any time after one or more reject decisions have been reached, pending a review of the contractor's efforts to improve the equipment, the equipment parts, the equipment quality control, etc., so that the entire contract quantity will show an accept decision.

4.4.3.3 Test Details - The test details such as the length of the Test Cycle, the length of the heat portion of the cycle, the performance characteristics to be measured, special failure criteria, preventive maintenance to be allowed during the test, etc., shall be part of the test procedures to be submitted by the contractor and approved by the procuring activity prior to the beginning of the Qualification Test Phase of the Reliability Assurance Tests.

4.4.4 Special Tests - Special tests shall be conducted on a quantity of equipments for the purpose of checking the effect of any design or material change on the performance of the equipment and to assure adequate quality control. The equipment selected for special tests may be selected from equipments previously subjected to the sampling or reliability assurance tests.

4.4.4.1 Special Tests Schedule - Selection of equipments for special tests shall be made as follows:

(1) On an early production equipment, after an engineering or material change.

(2) Whenever failure reports or other information indicate additional tests are required. (This will be determined by the procuring activity.)

4.4.4.2 Scope of Tests - Special tests shall consist of such tests as are approved by the procuring activity. Test procedures previously approved for the preproduction tests shall be used where applicable. When not applicable, the contractor shall prepare a test procedure and submit it to the procuring activity for approval prior to conducting the tests.

4.4.5 Equipment Failure - Should a failure occur during either the sampling, reliability assurance, or special tests, the following action shall be taken.

(1) Determine the cause of failure.

(2) Determine if the failure is an isolated case or design defect.

(3) Submit to the procuring activity for approval, proposed corrective action intended to reduce the possibility of the same failure(s) occurring in future tests (see 6.3).

(4) Where practical, include a test in the individual test to check all equipment for this requirement until reasonable assurance is obtained that the defect has been satisfactorily corrected.

4.5 Life Test - The contractor shall furnish all samples and shall be responsible for accomplishing the life test. The test shall be of 300-hours duration and shall be conducted on equipments that have passed the individual tests. The life test shall be performed under the conditions specified in 4.5.1. The life test sample shall be selected by

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

the government inspector in accordance with the following. (Equipments which have successfully passed the Initial Production Test, Sampling Tests, Reliability Assurance Tests, or Special Tests may be selected for life tests.) When reliability tests are conducted, the life test may be omitted if, during the reliability tests, a quantity of equipments equal to, or more than, that listed below receive at least 300 hours each of test time.

Quantity of Equipments Offered for Acceptance	Quantity to be Selected for Life Test
First 25	1
Next 175	1
Next 300	1
	1 for each additional 500 or fraction thereof

4.5.1 Test Conditions - The life test shall be conducted under the following simulated service conditions:

Temperature	Room ambient (30 ± 10°C)
Altitude	Normal ground (0 - 5000 ft.)
Humidity	Room ambient
Input Voltage	115 ± 10% (at lowest applicable frequency) 27.0 ± 2.0 volts d-c
Vibration	None

4.5.2 Test Periods - The test may be run continuously or intermittently. However, only the time during which the test set is energized shall count toward the 300-hour test duration. Any period of operation shall be of sufficient duration to permit the equipment temperature to stabilize. Periodically, the equipment shall be turned on and off several times and put through its various phases of operation.

4.5.3 Performance Check - At approximately 8-hour intervals during the test, a limited performance check shall be made. The performance check proposed by the contractor shall be subject to approval by the procuring activity.

4.5.4 Test Data - The contractor shall keep a daily record of the performance of the equipment, making particular note of any deficiencies or failures. In the event of part failures, the defective part shall be replaced and the operation resumed for the balance of the test period. A record shall be kept of all failures throughout the test. This record shall indicate the following:

(1) Part type number
(2) The circuit reference symbol number
(3) The part function
(4) Name of the manufacturer
(5) Nature of the failure
(6) The number of hours which the part operated prior to failure

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

4.5.4.1 Failure Report - In the event of a failure, the government inspector shall be notified immediately. A report shall be submitted to the procuring activity upon completion of the test (see 6.3). In this report, the contractor shall propose suitable and adequate design or material corrections for all failures which occurred. The procuring activity will review such proposals and determine whether they are acceptable.

4.5.5 Reconditioning of Life Test Samples - An equipment which has been subjected to the life test shall be reconditioned as follows:

(1) On completion of the life test, the equipment shall be reworked by the contractor by replacing all "wear" items. The "wear" items shall be determined by agreement between the contractor and the procuring activity.

(2) After reworking, the contractor shall resubmit the equipment for acceptance.

4.6 Test Procedures - The procedures used for conducting preproduction tests, acceptance tests and life tests shall be prepared by the contractor and submitted to the procuring activity for review and approval (see 6.3). The right is reserved by the procuring activity or the government inspector to modify the tests or require any additional tests deemed necessary to determine compliance with the requirements of this specification and the contract. MIL-T-18303 shall be used as a guide for preparation of test procedures. When approved test procedures are available from previous contracts such procedures will be provided and may be used when their use is approved by the procuring activity. However, the right is reserved by the procuring activity to require modification of such procedures, including additional tests when deemed necessary.

4.7 Reconditioning of Tested Equipment - Equipment which has been subjected to acceptance and life tests shall be reconditioned by the contractor by replacing all "wear" or damaged items. After reworking, the contractor shall resubmit the equipment for acceptance.

4.8 Presubmission Testing - No item, part or complete equipment shall be submitted by the contractor until it has been previously tested and inspected by the contractor and found to comply, to the best of his knowledge and belief, with all applicable requirements.

4.9 Rejection and Retest - Equipment which has been rejected may be reworked or have parts replaced to correct the defects and be resubmitted for acceptance. Before resubmitting, full particulars concerning previous rejection and the action taken to correct the defects found in the original shall be furnished the government inspector (see 6.3).

5. PREPARATION FOR DELIVERY

5.1 General - All major units and parts of the equipment shall be preserved, packaged, packed and marked for the level of shipment specified in the contract or order in accordance with MIL-E-17555 (see 6.3).

6. NOTES

6.1 Intended Use - Weapons Release Computer Test Set AN/ASM-150 is intended to be used to determine the operational capability of Weapons Release Computer CP-741(V)/A and related cockpit controls and indicators. The equipment shall be used on the flight line to test the computer, Pilot's Control Module, Bomb Button switch, and cockpit warning lamps. At shop facilities the equipment shall be used to test only the computer.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

6.2 Precedence of Documents - When the requirements of the contract, this specification, or applicable subsidiary specifications are in conflict, the following precedence shall apply:

(1) Contract

(2) This Specification

(3) The Drawings of DL 63A25E1

(4) Referenced Specifications

6.3 Ordering Data - Purchasers should exercise any desired options offered herein and procurement documents should specify the following:

(1) Title, number, and date of this specification.

(2) Selection of applicable levels of packaging and packing (see 5.1).

(3) Nonstandard parts and material approval (see 3.3.2).

(4) Parts replacement data (see 3.4.1.2).

(5) Preproduction test data (see 4.2.1).

(6) Accessory material (see 4.3.2).

(7) Acceptance test reports (see 4.4).

(8) Operational test data (see 4.4.1.2).

(9) Reliability test summary (see 4.4.3.2.1).

(10) Equipment failure (see 4.4.5).

(11) Failure Report (see 4.5.4.1).

(12) Test Procedures (see 4.6).

(13) Rejection and Retest Data (see 4.9).

6.4 Definitions -

6.4.1 Preferred Parts - Preferred parts are those in either of the following two categories:

(1) Parts manufactured to established reliability military specifications having quantitative reliability and qualification approval (QPL) requirements.

(2) Parts which meet the quantitative reliability requirements of the component drawing and quality assurance information requirements of NASC Specification 64A6A100 and are manufactured in a plant listed on a Mil Specification Qualified Products List (QPL) for the generic part type or in a plant which has been approved on the basis of a vendor technical evaluation.

6.4.2 Preliminary Parts - Preliminary parts are those parts that do not meet the requirements of the preferred or Qualified category but have been approved for use by the procuring activity on the basis of need, quality, reliability and vendor information.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

6.4.3 Qualified Parts - Qualified parts are those in either of the following two categories:

(1) Parts manufactured to conventional "MIL", "MS", or "AN" Specifications having Qualification Approval (QPL) requirements.

(2) Parts which meet the acceptance inspection requirements for "Quality Assurance Information" in accordance with NASC Specification 64A7A100 and are manufactured in a plant listed on a Mil Specification Qualified Parts List (QPL) for the generic part type or in a plant which has been approved on the basis of a vendor technical evaluation.

6.4.4 Vendor Technical Evaluation - A vendor technical evaluation is the obtaining of first-hand knowledge that the manufacturer has the technical capacity to produce products satisfactorily to the quality, reliability, and functional requirements specified. The vendor technical evaluation is conducted by and/or under the cognizance of the procuring activity.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 119-R004

INSTRUCTIONS

This sheet is to be filled out by personnel either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity *(as indicated on reverse hereof)*.

SPECIFICATION
MIL-T-81540(AS) TEST SET, COMPUTER, WEAPONS RELEASE AN/ASM -150

ORGANIZATION *(Of submitter)*	CITY AND STATE

CONTRACT NO.	QUANTITY OF ITEMS PROCURED	DOLLAR AMOUNT
		$

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES.

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

☐ YES ☐ NO IF "YES", IN WHAT WAY?

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity)*

SUBMITTED BY *(Printed or typed name and activity)*	DATE

DD FORM 1 APR 63 1426

C-8279

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T05:39Z
Check the source to verify that this is the current version before use.