MILITARY SPECIFICATION
CIRCUIT CARD ASSEMBLY: 10559315 (LINE DRIVER)

1. SCOPE

1.1 This specification covers one type of electronic assembly known as Circuit Card Assembly: 10559315, (Line Driver) (see 6.1).

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposal, form a part of this specification to the extent specified herein.

SPECIFICATIONS

Military

MIL-F-13926	Fire Control Materiel: General Specification Governing the Manufacture and Inspection of
MIL-P-14232	Parts, Equipment and Tools for Army Materiel: Packaging and Packing of
MIL-I-45607	Inspection Equipment, Supply and Maintenance of

STANDARDS

Military

MIL-STD-105	Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-109	Quality Assurance Terms and Definitions
MIL-STD-810	Environmental Test Methods

DRAWINGS

U.S. Army, Frankford Arsenal

F10559315	Circuit Card Assembly - Line Driver

FSC 1240

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

PACKAGING DATA SHEET

10559315 Packaging of Circuit Card Assembly-(Line Driver): 10559315

(Copies of specifications, standards, drawings, and packaging data sheets required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

3. REQUIREMENTS

3.1 Fabrication. - The circuit card assembly shall be manufactured in accordance with Drawing F10559315 and drawings pertaining thereto.

3.2 General specification. - The circuit card assembly shall meet the following requirements, where applicable, of MIL-F-13926:

(a) Order of precedence
(b) Dimensions and tolerances
(c) Part identification and marking

3.2.1 Electronic workmanship. - The circuit card assembly shall meet the workmanship requirements of Drawing F10559315 and drawings pertaining thereto.

3.3 Performance. - Unless otherwise specified, the circuit card assembly shall meet the performance requirements of this specification at standard ambient temperatures between 60 degrees Fahrenheit (^{o}F) and 90°F.

3.3.1 Loads, power and signals. - The circuit card assembly shall perform as specified herein when the loads, power, and signals of Table I are applied as specified.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

TABLE I

ITEM	CONDITION	CHARACTERISTICS	INSTRUCTIONS
1.	Loads:		Full or reduced load as specified, connected to each output terminal listed in Table II, with the returns to P1-16B (see 3.3.1.1 and 3.3.1.2)
1.1	Full load: resistor (12 required)	300 ohms ±5%	
1.2	Reduced load: resistor (12 required)	560 ohms ±5%	
2.	Power sources:	Maximum p-p ripple	Connected between the following pins of P1:
2.1	15 ±0.5 Vdc	25 mV	14B(+) and 16B(-)
2.2	5 ±0.2 Vdc	25 mV	15A(+) and 16B(-)
2.3	7.5 ±0.2 Vdc	25 mV	19A(+) and 16B(-)
3.	Signal sources:		Applied to the input terminals listed in Table II when specified herein.
3.1	Digital type A	Logical one: 4 ±1 Vdc Logical zero: 0.2 ±0.2 Vdc	

3.3.1.1 High level output. - With the full load and reduced load operating condition and the logical zero type-A signal of Table I applied singly or in sequence to the input terminals listed in Table II, 7.5 ±0.5 Vdc shall appear singly or in sequence at the corresponding output terminals of Table II.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

TABLE II

INPUT PINS OF P1	OUTPUT PINS OF P1
2B	32B
3A	31A
4B	30B
5A	29A
6B	28B
7A	27A
8B	26B
9A	25A
10B	24B
11A	23A
12B	22B
13A	21A

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

3.3.1.2 Low level output. - With the full load operating condition and the logical one type-A signal of Table I applied singly or in sequence to each input terminal listed in Table II, 0.0 ±0.5 Vdc shall appear singly or in sequence at the corresponding output terminals of Table II.

3.3.2 Environmental.

3.3.2.1 Storage temperature. - The circuit card assembly shall meet the requirements of 3.3.1 at ambient temperature (60°F to 90°F) after exposure and thermal stabilization at -80°F and 160°F.

3.3.2.2 Operating temperatures. - The circuit card assembly shall meet the requirements of 3.3.1 while exposed to and thermally stabilized at -40°F and +125°F, subsequent to which it shall meet the above requirements at ambient temperature (60°F to 90°F).

3.3.2.3 Vibration. - The circuit card assembly shall show no physical failure and shall meet the requirements of 3.3.1 after being exposed to the following vibratory conditions:

(a)	Amplitude:	0.5 inch maximum
(b)	Acceleration:	4g maximum
(c)	Crossover frequency:	12.5 Hertz
(d)	Sweep time:	5 to 500 to 5 Hertz in 15 minutes. Two sweeps in each of the three mutually perpendicular axes.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. - Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified, the supplier may utilize his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

4.4.1 General provisions. - The component and subassembly inspection requirements of MIL-F-13926 form a part of the quality assurance provisions of this specification. Definitions of inspection terms shall be as listed in MIL-STD-109.

4.2 First article (initial production) approval. - The requirement for first article approval and the responsibility (Government or contractor) for first article testing shall be as specified in the contract. The sample for first article approval tests shall consist of three circuit card assemblies. The sample shall be manufactured in the same manner, using the same materials, equipment, processes, and procedures as used in regular production. All parts and materials, including packaging and packing, shall be obtained from the same source of supply as used in regular production.

4.2.1 Government testing. - When the Government is responsible for conducting first article approval tests, the contractor, prior to submitting the sample to the Government, shall inspect the sample to insure that it conforms to all the requirements of the contract and submit a record of this inspection with the sample, including certificates of conformance for materials.

4.2.2 Contractor testing. - When the contractor is responsible for conducting first article approval tests, the sample shall be inspected by the contractor for all the requirements of the contract. The sample and a record of this inspection, including certificates of conformance for materials, shall be submitted to the Government for approval. The Government reserves the right to witness the contractor's inspection.

4.3 Inspection provisions.

4.3.1 Submission of product. - Unless otherwise specified by the contracting officer, inspection lot size, lot formation and presentation of lots shall be in accordance with "Submission of Product" provisions of MIL-STD-105.

4.3.2 Examination and tests.

4.3.2.1 Components and subassemblies. - All components and subassemblies shall be inspected in accordance with the inspection provisions contained in Supplementary Quality Assurance Provisions (SQAP) listed in the technical data package (TDP). In the absence of

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

SQAP's, the applicable Quality Assurance Provisions of MIL-F-13926 shall apply.

4.3.2.2 Final acceptance inspection.- Subsequent to first article approval, examination and tests related to Section 3 herein shall be performed on a single defect (individual characteristic) basis in accordance with MIL-STD-105 and the sampling plans specified in Tables III, IV and V herein. Examination and test for packaging and marking shall be in accordance with MIL-P-14232 and Section 5 herein. The tabulated classification of defects in Tables III, IV, and V shall constitute the minimum inspection to be performed by the supplier after first article approval and prior to Government acceptance or rejection by item or lot.

4.3.2.3 Functional tests.- The requirements and tests in Table III shall be inspected on a 100% basis. All examinations and tests shall be conducted at the standard ambient temperature (60° to 90°F).

TABLE III

(100 percent inspection)

CHARACTERISTIC	REQUIREMENT	TEST PROCEDURES
101. High level output	3.3.1.1	4.6.2
102. Low level output	3.3.1.2	4.6.3

4.3.3 Acceptance and rejection.- Rejected lots shall be screened for all defective characteristics. Removal or correction of defective units and resubmittance of rejected lots shall be in accordance with "Acceptance and Rejection" as specified in MIL-STD-105.

4.4 Special sampling.

4.4.1 General.- One circuit card assembly shall be selected at random by a Government representative as a control sample from each 100 produced. The control sample shall meet the requirements and tests in Table IV.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

TABLE IV

CONTROL TEST	REQUIREMENT	TEST PROCEDURES
301. Fabrication	3.1	Applicable drawings - Visual
302. General specification	3.2	MIL-F-13926 - Visual

4.4.2 Environmental. - Three circuit card assemblies shall be selected at random by a Government representative as a control sample from each 50 produced or from each month's production, whichever occurs first. The control samples shall meet the requirements and tests in Table V.

TABLE V

CONTROL TEST	REQUIREMENT	TEST PROCEDURES
303. Storage temperature	3.3.2.1	4.6.4.1
304. Operating temperature	3.3.2.2	4.6.4.1
305. Vibration	3.3.2.3	4.6.4.2

4.4.3 Failure sample. - Should any one item of a special sampling fail to meet the specified test requirements, acceptance of the product shall be suspended by the Government until necessary corrections have been made by the contractor and the resubmitted item has been approved (see 4.3.3).

4.5 Inspection equipment. - Except as otherwise provided for by the contract, the contractor shall supply and maintain inspection equipment in accordance with the applicable requirements of MIL-I-45607.

4.5.1 Government furnished inspection equipment. - Where the contract provides for Government furnished test equipment, supply and maintenance of test equipment shall be in accordance with the applicable requirements specified in MIL-I-45607.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

4.5.2 Contractor furnished inspection equipment.

4.5.2.1 Government design. - Unless otherwise specified in the contract, all inspection equipment specified by drawing number in specifications or SQAP forming a part of the contract shall be supplied by the contractor in accordance with applicable technical data listed in the technical data package (TDP).

4.5.2.2 Contractor design. - The contractor shall design and supply inspection equipment compatible with the "Test Methods and Procedures" specified in 4.6 of this specification and with the component inspection procedures specified in "Examination" and "Test Facilities" requirements of MIL-F-13926. Since tolerance of test equipment is normally considered to be within 10% of the product tolerance for which it is intended, this inherent error in the test equipment design must be considered as part of the prescribed product tolerance limit. Thus, concept, construction, materials, dimensions, and tolerances used in the design of test equipment shall be so selected and controlled as to insure that the test equipment will reliably indicate acceptability of a product which does not exceed 90% of the prescribed tolerance limit and permit positive rejection when nonconforming. Construction shall be such as to facilitate routine calibration of test equipment.

4.5.3 Test equipment. - In conjunction with 4.5.2, the standard test equipment listed in Table VI shall be utilized in performing the applicable test of 4.6.

TABLE VI

NOMENCLATURE	DESCRIPTION
1. D-C power supply	Plus 5 ±0.2V Ripple: 25 mV p-p max
2. D-C power supply	Plus 7.25 ±0.1 Vdc Ripple: 25 mV p-p max
3. D-C power supply	Plus 15 ±0.5V Ripple: 25 mV p-p max
4. D-C voltmeter	Range of 0-10V, Accuracy of ±1%
5. Signal source	Capable of providing a d-c level of amplitude specified in item 3.1, Table I

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

4.6 Test methods and procedures.

4.6.1 Test conditions. - Unless otherwise specified, the test conditions shall be in accordance with the "Test Facilities" requirements of MIL-F-13926.

4.6.1.1 Initial conditions. - Connect the power to the circuit card assembly as specified in Table I.

4.6.2 High level output. -

4.6.2.1 Full load. -

(a) Apply the initial conditions of 4.6.1.1.
(b) Connect the load resistors specified in Table I for full-load operation to the output pins listed in Table II.
(c) Apply the logical zero, type-A signal of Table I singly or in sequence to the input pins listed in Table II and observe the voltage at the corresponding output pins listed in Table II.

The output voltages shall be as specified in 3.3.1.1.

4.6.2.2 Reduced load. - Repeat the test procedure of 4.6.2.1 using the reduced-load resistors specified in Table I at the output pins. The output voltages shall be as specified in 3.3.1.1.

4.6.3 Low level output. - Repeat the test procedure of 4.6.2.1 using the logical one (instead of logical zero), type-A signal of Table I at the input terminals listed in Table II. The output voltages shall be as specified in 3.3.1.2.

4.6.4 Environmental tests. - The test equipment shall be in accordance with the "Test Facilities" requirements of MIL-F-13926 except that the circuit card assembly may be mounted on an inside surface of the test chamber for the temperature test and the tolerance requirements for vibration frequency measuring instruments shall not apply.

4.6.4.1 Temperature test. -

(a) Place the circuit card assembly in the test chamber and reduce the chamber temperature to -80°F. (See note below.)

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

(b) Soak the circuit card assembly at this temperature for at least 5 hours with the unit not operating.
(c) Raise the chamber temperature to -40°F.
(d) Following thermal stabilization at -40°F, place the circuit card assembly in operation and perform the tests specified in 4.6.2 and 4.6.3.
(e) Raise the chamber temperature to +160°F.
(f) Soak the circuit card assembly at +160°F for at least 5 hours with the assembly not operating.
(g) Reduce the chamber temperature to +125°F.
(h) Following thermal stabilization at +125°F, place the circuit card assembly in operation and perform the tests specified in 4.6.2 and 4.6.3.
(i) Reduce the chamber temperature to ambient.
(j) Following stabilization at ambient temperature, place the circuit card assembly in operation and perform the test specified in 4.6.2 and 4.6.3.

The circuit card assembly shall meet the requirements of 3.3.2.1 and 3.3.2.2.

NOTE: The rate of temperature change shall be less than 7°F per minute during temperature cycling.

4.6.4.2 Vibration. - With the circuit card assembly firmly mounted to the vibration table perform the following:

(a) Test in accordance with Method 514-I of MIL-STD-810 for category (f) equipment, except that the acceleration shall not exceed ±4g and the maximum excursion (double amplitude) shall be 0.5 inch.
(b) Sweep the frequency from 5 Hz to 500 Hz and back to 5 Hz in a period of 15 minutes. Perform two sweeps in each of the three mutually perpendicular axes.
(c) Following vibration cycling, examine the circuit card assembly for structural failures, loose hardware, wire breakage and abrasion.
(d) Place the circuit card assembly in operation and perform the tests specified in 4.6.2 and 4.6.3.

The circuit card assembly shall meet the requirements of 3.3.2.3.

5. PREPARATION FOR DELIVERY

5.1 Packaging, packing and marking. - Packaging, packing and marking shall be in accordance with Packaging Data Sheet 10559315.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.

The level of protection shall be as specified in the procurement document.

6. NOTES

6.1 Intended use. - This circuit card assembly is a plug-in module of the Transmitter-Receiver unit which accepts and processes selected signals from the counter module to provide the necessary signal levels to the computer, and also provides the necessary isolation from the computer.

6.2 Ordering data. - Procurement documents should specify the following:

(a) Title, number, and date of this specification.
(b) Applicable packaging data sheet number (see 5.1).
(c) Selection of applicable levels of preservation, packaging and packing.
(d) Applicable stock number.
(e) Requirement for First Article Submission.

Custodian:

Army - MU

Preparing activity

Army - MU

Project No. 1240-A141

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:59Z
Check the source to verify that this is the current version before use.