MILITARY SPECIFICATION

# MAINTENANCE KIT, ELECTRONIC EQUIPMENT MK-1035( )/ARC-131 (UNITS OF)

## 1. SCOPE

1.1 This specification covers the following units of one type equipment that is utilized in maintenance of Airborne Communication Radio Sets and is designated Maintenance Kit, Electronic Equipment MK-1035( )/ARC-131. (See 6.1 and 6.3):

| | |
|---|---|
| Test Set, Radio | TS-2575( )/ARC-131 |
| Simulator, Coupler, Antenna | SM-499( )/ARC-131 |
| Control Intercommunication Set | C-1611( )/AIC |
| Indicator | ID-48( )/ARN |
| Control, Radio Set | C-7088( )/ARC-131 |

## 2. APPLICABLE DOCUMENTS

2.1 Documents. - The following documents of the issue in effect at date of invitation for bids or request for proposal, form a part of the specification to the extent specified herein.

SPECIFICATIONS

FEDERAL

| | |
|---|---|
| T-T-871 | Twine, Cotton Wrapping. |
| PPP-B-636 | Box, Fiberboard. |
| PPP-B-640 | Box, Fiberboard, Corrugated, Triple-Wall. |
| PPP-F-320 | Fiberboard; Corrugated and Solid, Sheet Stock (Container Grade), and Cut Shapes. |
| PPP-F-291 | Paperboard, Wrapping, Cushioning. |
| PPP-S-760 | Strapping, Nonmetallic, (and Connectors). |
| PPP-T-97 | Tape: Pressure-Sensitive Adhesive, Filament Reinforced. |

MILITARY

| | |
|---|---|
| MIL-P-116 | Preservation, Methods of |
| MIL-T-5422 | Testing Environmental Aircraft Equipment |
| MIL-M-13231 | Marking of Electronic Items |
| MIL-F-14072 | Finishes for Ground Signal Equipment |



Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

| | |
|---|---|
| MIL-C-55194 | Control, Intercommunication Set C-1611( )/AIC |
| MIL-S-19500 | Semiconductor Devices (General Specification) |
| MIL-T-21200 | Test Equipment For Use With Electronic and Fire Control Systems, General Specification |
| MIL-I-25120 | Indicator ID-48( )/ARN |
| MIL-B-43291 | Boxes; Fiberboard; Corrugated, Double-Wall Weather Resistant |
| MIL-R-55563 | Radio Set AN/ARC-131( ) |

STANDARDS

MILITARY

| | |
|---|---|
| MIL-STD-105 | Sampling Procedures and Tables for Inspection by Attributes |
| MIL-STD-108 | Definitions of and Basic Requirements for Enclosures for Electric and Electronic Equipment |
| MIL-STD-129 | Marking for Shipment and Storage |
| MIL-STD-252 | Wired Equipment, Classification of Visual and Mechanical Defect |
| MIL-STD-454 | Standard General Requirements for Electronic Equipment |
| MIL-STD-810 | Environmental Test Methods for Aerospace and Ground Equipment |

DRAWINGS

Electronic Command

| | |
|---|---|
| SC-DL-620558 | Test Set, Radio TS-2575( )/ARC-131 |
| SC-DL-620621 | Simulator, Coupler Antenna SM-499( )/ARC-131 |

(Copies of specifications, standards and drawings required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.

3. REQUIREMENTS



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.1 Description. - The Maintenance Kit, Electronic MK-1035( )/ARC-131 is a portable test set which provides facilities and connections required for operational and maintenance test performed on Radio Set AN/ARC-131( ). The maintenance kit is contained in a lightweight water tight combination case. Connectors and cables are not exposed when the cover is in place. The maintenance kit operates from a nominal input voltage of 27.5 volts dc. Operating controls, connectors (including power input) and indicators are mounted on the front panel of the test set. A Control C-7088( )/ARC-131, C-1611( )/AIC, and an ID-48( )/ARN are supplied whith the maintenance kit. These units are easily removed from the front panel and may be replaced by a field unit for operational evaluation of the condition of that field unit. A front panel-mounted receptacle provides control signals and power for operation of the tuning motor in Coupler, Antenna CU-942/ARC-54. The test set provides interconnections with the external power sources, external standard test equipment, and the internal control and monitoring circuits to enable operation, test alignment, and repair of a Radio Set AN/ARC-131. Special cables, tools and adapters are stored within the test set to provide a facility for subassembly alignment where required.

3.2 Construction. - The units shall be constructed in accordance with the following drawing and data lists:

| | |
|---|---|
| SC-DL-620558 | Test Set, Radio TS-2575( )/ARC-131 |
| SC-DL-620621 | Simulator Coupler Antenna SM-499( )/ARC-131 |

3.3 Preproduction samples. - The contractor shall furnish three preproduction samples of equipment on order for approval, if required by the invitation for bids and contract. (See 4.3 and 6.2)

3.4 Cleaning. -

3.4.1 Parts. - After fabrication, parts shall be cleaned in accordance with good commercial practice, or as specified in an applicable document. Cleaning processes shall have no deleterious effect. Corrosive material shall be removed completely before the parts are mounted on chassis, panels, etc.

3.4.2 Units. - After assembly, equipment shall be cleaned thoroughly and shall be free from particles of solder, flux, and other foreign material. In addition, when necessary, such cleaning shall also be performed before final assembly of the equipment.

3.5 Controls. - All movable controls shall operate properly without binding or other undue restriction. Controls shall not be assembled in a misaligned condition.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.6 Finish, protective (See 4.4). - The equipment shall be given protective finish in accordance with Specification MIL-F-14072 and the equipment drawings. This includes finish of hardware, such as handles, hinges, screws, etc., and necessary touch-up after mounting. The final paint film on type 1 surfaces shall be semi-gloss, light gray (Film E) conforming to Specification MIL-F-14072.

3.7 Securing of parts. -

3.7.1 General. - Brackets, lugs, inserts, bolts, and other mounting arrangements shall retain items securely when subjected to specified service conditions.

3.7.2 Securing of parts by threaded fasteners. - Nylok or other screws with plastic devices and Loctite or simular sealants shall not be subjected to temperatures in excess of 250° F (as during baking of paint). Loctite or similar sealants shall be applied in accordance with the manufacturer's instruction.

3.8 Soldering. -

3.8.1 Solder. - Solder shall conform to the equipment drawings.

3.8.2 Acid or acid salts. - No acid or acid salts shall be used in preparation for or during soldering; however, exception is permitted for preliminary tinning of electrical connections and for tinning or soldering of mechanical joints not used to complete electrical circuits, but in no case shall acid or acid salts be used where they can come in contact with insulation material. Where acid or acid salts are used, as permitted above, they shall be completely neutralized and removed immediately after use.

3.8.3 Process. - There shall be no sharp points or rough surfaces resulting from insufficient heating. The solder shall feather out to a thin edge, indicating proper flowing and wetting actions, and shall not be crystalized, overheated, or underheated. The minimum necessary amount of flux and solder shall be used for electrical connections. Any means employed to remove an unavoidable excess of flux shall not incur the risk of loose particles of flux, brush bristles, or other foreign material remaining in the equipment; flux being spread over a larger area; or damage to the unit. Insulation material that has been subjected to heating during the soldering operation shall be undamaged and parts fastened thereto shall not have become loosened.

3.9 Wiring and cabling. - Wiring and cabling shall be neat and sturdy.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.9.1 Cabling. - Insulated wires shall be formed into cables except where operation of the equipment would be adversely affected thereby or where it is physically impracticable as in the case where the resulting cables would be excessively large and would interfere with operation or maintenance.

3.9.2 Slack. - Wires and cables shall be as short as practical except that sufficient slack shall be provided for the following purposes:

a. To prevent undue stress on cable forms, wires, and connections, including connections to resiliently supported parts.

b. To enable parts to be removed and replaced during servicing without disconnecting other parts.

c. To provide for at least two replacements of the part to which the wire or cable is connected, except where uninsulated wires are used.

3.9.3 Protection. - Wires and cables shall be so placed and protected as to avoid contact, under specified service conditions, with rough or irregular surfaces or sharp edges.

3.9.4 Support. - Wire and cable shall be properly supported and secured to prevent undue stress on the conductors and terminals and undue change in position of the wire or cable (I) during and after subjection of the equipment to specified service conditions or (II) after service or repair of the equipment in a normal manner.

3.9.5 Clearance. - Clearance between solder connections or bare conductors, on terminal boards, relays, or other parts, shall be such that no accidental contact can occur between adjacent connections when subjected to specified service conditions.

3.9.6 Splicing. - Wires in a continuous run between two terminals shall not be spliced during the wiring operation.

3.9.7 Connections. -

3.9.7.1 General. - Before being soldered to terminal lugs or fixed terminals, wires shall be mechanically secured so that the connections are not dependent for strength on solder alone. Where practicable, wires soldered to fixed terminals shall be looped at least one-half turn but not more than three-quarters turn around the terminal before soldering. Bared ends of wire leads to be terminated in solder-type terminal lugs shall be tinned, silver plated, or lead-alloy coated. No varnish, lacquer, inspection paint, or other coating shall be applied to completed electrical connections.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.10 Marking (See 4.4). -

3.10.1 General. - Marking shall conform to Specification MIL-M-13231. Front panel marking shall be Group 1.

3.10.2 Visibility. - Wherever practicable, parts and assemblies shall be so mounted that their identification marking will be readily visible with minimum disassembly of the equipment.

3.10.3 Serial numbers. - Each MK-1035( )/ARC-131 on order shall be serial numbered.

3.11 Semiconductors (transistors and diodes) (See 4.4). - These electron devices (semiconductors) shall conform to MIL-S-19500.

3.12 Tropicalization of materials. - Materials shall be treated as follows:

3.12.1 Treating materials. - Treating materials containing a mercury-bearing fungicide shall not be used. The contractor shall determine that the treating material is compatible with the material or surface to be treated. Selection of treating materials shall be such that any increase in flammability of treated material will be held to the practical minimum.

3.12.2 Toxicity. - Treating materials shall cause no skin irritation or other injury to personnel handling the treated material during fabrication, transportation, operation, or maintenance of the equipment, or during use of the finished items when used for the purpose intended.

3.12.3 Flexibility. - Treatment shall not affect the flexibility of treated materials, to the extent that the equipment may fail to meet specified requirements when subjected to specified service conditions.

3.12.4 Statement of treatment. - The contractor shall submit for approval, to the contracting officer, a statement describing in detail the materials to be treated and the treating materials and processes that he proposes to use. (See 6.2h)

3.13 Service conditions (See 4.8). - The equipment shall meet the following service conditions as specified, in accordance with MIL-T-21200 and MIL-T-5422. The equipment shall be capable of specified operation within 3 minutes after power is applied.

3.13.1 Temperature (See 4.8.1). - After each temperature test the equipment shall meet the operational requirement as specified herein.



Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

a. Operating. - Ambient temperature in the range of 0°C to +55°C. Intermittent at +71°C.

b. Non-operating. - Exposure in the range of -62°C to +85°C.

3.13.2 Relative humidity (See 4.8.2). - Up to 100 percent relative humidity including conditions wherein condensation takes place in the form of water. The equipment shall withstand the above conditions during non-operating conditions.

3.13.3 Altitude (See 4.8.3). -

a. Operating. - Up to 10,000 feet above sea level after subjection to 50,000 feet (non-operating).

b. Non-operating. - Up to 50,000 feet above sea level.

3.13.4 Spray-tight protection (See 4.8.4). - The equipment shall meet the Table I test conditions of MIL-STD-108 for "spray-tight" enclosure. There shall be no evidence of moisture inside the equipment.

3.13.5 Fungus (See 4.8.5). - The equipment shall show no evidence of visible fungus or corrosion when subjected to 28 days fungus test.

3.13.6 Vibration and shock (See 4.8.6). -

3.13.6.1 Vibration. - No impaired performance or damage to the equipment shall result from vibrations at any frequency between 10 and 55 Hz.

3.13.6.2 Shock. - The equipment shall not suffer damage or fail to operate after subjection to the requirements of Table I, as follows:

Table I

| Paragraph Heading | Paragraph No. | Performance After Test |
|---|---|---|
| Shock; bench-handling | 4.8.6.2 | Specified performance (Note A) |
| Shock; drop | 4.8.6.3 | No physical damage. Operable (Note A). Any physical damage shall be minor only. |

NOTE A: The equipment shall meet the following requirements: 3.14.1 and 3.17.

3.13.7 Sand and dust (See 4.8.7). - The equipment shall be required to pass the sand and dust requirements in accordance with MIL-T-21200 except that the equipment shall not be operated during the test and the cover of the combination case shall be in place.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.14 Electrical requirements (See 4.9). -

3.14.1 Audio Amplifier (See 4.9.1). -

3.14.1.1 Frequency response (See 4.9.1.1). - With 2.38 vrms at 1000 Hz applied to J110 and the speaker volume control adjusted for 3.0 vrms output across a 16 ohm resistor, the output voltage shall be 3.0 ± 1.5 vrms from 150 to 3000 Hz.

3.14.1.2 Speaker output (See 4.9.1.2). - The speaker audible output shall be free of audible distortion over the frequency range of 150 to 3000 Hz up to the maximum audio output that will produce at least 3 vrms across the speaker voice coil. The speaker output shall be continuously variable between a nominal inaudible level to the full available output.

3.14.2 Retransmit switch (See 4.9.2). - With circuit breaker CB101 to ON position and press the PUSH to TEST RETANS RECEIVER lamp DS101 the lamp shall light. Short J103 pin E or J127 pin HH to ground, lamp DS101 shall light, and when the RETRANS SIMULATE SWITCH S101 is depressed the resistance at J103 pin A and J127 pin U to ground shall be zero ohms.

3.14.3 Transmit switch (See 4.9.3). - When TRANSMIT switch S102 is placed to positions ON and MOM, the resistance between J-128 pin 33, J-127 pin q and chassis ground shall be zero ohms; in the OFF position the resistance shall be infinity.

3.14.4 Wide band/narrow band switch (See 4.9.4). - When switch S106 WB/NB is set to WB position, the resistance between J117 pin 39 (connect P102 and J102) and chassis ground shall be zero ohms; in NB position the resistance shall be infinity.

3.14.5 RF amp align switches (See 4.9.5) - With switches S104 HI/LO and S105 AGC set to the following positions, the continuity between the pins of J116 and the test points shall be as indicated. The measured voltage between pin A and C with S105 in the OFF position shall be 24 MHz.

| Switches | | Test Points | Resistance |
|---|---|---|---|
| S104 | S105 | Pins and TP | ohms |
| HI | OFF | B - F | 0 |
| LO | OFF | B - F | infinity |
| | ON | C - D | 0 |
| | OFF | C - D | 620 ± 10% |
| | | TP101 - TP102 | 0.1 ± 10% |



Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

3.14.6 Homer attenuators (See 4.9.6). - With 60.0 MHz at 1.0 vrms applied to J115 and the HOMER ATTEN(s) set as specified, the signal outputs at the pins of J117 shall be as indicated when measured as follows. The homer attenuators shall operate over the frequency range of 30 to 76 MHz and the accuracy at any position shall be -0.5 db:

| HOME ATTEN(s) | | Terminated Pins | | vrms at pins | |
|---|---|---|---|---|---|
| LEFT | RIGHT | A | B | A | B |
| 0 | 0 | Probe | Resistor | 0.94-1.0 | 0.94-1.0 |
| 0 | 6db | Probe | Resistor | 0.473-0.531 | - |
| 0 | 0 | Resistor | Probe | 0.94-1.0 | 0.94-1.0 |
| 6db | 0 | Resistor | Probe | - | 0.473-0.531 |

3.14.7 RF load (See 4.9.7). - With 60.0 MHz at 1.0 vrms applied to J113, the signal output at J114 shall be 0.1 $\pm$ 0.01 vrms.

3.14.8 Indicator ID-48( )/ARN (See 4.9.8). - The ID-48( )/ARN shall be in accordance with Specification MIL-I-25120. When installed in the Test Set and the Radio Set Control OFF-T/R-RETRAN-HOME switch placed in the HOME position the horizontal pointer on the ID-48( )/ARN shall deflect approximately 5/8 inch downward from the center position with 0.125 vdc applied between J117 pins 20 (positive) and 21 (negative). Place the SQUELCH control on the C-7088 to TONE position and with 7.0 vdc applied between J117 pins 10 (negative) and 16 (positive) the horizontal and vertical flag alarms on the ID-48 shall rest on their stops, increase the voltage to 14.0 vdc, the horizontal and vertical alarm flags shall deflect to a position behind the face mask of the ID-48.

3.14.9 Control, Intercommunication C-1611( )/AIC (See 4.9.9). - The C-1611 shall be in accordance with Specification MIL-C-55194, and when installed in the Test Set and 0.3 vrms at 1000 Hz is applied between J111 pin 3 and J111 pin 1 through a 5000 to 5 ohm pad, a 1000 Hz signal shall be audible from the speaker in the Test Set. With 0.5 vrms at 1000 Hz applied to J107 of the Test Set, 1000 Hz signal shall be audible from the speaker in the Test Set and J111, when the volume control of C-1611 is rotated clockwise.

3.14.10 Simulator Antenna Coupler SM-499( )/ARC-131 (See 4.9.10). - The SM-499 when connected to the Test Set shall indicate each frequency selected on the C-7088. The red indicator lamp on the SM-499 shall light and remain lit at each of the frequencies selected on the C-7088 from 30 to 49 MHz. The green indicator lamp on the SM-499 shall light and remain lit at each frequency selected on the C-7088 from 50 to 75 MHz except that the frequency indicator dial shall indicate 69 for frequencies 69 through 75 with the green lamp lit.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.14.11 Control, Radio Set C-7088( )/ARC-131 (See 4.9.11). - The C-7088 shall be in accordance with MIL-R-55563(EL). When installed in the Test Set the control shall meet the channeling requirements of 3.14.10 and the indicator requirements of 3.14.8.

3.14.12 Circuit breaker, trip out (See 4.9.12). - The switch shall perform its required function after an applied voltage trips the circuit breaker and the switch has been placed to "ON" position.

3.14.13 Transient protection (See 4.9.13). - When 29 vdc is applied to the Test Set an application of a positive step voltage of 80 vdc lasting for 0.1 second maximum shall not cause the output voltage to exceed 26 peak volts.

3.14.14 Voltage regulation (See 4.9.14). - With Circuit Breaker switch CB101 to ON position and Pilot switch S103 to OFF position and an input supply voltage of 28.0 vdc and an 80 ohm resistor connected between J128 pin 37 and a ground, R108 shall be adjusted on the Test Set for 24.0 vdc at J128 pin 37. With Circuit Breaker switch CB101 and Pilot switch placed in each specified position the output voltages under the following conditions shall be as indicated:

| Switches | | Input | Meter | J128 pin 37 | | J127a | J127n |
|---|---|---|---|---|---|---|---|
| CB101 | Pilot | +vdc | M101 | Output vdc | Load | vdc | vdc |
| ON | OFF | 24.0 | | 23.5 | 80 | | |
| ON | OFF | 25.0 | | 22.0 | 6.0 | | |
| ON | OFF | 29.0 | | 22.0 | 6.0 | | |
| ON | OFF | 29.0 | | 23.5 - 24.5 | 80 | | |
| ON | OFF | 28.0 | | | | | |
| ON | OFF | 28.0 | +28 ± 5% | | | 28 | 5.1 ± 10% |

3.15 Interchangeability (See 4.11). - Like units, assemblies, sub-assemblies, modules and replaceable parts shall be physically and functionally interchangeable, without modification of such items or of the equipment. Individual items shall not be hand-picked for fit or performance; however, matched pairs or sets, when permitted, may be interchangeable as such. Reliance shall not be placed on any unspecified dimension, rating, characteristic, etc.

3.16 Bounce preconditioning (See 4.6). - Test Sets shall be capable of meeting the requirements specified herein, without subsequent processing, after subjection to the bounce preconditioning.



Source: https://assist.dla.mil -- Downloaded: 202640-26T04:17Z
Check the source to verify that this is the currentversion before use.

3.17 Operational inspection (See 4.12). - The test set shall be capable of meeting the specified test after applicable processes, inspection and test have been completed to determine that each test set on order is operable prior to packaging.

3.18 Technical literature and running spares (See 6.2). - Technical literature and running spares and spare parts shall be furnished if specified in the contract. Running spares and spare parts shall be identical to corresponding parts in the equipment furnished on the order.

3.19 Workmanship (See 4.10). - The equipment shall be manufactured and assembled in accordance with the equipment drawings and requirement nine (9) of MIL-STD-454 and the following paragraphs herein.

| | |
|---|---|
| Cleaning | 3.4 |
| Controls | 3.5 |
| Securing of Parts | 3.7 |
| Soldering | 3.8 |
| Wiring and Cabling | 3.9 |
| Tropicalization of Materials | 3.12 |

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. - Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.2 Classification of inspection. - Inspection shall be classified as follows:

a. Preproduction inspection (does not include preparation for delivery). (See 4.3)

b. Inspection covered by subsidiary documents. (See 4.4)

c. Quality conformance inspection.



Source: https://assist.dla.mil -- Downloaded: 202640-26T04:17Z
Check the source to verify that this is the currentversion before use.

(1) Quality conformance inspection of equipment before preparation or delivery. (See 4.5)

(2) Quality conformance inspection of preparation for delivery. See 4.13)

4.3 Preproduction inspection. - This inspection will be performed by the overnment unless otherwise specified in the contract. It shall consist of he inspection specified in the subsidiary documents covering the items listed n 4.4 and the inspection specified for Group A, Group B, and Group C (See ables II, III and IV, respectively).

he preproduction inspection will normally be performed in this order: 1) vibration, (2) shock, benchhandling and (3) shock, equipment, other pre- roduction inspection may precede, follow, or be interspersed between the oregoing.

4.4 Inspection covered by subsidiary documents. - The following shall be nspected under the applicable subsidiary documents as part of the inspection f the units before preparation for delivery:

| Item | Where Required |
|---|---|
| Finish | 3.6 |
| Marking | 3.10 |
| Semiconductors | 3.11 |

4.5 Quality conformance inspection of equipment before preparation for elivery. - Each unit of each lot of equipment shall be subjected to bounce pre- onditioning (see 3.16) prior to inspection. The contractor shall perform the nspection specified in 4.4 and 4.5.1 through 4.5.4. This does not relieve the ontractor of his responsibility for performing any additional inspection which s necessary to control the quality of the product and to assure compliance ith all specification requirements. Failure to meet any requirement as a esult of bounce preconditioning shall be classified as a defect and recorded s such. The Government will review and evaluate the contractor's inspection rocedures and examine the contractor's inspection records. In addition the overnment -- at its discretion-- may perform all or any part of the specified nspection, to verify the contractors compliance with specified requirements, see 6.7). Test equipment for Government verification inspection shall be made vailable by the contractor.

4.5.1 Group A inspection. - Each unit of each lot of equipment shall be nspected for conformance to all the inspection and test requirements of Table I. Each lot will be subject to verification, utilizing the procedures of IL-STD-105 using the general inspection levels and the AQL's indicated in able II. Group A inspection shall be performed in any order which is atisfactory to the Government, except the operational inspection (3.17) shall e last. (see 6.6)



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

TABLE II - Group A Inspection

| Inspection | Reqt Par | Insp Par | AQL Major | AQL Minor |
|---|---|---|---|---|
| Visual and Mechanical | 3.19 | 4.10 | | |
| TS-2575( )/ARC-131: | | | | |
| Subassembly A1 | | | 0.65% | 2.5% |
| Subassembly A2 | | | 0.65% | 2.5% |
| ID-48( )/ARN | | | 1.0% | 4.0% |
| C-1611( )/AIC | | | 1.0% | 4.0% |
| C-7088( )/ARC-131 | | | 1.0% | 4.0% |
| TS-2575( )/ARC-131 (less cover) | | | 1.0% | 4.0% |
| TS-2575( )/ARC-131 (assembled) | | | 1.0% | 4.0% |
| MK-1035( )/ARC-131 (assembled) | | | 1.0% | 4.0% |
| Electrical: | | | | |
| Audio Amplifier | 3.14.1 | 4.9.1 | | |
| Retransmit Switch | 3.14.2 | 4.9.2 | | |
| Transmit Switch | 3.14.3 | 4.9.3 | | |
| Wide Band and Narrow Band Switch | 3.14.4 | 4.9.4 | 1%* for the group | |
| RF Amp. Align | | | | |
| Switches | 3.14.5 | 4.9.5 | | |
| Homer Attenuators | 3.14.6 | 4.9.6 | | |
| RF Load | 3.14.7 | 4.9.7 | | |
| Operational Inspection | 3.17 | 4.12 | 0.1% | |

*All electrical defects are considered major.

4.5.2 Group B inspection. - This inspection, including sampling, shall conform to Table III and to the procedures for small-sample inspection of Standard MIL-STD-105 using the special inspection levels. The AQL shall be 6.5 percent defective and the inspection level shall be S4 for normal, tightened and reduced inspection. Group B inspection shall normally be performed on inspection lots that have passed Group A inspection and on samples selected from units that have met the Group A inspection.

4.5.2.1 Order of inspection within Group B. - Group B inspection shall be performed in any order which is satisfactory to the Government.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

TABLE III - Group B Inspection

| Inspection | Reqt Par | Insp Par | AQL |
|---|---|---|---|
| Indicator ID-48( )/ARN | 3.14.8 | 4.9.8 | |
| Control Intercommunication C-1611( )/AIC | 3.14.9 | 4.9.9 | |
| Simulator Antenna Coupler SM-499( )/ARC-131 | 3.14.10 | 4.9.10 | 6.5% for the group |
| Control, Radio Set C-7088( )/ARC-131 | 3.14.11 | 4.9.11 | |
| Circuit Breaker | 3.14.12 | 4.9.12 | |
| Transient Protection | 3.14.13 | 4.9.13 | |
| Voltage Regulation | 3.14.14 | 4.9.14 | |
| Interchangeability | 3.15 | 4.11 | 6.5% |

4.5.3 Group C inspection. - This inspection shall be as listed in Table IV, and shall normally be performed on sample units that have been subjected to and met Group A and Group B inspection. No defects shall be allowed. Sample units shall be selected in accordance with paragraph 4.5.3.1.

TABLE IV - Group C Inspection

| Inspection | Reqt Par | Insp Par |
|---|---|---|
| Subgroup 1: | | |
| Temperature | 3.13.1 | 4.8.1 |
| Relative Humidity | 3.13.2 | 4.8.2 |
| Altitude | 3.13.3 | 4.8.3 |
| Vibration | 3.13.6.1 | 4.8.6.1 |
| Shock; Bench Handling | 3.13.6.2 | 4.8.6.2 |
| Shock; Drop | 3.13.6.2 | 4.8.6.3 |
| Subgroup II: | | |
| Fungus | 3.13.5 | 4.8.5 |
| Spray Tight Protection | 3.13.4 | 4.8.4 |
| Sand and Dust | 3.13.7 | 4.8.7 |



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.5.3.1 Sampling for inspection. - Units shall be selected at random for each group of inspections in Table III as specified in 4.5.3.1.1, through 4.5.3.1.2. The first samples selected shall be at the start of the contract from the first quality conformance inspection production lot. Selection of these samples shall be as specified and within 30 calendar days after selection these samples shall have been subjected to and passed the Group C inspections. (See 6.5)

4.5.3.1.1 Subgroup I. - For this subgroup, two units from the first 10 production units shall be selected for the first Group C inspection. For subsequent Group C inspections, two units per month shall be selected or fractions thereof.

4.5.3.1.2 Subgroup II. - For this subgroup, only one unit from the first 10 production unit shall be selected for the first Group C inspection. For subsequent inspection one unit shall be selected when one half of the units on order have been accepted by the Government's QA Representative.

4.5.3.2 Noncompliance. - The contractor shall immediately report in writing each Group C failure occurrence, including details of the failure and characteristics affected. The contractor shall immediately investigate the cause of failure and further report the results of investigation and details of the proposed corrective action on (i) the process and materials, as applicable, and (ii) all units of product which were manufactured under the same conditions and which the Government considers subject to the same failure. Reports shall be forwarded to the responsible technical activity designated in the contract through the Quality Assurance Representative. After corrective action has been taken, additional sample units shall be subjected to Group C inspection (all inspections, or the inspections which the sample failed, at the option of the Government) and Group A and B inspection may be reinstituted; however, final acceptance and shipment will be withheld until the Group C reinspection results have shown that the corrective action was effective.

4.5.4 Reinspection of conforming Group B and Group C sample units. - Unless otherwise specified, sample units which have been subjected to and passed Group B or Group C inspection, or both, may be accepted on contract, provided that they are subjected to and pass Group A inspection after repair of all visible damage and cleaned of all foreign materials.

4.6 Bounch preconditioning. - Maintenance Kit, MK-1035( )/ARC-131 shall be placed in its normal operating position on a L.A.B. ARV-30-200 vibration table and subjected to a two (2) minute vibration test. The vibration force shall be approximately 2G at 25 Hz.



Source: https://assist.dla.mil -- Downloaded: 202640-26T04:17Z
Check the source to verify that this is the currentversion before use.

4.7 Standard test conditions. - Unless otherwise specified, herein, all inspections shall be performed at room temperature, pressure and humidity under the following conditions:

a. Power supply voltage - 28 ± 1.0 vdc

b. Warm-up time -Not more than 5 minutes

c. Assemblies and connections -Indicator ID-48( )/ARN, Control, Radio Set C-7088( )/ARC-131 and Control, Intercommunication C-1611( )/AIC shall be removed from the TS-2575( )/ARC-131 and P101 and P102 cable plugs shall be removed from J101 and J102.

4.8 Service conditions. -

4.8.1 Temperature. - The equipment shall be subjected to the temperature test procedures of MIL-T-5422 to determine compliance with 3.13.1. After completion of the temperature test, the equipment shall meet the operational test of 4.12.

4.8.2 Relative humidity. - The equipment shall be subjected to the humidity test procedures of MIL-T-5422 to determine compliance with 3.13.2. Upon completion of the cycling and conditioning, the equipment shall meet the operational test of 4.12.

4.8.3 Altitude. - The equipment shall be tested in accordance with the test procedures of MIL-T-5422 to determine compliance with 3.13.3.

4.8.4 Spray-tight protection. - The equipment shall be assembled with cover on and subjected to the tests specified in Table I of referenced specification for compliance with paragraph 3.13.4.

4.8.5 Fungus. - The equipment shall be subjected to 28 days of the fungus test specified in Method 508 of MIL-STD-810. For gasket or other non-hermetically sealed equipment, the parts and materials of the chassis shall be sprayed with spore suspension. The interior of the case shall be subjected to the test in this open condition and as specified for compliance with 3.13.5.

4.8.6 Vibration and shock (See 3.13.6). -

4.8.6.1 Vibration. - Internal vibration of the equipment shall be measured as follows to determine conformance to 3.13.6.1.

a. Secure the test set directly to a vibration table that can be controlled within 10 percent of the specified amplitude. Mounting method shall be such that vibration within the equipment can be observed and measured.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

b. Vibrate the equipment successively in three mutually perpendicular directions over a frequency range of 10 to 55 Hz. The total excursion of the applied vibration shall be 0.030 inch.

c. In each of the three directions, change the frequency in steps of 1 Hz and maintain each frequency for at least 10 seconds.

d. Measure vibration amplitudes by optical means, or by other means provided that vibration of the part is not affected by the measurement.

e. Perform the operational test of 4.12 upon completion of the vibration test.

4.8.6.2 Shock: bench-handling. - The test set chassis-and-front-panel assembly shall be removed from its combination case, as for servicing, and placed in a suitable position for servicing on a solid, 2-inch fir bench top. The test shall be performed as follows, in a manner simulating shocks liable to occur during servicing:

a. Tilt up the assembly through an angle of 30 degrees, using one edge of the assembly as an axis, and permit the assembly to drop back freely to the horizontal. Repeat, using other practicable edges of the same horizontal face as axes, for a total of four drops.

b. Repeat "a", with the assembly resting on other faces, until it has been dropped for a total of four times on each face on which the assembly might practically be placed during servicing. Upon completion of the test, the equipment shall be tested for compliance with 3.13.6.2.

4.8.6.3 Shock; drop. - The equipment in its combination case shall be subjected to 18 impact shocks of 15 g. consisting of 3 shocks in opposite directions along each of 3 mutually perpendicular axes, each shock impulse having a time duration of 11 ± 1 milliseconds. Except for abrasion, paint chipping, and small local deformations, no damage shall occur. Upon completion of the test, without adjustment or repair, the equipment shall be tested for compliance with 3.13.6.22

4.8.7 Sand and dust. - The equipment shall be tested in accordance with the sand and dust test procedure of MIL-T-5422 to determine compliance with 3.13.7.

4.9 Electrical tests (See 3.14). -

4.9.1 Audio amplifier (See 3.14.1). -



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.9.1.1 Frequency response. - With standard test conditions and lead of speaker LS101 disconnected, connect the audio generator to HI and LO terminals of J110. Terminate pins 12 and 14 of TB102 with a 16 ohm load. Set the audio generator for 2.38 vrms at 1000 Hz and adjust speaker volume control for 3.0 vrms across the 16 ohm load, measure the output with input frequencies at 150 Hz through 3000 Hz for compliance with 3.14.1.1.

4.9.1.2 Speaker output. - With standard test conditions, apply 2.38 vrms to J110 and sweep the frequency range of 150 to 3000 Hz. A tone that is variable shall be heard. This tone shall be free from audible distortion. At least 3.0 vrms shall be measured across the speaker voice coil for compliance with 3.14.1.2.

4.9.2 Retransmit switch. - Press the required PUSH to test points to determine that the lamps operate, and make measurements for assurance that zero ohm appear as specified for compliance with 3.14.2.

4.9.3 Transmit switch. - Set the TRANS switch S102 to the specified positions and make measurements for compliance with 3.14.3.

4.9.4 Wide band/narrow band switch. - Set the WB-NB switch S106 to each specified position, with an ohm meter make the required measurements for compliance with 3.14.4.

4.9.5 RF amp. align switches. - Apply standard input power and measure the voltage at J116 with the AGC switch S105 in each specified position. With standard input power off, measure the resistance at J116 with switches S104 and S105 in the specified positions. These measurements shall be made for compliance with 3.14.5.

4.9.6 Homer attenuators. - With standard input power applied, connect signal generator to J115 and RF voltmeter through a 50 ohm probe to J117A and terminate J117B to ground with a 50 ohm resistor. Measurements shall be made at the specified points with the attenuators and load set to the indicated positions and points for compliance with 3.14.6.

4.9.7 RF load. - Connect signal generator to J113 and adjust output to 60MHz at 1.0 vrms, and RF voltmeter to J114 through a 50 ohm probe. Measure the output signal for compliance with 3.14.7.

4.9.8 Indicator ID-48( )/ARN. - The indicator shall be installed, and standard input power applied to the test set. Apply the specified dc voltages and determine that the pointers and flags operate as required and that the indicators meet the requirements of 3.14.8.



Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

4.9.9 Control Intercommunication C-1611( )/AIC. - The C-1611 shall be installed and standard input power applied to the test set. Set Function switch on the C-1611 to T/R position and the volume control fully clockwise and all the RECEIVER switches on the C-1611 to OFF position and the Transmit control to position 1. Rotate the Speaker control on the test set fully clockwise and set the test set XMIT switch S102 to ON position, connect audio generator set at the specified levels through the required pad to the test set and jumper HI and LO jack of J107 and J104, a 1000 Hz signal shall be audible from the test set speaker. Remove the jumpers between J104 and J107 and set RECEIVER switch No. 1 on the C-1611 to ON position and connect the audio generator set for 0.5 vrms at 1000 Hz to J107, rotate the Volume control on C-1611 clockwise, a 1000 Hz signal shall be present at pins 2 and 4 of J111 and the test set speaker. Determine that the signals are audible at the required points and that the Control C-1611 meets the requirements of 3.14.9.

4.9.10 Simulator Antenna Coupler SM-499( )/ARC-131. - Apply standard input voltage to the test set and connect SM-499 to J118 on the antenna coupler cable. Set C-7088 frequency selectors to each frequency from 30 to 49 MHz, the SM-499 frequency indicator shall display the same frequency. Set C-7088 frequency selectors to each frequency from 50 to 75 MHz, the SM-499 frequency indication shall display the same frequency; except from 69 to 75. Determine that the frequency indicators display the same frequency and the indicator lamp light for compliance with 3.14.10.

4.9.11 Control, Radio Set C-7088( )/ARC-131. - The C-7088 shall be tested for compliance with 3.14.11.

4.9.12 Circuit breaker, trip-out. - With switch CB101 to ON position, apply sufficient dc voltage to the 28 vdc power source cable. Load the output of CB101 for the time required to trip CB101. Remove the load and reset CB101 to "ON" position for compliance with 3.14.12.

4.9.13 Transient protection. - Connect P101 to J101 and P102 to J102, and an 80 ohm resistor to J128 pin 37, set input voltage to 29.0 vdc, apply a transient to the positive terminal of the input voltage line of 80 volts amplitude for a one (1) second maximum duration. The output at J128 pin 37 shall be measured for compliance with 3.14.13.

4.9.14 Voltage regulation. - Connect P101 to J101 and P102 to J102, place Circuit Breaker CB101 to ON and pilot switch S103 to OFF position, set input voltage to 28.0 vdc and connect a 80 ohm resistor between J128 pin 37 and ground. Adjust R108 on the test set for 24.0 vdc at J128 pin 37. Set input voltage at J128 pin 37 shall not be less than 23.5 vdc. With input voltages of 25.0 vdc and 29.9 vdc and the 80 ohm resistor replaced with a 6.0 ohm resistor the output voltage at J128 pin 37 shall be not less than 22.0 vdc and between 23.5 vdc respectively. Set the input voltage to 28.0 vdc and switch S103 to ON position, the 28.0 vdc shall be present at J127a and the voltage at J127n shall be between 4.6 vdc and 5.6 vdc, measurements shall be made for compliance with 3.14.14.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.10 Visual and mechanical inspection. - The equipment shall be examined for the defects in accordance with MIL-STD-252, and the assemblies before inclusion into the TS-2575( )/ARC-131 final assembly. The requirements of 3.19 shall be met.

4.11 Inspection for interchangeability. - The dimensions listed below shall be gaged or measured to determine compliance with the physical interchangeability requirements of 3.15. When a listed dimension is not within specified or design limits, it shall be considered a major defect.

a. External and internal dimensions of cases, covers, and insertable assemblies when such dimensions affect mating of parts.

b. Dimensions of cavities, of the console and other units, when such dimensions affect insertion of items.

c. Location of hinges and fasteners on separable parts of assemblies which must mate, such as cases, covers and mountings.

d. Location of connectors, locking pins, fasteners, slides and mountings which receive mating parts of plug-in assemblies and major units, and location of the mating parts on the plug-in assembly or major units.

e. Size and form of special threads.

4.12 Operational inspection test. - The equipment shall be inspected for assurance that all accessories are in place and that the equipment controls perform their required functions for compliance with 3.17.

4.13 Quality conformance inspection of preparation for delivery. - Preparation for delivery shall be inspected in accordance with Specification MIL-P-116 to determine conformance to the packaging requirements of Section 5.

4.14 Rough handling test (preparation for delivery). - When rough handling test in accordance with Specification MIL-P-116 is required by the contract the operational inspection test 4.12, shall be conducted to determine freedom from operational malfunction caused by rough handling.

5. PREPARATION FOR DELIVERY

5.1 Preservation and packaging. - Preservation and packaging shall be level A, or C as specified. (See 6.2)

5.1.1 Level A. -

5.1.1.1 Cleaning. - Each Maintenance Kit, MK-1035( )/ARC-131 shall be cleaned in accordance with process C-1 of MIL-P-116.



Source: https://assist.dla.mil -- Downloaded: 202640-26T04:17Z
Check the source to verify that this is the currentversion before use.

5.1.1.2 Drying. - Each Maintenance Kit, MK-1035( )/ARC-131 shall be dried in accordance with the applicable procedure of MIL-P-116.

5.1.1.3 Unit packaging. - Unit packaging shall be in accordance with the methods prescribed in MIL-P-116 as specified herein.

5.1.1.3.1 Technical literature. - Each technical literature shall be package method 1C-I.

5.1.1.3.2 Spare Fuses. - Fuses shall be stowed within the clips provided on the front panel of the Maintenance Kit. No further packaging required.

5.1.1.3.3 Cords and cables. - Each cord and cable shall be packaged individually, Method III as follows: Wind each item into a coil of proportionate dimensions. Tie in three places with cotton twine conforming to T-T-871, type 1, 6 ply. Secure the ends with ties.

5.1.1.3.4 Stowage. - Stow the cords and cables packaged as specified in 5.1.1.3.3 within the space provided in the cover of the maintenance kit. Fill all voids with paperboard conforming to PPP-P-291, type 1, to prevent movement. Close inner cover. Secure the cover of the kit by means of fasteners provided.

5.1.1.3.5 Maintenance Kit MK-1035( )/ARC. - Each Maintenance Kit MK-1035( )/ARC-131 shall be individually packaged Method III as follows: Cushion each Maintenance Kit on surfaces with cells or pads or both, fabricated of fiberboard conforming to PPP-F-320 W5c, designed and fabricated to protect all projections and absorb the shock of impact in handling and transit. Place the cushioned item within a close fitting fiberboard box conforming to PPP-B-636, W5c. Place the technical literature packaged as specified in 5.1.1.3.1 in the box directly under the lid of the box. Box closure shall be as specified in the appendix of the box specification.

5.1.2 Level C. - Maintenance Kit, MK-1035( )/ARC-131 shall be packaged in a manner that will afford adequate protection against corrosion deterioration and damage during shipment from the supply source to the first receiving activity.

5.2 Packing. - Packing shall be level A, B or C as specified. (See 6.2)

5.2.1 Level A. - A quantity of Maintenance Kit, MK-1035( )/ARC-131 packaged as specified in 5.1 shall be packed within a close-fitting fiberboard box conforming to MIL-B-43291 or PPP-B-640, class weather resistant, not to exceed the gross weight limitation of 200 pounds. Closure shall be in accordance with the appendix of the applicable box specification. The shipping container shall be reinforced by pressure-sensitive filament tape banding conforming to PPP-T-97, type IV or PPP-S-760, type II, respectively, as specified in the appendix of the applicable box specification.



Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

5.2.2 Level B. - A quantity of Maintenance Kit, MK-1035( )/ARC-131, packaged as specified in 5.1, shall be packed as specified in 5.2.1.

5.2.3 Level C. - A quantity of Maintenance Kit, MK-1035( )/ARC-131 packaged as specified in 5.1, shall be packed as specified in 5.2.1. Except that the fiberboard boxes shall be of the type, size and kind commonly used for the purpose and shall comply with the rules and regulations of the common carrier as applicable to the mode of transportation. Packing shall be accomplished in a manner that will afford adequate protection to the package and its contents during shipment from the supply source to the first receiving activity.

5.3 Marking. - In addition to any special marking required by the contract or order, interior packages and exterior shipping containers shall be marked in accordance with MIL-STD-129.

6. NOTES

6.1 Intended use. - Maintenance Kit, Electronic MK-1035( )/ARC-131 is used as an aid in maintenance, providing facilities for bench testing Radio Set AN/ARC-131( ) and Antenna Coupler CU-942( )/ARC-54.

6.2- Ordering data. - Procurement documents should specify the following:

a. Title, number, and date of this specification and any amendment thereto.

b. Level of packaging and level of packing required for shipment. (Level A, level B or level C).

c. The specific paragraphs of Section 5 which are applicable to the particular procurement.

d. Preproduction inspection. -

(1) Three (3) sample units of each item cited in Section 1 are generally required so that lengthy environmental tests can be completed on one sample unit while complete performance measurements can be made on the second sample unit. (See 3.3)

(2) Preproduction pack(s) as follows:

(a) Makeup of pack(s).

(b) Number of each kind of pack to be submitted.

(c) Inspection to performed thereon (including rough handling).



Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

(d) Marking and shipping of samples.

(e) Place of final inspection.

(f) Technical literature required. (See 3.18)

(g) Quantity of tools and running spare parts required.

(h) Submission of the statement of treatment referenced in 3.12 should be sixty (60) days after award of contract. This statement should be submitted to the contracting officer.

6.3 Nomenclature. - The parentheses in the nomenclature will be deleted or replaced by a letter identifying the particular design; for example: MK-1035W/ARC-131. The contractor should apply for nomenclature in accordance with the applicable clause in the contract.

6.4 Definition of Level B. - Level B packaging requirements detailed herein are designed to furnish protection against corrosion, deterioration, and physical damage during domestic shipments; covered storage for a period of three years or less; and distribution within the continental limits of the United States.

6.5 Group C inspection. - Approval to ship equipment on order may be withheld, at the discretion of the Government, pending decision from the contracting officer (PCO) on the adequacy of corrective action. (See 4.5.3.1)

6.6 Location of operational inspection. - It is desirable that the operational inspection 4.12 be performed at a location that will minimize handling (which might cause damage to the units) after this inspection. It is recommended that the entire lot (including the sample units) be inspected immediately prior to packaging.

6.7 Verification inspection- Verification by the Government will be limited to the amount deemed necessary to determine compliance with the contract and will be limited in severity to the definitive Quality Assurance provisions established in this specification and the contract. The amount of verification inspection by the Government will be adjusted to make maximum utilization of the contractor's quality control system and the quality history of the product.

Custodian:
Army-EL

Preparing Activity
Army-EL
Project 6625-A420



Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

To detach this form, cut along this line

# SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 22-R255

INSTRUCTIONS: This sheet is to be filled out by personnel, either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments and suggestions submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or serve to amend contractual requirements.

SPECIFICATION

ORGANIZATION

CITY AND STATE

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

☐ YES ☐ NO *(If "yes", in what way?)*

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity)*

SUBMITTED BY *(Printed or typed name and activity - Optional)*

DATE

DD FORM 1 JAN 66 1426

REPLACES EDITION OF 1 OCT 64 WHICH MAY BE USED.

ESC-FM 1068-68

Source: https://assist.dla.mil -- Downloaded: 2026l0-26T04:17Z
Check the source to verify that this is the currentversion before use.

FOLD

Department of the Army
Headquarters
U.S.Army Electronics Command
Fort Monmouth, New Jersey 07703

POSTAGE AND FEES PAID

OFFICIAL BUSINESS

Commanding General
U.S.Army Electronics Command
ATTN: AMSEL- ~~ID~~-SS
Fort Monmouth, New Jersey 07703

FOLD

To detach this form, cut along this line

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.