MILITARY SPECIFICATION

TEST SET, ELECTRONIC CIRCUIT PLUG-IN UNIT AN/ARM-87( ) (UNITS OF)

1. SCOPE

1.1 This specification covers the following units of Test Set, Electronic Circuit Plug-In Unit AN/ARM-87( ) which is capable of complete performance testing of each of the modules and sub-assemblies, except the harmonic filter module, of the Receiver-Transmitter, RT-348( )/ ARC-54. (See 6.3)

Test Set, Electronic Circuit Plug-In Unit TS-2061( )/ARM-87( )
Attenuator, Fixed CN-1097/ARM-87( ).

2. APPLICABLE DOCUMENTS

2.1 The following documents of the issue in effect on date of invitation for bids, or request for proposal, form a part of this specification to the extent specified herein:

SPECIFICATIONS

FEDERAL

T-T-871	Twine, Cotton, Wrapping
QQ-S-781	Steel, Strapping, Flat
PPP-B-585	Boxes, Wood Wirewound
PPP-B-591	Boxes, Fiberboard, Wood-cleated
PPP-B-601	Boxes, Wood, Cleated - Plywood
PPP-B-621	Boxes, Wood, Nailed and Lockcorner
PPP-B-636	Box, Fiberboard
PPP-B-640	Boxes, Fiberboard, Corrugated, Triplewall
PPP-C-650	Crates, Wood, Open and Covered
PPP-F-320	Fiberboard; Corrugated and Solid, Sheet Stock (Container Grade), and Cut Shapes

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

SPECIFICATIONS

FEDERAL

PPP-P-291	Paperboard, Wrapping, Cushioning
PPP-S-760	Strapping, Nonmetallic, (and Connectors)
PPP-T-45	Tape, Gummed, Paper, Reinforced and Plain for Sealing and Securing
PPP-T-76	Tape, Pressure-Sensitive Adhesive Paper, (for Carton Sealing)
PPP-T-97	Tape; Pressure-Sensitive Adhesive, Filament Reinforced

MILITARY

MIL-C-104	Crates, Wood; Lumber and Plywood Sheated, Nailed and Bolted
MIL-P-116	Preservation, Methods of
MIL-T-713	Twine, Impregnated, Lacing and Tying (For Use in Electrical and Electronic Equipment)
MIL-L-10547	Liners, Case, and Sheet, Overwrap; Water-Vaporproof or Waterproof, Flexible
MIL-M-13231	Marking of Electronic Items
MIL-F-14072	Finishes for Ground Signal Equipment
MIL-S-19500	Semiconductor Devices (General Specification for)
MIL-B-43291	Boxes, Fiberboard, Corrugated, Double-Wall, Weather Resistant

STANDARDS

MILITARY

MIL-STD-105	Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-108	Definitions of and Basic Requirements for Enclosures for Electric and Electronic Equipment
MIL-STD-129	Marking for Shipment and Storage

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

STANDARDS

MILITARY

MIL-STD-169	Extreme Temperature Cycle
MIL-STD-170	Moisture Resistance Test Cycle for Ground Signal Equipment
MIL-STD-252	Wired Equipment, Classification of Visual and Mechanical Defect
MIL-STD-454	Standard General Requirements for Electronic Equipment
MIL-STD-810	Environmental Test Methods for Aerospace and Ground Equipment

DRAWINGS

ELECTRONICS COMMAND

SC-DL-508536	Test Set, Electronic Circuit, Plug-in Unit TS-2061( )/ARM-87( )
SM-D-508437	Attenuator, Fixed, CN-1097/ARM-87( )

(Copies of specifications, standards and drawings required by contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer. Both the title and number or symbol should be stipulated when requesting copies.)

3. REQUIREMENTS

3.1 Description. - The Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) is contained in a lightweight, water-tight combination case and provides the necessary voltages, test signals, and metering circuits that are required for the performance and maintenance tests of the modules and sub-assemblies, except the Harmonic Filter, of Receiver-Transmitter RT-348( )/ARC-54. The test set utilizes semi-conductor devices on printed cards and is of modular construction; operation is provided by a self-contained internal power supply which operates on an input power of 115 volts RMS ± 10%, 47-1000 cps or 230 volts. Operating controls, power input connector, and module mating connectors are mounted on the front panel.

3.2 Construction. - Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) shall be constructed in accordance with drawing and data list SC-DL-508536.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.2.1 Attenuator, Fixed CN-1097/ARM-87 ( ) shall be constructed in accordance with drawing SM-D-508437.

3.3 Preproduction samples.- The contractor shall furnish two preproduction samples of equipment on order for approval, if required by the invitation for bids and contract. (See 4.3 and 6.2)

3.4 Cleaning.-

3.4.1 Parts.- After fabrication, parts shall be cleaned in accordance with good commercial practice, or as specified in an applicable document. Cleaning processes shall have no deleterious effect. Corrosive material shall be removed completely before the parts are mounted on chassis, panels, etc.

3.4.2 Units.- After assembly, units shall be cleaned thoroughly and shall be free from particles of solder, flux, and other foreign material. In addition, when necessary, such cleaning shall also be performed before final assembly of the units.

3.5 Controls.- All movable controls shall operate properly without binding or other undue restriction. Controls shall not be assembled in a misaligned condition.

3.6 Finish, protective.- The equipment shall be given protective finish in accordance with Specification MIL-F-14072. This includes finish of hardware, such as handles, hinges, screws, etc., and necessary touch-up after mounting. The final paint film on Type 1 surfaces shall be semi-gloss, light gray (Film E) conforming to Specification MIL-F-14072. (See 4.4)

3.7 Securing of parts.-

3.7.1 General.- Brackets, lugs, inserts, bolts, and other mounting arrangements shall retain items securely when subjected to specified service conditions.

3.7.2 Securing of parts by threaded fasteners.- Nylok or other screws with plastic devices and Loctite or similar sealants shall not be subjected to temperatures in excess of 250° F (as during baking of paint). Loctite or similar sealants shall be applied in accordance with the manufacturer's instructions.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.8 Soldering.-

3.8.1 Solder.- Solder shall conform to the equipment drawings.

3.8.2 Acid or acid salts.- No acid or acid salts shall be used in preparation for or during soldering; however, exception is permitted for preliminary tinning of electrical connections and for thinning or soldering of mechanical joints not used to complete electrical circuits, but in no case shall acid or acid salts be used where they can come in contact with insulation material. Where acid or acid salts are used, as permitted above, they shall be completely neutralized and removed immediately after use.

3.8.3 Process.- There shall be no sharp points or rough surfaces resulting from insufficient heating. The solder shall feather out to a thin edge, indicating proper flowing and wetting actions, and shall not be crystalized, overheated, or underheated. The minimum necessary amount of flux and solder shall be used for electrical connections. Any means employed to remove an unavoidable excess of flux shall not incur the risk of loose particles of flux, brush bristles, or other foreign material remaining in the equipment; flux being spread over a larger area; or damage to the unit. Insulation material that has been subjected to heating during the soldering operation shall be undamaged and parts fastened thereto shall not have become loosened.

3.9 Wiring and cabling.- Wiring and cabling shall be neat and sturdy.

3.9.1 Cabling.- Insulated wires shall be formed into cables except where operation of the equipment would be adversely affected thereby or where it is physically impracticable as in the case where the resulting cables would be excessively large and would interfere with operation or maintenance. The cabling of wires shall be effected by tape or twine conforming to Specification MIL-T-713. Individual conductors thus secured shall lie essentially parallel; however, this does not prohibit the use of twisted pairs.

3.9.2 Slack.- Wires and cables shall be as short as practical except that sufficient slack shall be provided for the following purposes:

a. To prevent undue stress on cable forms, wires, and connections, including connections to resiliently supported parts.

Source: https://assist.dla.mil -- Downloaded: 20260-26T04:17Z
Check the source to verify that this is the current version before use.

3.9.2 (Cont'd)

b. To enable parts to be removed and replaced during servicing without disconnecting other parts.

c. To provide for at least two replacements of the part to which the wire or cable is connected, except where uninsulated wires are used.

3.9.3 Protection.- Wires and cables shall be so placed and protected as to avoid contact, under specified service conditions, with rough or irregular surfaces or sharp edges.

3.9.4 Support.- Wire and cable shall be properly supported and secured to prevent undue stress on the conductors and terminals and undue change in position of the wire or cable (I) during and after subjection of the equipment to specified service conditions or (II) after service or repair of the equipment in a normal manner.

3.9.5 Clearance.- Clearance between solder connections or bare conductors, on terminal boards, relays, or other parts, shall be such that no accidental contact can occur between adjacent connections when subjected to specified service conditions

3.9.6 Splicing.- Wires in a continuous run between two terminals shall not be spliced during the wiring operation.

3.9.7 Connections.-

3.9.7.1 General.- Before being soldered to terminal lugs or fixed terminals, wires shall be mechanically secured so that the connections are not dependent for strength on solder alone. Where practicable, wires soldered to fixed terminals shall be looped at least one-half turn but not more than three-quarters turn around the terminal before soldering. Bared ends of wire leads to be terminated in solder-type terminal lugs shall be tinned, silver plated, or lead-alloy coated. No varnish, lacquer, inspection paint, or other coating shall be applied to completed electrical connections.

3.10 Marking.-

3.10.1 General.- Marking shall conform to Specification MIL-M-13231. Front panel marking shall be Group 1. (See 4.4)

3.10.2 Visibility.- Wherever practicable, parts and assemblies shall be so mounted that their identification marking will be readily visible with minimum disassembly of the equipment.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.11 Serial numbers. - Test Set, Electronic Plug-in TS-2061( )/ARM-87( ) and Attenuator, fixed CM-1097/ARM-87( ) shall be serial numbered.

3.12 Service conditions (See 4.7). - The equipment shall meet the following service conditions: Where a test is referenced, meeting the test shall be considered as compliance with the requirement.

3.12.1 Temperature (See 4.7.1). -

a. Operating. - Ambient temperature in the range of +55°C to -18°C. Exposure of the high temperature extreme not to exceed 72 hours, at any one time.

b. Non-operating. - Exposure in the range of -55°C to 71°C. Exposure at the high temperature extreme not to exceed 4 hours, and at low temperature extreme not to exceed 24 hours, at any one time.

3.12.2 Relative humidity (See 4.7.2). - Up to 95 percent relative humidity including conditions wherein condensation takes place in the form of water. This test shall be performed over a 10 day period.

3.12.3 Altitude (See 4.7.3). -

a. Operating. - Up to 10,000 feet above sea level. Maximum temperature shall be +86°F.

b. Non-operating. - Up to 50,000 feet above sea level.

3.12.4 Spray-tight protection (See 4.7.4). - The equipment shall meet the Table I test conditions of MIL-STD-108 for "spray-tight" enclosure. There shall be no evidence of moisture inside the equipment.

3.13 Vibration and shock. -

3.13.1 Vibration (See 4.7.5). - No impaired performance or damage to the equipment shall result from vibrations at any frequency between 10 and 55 cycles per second.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.13.2 Shock.- The equipment shall not suffer damage or fail to operate after subjection to the requirements of Table I, as follows:

Table I

Paragraph Heading	Paragraph No.	Performance After Test
Shock; bench-handling	4.7.6	Specified performance (Note A) No physical damage.
Shock; drop	4.7.7	Operable (Note A). Any physical damage shall be minor only.

NOTE A: The equipment shall meet the following requirement:

Variable Control Limits 3.14.4

3.14 Electrical Requirements (See 4.8).-

3.14.1 Voltage indication (See 4.8.1).- The 230 volt operation shall cause a 66.5 ± 5 percent test meter reading when the Press to Monitor voltage button is depressed.

3.14.2 Frequency, oscillators (See 4.8.2).- With the circuit selector switches in the indicated positions the frequencies shall be as follows:

Circuit Selector	Test Point	Frequency
2200	A3-J3	1 kc ± 50 cps
2295	A4-J3	500 kc ± 500 cps
2298	A3-J5	10.32 kc ± 500 cps
0189	A10-J1	3.974 mc ± 1 kc
0299	A10-J2	5.925 mc ± 1 kc
0473	A11-J1	30 mc ± 3 kc
0463	A12-J1	68 mc ± 5 kc

3.14.3 Oscillator/counter, 150 Cycle (See 4.8.3).- With input frequencies of 148 ± 0.1 cps and 152 ± 0.1 cps the Test Meter shall read 60 ± 10 percent.

Source: https://assist.dla.mil - Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

3.14.4 Variable Control Limits (See 4.8.4).-

Control	Circuit Selector	Test Point	Control Position CCW NMT	CW NLT
1 kc AMPL	0209	J3-13 (Trans.Audio)	0.1 v	2.2 v
10 kc AMPL	6758	J8-4(Rec. Audio)	0.5 v	1.5 v
500 kc AMPL	6904	A4-J3, 500 kc FMO	0.075 V	0.20 v
3 mc Low Freq. AMPL	0189	3 mc, Panel Conn.	5 mv	25 mv
5 mc " "	0299	5 mc, " "	5 mv	25 mv
30 High Freq. AMPL	0073	30 mc, " "	30 mv	120 mv
68 mc AMPL	0063	68 mc, Panel Conn.	30 mv	120 mv
150 cps AMPL	1021	J3-8 (Trans. Audio)	0.1 v	2.0 v

3.14.5 Distortion, 1 kc (See 4.8.5).- The distortion at A3-J3 on the 1 kc/10 kc card shall not exceed 2.0 percent.

3.14.6 Freq. response, audio amp/det (See 4.8.6).- With the Push to Test button depressed and the audio signal set for 15 mv at A5-J2, the Test Meter reading shall be 70 ± 10 percent at each frequency of 150 cps, 1 kc, 10 kc, and 500 kc.

3.14.7 R.F. det/amp (See 4.8.7).- When an RF Signal of 30.00 mc is applied to Connector VM-1 on the front panel and the Press to Test button is depressed, the Test Meter shall read 90 percent with an input level of 63 ± 10 mv.

3.14.8 Distortion, detector (See 4.8.8).- With an audio signal, with 2 percent distortion at J8-14 on the TS-2061( )/ARM-87( ), the meter reading shall be not more than 45 percent.

3.14.9 Band-pass, 500 kc filter (See 4.8.9).- When the Press to Test button is depressed the Test Meter reading shall be as indicated at the following oscillator frequencies:

Freq.	Meter Reading
502.00 kc ± 50 cps	NMT 30%
501.00 kc ± 50 cps	NMT 30%
500.00 kc ± 50 cps	NMT 40%
499.00 kc ± 50 cps	NMT 30%
498.00 kc ± 50 cps	NMT 30%

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

3.14.10 Power attenuator and detector (See 4.8.10). - With the Circuit Selecttor switches in position 0000 and the Press to Test button depressed, the Test Meter shall read 50 ± 10%.

3.14.11 Switches 500 kc and 30 mc (See 4.8.11). - With the Circuit Selector Switches in the positions indicated below, and with the press to Test Button depressed, the minimum amplitude and the test meter reading shall be as shown.

Circuit Selector	Test Point	Amplitude
500 kc Switch:		
6837	J13 (Homer Coax)	340 ± 50 mv P-P
6927	J13 (Homer Coax)	340 ± 50 mv P-P
30 mc Switch:		Test Meter
0413		50 ± 10%
0423		50 ± 10%
0503		75% min.
0513		50 ± 10%
0523		50 ± 10%

3.15 Interchangeability (See 4.10). - Like units, assemblies, sub-assemblies, modules and replaceable parts shall be physically and functionally interchangeable, without modification of such items or of the equipment. Individual items shall not be hand-picked for fit or performance; however, matched pairs or sets, when permitted, may be interchangeable as such. Reliance shall not be placed on any unspecified dimension, rating, characteristic, etc.

3.16 Bounce preconditioning (See 4.6). - Test Sets shall be capable of meeting the requirements specified herein, without subsequent processing, after subjection to the bounce preconditioning.

3.17 Technical literature and running spares. - Technical literature and running spares and spare parts shall be furnished if specified in the contract. Running spares and spare parts shall be identical to corresponding parts in the equipment furnished on the order. (See 6.2)

3.18 Tropicalization. -

3.18.1 Statement of treatment. - When required to be submitted by the contract, the statement of treatment shall describe in detail the materials to be treated and the treating material and processes that the contractor proposes to use.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

3.18.2 Fungus (See 4.7.8). - The unit(s) shall show no evidence of visible fungus or corrosion when subjected to 28 days fungus test.

3.19 Operational Inspection. - The test set shall be capable of meeting the specified test after applicable processes, inspection and test have been completed to determine that each test set on order is operable prior to packaging.

3.20 Semiconductors (transistors and diodes). - These electron devices (semiconductors) shall conform to MIL-S-19500. (See 4.4)

3.21 Attenuator, Fixed CN 1097/ARM-87 (See 4.12). - The Attenuator CN-1097/ARM-87 shall meet the requirements of SM-D-508437.

3.22 Workmanship. - The equipment shall be manufactured and assembled in accordance with the equipment drawings and requirement nine (9) of MIL-STD-454 and the following paragraphs herein.

Cleaning	3.4
Controls	3.5
Securing	3.7
Soldering	3.8
Wiring and Cabling	3.9

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. - Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified, the supplier may utilize his own facilities or any commercial laboratory acceptable to the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure that supplies and services conform to prescribed requirements.

4.2 Classification of inspection. - Inspection shall be classified as follows:

a. Preproduction inspection (does not include preparation for delivery). (See 4.3)

b. Inspection covered by subsidiary documents. (See 4.4)

c. Quality conformance inspection.

(1) Quality conformance inspection of equipment before preparation for delivery. (See 4.4 and 4.5)

(2) Quality conformance inspection of preparation for delivery. (See 4.13)

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

4.3 Preproduction inspection.- This inspection will be performed by the Government unless otherwise specified in the contract. It shall consist of the inspection specified in the subsidiary documents covering the items listed in 4.4 and the inspection specified for Group A, Group B, and Group C (See Tables II, III and IV, respectively).

The preproduction inspection will normally be performed in this order: (1) vibration, (2) shock, benchhandling and (3) shock, equipment, other preproduction inspection may precede, follow, or be interspersed between the foregoing.

4.4 Inspection covered by subsidiary documents.- The following shall be inspected under the applicable subsidiary documents as part of the inspection of the units before preparation for delivery:

Item	Where Required
Finish	3.6
Marking	3.10
Semiconductors	3.20

4.5 Quality conformance inspection of equipment before preparation for delivery.- The contractor shall perform the inspection specified in 4.4 and 4.5.1 through 4.5.4. This does not relieve the contractor of his responsibility for performance of any additional inspection which is necessary to control the quality of the product and to assure compliance with all specification requirements. The Government will review and evaluate the contractor's inspection procedures and examine the contractor's inspection records. In addition the Government, at its discretion, may perform all or any part of the specified inspection, to verify the contractor's compliance with specified requirements. (See 6.6) Test equipment for Government verification inspection shall be made available by the contractor. Each unit on order shall be bounce preconditioned after final assembly. (See 3.16)

4.5.1 Group A inspection.- This inspection, including sampling, shall conform to Table II and the inspection procedures of Standard MIL-STD-105, using the general inspection levels. Group A inspection shall be performed in any order which is satisfactory to the Government, except the operational inspection (3.19) shall be last. (See 6.5)

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

TABLE II - Group A Inspection

Inspection	Reqt Par.	Insp. Par.	AQL Major	AQL Minor
Visual and Mechanical.-	3.18	4.9		
Printed Wiring Assemblies:				
A1 Load/500 kc Filter			0.65%	2.5%
A2 150 cps Oscillator/Counter			0.65%	2.5%
A3 1 kc/10 kc Oscillator			0.65%	2.5%
A4 500 kc FM Oscillator			0.65%	2.5%
A5 Audio Amplifier Detector			0.65%	2.5%
A6 +28 v Regulator			0.65%	2.5%
A7 High Voltage Power Supply			0.65%	2.5%
A8 -28 v Regulator			0.65%	2.5%
A9 Load #1			0.65%	2.5%
A10 3.975/5.925 mc Oscillator			0.65%	2.5%
A11 30 mc Oscillator			0.65%	2.5%
A12 68 mc Oscillator			0.65%	2.5%
A13 RF Amplifier/Detector Switch			0.65%	2.5%
TS-2061( )/ARM-87( ) Assembly (less case and cover)			1.0%	4%
Case and Cover Assembly			1.0%	4%
AN/ARM-87( ) Final Assembly			1.0%	4%
Electrical:				
Voltage Indication	3.14.1	4.8.1		
Frequency Oscillators	3.14.2	4.8.2		
150 cps Oscillator/Counter	3.14.3	4.8.3		
Variable Control Limits	3.14.4	4.8.4		
Distortion, 1 kc	3.14.5	4.8.5	1%	
Freq. Response, Audio Amp/Det	3.14.6	4.8.6	for the	
RF Amplifier/Detector Switch	3.14.7	4.8.7	group	
Distortion, Detector	3.14.8	4.8.8		
Bandpass, 500kc Filter	3.14.9	4.8.9		
Power Attenuator and Detector	3.14.10	4.8.10		
Switches 500 kc and 30 mc	3.14.11	4.8.11		
Operational inspection.-			0.1%	

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.5.2 Group B inspection.- This inspection, including sampling, shall conform to Table III and to the procedures for small-sample inspection of Standard MIL-STD-105 using the special inspection levels. The AQL shall be 6.5 percent defective and the inspection level shall be S4 for normal, tightened and reduced inspection. Group B inspection shall normally be performed on inspection lots that have passed Group A inspection and on samples selected from units that have met the Group A inspection.

TABLE III - Group B Inspection

Inspection	Reqt Par.	Insp Par.	AQL
Attenuator CN-1097/ARM-87( )	3.21	4.12	6.5
Interchangeability	3.15	4.10	6.5%

4.5.3 Group C inspection.- This inspection shall be as listed in Table IV, and shall normally be performed on sample units that have been subjected to and met Group A and Group B inspection.

TABLE IV - Group C Inspection

Inspection	Reqt Par.	Insp Par.
Subgroup I		
Temperature	3.12.1	4.7.1
Relative Humidity	3.12.2	4.7.2
Altitude	3.12.3	4.7.3
Vibration	3.13.1	4.7.5
Subgroup II		
Spray Tight Protection	3.12.4	4.7.5
Shock, Bench Handling	3.13.2	4.7.6
Shock, Drop	3.13.2	4.7.7
Subgroup III		
Fungus	3.18.2	4.5.3.1.3

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.5.3.1 Sampling for inspection of equipment. - Units selected for each Group C inspection shall be selected without regard to their quality in accordance with the following:

4.5.3.1.1 Subgroup I. - For this subgroup, two units from the first 10 production units shall be selected for the first Group C inspection. For subsequent Group C inspections, one unit from each successive 50 shall be selected.

4.5.3.1.2 Subgroup II. - For this subgroup, two units from the 10 production units shall be selected for the first Group C inspection. For subsequent Group C inspection, one unit from each successive 50 shall be selected.

4.5.3.1.3 Subgroup III. - For this subgroup, only one unit from the first 10 production unit shall be selected for the first Group C inspection. For subsequent inspection one unit shall be selected when one half of the units on order have been accepted by the Government's QA Representative.

4.5.3.2 Noncompliance. - The contractor shall immediately report in writing each Group C failure occurrence, including details of the failure and characteristics affected. The contractor shall immediately investigate the cause of failure and further report the results of investigation and details of the proposed corrective action on (i) the process and materials, as applicable, and (ii) all units of product which were manufactured under the same conditions and which the Government considers subject to the same failure. Reports shall be forwarded to the responsible technical activity designated in the contract through the Quality Assurance Representative. After corrective action has been taken, additional sample units shall be subjected to Group C inspection (all inspections, or the inspections which the sample failed, at the option of the Government) and Group A and B inspection may be reinstituted; however, final acceptance and shipment will be withheld until the Group C reinspection results have shown that the corrective action was effective.

4.5.4 Reinspection of conforming Group B and Group C sample units. - Unless otherwise specified, sample units which have been subjected to and passed Group B or Group C inspection, or both, may be accepted on contract, provided that they are subjected to and pass Group A inspection after repair of all visible damage.

4.6 Bounce preconditioning. - Test Set, TS-2061( )/ARM-87( ) shall be placed in its normal operating position on a L.A.B. ARV-30-200 vibration table and subjected to a one (1) minute vibration test. The vibration force shall be approximately 1g at 25 Hz.

Source: https://assist.dla.mil.-- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.7 Service conditions.-

4.7.1 Temperature test.- The test set shall be subjected to the temperature cycle shown on Standard MIL-STD-169 except that step 3 will be at +130°F, step 6A will be at -67°F and step 8 will be at 0°F. Cycling will be such that the temperature will be lowered from step 3 (+130°F) to step 6A (-67°F) as rapidly as possible. Temperature at step 2A (+160°F) will be maintained for 4 hours, at step 3 (+130°F) for 8 hours, at step 6 (-67°F) for 24 hours and at step 8 (0°F) for 4 hours. The following tests shall be performed at Steps 1, 3, 8, and 10.

	Reqt.	Par.
Variable Control Limits	3.14.4	4.8.4

4.7.2 Relative humidity.- The test set shall be tested as follows:

4.7.2.1 Test conditions.-

a. The seal shall be broken for all five cycles.

4.7.2.2 Test method.-

a. Dry at 160° ± 5° F. for 4 hours non-operating.

b. Condition at 77° + 5° F. and 40 to 50 percent relative humidity for 12 hours.

c. Take measurements as specified in 4.7.2.3, and readjust or realign as necessary to meet full specification requirements.

d. Subject to continuous cycling for five 48-hour cycles. Temperature, relative humidity, and period of time for each portion of the cycle shall conform to Standard MIL-STD-170 except that measurements will not be taken during cycling.

e. After cycling has been completed, condition the equipment for one (1) hour at 77° ± 5°F. and 40 to 60 percent relative humidity. Then adjust the front panel control for optimum performance, using only those means provided by the equipment. No repair or replacement of parts shall be made. After adjustment, the equipment shall meet full specified performance for those measurements specified in 4.7.2.3.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.7.2.3 Performance.- Upon completion of the cycling and conditioning, perform the following tests:

	Reqt	Par.
Variable Control Limits	3.14.4	4.8.4

4.7.2.4 Failure.- If the equipment fails to meet full specification requirements after conditioning and adjustment, as specified in 4.7.2.2.e, it does not pass the test.

4.7.3 Altitude.- The test set shall be tested as follows: (Note: To check temperature stabilization, place a thermocouple on the largest internal mass centrally located within the equipment.)

a. With the equipment placed in the chamber, operating and stabilized at room temperature, the maximum (CW) amplitude of the 1 KH_z and 3 MH_z controls of the variable control limits test 4.8.4 shall be performed.

b. Reduce the barometric pressure to 20.6 $\pm$ 0.1 inches of mercury (simulated 10,000 feet above sea level), raise the temperature to +86°F and, after temperature and pressure stabilization, repeat the measurements specified in 4.7.3.a. The equipment shall meet specified performance for those measurements.

c. Remove the power from the equipment and further reduce the barometric pressure to 3.4 $\pm$ 0.1 inches of mercury (simulated 50,000 feet above sea level.) Maintain this condition for 1 hour.

d. Return the chamber to ambient pressure. Apply power to the equipment and, after stabilization perform the variable control limits test as specified in 4.8.4. The equipment shall meet specified performance for these measurements.

4.7.4 Spray-tight protection.- The equipment shall be mounted in its operating position and subjected to the tests specified in Table 1 of referenced specification for compliance with paragraph 3.12.4.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.7.5 Vibration. - Internal vibration of the equipment shall be measured as follows to determine conformance to 3.13.1.

a. Secure the test set directly to a vibration table that can be controlled within 10 percent of the specified amplitude. Mounting method shall be such that vibration within the equipment can be observed and measured.

b. Vibrate the equipment successively in three mutually perpendicular directions over a frequency range of 10 to 55 cycles per second. The total excursion of the applied vibration shall be 0.030 inch.

c. In each of the three directions, change the frequency in steps of one cycle per second and maintain each frequency for at least 10 seconds.

d. Measure vibration amplitudes by optical means, or by other means provided that vibration of the part is not affected by the measurement.

e. Perform the variable control limits test (4.8.4) upon completion of the vibration test.

4.7.6 Shock test; bench-handling. - (See 3.13.2) The test set chassis-and-front-panel assembly shall be removed from its combination case, as for servicing, and placed in a suitable position for servicing on a solid, 2-inch fir bench top. The test shall be performed as follows, in a manner simulating shocks liable to occur during servicing:

a. Tilt up the assembly through an angle of 30 degrees, using one edge of the assembly as an axis, and permit the assembly to drop back freely to the horizontal. Repeat, using other practicable edges of the same horizontal face as axes, for a total of four drops.

b. Repeat "a", with the assembly resting on other faces, until it has been dropped for a total of four times on each face on which the assembly might practically be placed during servicing.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.7.7 Shock test, drop. - The equipment in its combination case shall be subjected to 18 impact shocks of 15 g. consisting of 3 shocks in opposite directions along each of 3 mutually perpendicular axes, each shock impulse having a time duration of 11 ± 1 milliseconds. Except for abrasion, paint chipping, and small local deformations, no damage shall occur. Upon completion of the test, without adjustment or repair, the equipment shall be tested for compliance with 3.13.2.

4.7.8 Fungus. - The unit(s) shall be subjected to 28 days of the fungus test specified in Method 508 of MIL-STD-810. For gasket or other non-hermetically sealed equipment, the parts and materials of the chassis shall be sprayed with the spore suspension. The interior of the case shall also be sprayed. The unit(s) shall be subjected to the test in this open condition and as specified for compliance with 3.18.2.

4.8 Electrical tests. -

4.8.1 Voltage indication. - Connect the test set for 230 volt operation and in turn set the Power Selector switch in -27.5 v position and Normal position for compliance with 3.14.1.

4.8.2 Frequency, oscillators. - With the test set connected for 115 volt operation set the Power Selector switch to Normal position. Plug in the osc. cards and adjust Ampl. controls on the front panel fully cw for compliance with 3.14.2. Note: When measuring the frequency of the 500 KH_z oscillator, the 1 KH_z amplifier control must be fully CCW.

4.8.3 Oscillator/counter, 150 cycles. - With the 500 KH_z filter and Load No. 1, in use, feed an audio signal of 150 cps, 2v rms to J5-8 (Sel-call module connector) and set Circuit Selector switches to 3030. Depress the Press to Test button and adjust the frequency for a maximum reading. Adjust the 150 cps Cal. Control for a reading of 80 percent on the Test Meter. Adjust the audio signal to 148 cps and 152 cps for compliance with 3.14.3.

4.8.4 Variable control limits. - Set the Circuit Selector switches to each of the positions indicated and measure the voltages for compliance with 3.14.4.

4.8.5 Distortion, 1 KH_z. - Set Circuit Selector switches to 2200 and set 1 KH_z Amplifier Control to full cw position. Measure the distortion on the voltage at A3-J3 for compliance with 3.14.5.

4.8.6 Freq. response, audio amp/det. - Set Circuit Selector switches to 6500, apply on audio signal, through a 100 to 1 divider HP 65A-16D, or equal, of 15 mv to J2 on A5. The requirements of 3.14.6 shall be met.

Source: https://assist.dla.mil -- Downloaded: 20261O-26T04:17Z
Check the source to verify that this is the current version before use.

4.8.7 R.F. det/amp.- Set Circuit Selector switches to 0500. Apply a frequency of 3.0 MH_z to RF vml connector and adjust for a 63 mv at A13-X. The Test Meter shall read 90 percent. Set the frequency to 65 MH_z keeping the same output level at A13-X. The Test Meter shall read 90 percent. Set frequency to 30.0 MH_z, and adjust the signal level for a meter reading of 90%. Measure the voltage at A13-X for compliance with 3.14.7.

4.8.8 Distortion detection.- Set the Circuit Selector switch to 3119. Apply a 3.0 vrms, 1 KH_z tone with 2% distortion to J8-4. Adjust the Distortion Detector control for 45%. Set the Circuit Selector to 3109 and press the press to test switch and the meter for compliance with 3.14.8.

4.8.9 Bandpass, 500 KH_z Filter.- Set the Circuit selector switches to 6103 and set the voltage level at J12 (transmit audio) to 100 mv, and adjust the 500 KH_z filter control full CW. Vary the frequency for a peak reading on the Test Meter; the frequency shall be 500 KH_z $\pm$ 300 cps if meter pegs decrease the 500 KH_z Filter Control. Set the Circuit Selector switches to 2003 and depress the Press to Test button, and set the 500 KH_z Filter Control for a reading of 47%. Set the Circuit Selector switches to 2103 and depress the Press to Test button, a reading of 80% $\pm$ 5% on the meter shall be obtained. Depress the Press to Test button and read the Test Meter for compliance with 3.14.9.

4.8.10 Power attenuator and detector.- Set the Circuit Selector switches to 0000 and apply 10 watts of power to J9 on the RF chassis for compliance with 3.14.10. Test to be performed at 30.00 and 69.95 MH_z.

4.8.11 Switches 500 KH_z & 30 MH_z.- Connect a square wave generator through a 50 uf capacitor with the positive lead connected to J4-5 (Homer Connector) with an input signal of 100 cps, 10.0 v P-P. Set Circuit Selector switches to 6937. Connect the scope to monitor the voltage at J13 (Homer coax) and adjust the 500 KH_z Amplifier Control for an output of 500 mv P-P. Set Circuit Selector switch to the position indicated in 3.11.11 and record the minimum amplitude limits. Set Circuit Selector switches to 0523. Connect the 30 MH_z oscillator (30 MH_z Conn) output to RF VM-1. Press the Press to Test and adjust the High Frequency Amplifier Control for a meter reading of 100%. Disconnect from RF VM-1 and connect the 30 MH_z to RF SW IN. Connect RF SW OUT to RF-VM-1. Set circuit selector switches to positions indicated in 3.14.11. The requirements of 3.14.11 shall be met.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

4.9 Visual and mechanical inspection. - The equipment shall be examined for the defects in accordance with MIL-STD-252, and the printed circuit assemblies before inclusion into the TS-2061/ARM-87( ) final assembly.

4.10 Inspection for interchangeability. - The dimensions listed below shall be gaged or measured to determine compliance with the physical interchangeability requirements of 3.15. When a listed dimension is not within specified or design limits, it shall be considered a major defect.

a. External and internal dimensions of cases, covers, and insertable assemblies when such dimensions affect mating of parts.

b. Dimensions of cavities, of the console and other units, when such dimensions affect insertion of items.

c. Location of hinges and fasteners on separable parts or assemblies which must mate, such as cases, covers and mountings.

d. Location of connectors, locking pins, fasteners, slides and mountings which receive mating parts of plug-in assemblies and major units, and location of the mating parts on the plug-in assembly or major units.

e. Size and form of special threads.

4.11 Operational Inspection Test. - The test set shall be inspected for assurance that all accessories are in place and subjected to and meet the requirements of 3.14.4.

4.12 Attenuator, Fixed CN-1097/ARM-87( ) Test. - The Attenuator CN-1097/ARM-87( ) shall be subject to and meet the electrical requirements for compliance with 3.21. Compliance with the environmental requirements shall be demonstrated during Group C Tests for the TS-2061( )/ARM-87( ).

4.13 Quality conformance inspection of preparation for delivery. - Preparation for delivery shall be inspected in accordance with Specification MIL-P-116 to determine conformance to the packaging requirements.

4.14 Rough handling test (preparation for delivery). - When rough handling test in accordance with Specification MIL-P-116 is required by the contract the operational inspection test 4.11, shall be conducted to determine freedom from operational malfunction caused by rough handling.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

5. PREPARATION FOR DELIVERY

5.1 Preservation and packaging.- Preservation and packaging shall be level A or C, as specified.

5.1.1 Level A. Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( )

5.1.1.1 Cleaning.- Cleaning shall be accomplished in accordance with process C-1 of MIL-P-116.

5.1.1.2 Drying.- Drying shall be accomplished in accordance with the applicable procedure of MIL-P-116.

5.1.1.3 Unit packaging.- Unit packaging shall be in accordance with the methods prescribed in MIL-P-116 and as specified herein.

5.1.1.3.1 Technical literature.- Each technical literature shall be packaged method 1C-1, MIL-P-116.

5.1.1.3.2 Running spares, accessories and ancillary items.- Running spare parts, accessories and ancillary items as required, shall be packaged as follows:

5.1.1.3.2.1 Fuses and lamps.- Each item shall be packaged individually method III as follows: Cushion each item by wrapping in paperboard conforming to PPP-P-291, type III. Secure the wrap with gummed paper tape conforming to PP-T-45, type III, grade A.

5.1.1.3.2.2 Cable.- Each cable shall be packaged individually method III as follows: Wind each item into a coil of proportionate dimensions. Tie in three places with cotton twine, conforming to T-T-871, type 1, 6 ply; secure the ends with ties.

5.1.1.3.2.3 Stowage within compartments.- When stowage space is provided in the equipment, the applicable items packaged as specified above will be stowed within the compartments provided.

5.1.1.3.2.4 Consolidated package.- Consolidate the items packaged as specified above within a close-fitting fiberboard box conforming to PPP-B-636, type CF, class weather-resistant. Fill all voids with paperboard conforming to PPP-P-291, type III, to prevent movement. Box closure shall be as specified in the appendix of the box specification.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

5.1.1.3.2.5 Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) shall be packaged method III, as follows: Cushion each test set on all surfaces with cells or pads of fiberboard conforming to PPP-F-320. Place the cushioned test set within a close-fitting fiberboard box conforming to PPP-B-636. Seal the box in accordance with the appendix of the box specification. In addition, seal all seams and joints with pressure-sensitive tape conforming to PPP-T-76.

5.1.2 Level C.- Each Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) shall be preserved and packaged in a manner that will afford adequate protection against corrosion, deterioration and damage during shipment from the supply source to the first receiving activity.

5.2 Packing.- Packing shall be level A, B or C as specified.

5.2.1 Level A.- Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) packaged as specified in 5.1, shall be packed in containers selected from Table 1, based upon the most economical container required to provide minimum, adequate protection for the packaged item for this packing level of protection.

5.2.1.1 Container waterproofing.- When the containers being placed directly into the shipping container are not waterproofed, waterproofing shall be effected by use of an individual wrap or a caseliner conforming to MIL-L-10547, grade B, and appendix thereto, prior to packing. Dunnage not inclosed within the waterproof wrap or caseliner shall consist of materials treated to resist water. Wraps or caseliners may be omitted from fiberboard boxes provided all seams, corners and manufacturer's joint are waterproofed by sealing with tape, not less than 2 inches wide, conforming to PPP-T-76. The tape shall be centered over the seams and joints and shall extend over all corners and edges of the box a minimum of two inches onto the adjacent box panels. Tape shall be applied over the lengthwise seams of the outer flaps closing the openings of the box and over the manufacturer's joint prior to tape being applied to the edge seams of the box. The tape applied to the manufacturer's joint shall only fully cover the joint and not be extended over the corners of the box onto the adjacent panels.

5.2.1.2 Container closure.- Closure shall be in accordance with the applicable container specification or appendix thereto.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

5.2.1.3 Strapping and reinforcing.- Metal strapping conforming to QQ-S-781, type 1, class B shall be applied to wood and wood-cleated shipping containers in accordance with the requirements of the applicable box specification or appendix thereto. Fiberboard shipping containers shall be reinforced by pressure-sensitive filament tape banding or non-metallic strapping conforming to PPP-T-97, type IV and PPP-S-760, type II respectively; selection of the material and application shall be in accordance with the appendix of the applicable box specification.

5.2.2 Level B.- Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) packaged as specified in 5.1, shall be packed as specified in 5.2.1 except that Level B containers of Table 1 shall apply and 5.2.1.1 shall not apply.

5.2.3 Level C.- Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) shall be packed in shipping containers in a manner that will afford adequate protection against damage to the package and its contents during shipment from the supply source to the first receiving activity. Shipping containers shall comply with the rules and regulations of the common carrier as applicable to the mode of transportation.

5.3 Marking.- In addition to any special marking required by the contract or order, interior packages and exterior shipping containers shall be marked in accordance with MIL-STD-129.

TABLE V

CONTAINER REQUIREMENTS

Container	Specification	For Level A	For Level B	Max. Gross Wt. Limitation (lbs)
Boxes, Wood, Nailed and Lock-Corner, Style 4	PPP-B-621	Class 2	Class 1	200 (Note A)
Boxes, Wood, Nailed and Lock-Corner, Style 7	PPP-B-621	Class 2	Class 1	1000 (Note B)
Box, Wirebound, Style 2 or 3	PPP-B-585	Class 3	Class 1	200

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

TABLE V

CONTAINER REQUIREMENTS

Container	Specification	For Level A	For Level B	Max. Gross Wt. Limitation (lbs)
Box, Wood Cleated Fiberboard	PPP-B-591	Class II	Class 1	200 (Note A)
Box, Cleated Plywood	PPP-B-601	Overseas Type	Domestic Type	200 (Note A)
Boxes, Fiberboard, Corrugated, Triple Wall, Style E	PPP-B-640	Class 2	Class 1	200 (Note A)
Box, Fiberboard, Type CF	PPP-B-636	Class Weather-resistant	Class Domestic	(Note C)
Box, Fiberboard, Corrugated Double Wall, Weather Resistant	MIL-B-43291	Type CF	-	Table II
Crates, Wood, Open and Covered	PPP-C-650	Style B, Type V, Covered	Style B, Type V Covered	Table I (Note B)
Crates, Wood	MIL-C-104	Type, Class, Style, as applicable	Type, Class, Style as applicable	30,000 (Note B)

NOTE A. When the weight of a single item together with the shipping container exceeds 200 pounds, the maximum gross wight limitation of the container specification shall apply. In addition, skids, or pallet bases shall be applied in accordance with the requirements of the container specification, or if not specified in the specification, in a manner which will adequately support the item and facilitate the use of material handling equipment.

NOTE B. Style 7 containers conforming to PPP-B-621 shall be considered for use only when the weight of a single item exceeds 400 pounds. Covered crates conforming to PPP-C-650 shall be used only when the weight of a single item exceeds 1000 pounds. Sheathed crates conforming to MIL-C-104 shall be used only when the weight of a single item exceeds 4000 pounds.

NOTE C. The maximum gross weight limitations for Special Requirements as cited in PPP-B-636 shall apply.

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

6. NOTES

6.1 Intended use.- Test Set, Electronic Circuit Plug-in Unit AN/ARM-87( ) is used as an aid in maintenance, including adjustment and alignment, and performance of the modules except the Harmonic Filter module for the Receiver-Transmitter RT-348( )/ARC-54.

6.2 Ordering data.- Procurement documents should specify the following:

a. Title, number, and date of this specification and any amendment thereto.

b. Level of packaging and level of packing required for shipment. (Level A, level B or level C).

c. The specific paragraphs of Section 5 which are applicable to the particular procurement.

d. Preproduction inspection.-

(1) Two sample units of each item cited in Selection 1 are generally required so that lengthy environmental tests can be completed on one sample unit while complete performance measurements can be made on the second sample unit. (See 3.3)

(2) Preproduction pack(s) as follows:

(a) Makeup of pack(s).

(b) Number of each kind of pack to be submitted.

(c) Inspection to be performed thereon.

e. Marking and shipping of samples.

f. Place of final inspection.

g. Technical literature required. (See 3.17)

h. Quantity of tools and running spare parts required.

i. Submission of the statement of treatment referenced in 3.18 should be sixty (60) days after award of contract. This statement should be submitted to the contracting officer.

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

6.3 Nomenclature. - The parentheses in the nomenclature will be deleted or replaced by a letter identifying the particular design; for example: ARM-87(W). The contractor should apply for nomenclature in accordance with the applicable clause in the contract.

6.4 Definition of Level B. - Level B packaging requirements detailed herein are designed to furnish protection against corrosion, deterioration, and physical damage during domestic shipments; covered storage for a period of three years or less; and distribution within the continental limits of the United States.

6.5 Location of operational inspection. - It is desirable that the operational inspection 4.11 be performed at a location that will minimize handling (which might cause damage to the units) after this inspection. It is recommended that the entire lot (including the sample units) be inspected immediately prior to packaging.

6.6 Verification inspection. - Verification by the Government will be limited to the amount deemed necessary to determine compliance with the contract and will be limited in severity to the definitive Quality Assurance provisions established in this specification and the contract. The amount of verification inspection by the Government will be adjusted to make maximum utilization of the contractor's quality control system and the quality history of the product.

Custodian:
Army EL

Preparing Activity
Army EL
Project No. 6625-A268

Source: https://assist.dla.mil -- Downloaded: 202610-26T04:17Z
Check the source to verify that this is the current version before use.

FOLD

DEPARTMENT OF THE ARMY
HEADQUARTERS
U.S.ARMY ELECTRONICS COMMAND
FORT MONMOUTH, NEW JERSEY 07703

OFFICIAL BUSINESS

POSTAGE AND FEES PAID
DEPARTMENT OF THE ARMY

Commanding General
U. S. Army Electronics Command
ATTN: AMSEL-PP-
Fort Monmouth, New Jersey 07703

FOLD

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 119-R004

INSTRUCTIONS

This sheet is to be filled out by personnel either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity.

SPECIFICATION

ORGANIZATION	CITY AND STATE

CONTRACT NO.	QUANTITY OF ITEMS PROCURED	DOLLAR AMOUNT
		$

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

☐ YES ☐ NO IF "YES", IN WHAT WAY?

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity)*

SUBMITTED BY *(Printed or typed name and activity)*	DATE

DD FORM 1 OCT 64 1426

ESC-FM 2011-66

Source: https://assist.dla.mil -- Downloaded: 2026-10-26T04:17Z
Check the source to verify that this is the current version before use.