Superseding
MIL-E-22911C (OS)
17 May 1966

MILITARY SPECIFICATION

ELECTRONIC PANEL

(FOR TORPEDO MARK 37 MOD 2)

This specification has been approved by the Naval Ordnance Systems Command, Department of the Navy.

1. SCOPE

1.1 Scope. This specification establishes the requirements for the procurement of an Electronic Panel, LD 620172, NAVORD Drawing 2618165.

2. APPLICABLE DOCUMENTS

2.1 The following documents of the issue in effect on date of invitations for bids or request for proposal form a part of this specification to the extent specified herein.

SPECIFICATIONS

Military

MIL-P-116	Preservation, Methods of
MIL-E-82590	Environmental Requirements and Tests (For Torpedo Mk 37 Components and Assemblies)

STANDARDS

Military

MIL-STD-129	Marking for Shipment and Storage
MIL-STD-147	Palletized and Containerized Unit Loads, 40" x 48" Pallets, Skids, Runners, or Pallet-Type Base

FSC 1355

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T14:50Z
Check the source to verify that this is the current version before use.

DRAWINGS

Naval Ordnance Systems Command

LD 620172	Electronic Panel (Assembly)
LD 620202	Shipping (Packing) Condition for one Electronics Panel (LD 620172)
NAVORD Drawing 1874109	Electronic Panel Schematic
NAVORD Drawing 2103763	Driver
NAVORD Drawing 2618165	Electronic Panel Assembly

(Copies of specifications, standards, and drawings requested by the contractors in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

2.2 Other publications. The following documents form a part of this specification to the extent specified herein. Unless otherwise indicated, the issue in effect on date of invitation for bids or request for proposal shall apply.

National Bureau of Standards Publications

Handbook H28	Screw-Thread Standards for Federal Services

(Application for copies should be addressed to the Superintendant of Documents, Government Printing Office, Washington, D. C. 20402.)

3. REQUIREMENTS

3.1 Description. The electronic panel is mounted in the extender section of Torpedo Mk 37 Mod 2 and contains those components necessary to provide auxiliary control functions for the torpedo.

3.2 General requirements

3.2.1 Data required. No data is required by this specification (other than reports accompanying samples submitted for preproduction

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the current version before use.

and periodic production testing), or by applicable documents referenced in Section 2, unless specified in the contract or order (see 6.2).

3.2.2 Preproduction sample. Unless otherwise specified in the contract or order, preproduction samples of the electronic panel shall be manufactured using the methods and procedures proposed for the production lot. These units shall be tested as specified in Section 4 herein and are for the purpose of determining, prior to starting production, that the contractor's production methods are capable of producing electronic panels that comply with the technical requirements of the contract. See 4.3.1.

3.2.3 Materials. Unless otherwise specified in the contract or order, all materials and purchased parts entering into the final assembly of the electronic panel shall conform strictly to the detailed requirements indicated on the drawings and specifications listed in LD 620172.

3.2.4 Finishes, coatings, construction, and dimensions. Finishes, coatings, construction, and dimensions for the electronic panel shall be strictly in accordnace with the applicable drawings, specifications, and publications listed in LD 620172.

3.2.5 Moisture, fungus, and corrosion. The electronic panel shall be rendered moisture, fungus, and corrosion resistant in accordance with detail requirements specified in the drawings and specifications listed in LD 620172.

3.2.6 Marking. Marking of assemblies, subassemblies, and parts shall be in accordance with the applicable drawings listed in LD 620172.

3.2.7 Threads. Unless otherwise specified, all threads shall be in accordance with National Bureau of Standards Handbook H28. The class or fit for threads shall be as specified on the applicable drawings.

3.2.8 Conflicting requirements. Conflicting requirements arising between this specification or any specifications, publications, or drawings listed herein shall be referred in writing to the procuring agency or appointed agent for interpretation, clarification, and resolution (or correction).

3.3 Performance requirements and product characteristics. The electronic panel shall meet the following performance requirements and product characteristics. Unless otherwise specified, all terminals referred to hereafter are on S901, and are to be found on NAVORD Drawing 1874109. All applied voltages are direct current (dc). The positive (return) connection for all negative voltages specified herein is made through pin 1. All dc voltages have a tolerance of plus 10 percent minus 0 percent.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T14:50Z
Check the source to verify that this is the current version before use.

3.3.1 With S902 disconnected from the steering controller, ohmmeter readings shall be as specified in Table I (4.5.4.2).

3.3.2 With K907 energized, energizing K901 shall cause a closed circuit to appear between pins 10 and 18, and with negative 21 volts applied to pin 17, shall cause the steering controller to step in a counterclockwise direction, when viewed from the synchro end, in two degree increments each time K901 is energized.

3.3.3 With K907 energized, energizing K902 shall cause a closed circuit to appear between pins 12 and 18; 20,000 ohms plus or minus 10 percent to appear between pins 10 and 18; and with negative 21 volts applied to pin 17 (as in 3.3.2), shall cause the steering controller to step in a clockwise direction, when viewed from the synchro end, in two degree increments each time K902 is energized.

3.3.4 Energizing K905 shall prevent the steering controller from being stepped as in 3.3.2 and 3.3.3.

3.3.5 With K905 energized as in 3.3.4, connecting a jumper between pins 1 and 2 shall restore the ability of the steering controller to step as in 3.3.2 and 3.3.3.

3.3.6 With circuits as in 3.3.5, and with negative 21 volts connected to pin 18, deenergizing K907 shall prevent the steering controller from being stepped as in 3.3.2 and 3.3.3.

3.3.7 With negative 21 volts applied to pin 18, K903 shall energize on negative 0.5 to 1.5 volts input to pin 27. Energizing K903 shall produce a reading of 75,000 ohms plus or minus 10 percent between pins 10 and 18.

3.3.8 Energizing K905 shall cause the circuit between pins 6 and 15 to open, and the circuit between pins 15 and 16 to close.

3.3.9 With negative 21 volts applied to pin 19, energizing K903 shall cause K906 and K905 to energize and produce closed circuits between pins 13 and 18 and between pins 15 and 16, and open circuits between pins 17 and 1 and between pins 6 and 15.

3.3.10 With K906 and K905 energized as in 3.3.9, deenergizing K903 shall not affect the circuits of 3.3.9.

3.3.11 Applying negative 21 volts to pin 11 shall cause a 58 to 65 Hertz (Hz) signal of 100 to 120 volts peak-to-peak amplitude across a 500 ohm resistive load between pins 21 and 22.

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the current version before use.

3.3.12 With circuits as in 3.3.11, energizing K904 shall cause the 60 Hz signal to cease 5 plus or minus 0.5 seconds after application of power to the relay.

3.3.13 With circuits as in 3.3.12, energizing K905 shall cause the 60 Hz signal to return.

3.3.14 Energizing first K907 and then K904 shall cause the 60 Hz signal to appear for 5 plus or minus 0.5 seconds after K904 is energized.

3.3.15 With circuits as in 3.3.12, deenergizing K904 shall cause the 60 Hz signal to return 10 plus or minus 1.0 seconds after removal of power to the relay.

3.3.16 With negative 21 volts connected to pins 17, 18, and 19, and after waiting 5 seconds minimum for K904 to operate, applying negative 0.5 to 1.5 volts to pin 27 shall cause K905 to energize 10 plus or minus 1.0 seconds after application of voltage to pin 27.

3.3.17 With a 400 Hz power supply, 200 volts peak-to-peak (open circuit), connected in series with a 2700 ohm resistor between pins 1 and 26, the voltage measured between pins 1 and 26 shall be between 80 and 112 volts peak-to-peak.

3.3.18 Insulation resistance. The insulation resistance between all terminals and the electronic panel chassis shall be 50 megohms minimum, measured at an applied potential of 500 volts.

3.4 Environmental requirements. The electronic panel shall meet the other applicable requirements of this specification during or after the tests defined or specified in 4.4.

3.4.1 Vibration. The electronic panel shall meet the following vibration requirements:

3.4.1.1 Vibration, nonoperating. The electronic panel shall show no damage and shall meet all the performance requirements and product characteristics of this specification after being tested as in 4.4.1.2.

3.4.1.2 Vibration, operating. The electronic panel shall show no damage and shall meet all the performance requirements and product characteristics of this specification during and after the test specified in 4.4.1.3.

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the currentversion before use.

3.4.2 Temperature and humidity

3.4.2.1 High temperature and humidity, nonoperating. The electronic panel shall show no damage and shall meet all the performance requirements and product characteristics of this specification after being tested as in 4.4.2.1.

3.4.2.2 High temperature, operating. The electronic panel shall be capable of meeting all the performance requirements of this specification while undergoing the test specified in 4.4.2.2.

3.4.2.3 Low temperature, nonoperating. The electronic panel shall meet all the performance requirements and product characteristics of this specification after being tested as in 4.4.2.3.

3.4.2.4 Low temperature, operating. The electronic panel shall be capable of meeting all the performance requirements of this specification while undergoing the test specified in 4.4.2.4.

3.5 Cleanup. Prior to and after final assembly, all parts, components, and the assembly shall be thoroughly cleaned of loose, spattered, or excess solder, metal chips, and other foreign matter. Burrs and sharp edges as well as rosin flash shall be removed.

3.6 Workmanship. The electronic panel shall be consturcted and finished in a manner to ensure compliance with all requirements of this specification. Particular attention shall be paid to neatness and thoroughness of soldering, wiring, impregnation of coils, marking of parts and assemblies, plating, painting, riveting, machine screw assemblage, welding, brazing, and freedom of parts from burrs and sharp edges.

The standards of workmanship exhibited in any approved preproduction sample, subject to any qualification stated in the Government's notice of approval, shall be determinative of the requirements of the contract relative to workmanship insofar as not specifically covered by applicable specifications.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection. Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified in the contract or order, the supplier may use his own or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the current version before use.

by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.2 Classification of inspections. Inspection of the electronic panel shall be classified as follows:

(a) Preproduction inspection (paragraph 4.4)

(b) Quality conformance inspection (paragraph 4.5)

(c) Periodic production inspection (paragraph 4.4)

4.3 Sampling

4.3.1 Preproduction. A preproduction sample of five electronic panels, manufactured in accordnace with 3.2.2, shall be subjected to the preproduction tests detailed in 4.4 at an activity designated by the procuring activity. Acceptance of the preproduction sample shall be based on no defects in the sample. Further production of the electronic panel by the supplier, prior to the approval of the preproduction sample, shall be at the supplier's risk.

4.3.2 Lot size. Unless otherwise specified in the contract or order, each shipment of units of product shall be a separate "inspection lot" and may differ from the quantity specified in the total order or contract. In any event, all units of a single "inspection lot" shall be made to the same design, with the same materials and manufacturing techniques, and shall be part of one continuous production run.

4.3.3 Periodic production samples. From each succeeding lot or grand lot of 300 or less that have passed the quality conformance inspection of 4.5, a random sample of five electronic panels will be selected for submission to an activity designated by the procuring activity to determine compliance of the samples with the requirements of the contract, specification, and drawings. The electronic panels shall be considered satisfactory if they meet all specification and pertinent drawings requirements and withstand the test specified in 4.4 and 4.5. Failure of the periodic production sample to comply with these requirements will result in the rejection of the lot, as determined by the procuring activity.

4.4 Preproduction and periodic production inspection. The preproduction and periodic production samples, after satisfactorily passing the quality conformance inspections detailed in 4.5, shall be subjected to the following tests and examinations. Certified inspection data covering the results of preproduction and periodic production inspections shall be forwarded to the procuring activity.

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the currentversion before use.

4.4.1 Vibration

4.4.1.1 Mounting. The electronic panel, less pack or packaging, shall be mounted securely to a vibration device by means of its mounting holes and tested as specified in 4.4.1.2 and 4.4.1.3.

4.4.1.2 Vibration, nonoperating. The electronic panel shall be subjected to the "Vibration, nonoperating" test of MIL-E-82590 and thereafter shall meet the requirements of 3.4.1.1.

4.4.1.3 Vibration, operating. The electronic panel shall be subjected to the "Vibration, operating" test of MIL-E-82590 and during and thereafter shall meet the requirements of 3.4.1.2.

4.4.2 Temperature and humidity

4.4.2.1 High temperature and humidity, nonoperating. The electronic panel shall be subjected to the "High temperature and humidity, nonoperating" test of MIL-E-82590 and thereafter shall meet the requirements of 3.4.2.1.

4.4.2.2 High temperature, operating. The electronic panel shall be subjected to the "High temperature, operating" test of MIL-E-82590 and, while at the test temperature, shall meet the requirements of 3.4.2.2.

4.4.2.3 Low temperature, nonoperating. The electronic panel shall be subjected to the "Low temperature, nonoperating" test of MIL-E-82590 and thereafter shall meet the requirements of 3.4.2.3.

4.4.2.4 Low temperature, operating. The electronic panel shall be subjected to the "Low temperature, operating" test of MIL-E-82590 and, while at the test temperature, shall meet the requirements of 3.4.2.4.

4.5 Quality conformance inspection. Each electronic panel delivered under contract shall be subjected to the following tests and examinations. Failure of the panel to meet any requirement specified herein shall be considered cause for rejection.

4.5.1 Test and inspection equipment and facilities. The manufacturer shall furnish and maintain all necessary test equipment and facilities and shall provide the personnel for performing all quality conformance tests. The test equipment shall be adequate in quantity and, when definite requirements are not specified, shall be of sufficient accuracy and quality to permit performance of the required quality conformance tests.

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the currentversion before use.

4.5.2 Test equipment. The following test equipment is required to perform the quality conformance test set forth in this specification:

4.5.2.1 DC power source, 0-2.0 volts (adjustable) at 4 milliamperes.

4.5.2.2 DC power source, 7 volts at 10 milliamperes.

4.5.2.3 DC power source, 20-28 volts (adjustable) at 2 amperes.

4.5.2.4 Multimeter, AN/USM-34 or ME-25A/U, or equal.

4.5.2.5 Megohmmeter, capable of measuring insulation resistance at an applied voltage of 500 vdc over the range of 0.1 to 100 megohms with an accuracy of plus or minus 10 percent.

4.5.2.6 Wheatstone bridge, capable of measuring resistance values over a range of 1 to 100,000 ohms with an accuracy of plus or minus 1 percent.

4.5.2.7 Frequency meter to measure 60 Hz output, Hewlett-Packard Model 500B or equivalent.

4.5.2.8 AC power source capable of supplying 200 volts peak-to-peak (open circuit) at 400 cycles.

4.5.2.9 Oscilloscope, Tektronix Model 532 or equivalent.

4.5.3 Test conditions. Unless otherwise specified, the electronic panel shall be subjected to quality conformance tests under the following conditions:

4.5.3.1 Temperature: 65 degrees F to 95 degrees F (18.33 degrees centigrade (C) to 35 degrees C).

4.5.3.2 Altitude: Normal ground.

4.5.3.3 Vibration: None.

4.5.3.4 Humidity: Room ambient to 95 percent relative maximum.

4.5.4 Test procedure

4.5.4.1 Except where noted, all terminals given in this section are on connector S901. All applied voltages are dc. The positive (return) connection for all negative voltages specified herein is made through pin 1.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T14:50Z
Check the source to verify that this is the current version before use.

4.5.4.2 Disconnect S902 from the steering controller. Take the ohmmeter readings specified in Table I.

4.5.4.2.1 Reconnect S902 to the steering controller.

Table I

From	To	Reading
3-S901	6-S902	Closed
4-S901	7-S902	Closed
5-S901	8-S902	Closed
8-S901	5-S902	Closed
8-S901	Term 9-RB901	Closed
9-S901	4-S902	Closed
9-S901	Term 10-RB901	Closed
26-S901	-Pin 9-Z904	Closed

4.5.4.3 With all relays deenergized, take readings as specified in Table II.

Table II

From	To	Reading
3	4	100 ohms (approximate)*
3	5	100 ohms (approximate)*
8	9	100 ohms (approximate)*
20	1	Closed

*Value will vary with different type of synchro.

4.5.4.4 Energize K907 by connecting negative 21 volts to pin 7. Energize K901 by connecting 7 volts plus or minus 5 percent between pins 23 and 24. Connect negative 21 volts to pin 17. There shall exist a closed circuit between pins 10 and 18 and the steering controller shall step as specified in 3.3.2.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T14:50Z
Check the source to verify that this is the current version before use.

4.5.4.5 Energize K902 by removing the 7-volt lead on pin 23 and connecting it to pin 25. There shall exist a closed circuit between pins 12 and 18, 20,000 ohms between pins 10 and 18, and the steering controller shall step as specified in 3.3.3.

4.5.4.6 Energize K905 by connecting a negative 21-volt lead to pin 14. It shall be impossible to step the steering controller, as specified in 3.3.4.

4.5.4.7 Connect pin 2 to pin 1. The steering controller shall step as specified in 3.3.5.

4.5.4.8 Connect negative 21 volts to pin 18 and remove negative 21 volts from pin 7. It shall be impossible to step the steering controller, as specified in 3.3.6. Remove 21 volts from pins 14 and 17 and 7 volts from pins 24 and 25.

4.5.4.9 Connect less than 0.2 vdc to pin 27. Pins 19 and 20 shall be open. Gradually increase the dc power supply. The resistance between pins 19 and 20 shall change to 240 ohms plus or minus 10 percent at a voltage of negative 0.5 to 1.5 vdc and there shall exist 75,000 ohms plus or minus 10 percent between pins 10 and 18. Remove voltage from pin 27.

4.5.4.10 With relay K905 energized by the application of negative 21 volts to pin 14, an open circuit shall exist between pins 6 and 15 and a closed circuit between pins 15 and 16, as specified in 3.3.8. Remove the 21 volts from pin 14.

4.5.4.11 Apply negative 21 volts to pin 19. Then apply 0.5 to 1.5 volts to pin 27 to energize K903. Energizing K903 shall cause K906 and K905 to energize and produce closed circuits between pins 13 and 18 and pins 15 and 16, and open circuits between pins 17 and 1 and between pins 6 and 15, as specified in 3.3.9.

4.5.4.12 Remove voltage from pin 27. K903 shall deenergize and the circuits specified in 4.5.4.11 shall not change, as specified in 3.3.10.

4.5.4.13 Deenergize K906 and K905 by removing voltage from pin 19. An open circuit shall appear between pins 15 and 16 and a closed circuit between pins 6 and 15.

4.5.4.14 Connect a 500 ohm, 5 watt resistor between terminals 21 and 22. Connect negative 21 volts to pin 11. A 60 Hz voltage shall appear between pins 21 and 22, as specified in 3.3.11.

4.5.4.15 Energize K904 by connecting negative 21 volts to pin 17.

Source: https://assist.dla.mil -- Downloaded: 20260-19T14:50Z
Check the source to verify that this is the current version before use.

The 60 Hz signal between pins 21 and 22 shall cease in 5 plus or minus 0.5 seconds, as specified in 3.3.12.

4.5.4.16 Energize K905 by connecting negative 21 volts to pin 14. The 60 Hz signal shall return, as specified in 3.3.13.

4.5.4.17 Disconnect negative 21 volts from pins 11, 14, and 17. Energize K907 by connecting negative 21 volts to pin 7. Energize K904 by connecting negative 21 volts to pin 17. The 60 Hz signal shall appear for 5 plus or minus 0.5 seconds, as specified in 3.3.14.

4.5.4.18 Disconnect negative 21 volts from pin 7. Connect negative 21 volts to pin 11. Deenergize K904 by removing 21 volts from pin 17. The 60 Hz signal shall return in 10 plus or minus 1.0 seconds as specified in 3.3.15.

4.5.4.19 Remove negative 21 volts from all pins. Reconnect negative 21 volts to pins 17, 18, and 19. After waiting 5 seconds for K904 to energize, connect negative 0.5 to 1.5 volts to pin 27. K905 shall energize, as indicated by an open circuit appearing between pins 6 and 15 in 10 plus or minus 1.0 seconds, as specified in 3.3.16.

4.5.4.20 Disconnect all leads to the electronic panel. Connect the 200 volts peak-to-peak, 400 Hertz power supply source (4.5.2.8), in series with a 2700 ohm resistor, to pins 1 and 26. The voltage measured between pins 1 and 26 shall be between 80 and 112 volts peak-to-peak (clipped), to meet the requirements of 3.3.17. (Reference NAVORD Drawing 2103763.)

4.5.4.21 Insulation resistance. Disconnect all leads to the electronic panel. Connect all pins of S901 together and connect a megohmmeter between any pin and the electronic panel chassis. The insulation resistance at 500 vdc shall be at least 50 megohms, as specified in 3.3.18.

4.5.4.22 Visual and dimensional examination. Each item shall be examined to determine conformance with the requirements for workmanship and dimensions.

4.5.4.23 Preservation, packaging, packing, and marking. Preservation, packaging, packing, and marking shall be examined to ensure that it complies fully with the requirements of Section 5.

5. PREPARATION FOR DELIVERY

5.1 Preservation and packaging. The levels of preservation and

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T14:50Z
Check the source to verify that this is the current version before use.

packaging shall be as specified (see 6.2).

5.1.1 Level A

5.1.1.1 Unit packaging. The electronic panel shall be packaged in accordance with Method IID of MIL-P-116 and LD 620202.

5.1.2 Level B. Not applicable.

5.1.3 Level C

5.1.3.1 Unit packaging. The electronic panel shall be packaged in accordnace with Method III of MIL-P-116.

5.2 Packing. Packing shall be Level A or Level C, as specified (see 6.2).

5.2.1 Number of packages per pack. The number of unit packages per pack, for Level C, shall be as specified in the contract or order.

5.2.2 Level A

5.2.2.1 Unit pack. The electronic panel shall be packed in accordance with LD 620202 and may be shipped individually in small lots.

5.2.2.2 Palletizing. When specified, Level A packs shall be palletized in accordance with MIL-STD-147, Load Type III (see 6.2).

5.2.3 Level B. Not applicable.

5.2.4 Level C. The electronic panel shall be packed to afford protection against damage during direct shipment from the supply source to the first receiving activity for immediate use. Containers shall comply with common carrier regulations applicable to the mode of transportation.

5.3 Marking

5.3.1 Normal markings, Level A. Unit packs shall be marked in accordance with LD 620202.

5.3.2 Normal markings, Level C. Unit packages and shipping containers shall be marked in accordance with the requirements of MIL-STD-129.

5.3.3 Serial numbers. Unit packages and shipping containers shall be marked with the serial numbers of the units contained within.

Source: https://assist.dla.mil -- Downloaded: 2026-10-19T14:50Z
Check the source to verify that this is the current version before use.

6. NOTES

6.1 Intended use. The electronic panel is intended for use in Torpedo Mk 37 Mod 2.

6.2 Ordering data. Procurement documents should specify the following:

(a) Title, number, and date of this specification.

(b) Any exceptions to this specification.

(c) Required level of preservation and packaging (see 5.1).

(d) Required level of packing including palletizing (see 5.2).

(e) Assigned activity for preproduction and periodic production inspections.

(f) Data required other than that specified in 3.2.1.

(g) That additional samples required because of failure of any unit(s) to pass the prescribed periodic production inspections shall be provided and inspected at the expense of the supplier.

NOTE: Level C packaging and packing shall not be selected unless it is definitely known that the electronic panel will be put to immediate use.

6.3 Preparation for delivery criteria. Criteria for use of the proper level of preservation, packaging, and packing shall be as follows:

6.3.1 Level A. This level shall be used for those items which are to be shipped to indeterminate destinations or stored under indeterminate conditions for redistribution anywhere.

6.3.2 Level C. This level shall be used only when it is definitely known that the packaged items are to be shipped to domestic installations for immediate use at the first receiving activity.

Preparing Activity
Navy - OS
Project No. 1355-N180

☆ U. S. GOVERNMENT PRINTING OFFICE: 1971-433-694/3635

Source: https://assist.dla.mil -- Downloaded: 202610-19T14:50Z
Check the source to verify that this is the current version before use.