MIL-P-14818(MU)
22 July 1968
SUPERSEDING
FA(FC)PD-75
9 May 1961

MILITARY SPECIFICATION

POWER SUPPLY: 10512499

1. SCOPE

1.1 This specification covers one type of power supply used in the Radar Chronograph, M36. The power supply is used to convert the primary input power to the voltages necessary to operate the entire system.

2. APPLICABLE DOCUMENTS

2.1 The following documents, of the issue in effect on date of invitation for bids or request for proposals, form a part of this specification to the extent specified herein.

SPECIFICATIONS

Military

MIL-F-13926	Fire Control Materiel: General Specification Governing the Manufacture and Inspection of
MIL-P-14232	Parts, Equipment and Tools for Army Materiel, Packaging and Packing of
MIL-I-45607	Inspection Equipment, Supply and Maintenance of
MIL-C-46357	Computer, Gun Direction, M18, Manufacturing Processes and Inspection of

STANDARDS

Military

MIL-STD-105	Sampling Procedures and Tables for Inspection by Attributes
MIL-STD-109	Quality Assurance Terms and Definitions
MIL-STD-810	Environmental Test Methods

DRAWINGS

US Army, Frankford Arsenal

F10512499	Power Supply: 10512499

PACKAGING DATA SHEET

10512499	Packaging of Power Supply: 10512499

FSC 1290

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

(Copies of specifications, standards, drawings and packaging data sheets required by suppliers in connection with specific procurement functions should be obtained from the procuring activity or as directed by the contracting officer.)

3. REQUIREMENTS

3.1 Fabrication.- The power supply shall be manufactured in accordance with Drawing D10512499 and drawings pertaining thereto.

3.2 General specification.- The power supply shall meet the following requirements of MIL-F-13926 and MIL-C-46357.

3.2.1 MIL-F-13926

a. Order of precedence
b. Dimensions and tolerances
c. Inorganic protective surface finishes
d. Workmanship
e. Soldering electrical connections

3.2.2 MIL-C-46357

a. Wiring
b. Threaded fasteners
c. Marking
d. Finishes
e. Etched circuit assemblies

3.3 Environmental.

3.3.1 Shock.- The power supply shall be capable of continuous operation while being subjected to three (3) shocks of 200 gravity units (g's) of three (3) millisecond duration in each of the following directions:

a. Bottom down
b. Front down
c. Right side down
d. Back down
e. Left side down
f. Top down

Subsequent to the above shock, the power supply shall not have been damaged or adversely affected, and shall meet the requirements of 3.5.

3.3.2 Vibration.- The power supply shall be capable of continuous operation while being vibrated in a simple harmonic motion having an amplitude of 0.03 (0.06 inch maximum total excrusion) with the frequency being varied uniformly between the limits of ten (10) and fifty-five (55) hertz. The entire frequency range, from 10 to 55 hertz and return to 10 hertz, shall be uniformly traversed in 1 minute ± 15 seconds. This motion shall be

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

applied for a period of thirty (30) minutes ± one (1) minute in each of three (3) mutually perpendicular directions (x, y, z axis) for a total of 1.5 hours. Subsequent to the above vibration, the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5.

3.3.3 Humidity.- The power supply shall be capable of continuous operation during four (4) hours ± ten (10) minutes of continuous exposure to a relative humidity of ninety (90) to ninety-five (95) percent at a temperature of plus 100° ± 5°F. During and subsequent to the above humidity, the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5.

3.3.4 Sand and dust.- The power supply shall be capable of withstanding three (3) hours of continuous exposure to blowing sand of particle size 0.01 to 1.00mm and blowing dust of particle size 0.0001 to 0.01mm with a density between 0.1 and 0.5 gram per cubic foot of dust at a temperature of plus 75° ± 5°F, a relative humidity between fifteen (15) to thirty (30) percent, and a wind velocity of fifteen (15) knots. Subsequent to the above sand and dust exposure, the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5.

3.3.5 Altitude.

3.3.5.1 Operating.- The power supply shall be capable of continuous operation during four (4) hours of continuous exposure to an altitude of 10,000 feet at a temperature of plus 75°F. During and subsequent to the above exposure, the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5.

3.3.5.2 Non-operating.- The power supply shall be capable of withstanding four (4) hours of continuous exposure to an altitude of 50,000 feet at a temperature of minus 65°F. Subsequent to the above exposure, the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5.

3.3.6 Fungus.- The power supply shall be capable of withstanding twenty-eight (28) days exposure to a composite spore suspension consisting of the following cultures:

a. Chaetomium globosum
b. Aspergillus flavus
c. Aspergillus versicalor
d. Penicillum luteum
e. Rhizopus nigricans

The composite spore suspension shall be incubated at an ambient temperature of 81°F ± 4°F with an RH of 87 ± 2%. Subsequent to the above exposure, the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5.

3.3.7 Storage temperatures.- The power supply shall be capable of withstanding temperature stabilization at plus 160°F and minus 80°F for a period of eight (8) hours at each temperature extreme. Subsequent to each

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

of the above temperature extremes (+160°F and -80°F) after temperature stabilization at 75°F ± 15°, the power supply shall not have been damaged or adversely affected, and shall meet the requirements of 3.5.

3.3.8 Operating temperatures.- The power supply shall be capable of continuous operation for eight (8) hours at plus 140°F. The power supply shall also be capable of continuous operation for eight (8) hours at minus 50°F. During and subsequent to the above temperature extremes (+140°F and -50°F), the power supply shall not have been damaged or adversely affected and shall meet the requirements of 3.5 at least once at the beginning, middle, and ending of each 8 hour temperature extreme.

3.4 Electrical.

3.4.1 Continuity.- The power supply shall demonstrate continuity in accordance with the electrical schematic, Drawing F10525695.

3.5 Performance.- Unless otherwise specified, the power supply shall be capable of meeting the performance requirements of this specification at standard ambient temperatures between 60° and 90°F and at a barometric pressure of 28 and 32 inches of mercury with a RH up to 90%. All voltages shall have a ± 2% tolerance unless otherwise specified.

3.5.1 Primary power.- The power supply shall be capable of meeting all of the following requirements when operating from a primary power source exhibiting the following characteristics:

a.	Voltage	-	115 to 125VRMS (120V nominal)
b.	Frequency	-	380 to 420 Hz (400 hz nominal)
c.	Phase	-	Single Phase
d.	Distortion	-	3 percent maximum total harmonic

3.5.2 Power drain.- The power supply shall draw no more than 2 amperes from the primary power source when operating under full rated load.

3.5.3 Output voltages.- With the loads as specified in Table I connected to the power supply, the voltages shall be capable of being adjusted to the values listed in table I.

TABLE I

Output voltage	External Load Ohms, TOL ± 5% RL	Rn	Rh	Watts	Load Connections	Peak-to-peak Ripple Voltage
-500 VDC	7700	8850	10K	35	P1-3 to Gnd	125 MV
+22 VDC	50	58.7	67.4	10	P1-9 to Gnd	15 MV
+176 VDC	4250	6300	8350	10	P1-8 to Gnd	30 MV
+132 ± 12 VDC	5420	5900	6380	5	P1-10 to Gnd	25 MV
6.3 VAC	8	8.4	8.75	5	P1-A to P1-B	------

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

3.5.4 Regulation.- The output voltages specified in Table I shall vary no more than plus or minus 1 percent when the primary voltage and frequency are varied over their range as specified in Table II. The above results shall be obtained using RL and RH as loads.

TABLE II

f1 V1	f1 = 380
f1 V2	f2 = 420
f2 V1	V1 = 115VAC
f2 V2	V2 = 125 VAC

3.5.5 Ripple voltage.- The ripple voltage shall be no greater than the values listed in Table I when the power supply is operated as specified in 3.5.4.

3.5.6 Meter line.- The output at P1-7 shall be 70 ± 3MV when a 1K load is connected between P1-7 and grounds.

3.5.7 Meter DC.- The output at P1-4 shall be 70 ± 3MV when a 1K ohm load is connected between P1-4 and ground.

3.5.8 115VAC 400 Hz output.- The output between P1-1 and P1-2 shall be 115VAC 400 Hz when the primary input is 115VAC 400Hz.

3.5.9 Line fuses.- With 115VAC 400 Hz applied to the input and the 2 amp fuses removed, both fuseholder lights shall light.

3.5.10 Delayed - 500VDC.- The output at P1-13 -500VDC, shall have a 30 ± 6 second delay.

3.6 Reliability run-in.- In order to maximize component reliability, prior to acceptance by the Government each shall be subject to the following run-in conditions:

a. Temperature run-in.- The power supply without power applied, shall be temperature stabilized at plus 125°F and minus 25°F. At each temperature extreme, after temperature stabilization, power shall be applied and each unit shall be tested to all the performance requirements of 3.5 for a period of three (3) hours with a minimum of one (1) complete test to the requirements of 3.5 occurring at the beginning, middle and end of the three (3) hour period. Subsequent to the above tests, the power supply shall not have been damaged or adversely affected, and shall meet the requirements of 3.5.

b. Vibration run-in.- The power supply shall be capable of continuous operation while being vibrated in a simple harmonic motion having an amplitude of 0.03 (0.06 inch maximum total excursion) with the frequency being varied uniformly between the limits of ten (10) and fifty-five (55)

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

hertz and return to 10 hertz, and shall be uniformly traversed in 1 minute. This motion shall be applied for a period of ten(10) minutes in each of three (3) mutually perpendicular directions (x, y, z axis) for a total of 0.5 hours. During the above vibration, the power supply output voltage, -500 VDC at P1-13, shall be monitored. Subsequent to the above vibration, the power supply shall not be damaged or adversely affected, and shall meet the requirements of 3.5.

3.7 Failures during reliability run-in.- Replacement of defective components and correction of workmanship defects may be made during run-in under the following conditions:

a. Any part, module, component or subassembly that is used as a replacement shall have previously passed environmental tests consistent with the reliability run-in environmental requirements of the power supply.

b. Any replacement part shall have been exposed for at least one (1) hour at the extreme temperature being run immediately previous to being used as a replacement.

c. After a correction has been accomplished, at least one (1) hour of operation with a minimum of one (1) test to the requirements of 3.5 shall be successfully accomplished at the temperature at which the failure occurred.

d. A failure during 3.6.b shall necessitate a complete re-run of the conditions of 3.6.b.

4. QUALITY ASSURANCE PROVISIONS

4.1 Responsibility for inspection.- Unless otherwise specified in the contract or purchase order, the supplier is responsible for the performance of all inspection requirements as specified herein. Except as otherwise specified, the supplier may utilize his own facilities or any other facilities suitable for the performance of the inspection requirements specified herein, unless disapproved by the Government. The Government reserves the right to perform any of the inspections set forth in the specification where such inspections are deemed necessary to assure supplies and services conform to prescribed requirements.

4.1.1 General provisions.- The component and subassembly inspection requirements of MIL-F-13926 form a part of the quality assurance provisions of this specification. Definitions of inspection terms shall be as listed in MIL-STD-109.

4.2 First article (initial production) approval.- The requirement for first article approval and the responsibility (Government or contractor) for first article testing shall be as specified in the contract. The sample for first article approval tests shall consist of three (3) power supplies manufactured in the same manner using the same materials, equipment, processes, and procedures as used in regular production. All parts and materials, including packaging and packing, shall be obtained from the same source of supply as used in regular production.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

4.2.1 Government testing.- When the Government is responsible for conducting first article approval tests, the contractor, prior to submitting the sample to the Government, shall inspect the sample to insure that it conforms to all the requirements of the contract and submit a record of this inspection with the sample, including certificates of conformance for materials.

4.2.2 Contractor testing.- When the contractor is responsible for conducting first article approval tests, the sample shall be inspected by the contractor for all the requirements of the contract. The sample and a record of this inspection, including certificates of conformance for materials, shall be submitted to the Government for approval. The Government reserves the right to witness the contractor's inspection.

4.3 Inspection provisions.

4.3.1 Examination and tests.

4.3.1.1 Components and subassemblies.- All components and subassemblies shall be inspected in accordance with the inspection provisions contained in the applicable Quality Assurance Provisions of MIL-F-13926.

4.3.2 Acceptance and rejection.- Rejected lots shall be screened for all defective characteristics. Removal or correction of defective units and resubmittance of rejected lots shall be in accordance with "Acceptance and Rejection" as specified in MIL-STD-105.

4.4 Special sampling.- At the beginning of production and subsequent to First Article Approval (see 4.2), three units shall be selected by a Government representative and two from each 50 produced. The samples shall have successfully met all other examinations and acceptance tests specified herein, and shall meet the following requirements and tests:

	CHARACTERISTIC	REQUIREMENTS	TEST PROCEDURE
401.	Fabrication	3.1	Applic dwgs & Specs - Visual
402.	General specifications	3.2	MIL-F-13926 & MIL-C-46357
403.	Vibration	3.3.2	4.6.1.2
404.	Humidity	3.3.3	4.6.1.3
405.	Sand and dust	3.3.4	4.6.1.4
406.	Altitude-operating	3.3.5.1	4.6.1.5
407.	Altitude-non-operating	3.3.5.2	4.6.1.5.1
408.	Storage temperatures	3.3.7	4.6.1.7.1
409.	Operating temperatures	3.3.8	4.6.1.7.2

4.4.1 Failure of sample.- Should any one item of a special sampling fail to meet the specified test requirements, acceptance of the product shall be suspended by the Government until necessary corrections have been made by the contractor, and resubmitted samples have been approved (see 4.3.2).

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

4.5 Inspection equipment.- Except as otherwise provided for by the contract, the contractor shall supply and maintain inspection equipment in accordance with the applicable requirements of MIL-I-45607.

4.5.1 Government furnished inspection equipment.- Where the contract provides for Government-furnished test equipment, supply and maintenance of test equipment shall be in accordance with the applicable requirements of MIL-I-45607.

4.5.2 Contractor furnished inspection equipment.-

4.5.2.1 Contractor design.- The contractor shall design and supply inspection equipment compatible with "Test Methods and Procedures" specified in 4.6 of this specification, and with the "Component Inspection" requirements of MIL-F-13926. Since tolerance of test equipment is normally considered to be within 10% of the product tolerance for which it is intended, this inherent error in the test equipment design must be considered as part of the prescribed product tolerance limit. Thus, concept, construction, materials, dimensions and tolerances used in design of test equipment shall be so selected and controlled as to insure that the test equipment will reliably indicate acceptability of a product which does not exceed 90% of the prescribed tolerance limit and permit positive rejection when nonconforming. Construction shall be such as to facilitate routine calibration of test equipment.

4.6 Test methods and procedures.

4.6.1 Environmental.- Test equipment and test facilities utilized in the following environmental tests shall be in accordance with "Test Facilities" requirements of MIL-F-13926 and conditions specified in 3.5.

4.6.1.1 Shock.- The shock test shall be performed as specified in MIL-STD-810, Method 516, Procedure IV at the conditions specified in 3.3.1. During this shock test all voltages as specified in Table I and 3.5.10 shall be monitored. These voltages shall be continuous and uninterrupted. This test shall be conducted on a 100% basis. Subsequent to the 18 shocks, the power supply shall be visually examined for physical damage, then tested as specified in 4.6.2.

4.6.1.2 Vibration.- The vibration test shall be performed as specified in MIL-STD-810, Method 514 at the conditions specified in 3.3.2. Subsequent to the 1.5 hour vibration, the power supply shall be visually examined for physical damage, then tested as specified in 4.6.2.

4.6.1.3 Humidity.- The humidity test shall be performed as specified in MIL-STD-810, Method 507, Procedure I for four (4) hours at the conditions specified in 3.3.3. Subsequent to this test, the power supply shall be examined for damage then tested as specified in 4.6.2.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

4.6.1.4 Sand and dust.- The sand and dust test shall be performed as specified in MIL-STD-810, Method 510, with the following conditions: The sand and dust particle sizes, density, wind velocity, temperature, time duration and relative humidity shall be as specified in 3.3.4. Subsequent to this test, the power supply shall be visually examined for damage then tested as specified in 4.6.2.

4.6.1.5 Altitude-operating.- The altitude test shall be performed as specified in MIL-F-13926, Procedure I at an altitude of 10,000 feet and as specified in 3.3.5.1. The power supply shall be exposed to the above condition for a time period required to allow all entrapped air in the chamber to escape as evidenced by chamber pressure stabilization. The barometric pressure shall then be maintained to simulate 10,000 feet (20.58 inches of mercury) altitude condition. While the power supply is maintained at this pressure for four (4) hours, the power supply shall be subjected to the tests specified in 4.6.2.

4.6.1.5.1 Altitude non-operating.- The power supply shall be subjected to barometric pressure specified in MIL-F-13926, Procedure II for four (4) hours as specified in 3.3.5.2. Subsequent to this test, the power supply shall be visually examined for damage, then tested as specified in 4.6.2.

4.6.1.6 Fungus.- One (1) power supply shall be subjected to the fungus test specified in MIL-F-13926. At the end of the 28 day incubation period, the power supply shall be tested as specified in 4.6.2 for compliance with 3.3.6. Subsequent acceptance of power supplies shall be by certification.

4.6.1.7 Temperature cycling.

4.6.1.7.1 Storage temperatures.- This test shall be performed as specified in MIL-F-13926, Procedure II, and thermally stabilized at +160°F for eight (8) hours and at -80°F for eight (8) hours. The power supply shall be returned to room ambient temperature 75 ± 15°F, visually examined for damage then tested as specified in 4.6.2.

4.6.1.7.2 Operating temperatures.- The power supply shall be placed in a test chamber and the temperature gradually raised until thermally stabilized at +140°F for eight (8) hours. The power supply shall be tested as specified in 4.6.2 during the first hour, at the four (4) hour period, and within the last hour of the eight (8) hour period. The temperature shall then be gradually reduced to -50°F. When thermally stabilized at this temperature, the power supply shall be tested as specified in 4.6.2 at the three (3) time periods specified above. A 5 to 6 minute warm-up period shall be allowed prior to performance of the first test.

4.6.2 Performance.- Unless otherwise specified, the performance tests specified herein shall be performed on a 100% basis. All performance tests shall be met with the following inputs unless otherwise specified.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

a. 115VAC 400 Hz single phase (3% maximum total distortion) to J1-A
b. Neutral to J1-B
c. Ground to J1-C
d. Jumper P1-6 to P1-9

4.6.2.1 Power drain.- With a ammeter connected in series with J1-A, the power supply shall draw less than 2 amps.

4.6.2.2 Output voltage.- Connect load Rn as specified in Table I. Apply primary input power to J1 and turn power ON switch to up position, light indicator (OSI) shall light. The voltages shall be adjusted as follows:

a. With a voltmeter between J2 and ground adjust R11 to obtain a reading of -500VDC.

b. With a voltmeter between J3 and ground adjust R28 to obtain a reading of +176VDC.

c. With a voltmeter between J4 and ground adjust R37 and R43 to mid range (adjust to be made with power off). Adjust R37 until it has no further effect at J4. Adjust R43 to obtain +22VDC at J4. Replace 58.7 ohm load with 50 ohms, readjust R37 until it has no further effect at J4 if necessary. Remove 50 ohm load and replace by 58.7 ohms. Recheck +22VDC at J4 by turning power off and then reapplying power and noting that +22VDC doesn't vary while the delay relay comes on.

d. With a voltmeter connected between P1-10 and ground, the output at P1-10 shall be +132 ± 12 VDC.

4.6.2.3 Regulation.- Connect RN as specified in Table I. Vary the input voltages and frequencies as specified in Table II. The output voltages specified in Table I shall not vary more than ±1%. Repeat above test with RH as external load.

4.6.2.3.1 The above test shall be repeated using loads RL in place of RH.

4.6.2.4 Ripple voltage.- The ripple voltage shall be no greater than those values listed in Table I when testing to 4.6.2.2, 4.6.2.3 and 4.6.2.3.1.

4.6.2.5 Meter line.- With a 1K ± 1% resistor between P1-7 and ground and P1-B grounded, connect a voltmeter between P1-7 and ground. With the power supply on and the input voltage set at 120VAC 400 Hz, the voltage at P1-7 shall be 70 ± 3 MV.

4.6.2.6 Meter D-C.- With a 1K ± 1% resistor between P1-4 and ground, connect a voltmeter between P1-4 and ground. With the power supply on and the voltages adjusted as listed in Table I, the voltage at P1-4 shall be 70 ± 3MV.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

4.6.2.7 115 VAC 400 Hz output.- Connect a voltmeter between P1-1 and P1-2, the voltmeter reading shall be 115 $^{+0}_{-1}$ VAC when an input of 115 VAC 400 Hz is applied to J1.

4.6.2.8 Line fuses.- With an input of 115 VAC 400 Hz applied to J1 and the power switch on, the two 2A fuseholder lamps shall not light. With power switch off, remove fuses and replace fuseholder lamps. Turn power switch on, both fuseholder lamps shall light. Replace fuses.

4.6.2.9 Delayed-500 VDC.- With voltages adjusted as listed in Table I connect a voltmeter between P1-13 and ground. After turning on power switch, there shall be a 30 $\pm$ 6 second delay before the -500 VDC appears at P1-13.

4.6.3 Electrical.

4.6.3.1 Continuity.- Continuity shall be tested by standard measuring equipment for compliance with 3.4.1.

4.6.4 Reliability run-in.- The following run-in tests shall be performed on a 100% basis.

4.6.4.1 Temperature run-in.- The power supply shall be placed in a chamber and the temperature gradually raised until thermally stabilized at plus 125°F. After temperature stabilization, power shall be applied and maintained for three (3) hours. Five (5) minutes after power is applied, a complete test to the requirements of para 4.6.2 shall commence. A second test to the requirements of para 4.6.2 shall be accomplished during the second hour and a third test to the requirements of para 4.6.2 shall be accomplished during the third hour of the three (3) hour test. Repeat the above tests at a temperature of minus 25°F. Subsequent to the above temperature extremes (plus 125°F and minus 25°F) the power supply shall not have been damaged or adversely affected and shall meet the requirements of Para 4.6.2.

4.6.4.2 Vibration run-in.- The vibration test shall be performed as specified in MIL-STD-810, Method 516 at the conditions specified in 3.6b. During the above vibration test, the power supply shall meet the performance tests as specified in para 4.6.2.2. The voltages as specified in 4.6.2.2 and 3.6b shall be monitored for a continuous uninterrupted output. Subsequent to the vibration test, the power supply shall be visually examined for damage and shall meet the performance requirements of para 4.6.2.

4.6.4.3 Failures.- Failures occurring during Reliability Run-In shall not be cause for rejection, but shall be corrected as outlined in para. 3.6.1.

4.6.5 Packaging, packing, and marking.- Quality assurance provisions for packaging, packing, and marking shall be as specified in MIL-P-14232 and Section 5 herein.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

5. PREPARATION FOR DELIVERY

5.1 Packaging, packing and marking.- Packaging, packing and marking shall be in accordance with MIL-P-14232 and Packaging Data Sheet 10512499. The level of protection shall be as specified in the procurement document.

6. NOTES

6.1 Intended use.- The power supply is used to convert the primary power to D.C. voltages necessary to operate the system.

6.2 Ordering data.- Procurement documents should specify the following:

a. Title, number, and date of this specification
b. Selection of applicable levels of preservation, packaging, and packing
c. Applicable stock number
d. Applicable packaging data sheet (see 5.1)

Custodian:

Army - MU

Preparing activity:

Army - MU

Project No. 1290-A200

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

SPECIFICATION ANALYSIS SHEET

Form Approved
Budget Bureau No. 22-R255

INSTRUCTIONS: This sheet is to be filled out by personnel, either Government or contractor, involved in the use of the specification in procurement of products for ultimate use by the Department of Defense. This sheet is provided for obtaining information on the use of this specification which will insure that suitable products can be procured with a minimum amount of delay and at the least cost. Comments and the return of this form will be appreciated. Fold on lines on reverse side, staple in corner, and send to preparing activity. Comments and suggestions submitted on this form do not constitute or imply authorization to waive any portion of the referenced document(s) or serve to amend contractual requirements.

SPECIFICATION

ORGANIZATION

CITY AND STATE

CONTRACT NUMBER

MATERIAL PROCURED UNDER A

☐ DIRECT GOVERNMENT CONTRACT ☐ SUBCONTRACT

1. HAS ANY PART OF THE SPECIFICATION CREATED PROBLEMS OR REQUIRED INTERPRETATION IN PROCUREMENT USE?

A. GIVE PARAGRAPH NUMBER AND WORDING.

B. RECOMMENDATIONS FOR CORRECTING THE DEFICIENCIES

2. COMMENTS ON ANY SPECIFICATION REQUIREMENT CONSIDERED TOO RIGID

3. IS THE SPECIFICATION RESTRICTIVE?

[ ] YES [ ] NO *(If "yes", in what way?)*

4. REMARKS *(Attach any pertinent data which may be of use in improving this specification. If there are additional papers, attach to form and place both in an envelope addressed to preparing activity).*

SUBMITTED BY *(Printed or typed name and activity - Optional)*

DATE

DD FORM 1 JAN 66 1426

REPLACES EDITION OF 1 OCT 64 WHICH MAY BE USED.

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.

FOLD

Department of the Army

Frankford Arsenal
Philadelphia, Pa. 19137

OFFICIAL BUSINESS

POSTAGE AND FEES PAID
Department of the Army

Commanding Officer
Frankford Arsenal
ATTN: SMUFA-N1100
Philadelphia, Pa. 19137

FOLD

Source: https://assist.dla.mil -- Downloaded: 2026-10-18T04:49Z
Check the source to verify that this is the current version before use.