MIL-E-63511(AR)
AMENDMENT 5
13 MARCH 1987
SUPERSEDING
AMENDMENT 4
30 December 1986

MILITARY SPECIFICATION

ELECTRONICS-MCD ASSEMBLY
FOR
MINE, ANTI-TANK: BLU 91/B

This Amendment forms a part of Military Specification MIL-E-63511(AR), dated 15 June 1982, and is approved for use within the U.S. Army Armament, Munitions and Chemical Command, and is available for use by all Departments and Agencies of the Department of Defense.

PAGE 1

Preamble: Delete "Armament Research and Development Command" and substitute "Armament, Munitions and Chemical Command."

PAGE 2

SPECIFICATIONS, MILITARY:

MIL-S-19500/127: Delete in its entirety and add the following:

MIL-S-19500/444 - Semiconductor Device, Diode, Silicon, Switching Types 2N5711 and TX 2N5711"

PAGE 3

2.1.2, Other Government documents, drawings, and publications: US Army Armament Research and Development Command (ARRADCOM): Delete "and Development Command (ARRADCOM)" and substitute ", Development and Engineering Center (ARDEC)."

DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

PAGE 4

3.4.1 Transportation vibration. Delete in its entirety and substitute the following:

"3.4.1 Transportation vibration. The Electronics-MCD Assembly shall be safe to handle and transport. Test mines shall show no evidence of damage that will affect the function following transportation vibration test No. 119, Procedure 2 of MIL-STD-331."

PAGE 14

TABLE I:

Delete "Band Printed Wiring (Dwg. 9292230)" and substitute "Wiring, Printed Flexible (Dwg. 9292230)".

PAGE 17

4.4.2.1, Resistor, Fixed Composition, 5%, 1/8W:

TITLE: Delete "1/8W".

DRAWING NUMBER: Delete "MIL-R-39008/4" and substitute "MIL-R-39008/1/".

Part Number, Part Value: Delete in its entirety and substitute:

"Part Number 1/	Part Value
RCR05G 30 5 JR	3 M OHM
RCR05G 10 4 JR	100 K OHM
RCR05G 47 2 JR	4.7 K OHM
RCR05G 10 2 JR	1 K OHM
RCR07G 13 1 JR	130 OHM"

Major 101: Delete "MIL-R-39008/4" and substitute "MIL-R-39008/1/".

Add the following note:

"1/ Use MIL-R-39008/1 or /4 as applicable, See Dwg. Note 13".

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

PAGE 18

* 4.4.2.2, Resister, Fixed Film:

DRAWING NUMBER: Delete "P/N 9287099-1611" and substitute "P/N 9287099-1621".

PAGE 20

4.4.2.4, Transistor, (P/N 9287122-1, JNTXV2N2907 and 9287122-2 JNTXV2N2222A):

Title: Delete "(P/N 9287122-1, JNTXV2N2907 and 9287122-2 JNTXU2N2222A)" and substitute "(JXTXV2907 and JNTXV2N2222A)"

Drawing Number: Delete "9287122" and substitute" MIL-S-19500/291N/255"

Major 101: Delete "Wire material 32 1/ 3.2 Visual" and substitute "Bond Wire Material not aluminum -- 3.2 Certification"

PAGE 20

Major 102: Delete in its entirety.

Major 105: Delete in its entirety.

Major 106: Delete in its entirety.

PAGE 21

4.4.2.5 Semi-conductor Device, Diode, Type JANTX IN 645-1:

Drawing Number: Delete "9287168-2" and substitute "MIL-S-19500/240"

Critical 1: Delete in its entirety.

Critical 2: Delete in its entirety.

Add the following Major Categories:

"104, Missing or incorrect color band on cathode end of diode - 100% 3.2 Electrical 1/"

"105, Reverse current - 100% 3.2 MIL-STD-750, Method 4016, dc"

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

PAGE 22

4.4.2.6, Diode, Zener, JANTX IN 4463 and JANTX IN 4471:

Critical 1: Delete in its entirety

Critical 2: Delete in its entirety

Critical 3: Delete in its entirety

Add the following Major Categories:

"104, Missing or incorrect color band on cathode end of diode - 100% 3.2 Electrical, 1/"

105, Reverse current - 100% 3.2 MIL-STD-750, Method 4016, dc"

106, Zener breakdown voltage V_Z - 100% 3.2 MIL-STD-750, Method 4022"

PAGE 23

4.4.2.7, Diode, Hot Carrier (Jan lN 5711, MIL-S-19500/127): Change title to read "4.4.2.7, Diode, Hot Carrier (JAN lN 5711, MIL-5-19500/444)"

PAGE 25

4.4.2.9, Capacitor, Fixed, Electrolytic Tantalum, Solid (82 uF):

Major 104: Delete "10-1-2" and substitute "10-2-3"

Major 106: Delete "8-0-1" and substitute "8-1-2"

PAGE 26

4.4.2.10, Capacitor, Fixed, Electrolytic Tantalum, Solid:

Major 104: Delete "10-1-2" and substitute "10-2-3"

Major 106: Delete "8-0-1" and substitute "8-1-2"

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

PAGE 32

4.4.2.16, Board, Printed Wiring:

Major 105: Delete "Large circular cutout, 2 places" and substitute "Diameter of circular cutout, 2 places".

Major 106: Delete "0.40%" and substitute "1/"

Add the following Note:

"1/ Printed Wiring Board sample plan per MIL-STD-105, AQL 0.40%, Inspection Level S4. From each board, randomly select and inspect 32 hole diameters. A board shall be classed defective if any hole is defective".

PAGE 34

4.4.2.1.8, Microcircuit, Digital, CMOS:

Major 101: Delete "1/" and substitute "5-1-2"

Note 1/: Delete in its entirety.

PAGE 40

4.4.2.24, Receiver Coil Assembly:

Major 104: Delete "Spacing of coil... 0.40% 3.2 Gage" and substitute "Bonding of coil to flexable circuit board incorrect 0.40% 3.2 Visual".

PAGE 42

4.4.2.26, Board, Printed Wiring:

TITLE: Delete "Board, Printed Wiring" and substitute "Wiring, Printed Flexible".

Major 103: Delete "Diameter" and substitute "Length and Width".

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

PAGE 45

4.4.2.29, Lid Electronics Assembly:

DRAWING NUMBER: Delete "9292243" and substitute "9292243/9378308".

Minor 203: Delete in its entirety.

PAGE 46

4.4.2.30, Housing, Electronics Assembly:

DRAWING NUMBER: Delete "9332372" and substitute "9332372/9378309".

PAGE 56

4.4.2.35, Electronics-MCD Assy. (Prior to Assy of Test Mines):

Title: Delete "(Prior to Assy of Test Mines)"

Add the following Major Category:

"103 Improper soldering MCD flex cable - 0.40% 3.16 Visual"

PAGE 57

Add the following Major defect: "103 Impact failure 0-1 3.5 4.5.4"

PAGE 58

After paragraph 4.4.2.36, add paragraph 4.4.2.37, page 58a and 58b included consisting of Classification of Defects and Tests for Power Supply Molding, drawing number 9292221.

After paragraph 4.4.2.37, add paragraph 4.4.2.38, page 58c included consisting of Classification of Defects and Test for Power Supply Assembly, drawing number 9292241.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

PAGE 59

4.4.6 Launch Simulator

a. Delete "150 + 6.0" and substitute: "150 + 50"

PAGE 63

4.5.4.3, Disposition of Duds. Delete "ARRADCOM" and substitute "to the Government"

PAGE 67

In Table II Delete: "1. Shorting Bar Across Firing Capacitor 6 to 9 .2 to .7 OHMS" and substitute "1. Shorting Bar Across Firing Capacitor 6 to 9 .2 to .85 OHMS."

PAGE 68

Add the following new paragraphs:

"4.5.9 Power Supply Assembly.

4.5.9.1 Pull test of the Power Supply Assembly leads. Each welded lead shall withstand a non-destructive pull force 5 + 2 pounds along the longitudinal axis of the lead without degradation or failure. Additionally one power supply at the start of each shift and one Power Supply every 100 manufactured shall be subjected to a destructive pull force on each of the 4 leads of 9 pounds minimum along the longitudinal axis of the lead. Evidence of residual lead material shall be present at each weld after the pull test to assure weld integrity.

"4.5.9.2 Leak test of the Power Supply Assembly. One assembly at the start of each shift and one assembly of every 100 manufactured shall be tested for compliance with the reoss and fine leak requirements of MIL-B-48761. Any unit failing to meet the requirement shall reject the lot. (non-destructive test) (alternate lead material only).

NOTE: At the contractors option 4.5.9.1 & 4.5.9.2 may be conducted on battery and lead assemblies prior to assembly of the Power Supply Assembly dependent on the contractor process."

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET 1 OF 2		DRAWING NUMBER
4.4.2.37	Power Supply Molding				9292221
					NEXT HIGHER ASSEMBLY
					9292241
CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical	None defined				
Major					
101	I.D. of small center hole		0.40%	3.2	Gage
102	O.D. of bottom post (max)		0.40%	3.2	Gage
103	True position of O.D. of bottom post		0.40%	3.2	Gage
104	Width of bridge		0.40%	3.2	Gage
105	True position of bridge width		0.40%	3.2	Gage
106	I.D. of largest center hole		0.40%	3.2	Gage
107	True position of largest hole		0.40%	3.2	Gage
108	Height from bottom to top of bridge		0.40%	3.2	Gage
109	Material		0.40%	3.2	Certificate
110	Distance from center line to edge of shorting bar cavity (Section B-B), 2 places		0.40%	3.2	Gage
111	Depth of largest hole		0.40%	3.2	Gage
112	Height from bottom to top of upper post		0.40%	3.2	Gage
113	O.D. of upper post		0.40%	3.2	Gage
114	True position of upper post		0.40%	3.2	Gage
Minor					
201	Length from bridge to closed end of battery cell cavity (2 places)		0.65%	3.2	Gage

NOTES:

Source: https://assist.dla.mil -- Downloaded: 2024-10-23T03:00Z
Check the source to verify that this is the current version before use.

CLASSIFICATION OF DEFECTS & TESTS

PARAGRAPH	TITLE		SHEET	DRAWING NUMBER
4.4.2.37	Power Supply Molding		2 OF 2	9292221
				NEXT HIGHER ASSEMBLY
				9292241

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Minor					
202	True position of inside width of cavity (CD203), 2 places		0.65%	3.2	Gage
203	Width of battery cavity (2 places)		0.65%	3.2	Gage
204	Width of shorting bar cavity (Sect. B-B 2 places		0.65%	3.2	Gage
205	Length of shorting bar slot, max 2 places		0.65%	3.2	Gage
206	Depth of shorting bar cavity (Sect. B-B) 2 places		0.65%	3.2	Gage
207	Width of shorting bar slot, 4 places		0.65%	3.2	Gage
208	Distance from center line to edge of shorting bar cavity		0.65%	3.2	Gage
209	Poor workmanship		0.65%	3.6	Visual

NOTES:

Source: https://assist.dla.mil -- Downloaded: 2026-01-23T03:00Z
Check the source to verify that this is the current version before use.

QUALITY CONFORMANCE INSPECTION

CLASSIFICATION OF DEFECTS & TESTS

MIL-E-63511(AR)
AMENDMENT 5

PARAGRAPH	TITLE	SHEET	DRAWING NUMBER
4.4.2.38	Power Supply Assembly	1 OF 1	9292241
			NEXT HIGHER ASSEMBLY 9330377

CATEGORY	EXAMINATION OR TEST	NO. OF SAMPLE UNITS	AQL OR 100%	REQUIREMENT PARAGRAPH	PARAGRAPH REFERENCE /INSPECTION METHOD
Critical					
1	Pull test (weld integrity)		100%	3.2	4.5.9
Major					
101	Battery cell(s) not bonded to mold		0.40%	3.2	Visual
102	Length of lead(s) extending below mold (min)		0.40%	3.2	Gage
103	Solderability, 4 cell leads	15	0-1	3.9.1	MIL-S-45743
104	Battery leaks	1/	-	3.2	4.5.9
105	Height of cell(s) in nold over max.		0.40%	3.2	Gage
Minor					
201	Poor workmanship		0.65%	3.6	Visual

NOTES:

AMSMC Form 1570, 1 Feb 85 Replaces DRSMC-QA (D) Form 160, 1 Aug 83, which may not be used.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

5.1: Delete in its entirety and substitute the following:

"5.1 Packaging. The Electronics-MCD assembly shall be preserved and packaged in accordance with MIL-E-17555 with the following mandatory requirements:

Each individual Electronic-MCD Assembly shall be completely wrapped in metal foil (aluminum foil) to shield the units from electromagnetic and radio frequency energies.

The wrapped units shall be packaged in a corrugated fiberboard tray or box fitted with partitions and separators as required to keep the foil-wrapped units separated.

Cushioning as needed shall be used; the fiberboard trays or box shall be sealed in a barrier bag conforming to Tape I, or Class F, Style 1, Specification MIL-B-117. (Material used to fabricate the barrier bag must include metal foil).

The packaging materials shall not contain silicones, sulphur compounds or polysulphides."

6.3 Submission of inspection equipment designs for approval. Delete: "to: Commander, U.S. Army...New Jersey 07801" and substitute "to the Technical Agency specified in the contract."

PAGE 69

6.4 Submission of plans for approval. Delete "Commander: ARRADCOM, ... DRDAR-QAT-M" and substitute "the Technical Agency specified in the contract".

6.5 Submission of process control documents. Delete "to: Commander, ARRADCOM, ... DRDAR-QAT-M" and substitute "to the Technical Agency specified in the contract"

6.6 Distribution of ammunition data cards, inspection and test results, process controls. Delete "Commander: ARRADCOM, ... DRDAR-QAT-M" and substitute "the Technical Agency specified in the contract"

PAGE 70

6.9 Definitions:

h. Transportation Vibration failure: Delete in its entirety and substitute the following.

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.

"h. Transportation Vibration failure is defined as a test mine assembly that does not meet the requirements of 3.4.1, or in the event the borerider has functioned as a result of vibration the test shall be stopped and the Government Technical Agency specified in the Contract shall be notified for disposition of the test sample."

i. Impact failure: Delete in its entirety and substitute the following:

"i. Impact failure.

(1) Critical is defined as an Electronics-MCD Assembly that sustains damage due to impact resulting in critical failure modes for the MCD Assembly moves with respect to the Electronics Assembly (Dud failure analysis only).

(2) Major is defined as an Electronics-MCD Assembly that sustains damage due to impact resulting in a dud."

6.11 Drawings. Delete in its entirety and substitute:

"6.11 Drawings. Drawings listed in Section 2 of this specification under the heading US Army Armament Research, Development and Engineering Center (ARDEC) may also include drawings prepared by, and identified as US Army Armament Research and Development Command, Edgewood Arsenal, Frankford Arsenal, Rock Island Arsenal, or Picatinny Arsenal drawings. Technical data originally prepared by these activities is now under the cognizance of ARDEC."

The margins of this amendment are marked with an asterisk or vertical lines to indicate where changes (additions, modifications, corrections, deletions) from the previous amendment were made. This was done as a convenience only and the Government assumes no liability whatsoever for any inaccuracies in these notations. Bidders and contractors are cautioned to evaluate the requirements of this document based on the entire content irrespective of the marginal notations and relationship to the last previous amendment.

Custodian:
Army-AR

Preparing activity:
Army-AR

(Project 1345-A452)

Source: https://assist.dla.mil -- Downloaded: 2026-10-23T03:00Z
Check the source to verify that this is the current version before use.