CR1000	Attached Sensor/Device		
Terminal	**Wire/Terminal**	**Name**	**Measurements**
1H	High	VoltsDiff	irradiancia
1L	Low	VoltsDiff	irradiancia
⏚ (Ground)	Shield	VoltsDiff	irradiancia
	Black	034A/034B	WS_ms, WindDir
	Clear	034A/034B	WS_ms, WindDir
	White	034A/034B	WS_ms, WindDir
2H	Green	034A/034B	WS_ms, WindDir
2L	Red	108 (1)	T108_C
⏚ (Ground)	Purple	108 (1)	T108_C
	Clear	108 (1)	T108_C
	Purple	108 (2)	T108_C_2
	Clear	108 (2)	T108_C_2
3H	Red	108 (2)	T108_C_2
3L	Red	108 (3)	T108_C_3
⏚ (Ground)	Purple	108 (3)	T108_C_3
	Clear	108 (3)	T108_C_3
	Shield	VoltsSE	nivel_tanque
	Ground	VoltsSE	nivel_tanque
4H	Yellow	HMP45C (7WCS)	AirTC, RH
4L	Blue	HMP45C (7WCS)	AirTC, RH
⏚ (Ground)	Purple	HMP45C (7WCS)	AirTC, RH
	Black	HMP45C (7WCS)	AirTC, RH
	Clear	HMP45C (7WCS)	AirTC, RH
VX1 or EX1	Blue	034A/034B	WS_ms, WindDir
⏚ (Ground)			
P1	Red	034A/034B	WS_ms, WindDir
⏚ (Ground)			
P2			
⏚ (Ground)			
5H	Signal	VoltsSE	nivel_tanque
5L			
⏚ (Ground)			
6H			
6L			
⏚ (Ground)			
7H			
7L			
⏚ (Ground)			
8H			
8L			
⏚ (Ground)			
VX2 or EX2	Black	108 (1)	T108_C
⏚ (Ground)			
VX3 or EX3	Black	108 (2)	T108_C_2
	Black	108 (3)	T108_C_3
G			
5V			
G			
SW-12			
G			
12V	Red	HMP45C (7WCS)	AirTC, RH
12V			
G			

Terminal	Wire/Terminal	Name	Measurements
C1	Orange	HMP45C (7WCS)	AirTC, RH
C2			
C3			
C4			
G			
C5			
C6			
C7			
C8			
G			