

EVO64 BOM - Production Release v1

Updated: Aug 12th 2023

BOARD REFERENCE	QTY	VALUE	DESCRIPTION	MANUFACTURER PART #	MOUSER PART #	COMMENT
POWER Pack						
SW1	1	DPDT Power Switch	Recover from original system or NEW	SKY KS-SP-222A or SALECOM R8017L-R21	Not available	Try eBay
CN7	1	DIN7 Power connector	7 pin round DIN 45329	Original computer / NEW	Not available	Try Ali Express
VR2	1	7805 @ 1A	5v regulator 1A TO-220	L4941BV	511-L4941BV	
CR4	1	Bridge Rectifier @ 4A	Flat, inline package	GBU4G	512-GBU4G	No Longer Required for Boards dated 20230730 or newer
JP30	1	Header - Male 2x5	Crowbar protection. Close both +5v	10129381-910001BLF	649-1012938191001BLF	
Jumper caps	2	Jumper Cap - Female 1x2	Various jumper caps to short required header connections	M7582-46	855-M7582-46	
L4	1	250V,3.8mH,2.1A,150mOhms	AC Line Filter / Choke Original computer / NEW	SSR10V-21038	80-SSR10V-21038	
F1	2	Fuse Clip	Eaton Fuse Clip 5mm	AP/HTC-200M	504-AP/HTC-200M	
FUSE	1	1A	Glass Fuse, Small Form Factor 5x20mm 1A @ 250VAC fast blow	BK/S500-1-R	504-BK/S500-1-R	
HEATSINK	1	Heatsink for 7805	TO220 package @ 30mm	240-118ABEH-22	567-240-118ABH-22	
SOCKET Set						
U1,U2	2	40 PIN DIP Wide	Socket for 6526 CIA	1-2199299-5	571-1-2199299-5	
U7	1	40 PIN DIP Wide	Socket for 6510 or 8500 CPU	1-2199299-5	571-1-2199299-5	
U19	1	40 PIN DIP Wide	Socket for 6569/8569 (PAL) or 6567/8562 (NTSC) VICII	1-2199299-5	571-1-2199299-5	
U3	1	32 PIN DIP Wide	Socket for 27C010 / 20 / 40 / 80 Series EEPROM	1-2199300-2	571-1-2199300-2	
U181,U182	2	28 PIN DIP Wide	Socket for 6581/8580 SID or Various Clones	1-2199299-2	571-1-2199299-2	
U6	1	18 PIN DIP Narrow	Socket for 2114 SRAM for Video	1-2199298-5	571-1-2199298-5	
PIN Pack						
CN1	1	Header - Male 1x20	Keyboard (remove pin 2 from connector)	10129378-920001BLF	649-1012937892001BLF	
SID1, SID2	2	Header - Male 1x3	Selects SID voltage (12v for 6581, 9v for 8580, open for most clones)	77311-818-03LF	649-77311-818-03LF	
VIC-II	1	Header - Male 1x3	Selects VIC-II voltage level (12v for 6567/6569, 5v for 8569/8562)	77311-818-03LF	649-77311-818-03LF	
CN10	1	Header - Male 1x3	Standard power LED for case enclosure	77311-818-03LF	649-77311-818-03LF	
JP12	1	Header - Male 1x3 (optional)	Test points for NE556 Timer & Reset Signal only (optional - never close!)	77311-818-03LF	649-77311-818-03LF	
JP11, JP25	2	Header - Male 1x2	Reset (optional)	10129378-902001BLF	649-1012937890201BLF	
QAPLA'	4	Header - Female 2x8	QAPLA	68683-308	649-68683-308	
RePROM	1	Header - Male 2x8	Selects ROM and Cartridge Images	10129381-916001BLF	649-1012938191601BLF	
NuTube64 / Triode64	1	Header - Male 2x8	Power and audio signal routing for Triode64 and NuTube64 (optional)	10129381-916001BLF	649-1012938191601BLF	
QAPLA' JTAG	1	Header - Male 2x5 (optional)	JTAG Programmer for QAPLA CPLD (optional - not required)	10129381-910001BLF	649-1012938191001BLF	
MixSID	1	Header - Male 2x4	Selects configuration and address selection for SIDs	10129381-908001BLF	649-1012938190801BLF	
IN/OUT Connector	1	Header - Male 2x4	Test points for VIC-II Chroma & Luma signals, as well as SID audio in & out	10129381-908001BLF	649-1012938190801BLF	
Jumper caps	18	Jumper Cap - Female 1x2	Various jumper caps to short required header connections	M7582-46	855-M7582-46	
PORT Pack						
CN6	1	Cartridge port connector	Edge connector, dual row, female, 22x2 (44 pos) 0.100"	395-044-559-212	587-395-044-559-212	
CN8,CN9	2	DE-9 Joystick port connector	DE-9, multiple options	621-009-260-043	587-621-009-260-043	
CN4	1	DIN6 IEC port	6 pin round DIN 45322	Original computer / NEW	Not available	Try Ali Express
CN5	1	DIN8 Video port connector	8 pin round DIN 45326	Original computer / NEW	Not available	Try Ali Express
PREMIUM Pack						
OPTIONAL upgrades - THESE PARTS ARE NOT REQUIRED for a base EVO64 Build						
U1,U2,U7,U19	4	40 PIN Aries LP ZIF Sockets	Low profile zif sockets for CIA, CPU & VICII	40-526-10	535-40-526-10	
U4	1	32 PIN Aries Full Height ZIF Socket	Full height zif socket for ROM EPROM, as low profileis not available	32-6553-10	535-32-6553-10	
U181,U182	2	28 PIN Aries LP ZIF Sockets	Low profile zif sockets for SID chips	28-526-10	535-28-526-10	
L4	1	Coilcraft AC Filter Choke	Low Noise AC Filter Choke (SMD Part, please review BOM notes)	CG3528-ALD	994-CG3528-ALD	
VR2	1	EVO PWR 5v Switching vReg	Ultralow noise 5v switching regulator, designed by EVO team	https://retrospective.shop/evo64-rev-1-premium-ultra	Not available	EVO64 Exclusive
REPROM	1	DIP Array Dongle 8 positions	Convenient dip switch array that sits on top of 2x8 male headers for ROM config	https://retrospective.shop/evo64-rev-1-premium-ultra	Not available	EVO64 Exclusive
MIXSID	1	DIP Array Dongle 4 positions	Convenient dip switch array that sits on top of 2x4 male headers for SID config	https://retrospective.shop/evo64-rev-1-premium-ultra	Not available	EVO64 Exclusive
CROWBAR, SID1, SID2, VICII	5	Jumper Caps - RED	RED caps indicate configurable POWER settings	M7581-46	855-M7581-46	
VICII PAL/NTSC, JTAG CRT EN	3	Jumper Caps - BLUE	BLUE caps indicate configurable CONTROL settings	M7583-46	855-M7583-46	