

EnOcean Equipment Profiles

REVISION HISTORY

Ver.	Editor	Change	Date
2.6.8	NM	Last xml edition of the EEP-Specification	Dec 31, 2017

Copyright © EnOcean Alliance Inc. (2019). All rights reserved.

The information within this document is the property of the EnOcean Alliance and its use and disclosure are restricted. Elements of the EnOcean Alliance specifications may also be subject to third party intellectual property rights, including without limitation, patent, copyright or trademark rights (such a third party may or may not be a member of the EnOcean Alliance.)

The EnOcean Alliance is not responsible and shall not be held responsible in any manner for identifying or failing to identify any or all such third party intellectual property rights. This document and the information contained herein are provided on an “as is” basis and the EnOcean Alliance disclaims all warranties express or implied, including but not limited to

- (1) any warranty that the use of the information herein will not infringe any rights of third parties (including any intellectual property rights, patent, copyright or trademark rights, or
- (2) any implied warranties of merchantability, fitness for a particular purpose, title or non-infringement.

In no event will the EnOcean Alliance be liable for any loss of profits, loss of business, loss of use of data, interruption of business, or for any other direct, indirect, special or exemplary, incidental, punitive or consequential damages of any kind, in contract or in tort, in connection with this document or the information contained herein, even if advised of the possibility of such loss or damage. All Company, brand and product names may be trademarks that are the sole property of their respective owners.

The above notice and this paragraph must be included on all copies of this document that are made.

The EnOcean Alliance “EnOcean Equipment Profiles definitions” are available free of charge to companies, individuals and institutions for all non-commercial purposes (including educational research, technical evaluation and development of non-commercial tools or documentation.)

This specification includes intellectual property („IPR“) of the EnOcean Alliance and joint intellectual properties („joint IPR“) with contributing member companies. No part of this

System Specification



specification may be used in development of a product or service for sale without being a participant or promoter member of the EnOcean Alliance and/or joint owner of the appropriate joint IPR.

These errata may not have been subjected to an Intellectual Property review, and as such, may contain undeclared Necessary Claims.

EnOcean Alliance Inc.
2400 Camino Ramon, Suite 375
San Ramon, CA 94583
USA
Graham Martin
Chairman & CEO EnOcean Alliance

A5-13: Environmental Applications

RORG	A5	4BS Telegram
FUNC	13	Environmental Applications
TYPE	07	Wind Sensor

Submitter: Hideki Electronics Limited

Description

This profile provides wind sensor information.

That includes the current wind direction, the average and the maximum wind speed.

Data exchange

Direction: unidirectional

Addressing: broadcast

Communication trigger: time-triggered

Communication interval: 33 seconds

Trigger event: timer

Tx delay: N/A

Rx timeout: N/A

Teach-in

Teach-in method: 4BS teach-in 1

Security

Encryption supported: no

Security level format: N/A

System Specification

Offset	Size	Bitrange	Data	ShortCut	Description	Valid Range	Scale	Unit
0	4	DB3.7...DB3.4	Not Used (= 0)					
4	4	DB3.3...DB3.0	Wind Direction	WD	Shows the current wind direction	Enum:		
						0: NNE		
						1: NE		
						2: ENE		
						3: E		
						4: ESE		
						5: SE		
						6: SSE		
						7: S		
						8: SSW		
						9: SW		
						10: WSW		
						11: W		
						12: WNW		
						13: NW		
14: NNW								
15: N								
8	8	DB2.7...DB2.0	Average Wind Speed	AWS	Linear average wind speed	0...255	1...199.9	mph
16	8	DB1.7...DB1.0	Maximum Wind Speed	MWS	Maximum wind speed	0...255	1...199.9	mph
24	4	DB0.7...DB0.4	Not Used (= 0)					
28	1	DB0.3	LRN Bit	LRNB	LRN Bit	Enum:		
						0: Teach-in telegram		
						1: Data telegram		
29	2	DB0.2...DB0.1	Not Used (= 0)					
31	1	DB0.0	Battery Status	BS	Indicates if the battery is low	Enum:		
						0: Battery okay		
						1: Battery low		