

Risk Assessment No: WP-001		Task: CDE 200tph C&D Wash Plant — General Operation (whole-plant umbrella)							
Prepared By: Derick Bibby				Date: 02.08.2026			RA Review Date: 01.08.2027		
				Reviewed By: Lee Hardy			Date: 02.08.2026		
PPE: Safety Footwear, High Visibility Jacket, High Visibility Trousers, Hard Hat, Gloves, Ear Defenders, Mask, Eye Protection									
Hazard	Persons at Risk	L	S	R	Control Measures	L	S	R	
Contact with moving parts (drives, drums, agitators, augers)	Operator Maintenance Contractors	4	5	20	- Fixed guards to BS EN ISO 14120 secured with tooled fasteners. - No guard removed unless the machine is locked off in accordance with FoxSafe Isolation & Lock Out Procedure. - Emergency stops and pull-cord trip wires within reach; tested weekly. - Daily start-up checklist CL-WP-01 confirms all guards in place before running. - No loose clothing, jewellery or long hair uncovered.	1	5	5	
Entanglement — drums, drive shafts, couplings, take-up assemblies	Operator Maintenance	4	5	20	- Fixed guards on all drums, drives, couplings and take-up assemblies. - Belt-tracking adjusted from external take-up handles only. - Full LOTO before removing a guard, freeing a jammed belt or cleaning drums. - Signage “Guard must be in place before start” at each drum.	1	5	5	
Slips, trips and falls on the same level	All plant personnel	4	3	12	- Anti-slip walkways and stair-treads; wash-down at end of shift. - No trailing hoses or cables across walkways — stored on reels or coiled. - Immediate clean-up of oil, hydraulic fluid or fines spillage. - Adequate task lighting throughout the plant. - Correct footwear with slip-resistant sole to SRC.	2	3	6	
Struck by mobile plant (wheel loader, telehandler, tipper wagons)	Operator Loader driver Wagon drivers Visitors	4	5	20	- Traffic Management Plan segregates pedestrians from mobile plant. - Wheel loader fitted with reversing alarm, camera and beacons. - Wheel-stops at feed hopper; banksman when reversing at hopper. - Radio protocol between wash-plant operator and loader driver. - Visitors escorted at all times; hi-vis and site induction mandatory.	1	5	5	
Exposure to respirable crystalline silica (RCS) and other dusts	Operator Picking staff Loader driver	4	4	16	- Plant runs wet — spray bars on scalping and sizing screens for suppression. - Water suppression at feed hopper and stockpile transfer points. - FFP3 mask when dry-handling filter cake or working downwind of dust sources.	2	4	8	

					● Air-conditioned cabs with positive-pressure filtered air on all mobile plant. ● Personal RCS monitoring on rolling programme under health surveillance. ● No dry-sweeping — vacuum or damp-down only.			
Noise exposure ≥ 85 dB	All plant personnel	4	3	12	● Noise survey identifies zones ≥ 85 dB — mandatory hearing protection signage. ● Ear defenders SNR ≥ 27 dB issued and worn in mandatory zones. ● Audiometry health surveillance for staff regularly on the plant footprint. ● Noise-reducing enclosures maintained where fitted; damaged panels reported.	2	3	6
Hand-arm vibration (HAVS) / whole-body vibration	Picking staff Loader driver Fitters	3	3	9	● HAV / WBV exposures surveyed and time-limited per task. ● Low-vibration hand-tools and lagged hoses where practicable. ● Loader cab suspension seat maintained; tyre pressures correct. ● HSE Tier 1/2 HAVS health surveillance for exposed staff.	1	3	3
Manual handling of screen media, cloths, cyclone parts, hoses	Maintenance Operator	4	3	12	● Task-based manual handling assessment for screen cloths, cyclone apex and filter-press cloths. ● Mechanical lifting (chain block, telehandler, MEWP with man-basket) for loads > 20 kg. ● Two-person lift protocol for awkward items. ● LOLER-inspected lifting accessories only.	2	2	4
Electric shock — MCC, motor terminal boxes, damaged cables	Operator Maintenance Electricians	3	5	15	● Only competent authorised electrical persons open MCC panels or motor terminal boxes. ● Electrical work under signed permit-to-work with LOTO and voltage test. ● Fixed installation inspection to BS 7671 on documented periodic cycle. ● RCD protection tested monthly; results recorded. ● Cable routes protected against mechanical damage.	1	5	5
Stored energy — hydraulic accumulators, pneumatic receivers	Maintenance Contractors	3	5	15	● Bleed hydraulic accumulators to zero pressure and confirm via gauge before opening manifolds. ● Drain air receivers to zero via test valve before hose or fitting removal. ● Padlock the isolator on the pump or compressor supplying the circuit. ● PSSR examination of accumulators and receivers at statutory interval.	1	5	5
Fire — hydraulic oil, diesel, electrical fault, hot works	All personnel Site neighbours	3	5	15	● Hot works permit required for welding, cutting or grinding. ● Fire extinguishers (CO₂ and foam) at MCC, filter press and oil skid — serviced annually. ● Fire evacuation plan tested; assembly points marked and known at induction. ● No smoking outside designated area. ● Housekeeping to prevent accumulation of combustibles.	1	5	5
Chemical exposure — flocculant, lubricants,	Maintenance Operator	3	3	9	● COSHH assessment for every chemical on site; SDS held at MCC and maintenance office. ● Chemical-resistant gloves and eye/face protection during handling and dosing.	1	3	3

coolants, hydraulic fluid					- Bunded storage; spill kits at each storage point. - Emergency eyewash station at MCC and picking station. - Waste chemicals disposed via licensed contractor; consignment notes retained.			
Environmental release — silt-laden runoff, oil spillage	Environment Site neighbours	3	4	12	- Closed-loop water recycling via thickener and filter press; filter cake removed as solid. - Silt-trap and interceptor at yard discharge; inspected weekly. - Environmental permit monitoring and sampling per permit schedule. - Spill kits at fuel, oil and flocculant points. - Bunded storage on all above-ground tanks meeting oil storage regulations.	1	4	4
Adverse weather — wind, lightning, freeze, heat stress	All plant personnel	3	3	9	- Stop work at height and lifting when wind > 25 mph or per Appointed Person direction. - Cease outdoor works during electrical storms. - Freezing conditions — grit walkways, drain lines liable to freeze, heaters on filter press. - Heat-stress toolbox talk; welfare with water, shade and task rotation.	1	3	3
Lone working during out-of-hours starts, wash-downs or fault-finding	Operator Maintenance	3	4	12	- Lone-worker device or hourly radio/phone check-in with supervisor. - No high-risk task (work at height, confined space, hot works) performed alone. - Radio and mobile signal verified across plant footprint. - Emergency contact list posted at MCC and welfare unit.	1	4	4
Unexpected items in feed — asbestos, gas cylinders, chemical drums	Picking staff Operator Downstream equipment	4	4	16	- Pre-acceptance and duty-of-care checks on incoming C&D waste; refuse non-conforming loads. - Picking station staff trained to STOP the belt via e-stop on suspicious items. - Documented protocol — isolate, evacuate, notify SHEQ Manager, do not attempt removal without written safe method. - Toolbox talk on suspect-item recognition every six months. - Gas-cylinder and asbestos identification aids at picking-station kiosk.	2	4	8