

Esp 32 –

Ground → breadboard → 1) display ka gnd

2) R307 – black

ESP 32	Display
Vin	Vcc
D21	Sda
D22	Scl

Esp32	R307
VIn	5V(red)
RX	TX(yellow)
TX	RX(green)
ground	Gnd(black)

Esp32	Buzzer
Vp	+ve
Ground	-ve

Buttons ki ek side ground par hain aur dusri side digital pins par

To connect a Button

Button leg1 → connect to one end resistor

Connect to a digital pin

Button leg2 → connect to VIN

Resistor other leg → Connect to ground

```
//Arduino based EVM Code
#include<LiquidCrystal.h>
LiquidCrystal lcd(12, 11, 5, 4, 3, 2);
#define sw1 15
#define sw2 2
#define sw3 14
#define sw4 12
#define sw5 13
int vote1=0;
```

```
int vote2=0;

int vote3=0;

int vote4=0;

void setup()
{
    pinMode(sw1, INPUT);
    pinMode(sw2, INPUT);
    pinMode(sw3, INPUT);
    pinMode(sw4, INPUT);
    pinMode(sw5, INPUT);
    lcd.begin(16, 2);
    lcd.print("Voting Machine");
    lcd.setCursor(0,1);
    lcd.print("Circuit Digest");
    delay(3000);
    digitalWrite(sw1, HIGH);
    digitalWrite(sw2, HIGH);
    digitalWrite(sw3, HIGH);
    digitalWrite(sw4, HIGH);
    digitalWrite(sw5, HIGH);
    lcd.clear();
    lcd.setCursor(0,0);
    lcd.print("BJP");
    lcd.setCursor(4,0);
    lcd.print("INC");
    lcd.setCursor(8,0);
    lcd.print("AAP");
    lcd.setCursor(12,0);
    lcd.print("OTH");
```

```
}  
  
void loop()  
{  
    lcd.setCursor(0,0);  
    lcd.print("BJP");  
    lcd.setCursor(1,1);  
    lcd.print(vote1);  
    lcd.setCursor(4,0);  
    lcd.print("INC");  
    lcd.setCursor(5,1);  
    lcd.print(vote2);  
    lcd.setCursor(8,0);  
    lcd.print("AAP");  
    lcd.setCursor(9,1);  
    lcd.print(vote3);  
    lcd.setCursor(12,0);  
    lcd.print("OTH");  
    lcd.setCursor(13,1);  
    lcd.print(vote4);  
    if(digitalRead(sw1)==0)  
        vote1++;  
        while(digitalRead(sw1)==0);  
    if(digitalRead(sw2)==0)  
        vote2++;  
        while(digitalRead(sw2)==0);  
    if(digitalRead(sw3)==0)  
        vote3++;  
        while(digitalRead(sw3)==0);  
    if(digitalRead(sw4)==0)
```

```
vote4++;

while(digitalRead(sw4)==0);

if(digitalRead(sw5)==0)
{
    int vote=vote1+vote2+vote3+vote4;
    if(vote)
    {
        if((vote1 > vote2 && vote1 > vote3 && vote1 > vote4))
        {
            lcd.clear();
            lcd.print("BJP Wins");
            delay(2000);
            lcd.clear();
        }
        else if((vote2 > vote1 && vote2 > vote3 && vote2 > vote4))
        {
            lcd.clear();
            lcd.print("INC Wins");
            delay(2000);
            lcd.clear();
        }
        else if((vote3 > vote1 && vote3 > vote2 && vote3 > vote4))
        {
            lcd.clear();
            lcd.print("AAP Wins");
            delay(2000);
            lcd.clear();
        }
        else if(vote4 > vote1 && vote4 > vote2 && vote4 > vote3)
```

```

{
    lcd.setCursor(0,0);

    lcd.clear();

    lcd.print("OTH Wins");

    delay(2000);

    lcd.clear();
}

else if(vote4 > vote1 && vote4 > vote2 && vote4 > vote3)
{
    lcd.setCursor(0,0);

    lcd.clear();

    lcd.print("OTH Wins");

    delay(2000);

    lcd.clear();
}

else
{
    lcd.clear();

    lcd.print("   Tie Up Or   ");

    lcd.setCursor(0,1);

    lcd.print("   No Result   ");

    delay(1000);

    lcd.clear();
}

}

else

```

```
{  
    lcd.clear();  
    lcd.print("No Voting....");  
    delay(1000);  
    lcd.clear();  
}  
vote1=0;vote2=0;vote3=0;vote4=0,vote=0;  
lcd.clear();  
}  
  
}
```