

Digital display Operation

UP----Heating up, the machine need to warm up when
Running circle lines----Keep on heating, not 100%
can work at this condition, just spray time short
Static circle lines----standby mode, 100% finish
longest time.

1) MENU---Short press it to set menu data

Menu	Value	
A001	1-512	DMX address set
P100	1-100	Fog output vol
E000	1-7	LED color select
I060	5-999	Fog timing mode
0008	5-999	Fog timing mode duration

MENU---Long press it to set menu data below, normally no need to
change, long press menu again to exit.

Menu	Value	Function
H260	120-380	The highest temperature, no need to set
L195	100-280	The lowest temperature, no need to set
b	ON/OFF	Display LED background light ON/OFF
r	ON/OFF	Remote control ON/OFF
O	ON/OFF	No liquid protect ON/OFF
-005		No liquid protect data, don't change
-OF-	ON/OFF	Default setting

- 2) UP---Short press it to manual fogging at standby condition, short
press it again to exit, or change value when set menu data.
- 3) DOWN---Short press it to enter timing working mode at standby
condition(the interval time and duration time can be set in menu), short
press it again to exit, or change value when set menu data.
- 4) ENTER---Confirm

Manual

Fog Machine



Please read this manual carefully before operation