

RBF-FD Solver: Least Squares Method for Operator Reproduction

Dennis Corraliza

Updated: 9/16/25

Contents

1	Problem Setting	2
2	RBF-FD Method	3
2.1	Local Approximation setup	3
2.2	Polynomial Augmentation	3
2.3	Consistency Error Analysis	4
2.4	Growth Function	5
3	Local Least Square Weights RBF-FD	6
3.1	Weight Constraint Setup	6
3.2	Consistency Conditions for Finite Spaces and Interpolation Results	6
3.3	Consistency Results for Function Approximations	7

1 Problem Setting

Following the standard RBF-FD methods, let $u \in \mathcal{F}$ be a solution for a PDE in form of:

$$-Lu = -\nabla \cdot (A \nabla u) = f \quad \text{in } \Omega, \quad (1)$$

Let $1 < p < \infty$, $A \in W^{1,\infty}(\bar{\Omega}; \mathbb{R}^{d \times d}) : \bar{\Omega} \rightarrow \mathbb{R}^{d \times d}$ is an symmetric positive definite anisotropic tensor, where

$$\zeta |\xi|^2 \leq \mathbf{A}(\mathbf{x}) \xi \cdot \xi \leq \mathbf{Z} |\xi|^2, \quad \mathbf{0} < \zeta \leq \mathbf{Z} \quad (2)$$

Assume $\Omega \subset \mathbb{R}^d$ and $f \in W^{k,p}(\Omega)$ is the forcing term acting in the domain Ω . The problem is subject to Neumann and Dirichlet Boundary Conditions partitioned within $\partial\Omega$ of the form:

$$u = g_D \quad \text{on } \Gamma_D \subset \partial\Omega, \quad (3)$$

$$n \cdot A \nabla u = g_N \quad \text{on } \Gamma_N \subset \partial\Omega, \quad (4)$$

For simplicity, we assume Ω be a bounded $C^{1,1}(\partial\Omega)$ domain, with $\partial\Omega = \Gamma_D \cup \Gamma_N$ and $\Gamma_D \cap \Gamma_N = \emptyset$. Furthermore, let $g_D \in W^{k-1/p,p}(\partial\Omega)$, $g_N \in W^{k-1-1/p,p}(\partial\Omega)$. By *Agmon-Douglis-Nirenberg* Theorem [2], we have the following estimate for u :

$$\|u\|_{W^{k,p}(\Omega)} \leq C \left(\|Lu\|_{W^{k-2,p}(\Omega)} + \|g_D\|_{W^{k-1/p,p}(\partial\Omega)} + \|g_N\|_{W^{k-1-1/p,p}(\partial\Omega)} + \|u\|_{L^p(\Omega)} \right). \quad (5)$$

In the case that we work on a Hilbert space, we then have for $p = 2$ ($W^{k,2} := H^k$) the following estimate for u :

$$\|u\|_{H^k(\Omega)} \leq C \left(\|Lu\|_{H^{k-2}(\Omega)} + \|g_D\|_{H^{k-\frac{1}{2}}(\partial\Omega)} + \|g_N\|_{H^{k-\frac{3}{2}}(\partial\Omega)} + \|u\|_{L^2(\Omega)} \right). \quad (6)$$

If we want to study cases where $(Lu)(\mathbf{x}) \in L^\infty(\Omega)$. we can formulate the setup by having $f \in W^{s,p}(\Omega)$ and, by Morrey Embedding,

$$W^{s,p} \hookrightarrow C^{0,\alpha}, \quad \text{with } \alpha = s - \frac{d}{p} > 0 \quad (7)$$

In other words, $s > \frac{d}{p}$. Suppose $p = 2$, then $s > \frac{d}{2}$. Given an operator $L : H^{s+2}(\Omega) \rightarrow H^s(\Omega)$, we define an error functional of the form:

$$\xi_{L,x} : H^{s+2}(\Omega) \rightarrow \mathbb{R}, \quad \xi_{L,x} \in (H^{s+2})^*(\Omega) \quad (8)$$

Then by Riesz Representation Theorem, there exists a $v_{L,x} \in H^{s+2}(\Omega)$ such that $\xi_{L,x}(u) = \langle u, v_{L,x} \rangle_{H^{s+2}(\Omega)}$, and $\|\xi_{L,x}\|_{(H^{s+2}(\Omega))^*} = \|v_{L,x}\|_{H^{s+2}(\Omega)}$

2 RBF-FD Method

2.1 Local Approximation setup

To obtain an approximation of the operator L at point $\mathbf{z}$, we can approximate $\hat{u} \approx u$ on a neighborhood $\Omega \subseteq \mathbb{R}^d$ of $\mathbf{z}$ such that we approximate $Lu \approx L\hat{u}$. We define the basis functions in the form $\phi_i(\mathbf{x}) : \Omega \rightarrow \mathbb{R}$ for $i = 1, \dots, m$. Define the vector space $V_Y = \text{span}\{\phi_1, \dots, \phi_m\}$. Let $X = \{\mathbf{x}_1, \dots, \mathbf{x}_n\} \subseteq \Omega$ be a set of stencil nodes for a point $\mathbf{z}$ in Ω . For the classical approximation scheme, let $m = n$. We can now define $\Phi \in \mathbb{R}^{n \times m}$, where $\Phi_{ij} = \phi_j(\mathbf{x}_i)$. The role of these basis functions will be to approximate the operator L . The approximation of u takes the form of:

$$\hat{u}(\mathbf{x}) = \sum_{i=1}^n \lambda_i \phi_i(\mathbf{x}) \quad (9)$$

This will lead to the form $\Phi \lambda = \hat{\mathbf{u}}$ for $\hat{\mathbf{u}} = [u(\mathbf{x}_1), \dots, u(\mathbf{x}_n)]^T$. We can simplify for λ to obtain:

$$\hat{u}(\mathbf{x}) = \sum_{i=1}^n (\Phi^{-1} \mathbf{u})_i \phi_i(\mathbf{x}) = \phi(\mathbf{x})^T \Phi^{-1} \mathbf{u} \quad (10)$$

The approximation of Lu at $\mathbf{z}$ is in the form of:

$$Lu(\mathbf{z}) \approx L\hat{\mathbf{u}}(\mathbf{z}) = L\phi^T(\mathbf{z})\lambda = L\phi^T(\mathbf{z})\Phi^{-1}\mathbf{u} := \mathbf{w}^{L,\mathbf{X}}(\mathbf{z})\mathbf{u} \quad (11)$$

Thus, approximation the operator turns into local solver for the weights w_i from the form:

$$\Phi^T \mathbf{w}^{L,\mathbf{X}}(\mathbf{z}) = L\phi(\mathbf{z}) \quad (12)$$

Through the method of undefined coefficients on the basis $\{\phi_i\}$ we get the same resulting set of weights. Finally, we let the basis for V_Y be constituted by radial basis functions, with $\phi_i(\mathbf{x}) := \phi(\|\mathbf{x} - \mathbf{y}_i\|)$ and centers $\{\mathbf{y}_i\}_{i=1}^m \subseteq \Omega$. Thus we have defined the Radial Basis Function generated Finite Difference method (RBF-FD).

2.2 Polynomial Augmentation

For conditionally positive definite kernels, we augment them through the form:

$$\hat{u}(\mathbf{x}) = \sum_{j=1}^n \lambda_j \phi_j(\mathbf{x}) + \sum_{j=1}^l \beta_j \mathbf{p}_j(\mathbf{x}) \quad (13)$$

$$\sum_{i=1}^n \lambda_i p_j(\mathbf{x}_i) = 0, \forall j = 1, \dots, l \quad (14)$$

We can generate a Gram matrix equation as follows:

$$\begin{bmatrix} \hat{\mathbf{u}} \\ \mathbf{0} \end{bmatrix} = \begin{bmatrix} \Phi & P \\ P^T & \mathbf{0} \end{bmatrix} \begin{bmatrix} \lambda \\ \alpha \end{bmatrix} \quad (15)$$

Hence, we can approximate the operator as below:

$$(L\hat{u})(\mathbf{x}) = \begin{bmatrix} (L\phi)(\mathbf{x}) \\ (Lp)(\mathbf{x}) \end{bmatrix}^T \begin{bmatrix} \Phi & P \\ P^T & \mathbf{0} \end{bmatrix}^{-1} \begin{bmatrix} \hat{\mathbf{u}} \\ \mathbf{0} \end{bmatrix} := \begin{bmatrix} \mathbf{w}(\mathbf{x}) \\ \nu(\mathbf{x}) \end{bmatrix}^T \begin{bmatrix} \hat{\mathbf{u}} \\ \mathbf{0} \end{bmatrix} = \mathbf{w}^T(\mathbf{x})\hat{\mathbf{u}} \quad (16)$$

Thus, we get the local augmented operator reproduction scheme:

$$\begin{bmatrix} (L\phi)(\mathbf{x}) \\ (L\mathbf{p})(\mathbf{x}) \end{bmatrix} = \begin{bmatrix} \Phi^T & \mathbf{P} \\ \mathbf{P}^T & \mathbf{0} \end{bmatrix} \begin{bmatrix} \mathbf{w}(\mathbf{x}) \\ \nu(\mathbf{x}) \end{bmatrix} \quad (17)$$

The polynomial constraint setup can be viewed as a Lagrange multiplier to a minimization scheme for the weights. By [6], given the basis for V_Y , $(L\mathbf{p})(\mathbf{x}) \in \text{Range}(\mathbf{P}^T) \iff \text{Eq. (17)}$ is uniquely solvable, for any set X . Additionally, by [6], Eq. (16) hold $\iff \text{Eq. (17)}$ holds. Note that depending on the the basis V_Y , we get the degree of $p \in \Pi_{k-1}^d$. Below are common RBFs and their respective cpd orders:

Table 1: Common radial basis functions and their minimal CPD order.

RBF	Radial function $\phi(r)$	CPD order k
Gaussian	$\exp(-\varepsilon^2 r^2)$	0
Inverse multiquadric	$(r^2 + \varepsilon^2)^{-1/2}$	0
Multiquadric	$(r^2 + \varepsilon^2)^{1/2}$	1
Linear	r	1
Cubic	r^3	2
Thin-plate spline	$r^2 \log r$	2
Quintic	r^5	3

This order provides us both, the degree of the polynomials $k - 1$ and the number of terms:

$$l = \binom{d + k - 1}{k - 1} \quad (18)$$

As shown in [8], a polynomial augmentation can be added with a larger degree than required for the RBF, acting as a correction term while inheriting the non-oscillatory behavior of the RBF at the boundary $\partial\Omega$.

2.3 Consistency Error Analysis

We begin by defining the native space of solutions for (1) with (4). Suppose $\mathcal{F}_{\mathcal{K}} = H^{s+2}(\Omega)$. This defines an RKHS for functions $u \in H^{s+2}(\Omega)$, $Lu \in H^s(\Omega)$ and by Morrey Embedding, $L(\cdot)(\mathbf{x})$ is bounded, linear functional on $H^{s+2}(\Omega)$. Thus, by Riesz, $v_{Lu,x} \in H^{s+2}(\Omega)$. We can also define a Kernel $K : \Omega \times \Omega \rightarrow \mathbb{R}$ such that:

$$f(x) = \langle f, K(\cdot, x) \rangle_{\mathcal{F}_{\mathcal{K}}} \quad (19)$$

$$(Lf)(x) = \langle f, L_x K(\cdot, \mathbf{x}) \rangle_{\mathcal{F}_{\mathcal{K}}} \quad (20)$$

$$\mathbf{w}^T(\mathbf{x})\mathbf{f} = \langle f, \mathbf{w}^T(\mathbf{x})\mathbf{k}(\cdot) \rangle_{\mathcal{F}_{\mathcal{K}}} \quad (21)$$

$$\xi_{w,L,x}(f) := Lf(x) - \mathbf{w}^T(\mathbf{x})\mathbf{f} \quad (22)$$

$$\|\xi_{w,L,x}\|_{\mathcal{F}_{\mathcal{K}}^*} := \sup_{\substack{f \in \mathcal{F}_{\mathcal{K}} \\ \|f\|_{\mathcal{F}_{\mathcal{K}}} \leq 1}} |\xi_{w,L,x}(f)| \quad (23)$$

L_x indicates applying the operator acted on the variable $\mathbf{x}$ in the kernel. We define $\mathbf{k}(\mathbf{z}) = [k(\mathbf{z}, \mathbf{x}_1), \dots, k(\mathbf{z}, \mathbf{x}_n)]^T$. Since $\|\xi_{w,L,x}\|_{\mathcal{F}_{\mathcal{K}}^*} < \infty$, by Riesz Representation Theorem, $v_{w,L,x} = L_x K(\cdot, \mathbf{x}) - \mathbf{w}^T(\mathbf{x})\mathbf{k}(\cdot)$ with error estimate $\|\xi_{w,L,x}\|_{\mathcal{F}_{\mathcal{K}}^*} = \|v_{w,L,x}\|_{\mathcal{F}_{\mathcal{K}}}$. By [5], the functional

is continuous on $\mathcal{F}_K$ if $L_x K$ exists and both, polynomial consistency and operator exactness are guaranteed. Finally, We define the power function:

$$\mathcal{P}_{K,L,X}^2(x) = \min \left\{ \|v_{w,K,L,X,x}\|_{\mathcal{F}_K}^2 : \mathbf{w} \in \mathbb{R}^n, \xi_{w,L,x} p = 0, p \in \Pi_{k-1}^d \right\} \quad (24)$$

The RKHS norm can be simplified as

$$\begin{aligned} \|v_{w,K,L,X,x}\|_{\mathcal{F}_K}^2 &= \langle v_{w,K,L,X,x}, v_{w,K,L,X,x} \rangle_{\mathcal{F}_K} \\ &= \xi_{w,L,y} \xi_{w,L,z} K(y,z)|_{y=z=x} \\ &= \langle L_x K(\cdot, \mathbf{x}) - \mathbf{w}^T(\mathbf{x}) \mathbf{k}(\cdot), L_x K(\cdot, \mathbf{x}) - \mathbf{w}^T(\mathbf{x}) \mathbf{k}(\cdot) \rangle_{\mathcal{F}_K} \\ &= \langle L_x K(\cdot, \mathbf{x}), L_x K(\cdot, \mathbf{x}) \rangle_{\mathcal{F}_K} - 2 \langle L_x K(\cdot, \mathbf{x}), \mathbf{w}^T(\mathbf{x}) \mathbf{k}(\cdot) \rangle_{\mathcal{F}_K} + \langle \mathbf{w}^T(\mathbf{x}) \mathbf{k}(\cdot), \mathbf{w}^T(\mathbf{x}) \mathbf{k}(\cdot) \rangle_{\mathcal{F}_K} \\ &= L_y L_z K(y,z)|_{y=z=x} - 2 \sum_{i=1}^n w_i(\mathbf{x}) L_x K(\mathbf{x}, \mathbf{x}_i) + \sum_{i,j=1}^n w_i(\mathbf{x}) w_j(\mathbf{x}) K(\mathbf{x}_i, \mathbf{x}_j) \\ &= L_y L_z K(y,z)|_{y=z=x} - \sum_{i=1}^n w_i(\mathbf{x}) L_x K(\mathbf{x}, \mathbf{x}_i) - \sum_{i=1}^l v_i L p_i(\mathbf{x}) \end{aligned}$$

(*Need to check this line since [6] cancels the third term.*)

The last two line are carried out by Eq (17).

Now we have an error estimate for functions in $\mathcal{F}_K$ of the form:

$$\begin{aligned} \|\xi_{w,L,x}\|_{\mathcal{F}_K^*} &= \sup_{\substack{f \in \mathcal{F}_K \\ \|f\|_{\mathcal{F}_K} \leq 1}} |\xi_{w,L,x}(f)| \\ \|\xi_{w,L,x}\|_{\mathcal{F}_K^*} &= \sup_{f \in \mathcal{F}_K} \frac{|\xi_{w,L,x}(f)|}{\|f\|_{\mathcal{F}_K}} \\ \|\xi_{w,L,x}\|_{\mathcal{F}_K^*} \|f\|_{\mathcal{F}_K} &\geq |\xi_{w,L,x}(f)| \\ \inf_{\substack{\mathbf{w} \in \mathbb{R}^n \\ \xi(\Pi_{k-1}^d)=0}} \|\xi_{w,L,x}\|_{\mathcal{F}_K^*} \|f\|_{\mathcal{F}_K} &\geq |\xi_{w^*,L,x}(f)| \\ \inf_{\substack{\mathbf{w} \in \mathbb{R}^n \\ \xi(\Pi_{k-1}^d)=0}} \|v_{w,K,L,X,x}\|_{\mathcal{F}_K} \|f\|_{\mathcal{F}_K} &\geq |\xi_{w^*,L,x}(f)| \\ \mathcal{P}_{K,L,X}^2(x) \|f\|_{\mathcal{F}_K} &\geq |\xi_{w^*,L,x}(f)| \end{aligned}$$

2.4 Growth Function

Growth function is defined as follows:

$$\rho_{k-1,D}(\mathbf{z}, X, \mu) := \sup Lp(\mathbf{z} : p \in \Pi_{k-1}^d, |p(\mathbf{x}_j)| \leq \|\mathbf{x}_j - \mathbf{x}\|_2^\mu, j = 1, \dots, n) \quad (25)$$

By [9], the dual form of ρ takes the form

$$\rho_{k-1,D}(\mathbf{z}, Z, \|\cdot\|) := \inf \left\{ \|\mathbf{w}\| : \mathbf{w} \in \mathbb{R}^n, \xi_{w,L,x} p = 0, p \in \Pi_{k-1}^d \right\} \quad (26)$$

$$S_{\mathbf{x},X} := \bigcup_{i=1}^N [\mathbf{x}, \mathbf{x}_i] \quad (27)$$

Then for $f : S_{\mathbf{x},X} \times S_{\mathbf{x},X} \rightarrow \mathbb{R}$.

3 Local Least Square Weights RBF-FD

3.1 Weight Constraint Setup

Rather than assuming a form for the solution, our goal is to approximate the operator through weights dual to u sampled at nodes. Suppose $m > n$ (for the case of $m < n$, refer to [1]), thus more center nodes than stencil nodes per stencil. Additionally, instead of assuming exactness of the form $L\phi_j(\mathbf{x}) = \sum_i^n w_i(\mathbf{x})\phi_j(\mathbf{x}_i)$ for $j = 1, \dots, m$ as in the classical RBF-FD, we define a residual function:

$$r_j(\mathbf{x}) := L\phi_j(\mathbf{x}) - \sum_{i=1}^n w_i(\mathbf{x})\phi_j(\mathbf{x}_i) \quad (28)$$

$$\mathbf{r}(\mathbf{x}) = L\boldsymbol{\phi}(\mathbf{x}) - \boldsymbol{\Phi}^T \mathbf{w}(\mathbf{x}), \quad \mathbf{w} : \mathbb{R}^n \rightarrow \mathbb{R}^n \text{ for } \mathbf{x} \in \Omega. \quad (29)$$

Suppose $\{p_i\}_{i=1}^l$ is a set of polynomials augmenting the radial basis functions. Let $\Pi_k = \text{span}\{p_i\}_{i=1}^l$ with polynomial degree up to k . We want to reproduce the operator exactly on the polynomial basis:

$$Lp_j(\mathbf{x}) := \sum_{i=1}^n w_i(\mathbf{x})p_j(\mathbf{x}_i) \text{ for } j = 1, \dots, l \quad (30)$$

$$L\mathbf{p}(\mathbf{x}) = \mathbf{P}^T \mathbf{w} \quad (31)$$

where $\mathbf{P}_{ij} := p_j(\mathbf{x}_i) \in \mathbb{R}^{n \times l}$. Thus, we have a constrained least squares problem in the form:

$$\begin{cases} \min J(\mathbf{w}(\mathbf{x})) := \min \frac{1}{2} \|\mathbf{r}(\mathbf{x})\|_2^2 & \text{for } \mathbf{x} \in \Omega \\ \text{subject to } \boldsymbol{\Phi}^T \mathbf{w} = L\mathbf{p} \end{cases} \quad (32)$$

We can solve this setup by defining the Lagrangian $\mathcal{L}$ for the problem as follows:

$$\begin{aligned} \mathcal{L}(\mathbf{w}, \boldsymbol{\nu}) &:= J(\mathbf{w}) + \langle \boldsymbol{\nu}, \mathbf{P}^T \mathbf{w} - L\mathbf{p}(\mathbf{x}) \rangle \\ &= \frac{1}{2} \langle \boldsymbol{\Phi}^T \mathbf{w}, \boldsymbol{\Phi}^T \mathbf{w} \rangle - \langle \boldsymbol{\Phi}^T \mathbf{w}, L\boldsymbol{\phi} \rangle + \frac{1}{2} \langle L\boldsymbol{\phi}, L\boldsymbol{\phi} \rangle \\ &\quad + \langle \boldsymbol{\nu}, \mathbf{P}^T \mathbf{w} - L\mathbf{p}(\mathbf{x}) \rangle. \end{aligned}$$

3.2 Consistency Conditions for Finite Spaces and Interpolation Results

The resulting KKT equations for this system are then:

$$\nabla_{\mathbf{w}} \mathcal{L} = 0 : \boldsymbol{\Phi} L\boldsymbol{\phi} = \boldsymbol{\Phi} \boldsymbol{\Phi}^T \mathbf{w} + \mathbf{P} \boldsymbol{\nu} \quad (33)$$

$$\nabla_{\boldsymbol{\nu}} \mathcal{L} = 0 : \mathbf{P}^T \mathbf{w} = L\mathbf{p} \quad (34)$$

The augmented matrix then takes the form:

$$\begin{bmatrix} \boldsymbol{\Phi} \boldsymbol{\Phi}^T & \mathbf{P} \\ \mathbf{P}^T & \mathbf{0} \end{bmatrix} \begin{bmatrix} \mathbf{w} \\ \boldsymbol{\nu} \end{bmatrix} = \begin{bmatrix} \boldsymbol{\Phi} L\boldsymbol{\phi} \\ L\mathbf{p} \end{bmatrix} \quad (35)$$

From [6], Equation (35) has a unique solution given $L\mathbf{p} \in \text{Range}(\mathbf{P}^T)$. The primary goal is to approximate $Lu(\mathbf{x}) \approx \mathbf{w}^T(\mathbf{x})\mathbf{u}$, with $\mathbf{u} = [u(\mathbf{x}_1), \dots, u(\mathbf{x}_n)]^T$. Define $L_h f(\mathbf{x}) := \mathbf{w}^T(\mathbf{x})\mathbf{f}$ for some

function f . Thus, we have the following:

$$\begin{aligned}
L_h f(x) &= \mathbf{w}^T(x) \mathbf{f} \\
&= [\mathbf{w}^T \quad \boldsymbol{\nu}^T] \begin{bmatrix} \mathbf{f} \\ \mathbf{0} \end{bmatrix} \\
&= \left(\begin{bmatrix} \boldsymbol{\Phi} \boldsymbol{\Phi}^T & \mathbf{P} \\ \mathbf{P}^T & \mathbf{0} \end{bmatrix}^{-1} \begin{bmatrix} \boldsymbol{\Phi} L \phi \\ L \mathbf{p} \end{bmatrix} \right)^T \begin{bmatrix} \mathbf{f} \\ \mathbf{0} \end{bmatrix} \\
&= [L \phi^T \boldsymbol{\Phi}^T \quad L \mathbf{p}^T] \begin{bmatrix} \boldsymbol{\Phi} \boldsymbol{\Phi}^T & \mathbf{P} \\ \mathbf{P}^T & \mathbf{0} \end{bmatrix}^{-T} \begin{bmatrix} \mathbf{f} \\ \mathbf{0} \end{bmatrix} \\
&= [L \phi^T \boldsymbol{\Phi}^T \quad L \mathbf{p}^T] \begin{bmatrix} \mathbf{q} \\ \boldsymbol{\alpha} \end{bmatrix} \\
&= L \phi^T(x) (\boldsymbol{\Phi}^T \mathbf{q}) + L \mathbf{p}^T(x) \boldsymbol{\alpha}
\end{aligned}$$

Next, we can show that the coefficients $\mathbf{q}, \boldsymbol{\alpha}$ relate to the coefficients of u as follows:

$$\begin{bmatrix} \mathbf{f} \\ \mathbf{0} \end{bmatrix} = \begin{bmatrix} \boldsymbol{\Phi} \boldsymbol{\Phi}^T & \mathbf{P} \\ \mathbf{P}^T & \mathbf{0} \end{bmatrix} \begin{bmatrix} \mathbf{q} \\ \boldsymbol{\alpha} \end{bmatrix} \quad (36)$$

Define $V_h = \{\rho(x) : \rho(x) = \sum_{i=1}^m \lambda_i \phi_i(x) \text{ such that } \lambda \in \text{Range}(\boldsymbol{\Phi}^T)\} \subseteq V_Y$. Let $s \in V_h + \Pi_k$. Thus, $s(x) = \phi^T(x) \boldsymbol{\Phi}^T \mathbf{q} + \mathbf{p}^T(x) \boldsymbol{\alpha}$ where $\mathbf{q} \in \mathbb{R}^n$ and $\boldsymbol{\alpha} \in \mathbb{R}^l$. Then:

$$\mathbf{s} = s(X) = \boldsymbol{\Phi} \boldsymbol{\Phi}^T \mathbf{q} + \mathbf{P} \boldsymbol{\alpha} = f(X) = \mathbf{f} \quad (37)$$

$$\mathbf{P}^T \mathbf{q} = \mathbf{0} \quad (38)$$

Hence, we get interpolation of f at the node set X . Furthermore, from the KKT matrix we can show that $\boldsymbol{\Phi} \mathbf{r} = \mathbf{P} \boldsymbol{\nu}$ which implies that $\boldsymbol{\Phi} \mathbf{r} \in \text{range}(\mathbf{P}) = (\ker(\mathbf{P}^T))^\perp$. Thus, we get the relationship:

$$\mathbf{r}^T (\boldsymbol{\Phi}^T \mathbf{z}) = \mathbf{0} \text{ for } \mathbf{P}^T \mathbf{z} = \mathbf{0} \quad (39)$$

Finally, we check the consistency error for $s \in V_h + \Pi_k$ with $\mathbf{P}^T \mathbf{q} = \mathbf{0}$.

$$\begin{aligned}
Ls(x) - L_h s(x) &= L(\phi^T(x) \boldsymbol{\Phi}^T \mathbf{q} + \mathbf{p}^T(x) \boldsymbol{\alpha}) - \mathbf{w}^T(x) \mathbf{s} \\
&= L \phi^T(x) \boldsymbol{\Phi}^T \mathbf{q} + L \mathbf{p}^T(x) \boldsymbol{\alpha} - \mathbf{w}^T(x) (\boldsymbol{\Phi} \boldsymbol{\Phi}^T \mathbf{q} + \mathbf{P} \boldsymbol{\alpha}) \\
&= L \phi^T(x) \boldsymbol{\Phi}^T \mathbf{q} + L \mathbf{p}^T(x) \boldsymbol{\alpha} - \mathbf{w}^T(x) \boldsymbol{\Phi} \boldsymbol{\Phi}^T \mathbf{q} - \mathbf{w}^T(x) \mathbf{P} \boldsymbol{\alpha} \\
&= (L \phi(x) - \boldsymbol{\Phi}^T \mathbf{w}(x))^T \boldsymbol{\Phi}^T \mathbf{q} + (L \mathbf{p}^T(x) - \mathbf{P}^T \mathbf{w}(x))^T \boldsymbol{\alpha} \\
&= \mathbf{r}^T \boldsymbol{\Phi}^T \mathbf{q} + (L \mathbf{p}(x) - \mathbf{P}^T \mathbf{w}(x))^T \boldsymbol{\alpha}
\end{aligned}$$

$$Ls(x) - L_h s(x) = 0 \text{ due to (34) and (39)} \quad (40)$$

3.3 Consistency Results for Function Approximations

Let u be a solution to (1) and $s \in V_h + \Pi_k$. We can say $u = s + (u - s)$ to get the following:

$$\begin{aligned}
\mathcal{E}[u](\mathbf{x}) &:= Lu(\mathbf{x}) - L_h u(\mathbf{x}) \\
&= Lu(\mathbf{x}) - \mathbf{w}^T(\mathbf{x})\mathbf{u} \\
&= L((u - s) + s)(\mathbf{x}) - \mathbf{w}^T(\mathbf{x})\mathbf{u} - L_h s(\mathbf{x}) + L_h s(\mathbf{x}) \\
&= L(u - s)(\mathbf{x}) + (Ls(\mathbf{x}) - L_h s(\mathbf{x})) + L_h(s - u)(\mathbf{x}) \\
&= L(u - s)(\mathbf{x}) - \mathbf{w}^T(\mathbf{x})(\mathbf{u} - \mathbf{s}), \text{ by (40)} \\
&= Le(\mathbf{x}) - \mathbf{w}^T(\mathbf{x})e, \quad e(\mathbf{x}) = u(\mathbf{x}) - s(\mathbf{x}) \\
&= \mathcal{E}[e](\mathbf{x})
\end{aligned}$$

References

- [1] Slak, J. (2026). *Adaptive RBF-FD method*. PhD Thesis, University of Ljubljana. <https://e6.ijs.si/~jsslak/files/phd.pdf>
- [2] Agmon, S., Douglis, A. and Nirenberg, L. (1959). *Estimates near the boundary for solutions of elliptic partial differential equations satisfying general boundary conditions*. I. Comm. Pure Appl. Math., 12: 623–727.
<https://doi.org/10.1002/cpa.3160120405>
- [3] Petras, A., Ling, L., Piret, C. and Ruuth, S. J. (2018). *A least-squares implicit RBF-FD closest point method and applications to PDEs on moving surfaces*. Journal of Computational Physics, 363: 94–114.
<https://doi.org/10.1016/j.jcp.2018.02.023>
- [4] Beatson, R., Davydov, O. and Levesley, J. (2009). *Error bounds for anisotropic RBF interpolation*. Journal of Approximation Theory, 162(1): 1–20.
- [5] Davydov, O. (2025). *Error bounds for numerical differentiation using kernels of finite smoothness*. November 15, 2025.
- [6] Davydov, O. (2020). *Approximation with Conditionally Positive Definite Kernels on Deficient Sets*. arXiv preprint arXiv:2006.13543.
<https://arxiv.org/abs/2006.13543>
- [7] Flyer, N., Fornberg, B., Bayona, V. and Barnett, G. A. (2016). *On the role of polynomials in RBF-FD approximations: I. Interpolation and accuracy*. Journal of Computational Physics, 321: 21–38.
<https://doi.org/10.1016/j.jcp.2016.05.026>
- [8] Bayona, V. (2019). *An insight into RBF-FD approximations augmented with polynomials*. Computers & Mathematics with Applications, 77(9): 2337–2353.
<https://doi.org/10.1016/j.camwa.2018.12.029>
- [9] O. Davydov and R. Schaback. *Minimal numerical differentiation formulas*. Numerische Mathematik, 140(3):555–592, 2018.
<https://num.math.uni-goettingen.de/schaback/research/papers/MNDF.pdf>
- [10] D. T. Oanh, O. Davydov, and H. X. Phu. Adaptive RBF-FD method for elliptic problems with point singularities in 2D. Preprint, 2016.
- [11] R. Schaback. Error analysis of nodal meshless methods. Preprint, 2016.
- [12] B. Seibold. M-Matrices in Meshless Finite Difference Methods. Dissertation, University of Kaiserslautern, 2006.
- [13] B. Seibold. Minimal positive stencils in meshfree finite difference methods for the Poisson equation. Comput. Methods Appl. Mech. Eng., 198(3-4):592–601, 2008.
- [14] H. J. Stetter. Analysis of Discretization Methods for Ordinary Differential Equations. Springer, New York, 1973.

4 Appendix

Tasks: Define my new RKHS.

Define my reproducing Kernel

- Simplify to the discrete case
quadrature rule form
- Show conditions for being PSD and PD.
- Show or state is reproducing property. Convergence guaranteed

Discrete Quadrature
cannot increase approximation capacity.

Discrete RKHS:

→ Smaller subspace for N nodes instead T

→ Show conditions for nonsingularity
 $\lambda \in \text{range}(\mathbb{Q}^T) \cap \text{Ker}(\mathbb{R}^T)$

→ Scheme degenerates to standard RK-FD when $X=Y$

→ $\lambda_{\min}(\mathbb{G})$ improves, eigenvalues increase monotonically.

Final why $\mathbb{G}$ is nondecreasing in the Loewner order.

$$\mathcal{H}_K(u_i) \subseteq \mathcal{H}_K(u_{i+1})$$

$\mathbb{G} \mapsto \mathbb{G} + \mathbb{V} \mathbb{V}^T$ monotonically.

→ stable for fixed $\mathbb{Q}$ & $\mathbb{R}$, degrades for PHS with Expanding $\mathbb{Q}$ & $\mathbb{R}$.

9/21/26

The RKHS starts from functions $\phi \in H^2$

Then define the kernel in the form of

$$K(x, y) = \int \phi(x-z) \phi(y-z) dz$$

By Moore-Aronszajn, K is a proper kernel for an RKHS,

Theorem: Suppose K is a symmetric, p.d. kernel on a set X . Then there is a unique Hilbert space of functions on X for which K is a reproducing kernel

* Define RKHS explicitly,

Show it is positive Definite on $\mathcal{Y}$:

$$G_{\infty} := [K(y_i, y_j)]$$

$$C^T G_{\infty} C = 0 \Rightarrow \sum_k C_k \phi(y_k - z) = 0 =: F(z)$$

Then $C K = 0$ ~~more~~. This starts from

$$K(x, y) = \int \phi(x-z) \phi(y-z) dz$$

$$C^T G_{\infty} C = \sum_{ij} \bar{C}_i C_j K(x_i, y_j)$$

$$= \int_{\Omega^c} \sum_i \bar{C}_i C_j \phi(y_i - z) \phi(y_j - z) dz$$

$$= \int_{\Omega^c} |\sum_i \bar{C}_i \phi(y_i - z)|^2 dz = \int_{\Omega^c} |F(z)|^2 dz$$

Suppose $d \geq 2$, y_i 's are distinct, ϕ is real analytic on $\mathbb{R}^d \setminus \{y_0\}$,
 Ω^c contains non-empty open subsets.
 F variables $\rightarrow$

$F(z) = \sum_k C_k \phi(y_k - z)$ is real analytic on $D = \mathbb{R}^d \setminus \{y_1, \dots, y_k\}$

$\rightarrow D$ is still connected, then
 $F \equiv 0$ on D . (real-analytic identity theorem).

F is continuous, then
 $F(z) = 0 \forall z \in \Omega^c$.

* Do not need y_i 's so far inside the open ball.

Order: ϕ is continuous, then K_{Ω^c} is p.s.d (1)

And if Mercer's theorem applied, then
 K_{Ω^c} is injective and hence,
 $H_{K_{\Omega^c}} \cong L^2(\Omega^c)$. (2)

And if ϕ is real analytic away from $d \geq 2$,
 then $G_{\Omega^c} \succ 0$ on set of nodes.

Through injectivity, $K_{\Omega^c} \succ 0$, and not
~~matrix~~ augmentation required.

$\rightarrow$ form Diagonal D
 $K_M = \sum_{i=1}^M w_i \phi(x-z_i) \phi(y-z_i)$ via quadrature

$\hookrightarrow$ Show this converges to K

$$K_M \xrightarrow{M \rightarrow \infty} K.$$

Node Subspace: $T_M := \text{span} \{K_M(\cdot, y_k)\}_{k=1}^N$

$$G_M = \tilde{\Phi} D \tilde{\Phi}^T$$

$$\dim(T_M) = \text{rank}(G_M) = \text{rank}(\tilde{\Phi}).$$

$$T_M \neq \mathcal{H}_{K_{\text{osc}}}, \text{ best}$$

$$T_M \rightarrow T_{\infty} \subset \mathcal{H}_{K_{\text{osc}}}$$

$\tilde{\Phi}$ has full row rank and W is invertible
 then $G_M \succeq 0$. From how G_M is defined
 and by $K_M \rightarrow K$, then
 $G_M \rightarrow G_{\infty}$.

By Wey's Eigenvalue inequality,

$$\lambda_{\min}(G_M) \geq \lambda_{\min}(G_{\infty}) - \|G_M - G_{\infty}\|_2 > 0.$$

For $f \in T$, exact reproduction. We do
 have $w_M \rightarrow w_{\infty}$. Then there is
 error $w_M^T(x)f - w_{\infty}^T f$ added to the
 convergence analysis given the new RKHS
 norm. The first term with the infinite
 w_{∞} , turns into the standard
 power function. The second is dependent on
 $M \rightarrow \infty$.

In regards to stability $\lambda_{\min}(G_M) \geq \lambda_{\min}(G_0) - \epsilon_M$

$$\|W_M\|_2 \leq \|G_M^{-1}\|_2 \|b_M\|_2$$

$$\leq \frac{\|b_M\|_2}{\lambda_{\min}(G_M)}$$

$$\leq \frac{\|b_M\|_2}{\lambda(G_0) - \epsilon_M} \quad \text{have } \epsilon_M \sim C_x h_x^q?$$

Although...
nevermind, it does work...

$$\begin{aligned} \phi(x-z)\phi(y-z) &= e^{-\epsilon(\|x-z\|^2 + \|y-z\|^2)} \\ &= e^{-\epsilon(\|x\|^2 - 2\|x\|\|z\| + \|z\|^2 + \|y\|^2 - 2\|z\|\|y\| + \|z\|^2)} \\ &= e^{-\epsilon(\|x\|^2 - 2(\|x\| + \|y\|)\|z\| + \|y\|^2 + 2\|z\|^2)} \\ &= e^{-\epsilon(\|x\|^2 - 2(\|x\| + \|y\| - \|z\|)\|z\| + \|y\|^2)} \\ &= e^{-\epsilon(\|x\|^2 - 2(\|x\| + \|y\| - \|z\|)\|z\| + \|y\|^2)} \end{aligned}$$

$$\text{if } \|z\| = \|y\| \Rightarrow$$

~~approximation~~

$$= e^{-\epsilon\|x-y\|^2}, \text{ the standard method.}$$