

X1 Carbon — Specifications

Figures below are from Bambu Lab's [X1-Carbon technical specifications PDF](#) and the [X1 Series wiki](#) AMS 2 Pro figures are from the [AMS 2 Pro store specs](#) and [AMS 2 Pro intro and connection guide](#).

Printer (X1 Carbon)

Item	Official value
Technology	Fused Deposition Modeling
Build volume (W×D×H)	256 × 256 × 256 mm³
Chassis	Steel
Shell	Aluminum & glass (enclosed)
Motion	CoreXY (X/Y steppers and belts); Z via three lead screws and one stepper
Hotend	All-metal
Extruder gears	Hardened steel
Nozzle (included)	Hardened steel, 0.4 mm
Nozzle (optional)	0.2 mm, 0.6 mm, 0.8 mm
Max hotend temperature	300 °C
Filament diameter	1.75 mm

Filament not supported	TPE, generic TPU, PVA (damp), BVOH (damp), Bambu PET-CF / TPU 95A, and other filament that contains carbon fiber or glass fiber	Store specs
RFID	Supported; official Bambu tags enable remaining-filament estimation and auto filament backup	Store specs intro and connection guide
Drying modules	Two modules (heaters, fans, temperature sensors); highest temperature 65 °C	Store specs intro and connection guide
Active moisture discharge	Supported (actively controlled intake/exhaust vents)	Store specs
Sealed storage	Supported	Store specs
Temperature & humidity	Real-time display on the printer screen, Bambu Studio, and Bambu Handy	Store specs
Power input (drying)	24 V 4 A official Switching Adapter	Store specs
X1C drying power	X1C cannot power AMS 2 Pro drying. Each AMS 2 Pro used for drying needs its own official Switching Adapter. Power icon on Drying and Humidity should be green.	X1C drying from screen store FAQ
X1C connection	Filament buffer + PTFE + 4-pin (printer to buffer) + 6-pin (AMS 2 Pro to buffer). Users should not rewire; contact Ryan if disconnected.	Install AMS 2 Pro on X1C intro and connection guide
Multi-AMS on X1	Filament buffer is replaced by an AMS Hub; X1/P1 can connect up to 4 AMS units (AMS, AMS 2 Pro, AMS HT)	Store install wiki
Firmware	Drying on X1C requires firmware that supports AMS 2 Pro drying	X1 firmware update

Filaments the store marks with * for drying (ABS, ASA, PET, PA, PC, PVA, BVOH, POM, HIPS, Bambu PLA-CF / PAHT-CF / PETG-CF, TPU for AMS) need a higher drying temperature than AMS 2 Pro can fully provide. Bambu recommends AMS HT for better drying of those materials. Maximum 65 °C is only achievable when ambient temperature is above 25 °C.

TPU is listed as supported **on the X1C printer**, but generic TPU is **not** supported in AMS 2 Pro. Use **TPU for AMS** in the unit, or the rear spool holder for generic TPU.

Whether the shop Switching Adapter is currently plugged in is not recorded here. Drying requires the official adapter; if the power icon is not green, ask Ryan.

Notes & references

- [Bambu Lab X1-Carbon technical specifications \(PDF\)](#)
- [X1 Series wiki](#)
- [Introduction to X1/X1C](#)
- [Install AMS 2 Pro on X1C](#)
- [Use AMS 2 Pro drying from the X1C screen](#)
- [AMS 2 Pro intro and connection guide](#)
- [AMS 2 Pro drying function](#)
- [AMS 2 Pro drying on X1/P1 series](#)
- [AMS 2 Pro basic maintenance](#)
- [AMS 2 Pro product specs](#)
- [X1 firmware update for AMS 2 Pro / AMS HT](#)
- [Bambu Studio download](#)