Arcadance User Manual

version 0.2.47

1. Welcome

Arcadance turns a game controller into a MIDI instrument and, above all, a MIDI looper: sticks, triggers and the touchpad send continuous controllers (CC), buttons play notes and chords, and every channel can carry its own layout. It runs as a standalone program next to your DAW or synthesizer and sends MIDI to any port on your system.

Arcadance was designed around the Sony DualSense (PlayStation 5) controller, whose touchpad tracks two fingers. Xbox, Nintendo and other controllers recognised by SDL3 work too: Arcadance names their buttons as printed on them and leaves out what a controller lacks (chapter 5). A controller with motion sensors also plays when you tilt it.

A MIDI looper in your hands

Looping is what Arcadance does best. Hold one button, play, release: what you just played repeats at once, in time with itself, and your hands are free again to play over it. No DAW recording, no clip to set up, no bar count to choose beforehand.

- **Loop notes and chords:** a chord progression, a bass line or a riff played on the buttons, the D-pad or the touchpad pads loops with its exact timing and velocity.
- **Loop movements:** a stick gesture, a trigger squeeze or a finger slide on the touchpad loops as a CC curve, a hand-drawn LFO for a filter, a pan or an effect send.
- **Layer a whole arrangement:** each of the sixteen MIDI channels has its own loops, and all of them play together. Loop chords on channel 1, switch to channel 2 and loop a bass line, then add a filter sweep on top.
- **Keep playing live:** movement loops play on CCs of their own, beside the control that recorded them, so the stick or finger stays free to play live over its own loop.
- **Shape it as you go:** add notes with overdub, play loops forwards, backwards or back and forth, pause and restart every loop at once with Play and Stop, and, with Shift, stretch a movement loop up to 100 times longer or 20 times shorter, or narrow its swing, while it plays, and lock a loop so that Record keeps it.

Because the loops are plain MIDI, they drive any instrument: a plugin in your DAW, a standalone synthesizer or a hardware synth on a MIDI interface. Chapter 9 explains looping in detail.

What you can do with Arcadance

- **Play notes and chords** from the face buttons, the D-pad, the shoulder buttons and the four zones of the touchpad, momentarily or latched (toggle).
- **Sculpt sounds** with the two sticks, the analog triggers L2/R2 and two touchpad fingers, each sending a CC with its own range and direction.
- **Freeze** a stick at its current value, so a filter or effect stays put while your hands do something else.

- **Record loops** of notes and movements on every channel, and layer them live (see above); lock the ones to keep, and keep up to eight clips per channel, launched in time from the session screen, played in chains, and laid out into a whole song on the song screen.
- **Play in time** with Arcadance's own clock, or with your DAW through Ableton Link: loops snap to whole beats or bars, their notes onto a grid if you like, and follow the tempo, which you can set, type or tap. Or play free.
- **Edit loop notes** in a large piano roll: move a note, a chord or a selection (onto the scale if you like), change their length, or delete them, and shorten or lengthen the loop, without recording again.
- **Save sessions**: every channel's clips and chains, the song, the preset, the tonality and the tempo in one file, to open again later; New Song starts an empty one.
- **Switch MIDI channels** on the fly, each channel with its own mapping, so one controller drives a whole multitimbral setup.
- Give every button a second meaning with a Shift layer: while a Shift button is held or latched, the buttons, the D-pad and the touchpad pads play their Shift mapping.
- **Change programs** on your synthesizer from a button or by sweeping a stick through a range of presets.
- **Humanize** velocity and timing for a less mechanical feel.
- Choose a theme: the default one, or Phosphor Blue and Phosphor Green, lines on black in the light tint of an 80s monochrome screen.
- Let a movement loop modulate the amplitude of others, each at its own pace, or move a loop up or down; mute or solo channels on the session screen; tilt the controller to move two more controls, and loop them.

Who this manual is for

This manual assumes you know what MIDI notes, channels and CCs are, and that you have a DAW or synthesizer on your computer. It does not assume you have used Arcadance before: chapters 2 and 3 take you from installation to your first sound, and the later chapters describe every part of the window in order.

The manual describes Arcadance on **Linux**. Notes for Windows and macOS will appear in boxes marked *Windows* and *macOS* when those versions are available.

Conventions

Notation	Meaning
Options	A label, button or menu entry as it appears on screen
☰ › **Settings**	A menu path: open the ☰ menu, then choose Settings
`Ctrl+S`	A keyboard shortcut
Cross, Circle, Square, Triangle	The DualSense face buttons (A, B, X, Y on other controllers)

Notation	Meaning
L1/R1, L2/R2, L3/R3	Shoulder buttons, analog triggers, stick clicks
CC 40	MIDI Control Change number 40
C4 = 60	Note names: middle C is C4, MIDI note 60

> **Note:** boxes like this one give tips and details you can skip on a first reading.

2. Installation on Linux

The quickest way to install Arcadance is the **AppImage**, a single file that runs on most Linux distributions (Ubuntu 22.04 or newer, Debian 12, Fedora and others):

1. Download `Arcadance-0.2.44-x86_64.AppImage` from the releases page. A `.tar.gz` archive with the plain program is attached too.
2. Make it executable and start it (next section).

```
chmod +x Arcadance-0.2.44-x86_64.AppImage
```

To build Arcadance from source instead, you only need a compiler and the ALSA headers: the build downloads its own libraries, and takes about five minutes on a recent machine.

Building from source: requirements

Item	Version or package
Compiler	C++20: GCC 13 or newer (tested), or a recent Clang
Build tools	CMake 3.25 or newer, Ninja, Git
ALSA headers	`libasound2-dev` (Debian, Ubuntu), `alsa-lib-devel` (Fedora)
JACK	Optional
Controller	DualSense over USB or Bluetooth; any SDL3 gamepad without touchpad

On Debian or Ubuntu, install everything in one command:

```
sudo apt install build-essential cmake ninja-build git libasound2-dev
```

Building

1. Get the source code and enter its folder.
2. Configure, build and (optionally) run the tests:

```
cmake --preset release
cmake --build --preset release
ctest --preset release
```

The program is created at `build/release/src/app/arcadance`. You can start it from there, or copy it to a folder on your `PATH`, such as `~/.local/bin`.

Giving Arcadance access to the touchpad and motion sensors

The sticks, triggers and buttons work as soon as the controller is connected. The DualSense touchpad and motion sensors are read directly from the device (`/dev/hidraw*`), which needs a udev rule. Without it, Arcadance works but the TOUCHPAD module stays inactive and there is no tilt, and Arcadance tells you so when the controller connects.

Create the file `/etc/udev/rules.d/70-dualsense.rules` with this content:

```
# USB
KERNEL=="hidraw*", SUBSYSTEM=="hidraw", ATTRS{idVendor}=="054c",
ATTRS{idProduct}=="0ce6", MODE="0666"
# Bluetooth
KERNEL=="hidraw*", SUBSYSTEM=="hidraw", KERNELS=="0005:054C:0CE6.*", MODE="0666"
```

Then reload the rules and reconnect the controller:

```
sudo udevadm control --reload-rules && sudo udevadm trigger
```

Connecting the controller

- **USB:** plug in the cable. The controller is ready at once.
- **Bluetooth:** hold **Create** and the **PS** button until the light bar flashes, then pair *DualSense Wireless Controller* in your system's Bluetooth settings.

Arcadance finds the controller whether you connect it before or after starting the program. The status bar at the bottom right of the window shows its name and a green dot when it is connected.

First launch

Start Arcadance:

```
./Arcadance-0.240-x86_64.AppImage
```

If you built it yourself, start `build/release/src/app/arcadance` instead. In this manual, `arcadance` on a command line stands for either.

On the very first launch, Arcadance does not know where to send its MIDI yet, so the **MIDI output** window asks you to choose a port. Chapter 3 explains which one to pick. Until you choose, Arcadance sends to its own virtual port, named *Arcadance*.

> **Note:** Arcadance keeps reading the controller while its window is in the background, so you can play while your DAW has the focus.

> **Windows / macOS:** installation notes will be added with those versions.

Coming from MidiPad

Arcadance was called MidiPad until version 0.238. On its first start, Arcadance takes your settings, presets and sessions over: it copies the folder `~/.local/share/MidiPad/MidiPad` to `~/.local/share/Arcadance/Arcadance` (unless Arcadance already has settings there), marks the presets of its presets folder as Arcadance presets, and renames the sessions from `.midipad` to `.arcadance`. This happens once; the MidiPad folder stays as it was. Preset and session files made by MidiPad still open.

The virtual port keeps the name you had, *MidiPad*, so the connections of your DAW still work; a new installation calls it *Arcadance*.

3. Quick start


Five steps take you from a fresh installation to playing a synthesizer in your DAW: connect, choose an output, set up a track, play, save.

Step 1: connect the controller and start Arcadance

Connect the DualSense by USB or Bluetooth, then start Arcadance. The green dot at the bottom right confirms that the controller is seen.

Step 2: choose where the MIDI goes

On the first launch, the **MIDI output** window lists every MIDI port on your system.



Pick the port your DAW can read:

- **Virtual port "Arcadance"**: a software port. DAWs that use the ALSA sequencer or JACK (Reaper, Ardour, Qtractor) see it directly as an input named *Arcadance*.
- **VirMIDI ports**: kernel MIDI ports, seen by every program, including those that only list hardware devices. Choose **VirMIDI 0-0**, then select the input shown on the right (*Virtual Raw MIDI*) in your DAW. If no VirMIDI port exists, the window offers to create them (see chapter 11).
- **Later**: keep the virtual port for now; the question comes back at the next start.

Arcadance remembers your choice and reconnects to the same port at every start. You can change it at any time in ☰ › **Settings**.

> **Tip:** if you are unsure, start with VirMIDI 0-0. It works with every DAW on Linux.

Step 3: set up a track in your DAW

1. Create an instrument track with a synthesizer.
2. Set the track's MIDI input to the port chosen in step 2, on all channels or channel 1.
3. Arm or monitor the track so it plays what it receives.

Step 4: play

- Press **Cross**: the chord shown under the Cross pad sounds. The pad lights up while the chord plays.
- Move the **left stick**: it sends CC 40 (left-right) and CC 41 (up-down). Use your DAW's MIDI learn to assign them to a filter cutoff or any parameter.
- Press a **D-pad** direction: in the demo preset, Up, Right, Down-left and Left latch chords (press again to stop them).

Every change you hear is also shown in the window: the stick's screen follows your thumb, the CC pills light up, and the piano roll scrolls the notes you play.

Step 5: make it yours and save

Click any control in the window to change what it sends: a pad, a D-pad row, a CC pill, a module's screen. Chapter 6 describes these mapping windows. When you are happy, press `Ctrl+S` or click **Save preset**.

> **Note:** changes are heard at once but written to disk only when you save. Unsaved changes are kept if you only switch channels; Arcadance asks before discarding them when you open another preset or quit.

4. The main window

Arcadance has a single window that plays and edits at the same time: every module mirrors a part of the controller, shows what it sends, and opens its settings when you click it. The window is built for the stage, so everything you need while playing is one click away.

The screenshots in this manual use a preset called *Electronica Demo*, in F minor, with loops playing.



#	Area	What it does
1	☰ menu	New Song, Open, Save, Save as (sessions), Settings, Themes, Fullscreen (F11), About, Quit (Ctrl+Q)
2	Preset menu	Opens, creates, saves and deletes presets; arrows load the previous or next preset
3	Play / Stop	Plays or pauses the clips of every channel, or, on the song screen, plays the song from the section chosen and stops it; Play turns green while something plays, and does nothing then. With Ableton Link, they can also start and stop the Link session

#	Area	What it does
4	Clock (LINK / CLOCK)	FREE without a clock; otherwise the tempo of the internal clock or of the Link session (with the number of Link peers) and the beats of the bar. The wheel or a double-click on the tempo changes it; a click elsewhere turns the clock off or back on
5	TAP	Tap tempo: tap in time and the clock's tempo follows, from the second tap
6	Session	Shows the session screen, the clips of every channel, in place of the modules (Tab, which then goes on to the song screen); lit green while it shows, violet and reading EDIT in the edit mode
7	PANIC	Silences everything at once: all notes off, loops stopped, delayed notes dropped
8	LEFT STICK	Stick position, its CCs, the stick-click (L3) action and its loop
9	RIGHT STICK	The same for the right stick (R3)
10	TRIGGERS	L2 and R2 travel, their CCs, their button actions and their loop
11	D-PAD	The eight directions, including diagonals, and what each plays
12	TOUCHPAD	Finger positions and their CCs, or the four pad zones, and the finger loops
13	Piano roll	The notes of the active channel, scrolling or as a loop clip
14	SCALE	The tonality; click to choose a root and a scale
15	CHANNEL	The active channel in large digits, with its name; its arrows or the wheel change the channel, a click opens its menu
16	Button strip	One pad per button: L1, L2, L3, Create, Cross, Circle, Square, Triangle, Options, PS, Touchpad click, Mute, R3, R2, R1
17	MIDI out	The port Arcadance sends to, and the name your DAW sees it under
18	Controller	The connected controller, and + touchpad when the touchpad is readable
19	Song	Shows the song screen, the sections of the song and what each channel plays in them (chapter 9); lit green while it shows. A click again goes back to the main screen

Reading the window

- **A green dot** in a module's header means the controller is connected and that part is active.
- **Pills** such as *X CC 40* show what an axis sends; they light up as the value moves. *inv* marks an inverted axis, *PC 1-16* an axis that selects programs.
- **Pads** in the button strip flash on every press and stay lit while their note or chord sounds. A latched (toggle) chord stays lit until released. The label under each pad shows its action: a chord name, a note, *Freeze*, *Ch +1*, *Rec*, *Shift*, *PC 1* and so on; - means nothing is assigned. While Shift is on, the pads, the D-pad rows and the touchpad zones show their Shift layer.
- **The ↻ icon** next to a D-pad chord marks a toggle: press once to start, again to stop.

Clicking to edit

Click a control to open its mapping window over the view: a pad, a D-pad row, a CC pill, a module's screen, a LOOP panel or the piano roll. On channel 1, the window edits channel 1's mapping, which every channel without its own plays; on another channel, your first change gives that channel its own mapping (chapter 8). The view keeps playing behind it, so you hear each change at once.

From the controller: edit mode, menus and help

Arcadance can be set up with the controller in your hands. Playing never changes a setting by accident: the controller drives the interface only in the session and song screens (chapter 9) and in the **edit mode**, which you open on purpose.

The buttons. The **Mode** action, given to a button in the mapping (chapter 6; PS / Guide without one), opens and closes these screens:

- **Mode:** the session screen; again, the song screen; again, back to the main screen. Back also leaves them.
- **Shift + Mode:** the edit mode, and back.
- **Mode held** half a second: the help of the screen you are on, with your own buttons; it goes when you let go.

Three more buttons drive these screens, chosen in ☰ › Settings › EDIT MENU (chapter 11): **Select** (launch, choose, open; L3 and R3 when none is chosen), **Menu** (the menu of what is under the cursor) and **Back** (close a menu, leave the edit mode). Select and Menu may be the same button: a press then opens the menu, and the same button chooses in it. There, they do this instead of their usual action; on the main screen they play as usual, so a button can play a chord and be Select in the session screen.

The edit mode. The session button of the top bar turns violet and reads **EDIT**, and a cyan cursor goes over the main screen: the lanes of the LOOP panels, the piano roll, the screens of the modules, their pills and rows, the pads.

- The **left stick** or the **D-pad** moves the cursor to the nearest item that way.
- The **right stick**, left or right, changes the channel, wherever the cursor is. Up or down, on a lane of a LOOP panel, it stretches or compresses that loop in time, as Shift and a stick do.
- **Select** opens what is under it, as a click: the window of a control, the note loop editor. In a window, the D-pad goes from field to field and Select changes the field; Back cancels a field being typed, then closes the window.
- **Menu** opens the menu of the item (below). **Back**, outside a window, leaves the edit mode, as Shift + Mode does.


The buttons that are not Select, Menu or Back still play.

Menus. A right-click, or Menu with the controller, opens a small menu beside the item, with what can be done to it:

- **A lane of a LOOP panel**: Lock or Unlock, Clear that axis, Back to 1x · 100%, Modulate the amplitude of..., Stop modulating, Send its CC: on or off (chapter 9), Settings...; the header of a panel: the same for all of its axes.
- **The piano roll**: Lock or Unlock the note loop, Edit the notes..., Clear.
- **The CHANNEL block**: Next channel, Previous channel, Rename..., Copy mapping from... (chapter 8).
- **A clip** in the session screen: Launch or Stop, Record here, Duplicate (into the first free slot), Add to the chain, Add to the song (the cell chosen on the song screen), Clear.
- **A step of a chain**: Start from here, Random (R), Silence (S), Insert a step, Delete the step, Empty it.
- **A channel** (the header of its column, or its stop, M and S buttons): Stop, Mute or Unmute, Solo or Solo off, Rename..., Copy mapping from..., Chain on or off; on the song screen, the header of a column: Mute, Solo, Rename.... The CHAIN cell at the end of the chain: Play or Stop the chain, Then: back to step 1, stop or chain B, Previous chain, Next chain, Duplicate, Rename..., Add to the song, Clear.
- On the song screen, a section: Play from here (or Go here, or Stop the song), Loop section, Loop song, Rename..., Length: fixed or = longest channel, Duplicate, Insert a section above, Move up, Move down, Delete. A cell: Edit, Clear, Copy, Paste. An item of a cell: Change..., start right after the one before or on a bar of its own, Move a bar left or right, After its repeats: silence or loop on, Make it a chain (or a clip), Duplicate, Delete; a silence, a bar or a beat longer or shorter.

With the controller, the D-pad or a stick goes up and down the menu (greyed items are skipped), Select chooses, Menu or Back closes it.


ARCADANCE
PRESET
Electronica Demo
LINK FREE
TAP
EDIT
PANIC
LEFT STICK
RIGHT STICK
TRIGGERS
D-PAD
TOUCHPAD
FROZEN
L2
R2
MIDI
X CC 40
Y CC 41 inv
L3 free
X CC 42
Y CC 43 inv
R3 frozen
L2 CC 50 button: -
R2 CC 51 button: -
Up Abmaj9
Up-right CC 46
Right Fm11
Down-right CC 47
Down CC 45
Down-left Ebadd9
Left Dbmaj7#11
Up-left CC 44
FINGER 1 X CC 60 Y CC 61
FINGER 2 X CC 62 Y CC 63
LOOP
B&F
FWD
LEFT STICK · loop Y
Lock
Clear Y
Back to 1x · 100%
Settings...
F natural minor
CHANNEL
1
KEYS



Themes

☰ › **Themes** changes the look of the window, at once, and Arcadance remembers it:

- **Default**: the panels and colours shown in this manual.
- **Phosphor Blue** and **Phosphor Green**: lines on black, in the tint of an 80s monochrome screen, blue or green, with bright frames and readable text. Phosphor Blue draws its blocks with cut corners; Phosphor Green with thin square frames over a grid in perspective.





The theme changes nothing to what Arcadance plays or sends. In the phosphor themes the colours draw closer to one another, so the clips playing stand out less than in the default theme.

5. Control modules

Each module stands for one part of the controller and has the same layout from top to bottom: an animated screen that follows your hands, a MIDI area showing what is sent, and a LOOP panel for the recorded movements.

Sticks

Each stick sends two CCs, one per axis. In the demo preset the left stick sends CC 40 (X) and CC 41 (Y), the right stick CC 42 and CC 43, with Y inverted so that pushing up raises the value. A new preset starts empty: every axis and button is unassigned until you set it.

- **Screen:** a glowing shape follows the stick. Its size grows with the distance from the centre.
- **Pills:** *X CC 40* and *Y CC 41 inv* show the CC numbers; *inv* marks an inverted axis.
- **Stick click row:** shows the action of L3 or R3, with *free* or *frozen* on the right.

A stick sends a value only when it changes, so a stick at rest adds no traffic.

Freeze

A button set to **Axis freeze** (L3 and R3 in the demo) holds the chosen axes at their current value: one press freezes, the next one releases. While frozen, the shape turns ice blue and keeps following your thumb, a ghost and a crosshair mark the frozen position, and the screen shows **FROZEN**. Bring the stick back to the crosshair before releasing if you want the value to continue smoothly.

Triggers

L2 and R2 are both analog axes and buttons. As axes they send a CC over their whole travel (CC 50 and CC 51 in the demo). As buttons they can play a note, a chord or any other action: they press at 25 % of the travel and release at 15 %, so a light touch does not trigger them by accident.

The TRIGGERS module shows both travels side by side, the CC pill and the button action of each trigger, and a LOOP panel with both recorded curves.

D-pad

The D-pad plays eight directions: the four arrows and the four diagonals. Each row of the module shows a direction, its action and, for a toggle, the ↻ icon. The screen shows a 3D D-pad with the pressed direction raised in red, and the name of what it plays.

Your thumb never presses or releases the two arrows of a diagonal at exactly the same moment. To keep the arrow crossed on the way silent, a new direction plays only after it has stayed stable for a short time: 15 ms by default, adjustable in Settings. Releasing the whole D-pad stops the sound at once.

Touchpad

The DualSense touchpad tracks two fingers. Each finger works in one of three modes, chosen in the touchpad window:

Mode	What the finger does
Off	Nothing
X/Y position → CC	Sends two CCs: left-right and bottom-top (finger 1: CC 60/61, finger 2: CC 62/63 in the demo)
4 zones → pads	Splits the touchpad into four quarters; touching a quarter plays its note or chord

The screen shows each finger as a numbered dot. In pad mode it shows the four zones and lights the one being touched.

> **Note:** the touchpad needs the udev rule described in chapter 2. Without it, the module stays inactive and the status bar does not show *+ touchpad*.

Tilt

A controller with motion sensors (DualSense, DualShock 4, Switch Pro Controller…) sends two more controls when you tilt it: **X** when you lean it left or right, **Y** when you lean it towards you or forward. The tilt is off by default: turn it on in its window.



- **Where:** on a controller with a touchpad, the last column has two tabs, **TOUCHPAD · TILT**: click one to show it. Without a touchpad, the column is TILT. Without motion sensors, there is no tilt.
- **Screen:** a ball rolls in a dish towards the side that dips, larger as it comes towards you, smaller away from you. Dimmed, the tilt waits for its button; *OFF*, it is off.
- **Pills:** what X and Y send (CC 64 and CC 65 by default).
- **Row:** *while Mute held* or *always*, with *active* or *idle* on the right; *tilt off* when it is off.
- **LOOP:** the loops of the tilt, one lane for X and one for Y.

Click the screen, a pill or the row to open the **Tilt** window:



Setting	What it does
Enabled	Turns the tilt on or off (off by default)
Active	**Always**, or **While held**: only while the chosen button is held: L1, R1, L2, R2 or a D-pad arrow (L1 by default)
Angle	How far to lean for the whole range: 15° to 90° each way (45° by default)
Center	Takes the position the controller is held in now as the centre
X, Y	Each axis as a stick axis: CC, Program change, Velocity or Transpose, with its range and Invert (chapter 6)

The centre is where the controller was when the tilt first moved; **Center**, or a button set to **Recenter tilt**, takes it again. Released and held again, the tilt goes on from the value it had, without a jump.

In the list of buttons, the Shift button reads *(Shift)*: held for the tilt, it would be Shift too, and under Shift moving the controller records nothing (chapter 9). Turning the tilt on while its button is Shift picks the first free button instead.

> **Note:** like the touchpad, the motion sensors of a DualSense need the udev rule of chapter 2.

Other controllers

Arcadance recognises the controller connected and follows it:

Family	Face buttons (bottom, right, left, top)	Shoulders, triggers	Other buttons
PlayStation	Cross, Circle, Square, Triangle	L1, R1, L2, R2	Create, Options, PS, Mute
Xbox	A, B, X, Y	LB, RB, LT, RT	View, Menu, Xbox, Share
Nintendo	B, A, Y, X	L, R, ZL, ZR	Minus, Plus, Home, Capture
Other	Bottom, Right, Left, Top	L1, R1, L2, R2	Select, Start, Home

- Every name follows it: the button strip, the windows, the menus, the help, the TRIGGERS module and the loop lanes. Xbox buttons take their colours.
- Presets keep the buttons by place: what Cross plays on a DualSense, A plays on an Xbox controller and B on a Nintendo one.
- The button strip shows only the buttons the controller has, with its paddles (P1–P4). A module it has nothing for (sticks, triggers, a touchpad) is dimmed; its settings stay in the preset.
- Triggers without travel (ZL and ZR on most Nintendo controllers) go straight from 0 to 100 %.

Button strip

The strip at the bottom has one pad per button, in this order: L1, L2, L3, Create, Cross, Circle, Square, Triangle, Options, PS, Touchpad click, Mute, R3, R2, R1. The face buttons use their PlayStation colours. Click a pad to choose its action.

Piano roll, SCALE and CHANNEL


Below the modules, three blocks show the musical state of the active channel:

- **Piano roll**: the notes and chords played, scrolling towards the now line on the right; when a note loop runs, it turns into a clip of the whole loop; click it to open the note loop editor (chapter 9). A VEL chip beside the loop's length shows by how much a Velocity axis makes the note loop louder or softer (chapter 6).
- **SCALE**: the chosen tonality on a one-octave keyboard, with the notes of the scale lit. *no scale* means none is chosen. Click it to choose one (chapter 7).
- **CHANNEL**: the active channel in large digits, and its name if it has one. Click the arrows on its sides, or turn the wheel over it, to go to the previous or next channel; click its middle, or right-click it, for its menu: next, previous, Rename… (chapter 8).

6. Mapping windows

A mapping window sets what one control sends. Click a control in the main window to open it; the window floats over the view, which keeps playing, so you hear every change as you make it.

Anatomy of a mapping window




- **Title:** the control being edited (here *Cross*).
- **Scope line:** on channel 1, *Editing channel 1: every channel not changed on its own plays this mapping*; on another channel, *…it plays channel 1's mapping until you change it*, then *Editing the mapping of channel N (its own)*, with a **Use channel 1's mapping again** button (chapter 8). The note loop editor has none: a loop belongs to its channel.
- **Normal and Shift tabs** (buttons, D-pad directions and touchpad pads): what the control plays normally, and what it plays while Shift is on. The tab reads *Shift ** once something is set there.

- **Action:** the type of action; the fields below change with it.
- **Save preset** (`Ctrl+S`) writes the preset to disk. **Revert** reloads the saved version and discards your changes, once you confirm. **Close** (or `Esc`) closes the window and keeps your changes in memory.

The Shift layer

Every button, D-pad direction and touchpad pad has two layers. The **Normal** tab sets what it plays; the **Shift** tab sets what it plays while a Shift button is held, or latched in Toggle mode. A control whose Shift tab stays on *No action* plays its normal mapping under Shift too, so only the controls you set there change.



Give a button or a D-pad direction the **Shift** action to reach the layer (L1 in the demo); a Shift control has no Shift layer of its own. Each channel's mapping has its own layer. While Shift is on, the main window shows the layer on the pads, the D-pad and the touchpad, and the sticks and fingers reshape their loops instead of sending CCs (chapter 9).

A window opens on the layer shown last: after working on the Shift tab of one control, the next control you click opens on its Shift tab too. A control clicked while Shift is on opens on its Shift tab.

Button actions

Every button, D-pad direction, trigger (as a button) and touchpad zone can take one of these actions:


Action	Sends or does	Main settings
No action	Nothing	—
Note	One note	Note, Velocity, Mode, Humanize
CC	A Control Change	CC number, Value on press, Value on release, Mode
Chord	Several notes at once	Chord, Octave, Bass root, Velocity, Mode, Humanize
Transport	MIDI Start, Stop or Continue	Command
Channel change	Moves to the previous or next channel	Previous (-1) or Next (+1)
Axis freeze	Holds axes at their current value	Axes to freeze
Loop record	Records loops while held	— (see chapter 9)
Program change	Selects a program on the synthesizer	Program, Next or Previous, Bank select (chapter 10)
Shift	While on, the buttons, D-pad and touchpad pads play their Shift layer, and sticks and fingers reshape their loops	Mode (see The Shift layer above, and chapter 9)
Tap tempo	Sets the clock's tempo from your taps, from the second one	— (see chapter 9)
Mode	A press opens or closes the session screen; with Shift, the edit mode; held, the help (chapter 4)	— (see chapter 9); without one in the preset, PS / Guide does it
Recenter tilt	Takes the position the controller is held in now as the tilt's centre	— (see Tilt, chapter 5)
MIDI effect	Retrigger or Delay: plays the notes of the active channel again, several times, on the tempo	Effect, Retriggers or Echoes (1–16), Every (1/8 to 1/64, triplets), Velocity of each; for Delay, Transpose each echo and Mode

MIDI effects

A **MIDI effect** button plays the notes of the active channel again, on the tempo. Choose the **Effect**, **Retrigger** or **Delay**. Both repeat the notes 1 to 16 times (**Retriggers** or **Echoes**), one every **Every**: 1/8, 1/8 triplet, 1/16, 1/16 triplet, 1/32, 1/32 triplet or 1/64, on the beat clock or at the tempo set.

- **Retrigger**: a press takes every note sounding on the active channel at that moment, played live or by a loop, chords included, and ends and starts each again at every repeat. A note that ends meanwhile is no longer played again; a loop's note is played again as the loop's, so a muted channel stays silent. The button strip reads *Retrig ×4*.
- **Delay**: every note you play live on the active channel while the effect is on echoes. Each echo lasts as long as the note, at most 90 % of the time between two echoes. **Transpose each echo** moves each echo up or down by that many semitones more than the one before (+12: an octave, then two octaves). In **Momentary** mode the delay is on while the button is held; in **Toggle** mode a press turns it on, the next one off. The notes played by a loop never echo. The button strip reads *Delay ×4*.

Velocity sets the velocity of each repeat, in percent of the note's, from 5 to 200 % (the result stays between 1 and 127). Drag a bar up or down, or pick a shape: **Flat** (all at 100 %), **Fade out**, **Fade in** or **Accent** (every other repeat softer). A new repeat starts with the velocity of the last one.



While the note loop records or overdubs, the repeats of a note played live are recorded too: the loop plays the note in pieces, or with its echoes, as you heard it. Those of the loop's own notes are heard but

not recorded, so the loop never cuts its notes. In the piano roll, each repeat shows as a note of its own.

Mode: Momentary or Toggle


- **Momentary:** the note, chord or CC lasts as long as you hold the control. A CC sends *Value on press*, then *Value on release*.
- **Toggle:** the first press starts, the second stops. A latched note or chord keeps sounding with your hands free.

Toggles within one family of controls exclude each other: starting a latched chord on the D-pad stops the one already latched there. The families are the buttons, the D-pad, and each touchpad finger. CC toggles are always independent.


Velocity and Humanize

Velocity (1–127) sets how hard the note is played. The **Humanize** box lets this control follow the random velocity and timing set for its channel in Settings (chapter 11); the text beside it tells you whether humanization is active on any channel. Untick it to keep this control exact, for a kick drum for example.

Other button windows




Channel change steps through the sixteen channels, wrapping from 16 to 1. If the preset has a mapping for the new channel, it applies at once.



Axis freeze holds any combination of the six axes: left stick X/Y, right stick X/Y, L2 and R2. One press freezes, the next releases.

Axis windows

Click a stick's screen, the TRIGGERS screen or the TOUCHPAD screen to edit its axes together. Click a single pill (such as *X CC 40*) to edit that axis alone.




Each axis has these settings:

- **Enabled:** untick to silence the axis.
- **CC, Program change, Velocity or Transpose:** what the axis does. Program change is described in chapter 10, Velocity and Transpose below. The fields that follow are those of the CC mode.
- **CC:** the controller number (0–127).
- **Min and Max:** the value sent at each end of the travel. A Min above Max reverses the direction.
- **Invert:** flips the travel, for example so that pushing a stick up raises the value.
- **The bar** under the fields shows the value being sent right now.

A stick sends its minimum at one edge, its maximum at the other, and the middle of the range at rest.



The stick, trigger and touchpad windows also hold the settings of their loop (**Playback**, loop CCs, a lane per axis loop to change its length, **Steps**, **Clear the loop**), described in chapter 9.




In the touchpad window, choose each finger's **Mode** first: *Off*, *X/Y position → CC* (two axes, as above) or *4 zones → pads* (a button action for each quarter: top left, top right, bottom left, bottom right). The window scrolls to show finger 2.

> **Note:** when a loop uses the same CC as a live axis, the window shows a red warning: both would send to the same parameter and fight. Choose different CCs.

Velocity and Transpose axes

An axis does not have to send a CC: set it to **Velocity** or **Transpose** and it shapes the notes you play instead. Choose the mode with the radio buttons at the top of the axis form.



Velocity

The axis changes the velocity of the notes then played, starting from the velocity set in their mapping:

- **Stick or finger:** away from the middle one way, the velocity rises towards 127 in proportion to the room left (halfway, a note mapped at 100 plays at 114); the other way, it falls towards 1.

- **Trigger:** pressing it only raises the velocity.
- Shapes chooses what it acts on: the notes played (the default), the note loop, or both (below).

On the note loop. Set Shapes to *the note loop* (or *both*) and the axis makes the active channel's note loop louder or softer as it plays: each note goes up or down from the velocity it was recorded with, by the same rule, so the accents you played stay. Record the axis's movement and it becomes an accent pattern over the note loop. The pill reads VEL LOOP at rest, and the piano roll shows a VEL chip with the change (VEL +40%).

Transpose

The axis transposes the notes then played, or the note loop:

- **Down** and **Up** set how far it goes at each end of its travel, from 0 to 24 semitones each way. A trigger has **Up** only.
- **Transposes the notes played / the note loop** chooses what it moves. The note loop is the active channel's.
- With a tonality chosen (chapter 7), the axis moves **by degrees of the scale**: 12 semitones make one octave of degrees, notes stay in the key and chords stay chords of the key (in F minor, one degree up turns Fm into Gdim). Without a tonality, it moves by semitones. A note outside the scale first goes to the nearest note of the scale.

What both have in common

- A note takes the value when it starts, and always stops at the pitch it started at.
- A stick at rest changes nothing: it has a small dead zone in the middle.
- A finger on the touchpad keeps its last value once lifted: set a velocity or a transposition, take your finger off, and it stays.
- A frozen axis (Axis freeze) keeps the value it had when it froze.
- A loop of such an axis plays the velocity or transposition instead of CCs: record a stick moving and the transposition follows the recorded gesture.
- Several axes set to the same mode add up.
- The axis pills show the live value: *VEL +40%*, *TR +3*, or VEL LOOP and *TR LOOP* for an axis set on the note loop.

> **Note:** in headless mode there is no tonality, so Transpose always moves by semitones.

7. Notes, chords and scales

Arcadance plays named chords such as *Fm9* or *Dbmaj7#11*, and can restrict every note and chord menu to the notes of a chosen scale, so you build a playable layout without leaving the key.

Notes

A **Note** action plays one MIDI note. Without a tonality, type its number (0–127); Arcadance shows its name beside it (60 = C4). With a tonality, the field becomes a menu of the notes of the scale on every octave, and the arrows step to the previous or next note of the scale.

Chords



A **Chord** action plays several notes at once, all with the same velocity:

- **Chord**: type a chord name in Free entry, or pick one in Chord of the key when a tonality is set.
- **Notes**: the notes the chord will play, spelled out, so you can check it before playing it.
- **Octave**: the octave of the root (4 by default: C4 = 60). The other notes stack above it.

- **Bass root**: None, 1 octave below or 2 octaves below. Doubles the root lower down to anchor the bass, as on the Cross button of the demo, where Fm9 is played over a low F.
- **Inversion**: Root, 1st, 2nd..., one step per note of the chord after the first. Each step moves the lowest note of the chord up an octave: C E G becomes E G C (1st), then G C E (2nd). The bass root stays below.
- **Closest to the previous chord** (voice leading): each time it plays, the chord takes the inversion nearest to the chord played before on the same channel, at its octave or the one below, so the voices move as little as possible. After C (C4 E4 G4), F plays C4 F4 A4 instead of F4 A4 C5. With no chord played before, it plays as set.

A chord whose notes would fall outside the MIDI range (0–127) is refused; lower the octave.

Writing chord names

A chord name is a root (C, C#, Db ... B) followed by a type. Arcadance recognises these types:

Family	Types
Triads	(major), m, 5, dim, aug, sus2, sus4
Sixths	6, m6, 69, m69
Sevenths	7, maj7, m7, mmaj7, dim7, m7b5, 7sus4, 7#5, 7b5, maj7#5
Ninths	add9, 9, maj9, m9, mmaj9, 9sus4, m9b5, 7#9, 7b9
Elevenths	11, maj11, m11, m11b5, maj7#11, 9#11
Thirteenths	9b13, 13, maj13, m13

Useful details:

- A capital **M** means major: *CM7* is Cmaj7, not Cm7.
- *C6/9* is accepted for C69.
- A slash chord such as *Ab/C* plays the bass note one octave below the root's octave.

Tonality

Click the **SCALE** block to choose a tonality: a root on the left, a scale on the right. The tonality is shared by all channels and saved with your settings, not with the preset.



Available scales: major, natural minor, harmonic minor, melodic minor, dorian, phrygian, lydian, mixolydian, locrian, major pentatonic, minor pentatonic, blues and whole tone. Choose **None** as the root to remove the tonality.

With a tonality set:

- **Note** menus list only the notes of the scale.
- **Chord of the key** lists, degree by degree, every chord whose notes all belong to the scale.
- **Free entry** stays available for anything else. A note outside the scale is marked *out of key*; a chord with such notes shows *Contains notes outside* followed by the tonality. Both still play. An unknown chord name shows *Unknown chord*, and the previous chord stays active.
- The SCALE block shows the name of the tonality and lights its notes on the keyboard.

> **Tip:** set the tonality before building a preset. The Chord of the key menu then offers only chords that fit, which is the fastest way to fill the D-pad and the face buttons.

8. Channels

Arcadance sends on one MIDI channel at a time, the active channel, and you can switch channels while playing. Point each channel to a different instrument in your DAW and one controller plays a whole band: pads on channel 1, bass on channel 2, drums on channel 16.

Switching channels

- **In the window**: click the arrows of the CHANNEL block, at the bottom right, or turn the wheel over it.
- **In the edit mode**: push the right stick left or right (chapter 4).
- **From the controller**: give a button the **Channel change** action, Previous (-1) or Next (+1). In the demo, Create steps down and Options steps up.

Channels wrap around from 16 to 1.

The CHANNEL block shows the active channel in large digits, with its name. To see on which channels loops play, open the session screen (chapter 9).

Naming channels

Give a channel a name, such as BASS or PADS, to know at a glance what it plays: open the menu of the CHANNEL block (click its middle or right-click it; in the edit mode, put the cursor on it and press Menu) and choose **Rename...**. The menu of a column on the session screen, and of a column's header on the song screen, has Rename... too, and a double-click on a column's name renames the channel at once. Type up to 24 characters; an empty name removes it. The name shows under the channel's number, in the headers of the session and song screens and over the chain. It belongs to the preset: save the preset to keep it.



Channel colours

Each channel has a colour, which fills its clips and chain steps and draws its items on the song screen. **Colour...** in the channel's menu (on the session or song screen, or the CHANNEL block) changes it: one of 48 colours, or any other with the square (saturation and brightness), the bar (hue) or the R, G, B and hex fields. The screens follow at once. **Default** gives the channel its own colour back. Colours are kept in the preset.





Channel 1's mapping and channel mappings

Channel 1's mapping is the preset's main mapping: every channel plays it unless it has a **mapping of its own**. A channel's own mapping replaces channel 1's entirely while that channel is active: when you switch to it, every control takes its new meaning at once.

Copying a mapping from another channel

- **A whole channel, or some of its parts**: **Copy mapping from...**, in the menu of the CHANNEL block or of a column on the session screen, opens a window: choose the channel to copy from (channel 1 by default) and the parts to copy: Buttons, D-pad, Left stick, Right stick, Triggers (their axes and their button actions), Touchpad, Tilt, Loop settings. Copy replaces those parts of the channel; a channel without a mapping of its own gets one.
- **One control**: at the top of a control's window, **Copy from** a channel and **Copy** take that one control as the other channel has it: a button (with its Shift tab), a D-pad direction, a touchpad pad, a stick or the triggers (with their loop settings), a finger, the tilt (with its loop settings).





A copy changes the preset as any edit does: Revert brings the preset back as it was saved. The channel's name is not copied.

The demo preset uses this to give each channel its own role:

Channel	Mapping	Role in the demo
1	Base	Chords on the face buttons and D-pad, CCs on sticks and touchpad
2	Own	Other chords, notes on L2/R2
3–15	Base	Same as channel 1
16	Own	Single notes, touchpad split into four drum pads

On channel 1, the mapping windows edit channel 1's mapping, and every channel without its own follows. On channels 2 to 16, a channel plays channel 1's mapping until you change something there: that first change gives it its own mapping, a copy of channel 1's with your change, and from then on it no longer follows channel 1. The scope line at the top of each window tells you which one you are editing. Save and Save as keep every channel's own mapping.

> **Note:** to make a channel follow channel 1 again, open a mapping window on that channel, click **Use channel 1's mapping again** at the top and confirm: its own mapping is removed. Revert brings it back until you save the preset.

Shift and Loop record on every channel

A button, D-pad direction or touchpad pad set to **Shift** or **Loop record** on channel 1 keeps that role on every channel, even on a channel with its own mapping: you can always record, and always reach the Shift layer, whichever channel is active. On another channel, the mapping window of that control says *On every channel, this control is channel 1's Shift* (or *Loop record*) and stays greyed out: change it on channel 1. The layer itself still belongs to each channel: on channel 2, Shift brings up channel 2's Shift layer.

Notes never get stuck

A note always stops on the channel where it started. You can switch channels, or even presets, while holding a chord: its release still reaches the right instrument.

9. Loops and the piano roll

Arcadance records what you play and plays it back in a loop, on the channel where you played it, while your hands stay free for something else. It records two kinds of loops: **movement loops** (sticks, triggers, touchpad fingers), which work like hand-drawn LFOs, and **note loops**, which repeat the notes and chords you played.

Everything starts from a button set to **Loop record** (R1, labelled *Rec*, in the demo). Set on channel 1, it records on every channel (chapter 8).



Recording a movement loop

1. Hold **Loop record**.
2. Move a stick, press a trigger, slide a finger on the touchpad or tilt the controller. You can move several at once.
3. Release **Loop record**. Each movement starts looping at once, from the start.

Only what moves is recorded: a stick must travel about 12 % from the centre to count. **Each axis records on its own:** a stick's left-right (X) and up-down (Y), a finger's sideways and up-down moves, L2 and R2 are separate loops. Each starts when its axis moves, so the two can have different lengths, and you can record one axis now and the other one later. An axis that is not **Enabled** in its window is never recorded. For the touchpad, the moments when the finger was lifted are recorded too, and play nothing. A loop lasts up to 60 seconds.

The loop plays **beside** the control, on CCs of its own, so the stick or finger stays free to play live on its usual CCs. The loop CCs are set in the window of the stick, triggers, touchpad or tilt (an axis set to Velocity or Transpose has none: its loop plays as that, and the window reads X: plays as Velocity):

Source	Loop CCs (default)
Left stick	70 / 71
Right stick	72 / 73
Touchpad finger 1	74 / 75
Touchpad finger 2	76 / 77
Triggers L2 / R2	78 / 79
Tilt X / Y	80 / 81




In the same window, **Playback** chooses the direction: *Forward*, *Reverse* or *Back & forth*. **Clear X** and **Clear Y** (**Clear L2** and **Clear R2** for the triggers) erase one axis' loop, **Clear both** the two.

A movement loop has a fourth choice, **Envelope**: it plays once from its start each time a note starts on the channel, played live or by the note loop, then holds its last value until the next note. A filter that opens on every chord, a hand-drawn attack and decay: record the gesture once, and every note plays it. With **Legato** ticked, only a note that starts while no other sounds starts it again, so a phrase played legato shapes once. Its LOOP panel reads *ENV*. The note loop cannot be an envelope.

Reading the LOOP panels

The LOOP panel of each module shows the loops of the active channel, **one lane per axis**: X and Y for a stick, L2 and R2 for the triggers, 1 X and 1 Y for the touchpad (2 X and 2 Y too once finger 2 holds a loop). Each lane spans the whole width whatever the length of its loop, with its own playhead: a shorter loop is drawn just as wide, and its playhead crosses it faster. A lane shows its name at the top left, its length at the top right (*4.0 s*, or *1.5 BARS* for a loop synced to a clock; in red while it records) and its loop CC at the bottom right (VEL or TR for an axis set to Velocity or Transpose); the header shows the playback mode (FWD, REV or B&F). The curves show what the loop sends: the higher the value, the higher the curve, so an inverted axis is drawn upside down. The lane of an axis that is not enabled reads *not enabled · not recorded*. Click the panel to open its settings; right-click a lane for its menu: lock, clear, back to 1x · 100% (chapter 4).




Over a lane, a small red × appears beside its name: click it to clear that axis' loop alone, the other one playing on. A locked lane has none. In the control's window, each lane has its × too.

The LOOP panels with nothing recorded show a grey screen. On two of them, chosen at random for each channel, a little 1980s arcade game plays: Pac-Man, Space Invaders, Asteroids, Pong, Breakout, Missile Command, Tetris, Galaga, Donkey Kong or Q*bert. So you can tell at a glance which loops are free. It is decoration only.

Axis loop lengths and steps

The window of a stick, the triggers or the touchpad (click its screen or its LOOP panel) shows, under its loop settings, a lane for each axis loop that plays, over its own length, and below them the step settings of each axis. Scroll the window down to reach them.

Shortening or lengthening an axis loop. Drag the violet handle at the right end of a lane, as in the note loop editor. Shorter, the part cut is hatched; longer, the time added is drawn as a dashed line from the loop's last value back to its first, so that the loop closes without a jump. The chip reads the old and the new length (*4.0 s to 4.6 s*); release to apply it, or press Escape to cancel. A loop synced to a clock keeps whole beats; a loop in steps, whole steps.



Loops in steps. Each axis has a **Steps** box. Ticked, its loop no longer glides: it holds one value per step and jumps to the next, like a step sequencer. **Levels** (2 to 128) sets how many values it may take, each rounded to the nearest; **Step** sets how long each value lasts, as a note value: 1/32, 1/16, 1/8, 1/4 (a beat), 1/2 or 1 bar. The beat is that of the loop when it is synced to a clock, otherwise the tempo shown in the top bar.

Steps apply as the loop plays: what was recorded stays as it was, so you can change them or turn them off at any time. The lane draws the staircase the loop plays, the recorded curve faintly behind it, and the step grid. Steps are saved in the preset, with each mapping's loops.

Recording a note loop

1. Hold **Loop record**.
2. Play notes or chords: face buttons, D-pad, triggers used as buttons, touchpad pads.
3. Release **Loop record**. The notes loop on the channel where you played them, with their velocity and humanization.


Each channel has one note loop. Recording a new one replaces it. A note still held at the end of the recording (a latched chord) sounds until the end of the loop, and everything sounding stops when the loop starts over.

The piano roll

Without a note loop, the piano roll scrolls the last seconds of the active channel towards the *now* line on the right edge: white for what you play, violet for what a loop plays. Its keyboard follows the range of the notes played.

While a note loop plays, the piano roll becomes a **clip**: the whole loop, from *start* to its end, standing still, with a playhead sweeping it in the playback direction. Its notes are white, as opaque as they are loud, and get a violet halo as the playhead crosses them. Beneath the clip, the notes you play live keep scrolling from the right edge in faint cyan, as without a loop. Click the piano roll to open the note loop editor: a large piano roll to edit the notes (below), the playback mode and Clear the loop.





Editing the notes of a loop

The note loop editor, opened by a click on the piano roll, holds a large piano roll of the loop. Edit its notes there with the mouse, without recording again, while the loop keeps playing; the piano roll of the main view only shows the loop.


Gesture	What it does
Drag a note	Moves it, in time and pitch, its length kept; on a selected note, moves the whole selection as a block
Drag over empty space	Selects the notes in a rectangle (with Ctrl, adds them to the selection)

Gesture	What it does
Ctrl + click a note	Adds it to the selection, or takes it out
Double-click a note	Selects its chord: every note of the same press, even spread by humanization
Drag the end of a selected note	Lengthens or shortens every selected note alike
Right-click a note, or Delete	Deletes it, or the whole selection it belongs to
Click on empty space, or Escape	Clears the selection

Notes are white, as opaque as they are loud: solid white at velocity 127, faint near 0. Selected notes are mauve, shaded the same way and outlined in cyan; notes the playhead crosses have a white glow.


Zoom


Hold **Ctrl** and turn the mouse wheel over the editor's piano roll to zoom in or out around the mouse, from the whole loop to a second (or a beat) across; the wheel alone, or a sideways scroll, moves along the loop. The scrollbar under the roll shows the part in view: drag its thumb, or click beside it to go there. Every gesture works zoomed in, and the loop's end handle shows when the end of the loop is in view.



Moving on the scale

SCALE and **CHROMATIC**, at the top of the editor, set how the channel's notes move; each channel keeps its choice, saved with the preset. SCALE (the default) keeps moved notes in key, with a tonality chosen: up and down go by degrees of the scale, so each note of a chord moves by its own interval, and a note outside the scale goes to the nearest note of it; rows outside the scale are darkened, and the root's rows tinted blue. CHROMATIC moves notes by semitones over every row alike, each row named (C3, C#3, D3...): the one for drums, where each note is a pad of a drum rack.






While you drag, cyan copies show where the notes go; release the mouse button to move them. A group keeps the exact gaps between its notes, so a humanized chord keeps its feel. With a clock and

the quantizer on, the group's first note snaps to the grid and the others follow. The group stays inside the loop as a block; notes of the same pitch it lands on are cut short, and notes sounding stop cleanly.

Note lengths


Point at the right end of a selected note: the cursor becomes a double arrow. Drag it to lengthen or shorten every selected note by the same amount; while you drag, cyan shows where the notes will end. With the quantizer, the grabbed end snaps to the grid. Each note keeps a minimal length, ends inside the loop, and stops where the next note of its pitch starts.



Loop length

The violet bar at the right edge of the editor's piano roll is the end of the loop; its grip sits in the middle. Point at it: the cursor becomes a double arrow. Drag it to correct a loop whose Loop record was released too late, or to make room for overdubs.

- **Drag left** to shorten the loop. The part that goes is dimmed and hatched, and the notes that start there turn red: they will be deleted. Notes still on at the new end end there.
- **Drag right** to lengthen it, up to a minute. The bar stays at the edge and the loop narrows to make room; the silence added is tinted violet. The mouse may leave the piano roll, and the window, while you drag.



The chip at the top right shows the new length while you drag. Release the mouse button to apply it, or press Escape to keep the loop as it was. A loop synced to a clock changes by whole beats, one at least, so it stays in time with the other loops; a free loop changes freely. What sounds stops cleanly, and the playhead starts over if it was past the new end. There is no undo: a shortened loop's notes are gone.

Overdub

Overdub adds notes to a note loop without changing its length.

1. While a note loop plays, tap **Loop record** briefly (less than half a second) without playing anything: overdub is on.
2. Play: every note is added to the loop where it plays.
3. Tap **Loop record** again to turn overdub off.

During overdub, the piano roll shows **OVERDUB** and an orange playhead, each added note appears in orange while you hold it, and the Rec pad is circled in orange.




Stopping and restarting loops

You do	Result
Tap Loop record, no note loop playing, nothing moved	Stops the loops of the active channel, except the locked ones
Hold Loop record without playing or moving	Stops the loops of the active channel, except the locked ones
Click ■ (Stop) in the top bar	Pauses the loops of every channel, without erasing them
Click ▶ (Play)	Restarts the clips that were playing, from their start; Play turns green while loops run, and does nothing then. On the song screen, it plays the song instead
Record while loops are paused	Restarts all loops together with the new one
Click PANIC	Stops every loop on every channel, the locked ones too, and silences everything

Locking a loop

A locked loop stays: pressing Loop record again neither replaces it nor stops it, so you can go on recording the other controls, or tap and hold Loop record freely, without losing it. **Each axis locks on its own:** lock a stick's X loop and record its Y later; the locked one stays as it is.



- **With the mouse:** right-click a lane of a LOOP panel and choose **Lock** (or **Unlock**) for that axis' loop; right-click the panel's header for all of its axes (an axis without a loop stays free to record); right-click the piano roll for the note loop. Only a recorded loop locks.
- **From the controller, with the menus:** in the edit mode (Shift + Mode), put the cursor on a lane or the piano roll and press Menu (chapter 4).
- **From the controller, while playing, a movement loop:** with Shift on (held, or latched in Toggle mode), hold Loop record and move the axis whose loop you want to lock or unlock: a stick left-right for its X, up-down for its Y, L2 or R2, or a finger on the touchpad (axis mode) sliding sideways or up and down once it has landed. Each axis changes once per press of Loop record. Meanwhile the controls neither stretch loops nor send CCs, and releasing Loop record does nothing else.
- **From the controller, while playing, the note loop:** with Shift on, tap Loop record twice quickly (within 0.35 s), playing nothing in between. The overdub the first tap turned on is taken back; when the first tap would stop the loops, it waits 0.35 s for a second one.

A locked lane shows a padlock beside its name and a solid outline in its colour, and the panel a padlock next to LOOP (on the piano roll, beside its LOOP chip). The lock belongs to the loop of the active channel; in 4-pad mode the touchpad panel shows the note loop and locks it.

A locked note loop takes no overdub. ■ and ▶ pause and restart locked loops as usual, Shift still stretches and widens them, and you can still edit the notes or use **Clear the loop**. PANIC clears every loop, the locked ones too. Sessions keep which loops are locked.


Stretching loops in time and amplitude

A movement loop (sticks, triggers, touchpad in axis mode) can be reshaped while it plays, without recording it again, right from the gamepad: stretched or compressed **in time**, and narrowed **in amplitude**. The note loop is not concerned.

Shift: hold a button, move an axis

Give a button or a D-pad direction the **Shift** action. Hold it (or, in Toggle mode, press it once), then move the stick or the finger whose loops you want to reshape. Each axis loop changes on its own:

- **Stick left or right** compresses or stretches its **X** loop **in time**, **up or down** its **Y** loop: up to **100 times longer** (*+100x*), up to **20 times shorter** (*-20x*), by steps of a half (*+1.5x*, *+2x*, *+2.5x* ...). Right and up lengthen.
- **Click the stick** (L3 or R3) while Shift is on to switch it to the **amplitudes**: left or right then widens or narrows X's, up or down Y's, around the loop's middle (halfway between its lowest and highest values): from **0 %** (still) through **100 %** (as recorded) up to **800 %**, by steps of 5 % below 100 % and of 25 % above. Click again for the **offsets**: left or right moves X's loop down or up, up or down Y's, by steps of 5 % of the travel from -100 % to +100 %, the curve keeping its shape and bending softly where it would pass an end. Click once more to go back to the lengths. While Shift is on, a LEN, AMP or OFS badge at the top right of the stick's screen tells which it changes; the touchpad's click does the same for the fingers.
- Widened past 100 %, a swing would run beyond the ends of the CC range (0 and 127), so Arcadance **clips it softly**: the curve bends towards the end, then stays flat there, like an LFO driven into saturation. The bend grows with the amplitude, from none at 100 % to a tenth of the range from 200 %. A small swing widened 3 or 4 times fills the whole range; a wide one widened far turns into a square wave.
- The stick works as a wheel kept turning: nothing in the dead zone around the centre, then faster the further you push. Only the way it mostly moves counts, so a diagonal never changes both at once.
- **On the touchpad** (axis mode), slide a finger: each short slide counts one step, sideways for the X loops, up and down for the Y loops. Click the touchpad while Shift is on to switch between lengths and amplitudes (LEN or AMP on its screen).
- **The triggers'** loops (L2, R2) are reshaped with the mouse (below).
- Crossing from compressed to stretched, the length waits a moment at 1x (and the amplitude at 100 %, crossing it either way), so the recorded loop is easy to find again.
- Release the button (in Toggle mode, press it again): everything you set stays. Recording the loop again puts it back to 1x and 100 %.




While Shift is on, the sticks and fingers only reshape loops: they send no CC and start no recording; the gauges of the lanes show what changes (below).

The loop goes on from the same point when it changes, so it never jumps. Stretched, it is smoothed between its recorded points; compressed, each value is the average of the points it passes over; a change of amplitude is eased in over a few milliseconds. A loop of a Velocity or Transpose axis is reshaped the same way.

What you see

While the length or the amplitude of a loop changes, a gauge appears at the bottom of its lane: a log scale from -20x to +100x for the length, a scale from 0 % to 800 % for the amplitude, with 100 % marked, and from -100 % to +100 % for the offset, with 0 marked. It fades out a moment after the last change.



Once set, chips stay on the lane next to its length (*+2.5x*, *AMP 60%*), and the curve is drawn as it plays, narrowed, widened or moved (flat where it is clipped), the recorded one faintly behind. The length shown is the stretched one (*10.0 s*, or *12:30 min* beyond a minute; in beats or bars for a loop synced to a clock).

At the computer

The same changes are also at hand with the mouse, over a lane of a LOOP panel: the **Shift** key + wheel for its length, **Ctrl** + wheel for its amplitude, Alt + wheel for its offset (up stretches, widens or raises); over the panel's header, every lane at once. Turned quickly, the wheel takes bigger steps. This is also how the triggers' loops are reshaped.


Modulating a loop's amplitude with another loop

A movement loop (a stick's X or Y, L2 or R2, a finger's X or Y) can modulate the amplitude of other movement loops of the same clip, as many as you like, each with its own depth, like a slow LFO: when it is high, the other loop swings as wide as its amplitude (AMP) lets it; when it is low, the other loop closes in on its centre. Each loop keeps its own length, so the modulation turns at its own pace. For example, R2 looped slowly over eight bars makes a filter sweep on the left stick's X breathe.



Setting it up

- Right-click the lane of the loop that modulates (or press Menu on it in the edit mode) and choose **Modulate the amplitude of…**. The list shows the other loops of the clip; those with nothing recorded, and those that modulate this one (even through others), are greyed. Tick as many as you like: each loop it modulates is ticked, with its depth (70 % · inverted); choosing it again removes it.
- **Depth** and **Direction**, at the bottom of the list, set those of one loop it modulates, named there: the ticked loop under the cursor, else the last one ticked. Depth goes by steps of 10 % (a click or Select goes up, the right stick left or right down or up): at 100 % the loop closes in to nothing when the modulating one is at its lowest; at 30 %, its amplitude only varies between 70 and 100 %. Direction switches to inverted: the loop is then widest when the modulating one is at its lowest. The list stays open while you set it.
- The lane's menu also has **Stop modulating** (every loop it modulates), and **Send its CC: on / off**. By default the loop that modulates still sends its own CC; turned off, it only modulates, and its lane reads MOD instead of its CC.





The window of the control (a click on its LOOP panel) has the same settings in its **Modulation** section: for each axis loop playing, a row per loop it modulates (which, its depth, inverted, × to stop), a + list to add one, and sends its CC.



Rules

- A loop modulates as many loops as you like, and is modulated by one loop at a time: choosing a new one for it takes it from the one before. A loop never modulates itself, nor a loop that modulates it, even through others.
- The modulation belongs to the clip, with its loops: duplicating the clip copies it, sessions keep it. Clearing either loop removes it; recording one again keeps it. While the loop that modulates does not play, the other one plays at its own amplitude.
- A modulated loop's other changes (stretch, amplitude, steps, sync) work as usual: the modulation multiplies its amplitude.

Playing in time: internal clock or Ableton Link

By default Arcadance keeps no beat: a loop lasts exactly as long as you held the button. Give it a clock and loops come out a whole number of beats long, start on the beat and follow the tempo. There are two clocks: the **internal clock**, Arcadance's own tempo, with no network needed, and **Ableton Link**, which joins the tempo and beat of your DAW, or of any app using Link on the same network.

Choose the clock in ☰ › **Settings** › SYNC › **Clock**. The clock button of the top bar then reads *CLOCK 92.5 BPM* or *LINK 120.0 BPM · 2* (with Link, the number of peers: the other Link apps in the session), with a square for each beat of the bar, the current one lit. Without a clock it reads *FREE*. A click on the button, away from the tempo, turns the clock off, and another turns the same clock back on. Alone on the network, a Link session starts at 120 BPM.




A loop recorded while a clock runs:

- **Snaps to whole beats.** When you release Loop record, the length is rounded to the nearest whole number of beats (or bars, see SYNC in Settings), one at least. Hold for about six beats and you get exactly six: *1.5 BARS*. One beat, three beats, one bar, two and a half bars: anything goes.
- **Starts on the beat.** Its start moves to the nearest beat, so it stays in phase with the clock and with the other loops.
- **Follows the tempo.** It plays in beats, not in seconds: change the tempo, in Arcadance or with Link in your DAW, and the loop speeds up or slows down with it, still in phase.
- **Shows beats and bars.** Its header gives the length in beats or bars (*1 BEAT*, *3 BEATS*, *1 BAR*, *1.5 BARS*). The clip of the piano roll draws a grid of the beats, stronger on the bars, with the bar numbers on top; where the beats would crowd, only the bars, or every few bars.
- **Still stretches.** Shift works as before: *+2x* makes a one-bar loop last two bars, *-2x* half a bar. Forward, Reverse and B&F all work; in B&F each pass lasts the loop's length.

Note loops and movement loops behave alike.

Setting the tempo

The tempo belongs to the clock. The internal clock's is Arcadance's own and is kept for the next launch. With Link, any app in the session can change it and every other one follows: change it in Arcadance and your DAW follows, as Arcadance follows your DAW.



- **Mouse wheel over the tempo**: 1 BPM a notch, 0.1 with the Shift key; turned quickly, it takes bigger steps.
- **Double-click on the tempo**: type a value (for example 92.5), then Enter. Escape cancels.
- **TAP**, next to the clock button: tap in time; from the second tap, the tempo follows your taps. It takes the median of the last four intervals, so one tap clearly off is ignored; a pause of more than two seconds starts over.
- **Tap tempo on the controller**: give a button the *Tap tempo* action (chapter 6) to tap with the gamepad in your hands.

Tempos go from 20 to 999 BPM.

Quantizing notes

With a clock running, ☰ › Settings › SYNC › **Quantize notes** (*Off*, *1/8*, *1/16*, *1/32*) puts the notes recorded into a note loop on a grid of eighth, sixteenth or thirty-second notes. What you hear while playing is never delayed: only the loop's copy moves.

- Each press moves as a whole: its first note goes to the nearest step, earlier or later, and its release moves with it, so the note keeps its length. A note played just before the loop's end goes to its start.
- A chord lands on the grid together. Humanized, its first note goes on the grid and its other notes keep their spread, so the chord stays alive.
- Notes added in overdub are quantized as you play them.
- Notes of the same pitch never overlap: one still sounding when the next starts ends there, and two landing on the same step become one.

Free loops and movement loops are never quantized.

Start and stop. With Link and *Start / stop sync* on (the default), ▶ and ■ also start and stop the Link session, and Arcadance's loops pause and resume when another app starts or stops it. With the internal clock, ▶ and ■ act on Arcadance's loops.

MIDI clock out. With the internal clock, Arcadance also sends MIDI Clock to its output: 24 pulses a beat at the clock's tempo, Start when ▶ starts the loops, and Stop when ■ stops them or when you leave the internal clock. Drum machines, sequencers, arpeggiators and DAWs set to follow an external

MIDI clock then play in time with Arcadance. It is on by default; turn it off in ☰ › Settings › SYNC › MIDI clock out.

Free mode. Without a clock, loops keep the length you played, to the millisecond. A loop recorded free stays free when you turn a clock on; a synced loop goes on at its own pace when you turn the clock off.

> **Tip:** Link works over the local network. If Arcadance sees 0 peers while another app has Link on, check that both are on the same network and that no firewall blocks UDP multicast (Link uses port 20808).

Loops on several channels

Each channel has its own loops. Record on channel 1, switch to channel 2, record again: all loops play together, each on its own channel. The LOOP panels and the piano roll always show the loops of the active channel; the CHANNEL block marks the others with a violet dot.

> **Note:** loops are not saved with the preset. Save them in a session (below) to find them again after quitting Arcadance.

Clips and the session screen

Each channel keeps up to eight **clips**. A clip holds all of the channel's loops at one moment: the note loop, both sticks, the triggers and the touchpad fingers, with their stretch, amplitude, sync and lock. A channel plays one clip at a time, independently of the others: clip 1 on channel 1 can play beside clip 3 on channel 2. Everything described so far in this chapter (recording, overdub, locking, the note loop editor, the LOOP panels) acts on the **current clip** of the active channel.



Opening the session screen

- **From the controller:** a press on the button given the **Mode** action (chapter 6). Set on channel 1, it works on every channel; without one in the preset, the PS / Guide button does it.
- **With the mouse:** the button with four squares in the top bar, right of TAP (the one after it, with lanes, opens the song screen). **On the keyboard:** Tab.

The session screen takes the place of the modules: a column per channel, headed by its number and name, eight at a time (**Channels 9–16 ›** shows the others, and the screen follows the active channel), a row per clip slot, at the bottom of each column a square that stops the channel with M (mute) and S (solo) beside it, and under the columns the chain of the active channel (below).

Reading it

- A clip is filled with its channel's colour, brighter while it plays (in the Phosphor looks, a small screen). It shows its name (Clip 3), a light, and its notes as small bars; a clip without notes shows the movement of its first movement loop as a curve.
- The clip playing on a channel has a green outline, its light is green, and a bar along its bottom shows how far it is in its turn. The light of a clip waiting to start blinks; a clip being recorded is

outlined in red.

- The cyan frame is the cursor; its channel is the active one. On an empty slot it shows a +.


Playing clips

- **Move the cursor** with either stick or the D-pad: a step a push, repeating while held. Left and right change the channel (left of channel 1 comes channel 16, right of 16 comes 1), up and down the slot.
- **Press Select** (L3 or R3 unless you chose another button, chapter 11), or click a clip: it starts at the end of the turn of the clip playing on that channel, from its start. The turn is the note loop's, else the longest movement loop's; with a clock, the clip's length in beats. With nothing playing on the channel, it starts at once.
- **Press Select on the clip playing** (or click it): it stops at the end of its turn, its clips kept. On a clip waiting to start, or while a stop is waiting, the press calls it off. The square at the bottom of a column stops that channel too.
- **Press Menu** (or right-click a clip, a step or a column's header) for its menu: duplicate a clip, clear it, add it to the chain, and more (chapter 4).
- While the session screen shows, the sticks, the D-pad and the Select, Menu and Back buttons send, play and record nothing; the other controls play as usual.



Mute and Solo

Under each column, beside the stop square, **M** mutes the channel and **S** puts it in solo.



- **Mute**: the channel's clips, chains and song play on in time, but send nothing; the notes they were sounding end at once. Unmuted, the channel comes back where it is, in time. What you play live on a muted channel still sounds, so you can play over it.
- **Solo**: only the channels in solo sound; several channels can be in solo at once, and a solo wins over a mute. The clips of a muted channel are dimmed, those of the channels out of the solo a little less.
- From the controller, down past the last clip of a column comes the row of buttons: left and right go from the stop to M and S (and on to the next channel's), Select presses the button under the cursor, down again enters the chain. The menu of a column has Mute and Solo too.
- Sessions keep the channels muted and soloed; New Song clears them; PANIC leaves them as they are.

Recording a new clip

Put the cursor on an empty slot (or click it) and record with Loop record as usual: the take goes into a new clip there. The clip playing on that channel stops when the recording starts (it is kept), and the new clip plays as the current one once you let go. While Loop record is held, the sticks, the D-pad, L3 and R3 play and record as usual, so every loop can go into the new clip; once you let go, they move the cursor again (a stick once back at rest). On a slot that already holds a clip, Loop record replaces or overdubs that clip. Leaving the session screen, every channel records into its current clip again.

> **Note:** PANIC clears the current clip of every channel; the other clips stay. Sessions keep every clip, which one is current on each channel, and whether it plays.

Chains of clips


Each channel can play its clips in a sequence: a chain, up to eight steps played left to right. Each channel has up to eight chains, A to H, and plays one at a time. A step is a clip and how many turns it plays (×1 to ×64, or ∞); then the next step's clip starts, at the end of the turn, from its start. After the last step the chain goes back to its first step, stops the channel, or goes on to another chain of the channel. A turn is the clip's turn, as when you launch a clip.



- **Reading it.** The big number is the step's clip, with a sketch of it; the chip its repeats. The step playing is outlined in green, with its turn (3/4) and a progress bar; a step asked for next blinks. A

dashed step is empty: before the chain's last step that plays (or is silent) it is a bar of silence and reads 1 bar; after it, the chain skips it. The column of a channel with a chain shows a chain sign, green with its step (2/5) while it runs.

- **R, a random step** (violet, with two dice): each time the chain comes to it, it picks one of the channel's recorded clips at random and plays it its repeats; while it plays, it names the clip it picked.
- **Silence, a rest step** (grey, a rest sign): the channel is silent for as many bars as its repeats (×2: 2 bars, read under it; ∞: until you ask for the next step), then the chain goes on. A bar follows the tempo, on the beat clock when it runs.
- **∞** plays its clip until you ask for the next step (below) or stop the channel.
- **The CHAIN cell**, at the end of the strip, shows the chain you see (A to H), a dot per step and what follows it: then B, a round arrow (back to step 1, the default) or a square (the channel stops). Its arrows, the wheel or the right stick (up or down) show another chain; the right stick left or right sets what follows it; a click or Select plays it or stops it. Its menu duplicates, renames, clears it or adds it to the song. The header names the chain you see (CHAIN 1 KEYS · A).
- **CHAIN ON / OFF** starts the chain from its first step (or from the step under the cursor) or turns it off; the header then reads *step 2 · turn 3 of 4*. Launching or stopping a clip by hand, recording into another clip and PANIC turn the chain off; its steps stay.



From the controller, move the cursor down past the stop, M and S buttons under the clips to enter the chain, and up to leave it. There:

- The left stick or the D-pad goes from step to step.
- The right stick up or down chooses the step's clip (empty, 1 to 8, then R, then S for a silence), left or right its repeats (×1 … ×64, then ∞). In the chain the right stick sets values instead of moving the cursor.
- **Select** starts the chain from that step. On the step playing, it goes on to the next step at the end of the turn (this is how an ∞ step ends); on another step, the chain goes there at the end of the turn.
- **Menu** opens the step's menu: Start from here, Random (R), Silence (S), Insert a step, Delete the step, Empty it; on the CHAIN cell, the chain's. With L3 and R3 as Select (the default), R3 also empties the step.

With the mouse: drag a clip from the grid onto a step; turn the wheel over a step's number to choose its clip (past 8: R, then S), over its chip to choose its repeats; right-click a step for its menu. Sessions keep the chains.

The song screen

The song screen lays your clips and chains out in time. A song is a list of **sections** (intro, verse, chorus…), as many as you like, each with its name and its length in bars. In each section, every channel plays **clips, chains and silences**, one after the other or each on a bar of its own.



Opening the song screen

- From the controller: the Mode button on the session screen (Mode once opens the session screen, twice the song screen, three times the main screen again). Back leaves it.
- With the mouse: the button with lanes in the top bar, right of the session button; it is lit green while the song screen shows, and a click again goes back to the main screen. On the keyboard: Tab from the session screen.

Reading it

- **At the top**, the whole song at scale: a band per section, with its name and bars, and under it a lane per channel with what it plays. An item that loops on until the next one is drawn hollow. The green line is the playhead. The header reads 7 sections · 76 bars · 2:32, and while the song plays, where it is: VERSE 1 · bar 5 of 16 · 0:25 / 2:32. Click a section to go to it, double-click it to play from there.

- **In the middle**, a row per section and a column per channel that has a clip, a chain or something in the song, eight at a time (beyond eight, a link top left shows the others). Left of the first channel comes the last one; right of the last, the section names. A double-click on a channel's name renames it; a right-click opens its menu. The section's cell shows its name, its length in bars and fixed or = longest (as long as its longest channel), with a ▶ to play from there (■ while it plays). Each cell draws the items of its channel at scale in the section (Clip 3 ×4, Chain B), hollow where an item loops on, red where the section cuts it, with the playhead. + section, under the last row, adds a section.
- **At the bottom**, the editor of the cell under the cursor: a ruler of the section's bars, then each item in order, where it starts (bar 1, or right after the one before), how long it plays, and a + to add one. While no cell is chosen, the editor stays empty.



Building a song

- **Add a section** with + section, or Insert a section above in a section's menu. Its menu renames it (Rename...), duplicates it, moves it up or down, deletes it, and switches its length between fixed and = longest channel. The right stick on its name, or Ctrl + the wheel, sets its length: up or down a bar, left or right four.
- **Add an item**: Select (or a click) on a cell opens its editor; Select on + opens the list of what the channel can play: its recorded clips and its chains, each with its length in bars, and silences of a beat, a bar, two or four. A new item starts right after the one before, so clips shorter than a bar follow each other without a gap.
- From the session screen, the menu of a clip or of the CHAIN cell offers **Add to the song**: the clip or the chain goes at the end of the cell chosen on the song screen, named in the menu.
- **Change an item** in the editor: the right stick up or down changes the clip or chain (a silence: a bar longer or shorter), left or right its repeats (a silence: a beat). With the mouse, drag it to another bar, and turn the wheel over its left half (the clip or chain, a silence's bars) or its right half (its repeats, a silence's beats).
- An item's menu moves it a bar left or right, makes it start right after the one before or on a bar of its own, chooses what it does after its repeats (silence, or loop on until the next item), turns a clip into a chain and back, duplicates or deletes it.
- A cell's menu copies it, pastes it into another cell, or clears it.

Playing the song

- **▶ in the top bar**, on the song screen, plays the song from the section under the cursor; ■ stops it. With a clock, the song starts at once (internal clock) or on the next bar (Ableton Link). While the


song or the clips play, ▶ does nothing: press ■ first.

- **Select on a section's name** (or its ▶) plays from there; while the song plays, it goes there at the next bar.
- **LOOP SECTION** plays the section playing again and again, until you turn it off or go to another one.
- At the end of the last section the song stops, unless LOOP SONG, left of LOOP SECTION, is on: the song then plays again from its first section, until you turn it off. Sessions keep it. A channel with nothing in a section is silent there.

Sessions keep the song, with its sections and their items.


Sessions: saving and opening loops


Loops live in memory: quitting Arcadance loses them, unless you save them in a session. A session keeps every channel's clips and their loops (notes, sticks, triggers, touchpad, tilt, with their stretch, amplitude, sync, lock and modulation), the chains and their names, the song, the channels muted and soloed, a copy of the preset they play with, the tonality, the active channel and the tempo.




- ☰ **› New Song** starts an empty song: first it offers to save the session open (Save, Don't save or Cancel; a session never saved asks for a name). Then the loops stop and every clip, chain (with its name) and section goes. The preset, the tonality and the tempo stay. The new song has no name yet: Save asks for one.
- ☰ **› Save as...** names the session and saves it. A name already used asks first: *Replace* overwrites that session.
- ☰ **› Save** saves the current session again; the first time, it asks for a name.
- ☰ **› Open...** lists the saved sessions: double-click one, or select it and click *Open*. Opening replaces every loop, the preset and the tonality; unsaved changes to the preset are asked about first. To delete a session, right-click it, choose *Delete...* and confirm.

Quitting with a session changed since it was saved, opened or started (its loops, clips, chains, song, mute or solo) asks first: **Save**, **Don't save** or **Cancel**; an untitled session is named first.








Sessions are files ending in `.arcadance`, in `~/.local/share/Arcadance/Arcadance/Sessions/`. Sessions saved by MidiPad are renamed on the first start (chapter 2), and open as they are.

On opening, the preset comes back as it was: the preset of that name if it is unchanged, otherwise the session's copy, marked as changed (save it to keep it). Synced loops find the beat again under whichever clock runs: a session saved with the internal clock opens with Ableton Link, and the other way round. The session's tempo goes to the internal clock, or to the Link session only when Arcadance is alone in it: opening a session never changes another app's tempo.

10. Program Change and transport

Arcadance can change the sound of your synthesizer with MIDI Program Change messages, from a button or by sweeping an axis, and can send MIDI transport commands.

Program Change from a button



Give a button the **Program change** action, then choose:

- **Program:** always selects the same program (1–128).
- **Next (+1)** or **Previous (-1):** steps from the last program sent on the channel. The first press sends program 1. With **Wrap around**, stepping past 128 returns to 1 and the other way round; without it, stepping stops at the ends.
- **Bank select** (optional): sends a bank before the program, with **MSB (CC 0)** and/or **LSB (CC 32)**, each switched on separately.

The message goes out on the active channel. The pad label shows *PC 12* for a fixed program, *PC +1* or *PC -1* for a step.

Program Change from an axis

A stick axis, a trigger or a touchpad finger axis can select a program instead of sending a CC. In its axis window, choose **Program change** instead of CC, then set:

- **From** and **To:** the range of programs the travel covers, for example 1 to 16.
- **Invert:** reverses the direction.

- **Bank select:** a bank of its own for this axis, sent before every program.

Aim, wait, release. The program is sent only once the axis has stayed on it for 150 ms, so sweeping across the range does not load every program on the way. Nothing is sent when the axis springs back to rest, so the last program you chose stays. The axis pill shows *PC 1-16*.

Because each axis has its own bank, two axes can browse two different banks: the left stick one set of sounds, the right stick another.

Numbering

Arcadance shows programs from 1 to 128, as most synthesizers do; *Program 1* sends the value 0. Bank MSB and LSB are shown and sent as raw values (0–127). If your synthesizer counts banks from 1, enter the bank number minus 1.

> **Example: Arturia instruments.** Arturia's software instruments select presets inside a playlist: Bank MSB selects the playlist, Bank LSB the song, and the program the preset in that song, all counted from 0. For playlist 1, song 1, set MSB 0 and LSB 0; then *Program 1* loads the first preset of the song.


> **Note:** your DAW must pass Program Change messages on to the plugin. Some hosts do not forward them to VST3 plugins; if nothing happens, check with a MIDI monitor placed before the plugin, and try the VST2 version of the plugin.

Transport

The **Transport** action sends MIDI **Start**, **Stop** or **Continue**. These are system real-time messages: your DAW reacts to them only when it is set to follow external MIDI sync. Many DAWs offer MIDI learn on their transport buttons instead; in that case, use a **CC** action on the button and learn it in the DAW.


11. Settings

The Settings window holds the settings that belong to your computer rather than to a preset: the MIDI output, the VirMIDI ports, the clock (internal or Ableton Link), the quantizer, MIDI clock out, the D-pad delay, humanization, the presets folder and the frame rate. Open it from ☰ › **Settings**. Settings are saved at once, in `~/.local/share/Arcadance/Arcadance/settings.json`.



MIDI INTERFACE

The drop-down menu shows where Arcadance sends its MIDI. Click it to see every output:



- **Virtual port "Arcadance"** (*software port*): created by Arcadance itself, for programs that read ALSA sequencer ports.
- **VirMIDI N-M** (*seen as Virtual Raw MIDI …*): kernel MIDI ports. The hint on the right is the name under which programs that only list hardware devices show this port.
- **Hardware interfaces**, such as a USB MIDI interface, to drive an external synthesizer.

Refresh updates the list after you plug in a device. If the saved output is missing at startup, the menu shows it in red, marked *(not found)*, and Arcadance sends to its virtual port until you choose another.

> **Note:** the card number N of a VirMIDI port can change between reboots, depending on the order in which devices are found. Arcadance finds its port again regardless.

VirMIDI ports

Some programs only see the kernel's raw MIDI devices and ignore software ports such as *Arcadance*. The `snd-virmidi` kernel module provides such devices, and Arcadance can load it for you:

1. Under **Ports**, choose how many ports you want, from 1 to 4.
2. Tick **At every startup** to create them again after each reboot.
3. Click **Apply**. Your system asks for the administrator password, in its own dialog.

The status line shows how many ports exist and whether they come back at startup. **Remove** unloads the module and deletes the startup files; close the programs using the ports first.


With *At every startup*, Arcadance writes two small files: `/etc/modules-load.d/midipad-virmidi.conf` and `/etc/modprobe.d/midipad-virmidi.conf`. To load the module by hand instead:

```
sudo modprobe snd-virmidi midi_devs=4
```

Then choose **VirMIDI N-0** in Arcadance and, in the receiving program, the input *Virtual Raw MIDI* (VirMIDI N-1 appears as *Virtual Raw MIDI 2*, and so on).

SYNC

How Arcadance keeps time: no beat (free), its own internal clock, or Ableton Link. See *Playing in time* in the Loops chapter.



- **Clock**: *Free* (the default), *Internal* or *Ableton Link*, as the clock button of the top bar. The tempo shows beside it; with Link, the number of peers too.
- **Loops snap to**: the unit a loop recorded with a clock is rounded to: *1 beat* (the default), *1 bar*, *2 bars* or *4 bars*. *Free* keeps loops free even with a clock.
- **Beats per bar**: 1 to 16 (4 by default), for the bars shown in the headers, the grid and the clock button.
- **Quantize notes**: *Off* (the default), *1/8*, *1/16* or *1/32*: the grid the notes recorded into a synced note loop go on (see the Loops chapter).
- **MIDI clock out** (with the internal clock): On (the default) sends MIDI Clock, 24 pulses a beat, with Start on ▶ and Stop on ■, so external devices follow Arcadance's tempo; Off sends none.
- **Start / stop sync** (with Ableton Link): *On* (the default): ▶ and ■ start and stop the Link session, and the loops follow when another app does. *Off*: they only act on Arcadance.

D-PAD

Delay on press and **Delay on release** (0–80 ms, 15 ms by default) set how long a new D-pad direction must hold before it plays. They keep the arrow crossed while pressing or releasing a diagonal from sounding. Set 0 to play every direction at once.

HUMANIZE

Humanization varies velocity and timing at random, for a less mechanical feel.

- **Channels:** the channels it applies to. **All** and **None** select every channel or none.
- **Velocity:** a range in percent of the velocity set in the mapping (100 % by default).
- **Delay:** a range of delay, from 0 to 500 ms.


Every note, including each note of a chord, draws its own velocity and delay within these ranges. Its release is delayed by the same amount, so its length does not change. A control can opt out with the **Humanize** box of its mapping window. PANIC also drops notes still waiting to play.

PRESETS

Folder shows the folder Arcadance reads presets from; **Change...** picks another one. The default is `~/.local/share/Arcadance/Arcadance/presets`.

DISPLAY

How many frames a second the window draws. The view moves all the time, so it is drawn again on every frame; on a fast screen (120, 144 or 240 Hz) and a small graphics chip, that can keep the GPU busy.



- **Frame rate**: Screen (the default) draws as often as the screen refreshes; 60 or 30 draw at most that many frames a second, for less GPU work. The view stays smooth at 60.
- **30 fps when in the background**: while another window has the focus (your DAW, say), the window draws at most 30 frames a second, and goes back to its frame rate as soon as you click it. Off by default.

Render at standard resolution (off by default, from the next start): on a scaled screen (125 %, 200 % on Wayland), Arcadance draws its window at its size in points and the desktop stretches it to the

screen, instead of drawing every pixel of the screen itself. At 125 %, that is 36 % fewer pixels to draw, for a slightly less sharp picture. Where the screen is not scaled, or with X11, it changes nothing.

MIDI and the controller do not depend on it: they run on their own thread, 1,000 times a second.

EDIT MENU


The buttons that drive the session screen and the edit mode (chapter 4): **Select** (L3 / R3 by default), **Menu** and **Back** (none by default). Choose, for example, Cross, Triangle and Circle. Select and Menu may be the same button: a press opens the menu of what is under the cursor, and the same button then chooses in it. The lists offer the face buttons, the stick clicks, L1 and R1, the touchpad click, Create, Options, PS, Mute and the four D-pad arrows. There, these buttons do this instead of what the preset gives them; on the main screen they play as usual, so a Freeze on L3 and R3 keeps working once Select is on another button.

In the lists, a dot marks each button that already does something in channel 1's mapping; point at it to read what. Amber is a warning: the button plays a chord on the main screen, or a D-pad arrow would no longer move the cursor. Red, greyed out, cannot be chosen: Loop record (you could not record in the session screen), Shift (Shift + Mode opens the edit mode) and the Mode button. Under the lists, what the chosen buttons play on the main screen. The Mode button itself is an action of the mapping (chapter 6). These settings belong to Arcadance, not to a preset.



About and updates


☰ › **About…** shows Arcadance's version and license. **Check for updates** asks GitHub whether a newer version exists, only when you click (through `curl`): *Arcadance 0.24 is available.* comes with a **Download page** button, *You have the latest version.* otherwise. If GitHub cannot be reached, the window says so and offers the releases page.




12. Presets


A preset is a complete layout: channel 1's mapping, the other channels' own mappings and the loop settings, stored in one JSON file. Switch presets to move from one song or setup to another.

The PRESET menu



- Click the preset name to open the list: every preset of the presets folder, then **New...**, **Save as...** and **Delete...**.
- The ◀ and ▶ arrows on each side load the previous or next preset.
- **New...** creates an empty preset, asking for its name.
- **Save as...** saves a copy of the current preset under a new name and switches to it.
- **Delete...** deletes the current preset after a confirmation. The file is deleted for good.





Saving

Every change is heard at once but kept in memory until you save. Press `Ctrl+S` or click **Save preset** in any mapping window. If you open another preset or quit with unsaved changes, Arcadance asks

whether to **Save**, **Don't save** or **Cancel**.

Arcadance reopens the last preset used at the next start. To start from a given file instead, pass it on the command line; its folder becomes the presets folder:

```
arcadance ~/Music/live-set.json
```

The preset file

Presets are plain text files, `<name>.json`, in the presets folder. You can read, copy, share and edit them in any text editor; after editing a preset that is open in Arcadance, load another preset and come back to it with the arrows to load your changes, rather than clicking **Revert**, which only discards changes made in the window. Here is a short preset: Cross plays a chord, the left stick sends two CCs, and channel 16 has its own mapping and the name DRUMS.

```
{
    "format": "arcadance-preset",
    "version": 2,
    "name": "My Preset",
    "base": {
        "buttons": {
            "south": { "type": "chord", "chord": "Fm9", "octave": 4, "root_below": 2
},
            "right_shoulder": { "type": "loop_record" }
        },
        "dpad": {
            "up": { "type": "chord", "chord": "Abmaj9", "mode": "toggle" }
        },
        "axes": {
            "left_x": { "cc": 40 },
            "left_y": { "cc": 41, "invert": true }
        }
    },
    "channels": {
        "16": {
            "buttons": { "south": { "type": "note", "note": 53 } }
        }
    },
    "channel_names": { "16": "DRUMS" }
}
```

The top level holds `base` (channel 1's mapping, which every channel without its own plays) and, optionally, `channels`: one mapping per channel number, from "2" to "16" (a mapping under "1", from older files, is read as the base one). Each mapping has up to seven sections: `buttons`, `dpad`, `axes`, `touchpad`, `loops` and `shift` (its Shift layer) and tilt. Fields left out take their default value. channel_names, also optional, names channels (chapter 8): by channel number from "1" to "16", up to 24 characters each. Chapter 16 lists every key. Presets saved by MidiPad (format "midipad-preset") open as they are.

`channel_colors` holds the colour of each channel whose colour you changed, by channel number, as a hex value: `{"2": "#FF785A"}`.

> **Note:** if a preset file contains an error, Arcadance refuses it and names the faulty entry, for example `base.buttons.south.note: expected a MIDI note number or a name like "C4"`.

13. Using Arcadance with a DAW on Linux

Arcadance works with any DAW or synthesizer that receives MIDI. The only decision is which port to use, and it depends on how your DAW lists MIDI inputs.

Choosing the port

Your DAW lists...	Output to choose in Arcadance	Input to choose in the DAW
ALSA sequencer ports (most Linux DAWs)	Virtual port "Arcadance"	*Arcadance*
Only hardware MIDI devices	VirMIDI N-0	*Virtual Raw MIDI* (or the name shown next to the port in Arcadance)
JACK MIDI ports only	Virtual port "Arcadance", bridged with `a2jmidid`	*Arcadance* under the a2j bridge
An external synthesizer	Your USB MIDI interface	—

When in doubt, use a VirMIDI port: every program sees it.

Assigning CCs with MIDI learn

Most DAWs and synthesizers assign a CC to a parameter by MIDI learn: you click the parameter, then move the control. Sticks send two CCs at once, which can confuse MIDI learn. To learn one axis alone:

1. Open the stick window and untick **Enabled** for the axis you do not want to learn.
2. Start MIDI learn in the DAW and move the stick.
3. Tick **Enabled** again.

The same applies to loops: their CCs (70–79 by default) are separate from the live CCs, so learn them separately. Record a short loop, then start MIDI learn while it plays.

> **Tip:** use **Axis freeze** to hold a value steady while you assign or check a parameter.

A multitimbral setup

1. Create one instrument track per sound, each listening to the Arcadance port on its own MIDI channel.
2. In Arcadance, give each channel the layout it needs (chapter 8).
3. Put **Channel change** on two buttons to move between instruments while playing.
4. Record loops on each channel: they keep playing while you move on to the next instrument.

Latency

Arcadance reads the controller 1,000 times per second on a dedicated thread, with real-time priority when the system allows it, and sends MIDI directly from that thread. Drawing the window never delays the MIDI. On a typical machine, processing takes about 20 µs per reading. For the lowest latency, prefer a USB connection to Bluetooth.

> **Note:** for real-time priority, your user must be allowed to use it, usually by being in the `audio` group with the limits most audio distributions set up.

14. Running without a window

Arcadance can play a preset without its window, from a terminal: useful on a small computer dedicated to the stage, or to start Arcadance from a script. It reads the first controller connected, before or after the start, and creates a virtual MIDI port named *Arcadance* unless you choose another output.

```
arcadance --headless ~/.local/share/Arcadance/Arcadance/presets/"Electronica Demo.json"
```

The preset reloads automatically whenever its file is saved, so you can edit it in a text editor and hear the result at once. If the new version contains an error, the previous one stays active and the error is printed.

Option	Effect
`-c`, `--connect NAME`	Send to an existing port whose name contains NAME, instead of creating a virtual port (example: `-c "VirMIDI 0-0"`)
`-n`, `--port-name NAME`	Name of the virtual port (default: Arcadance)
`--api alsa|jack`	MIDI system to use on Linux (default: alsa)
`--channel N`	Starting MIDI channel, 1 to 16 (default: 1)
`-m`, `--monitor`	Print every MIDI message sent
`-i`, `--input`	Print the buttons pressed
`--stats`	Print the measured processing times on exit
`--poll-hz N`	Controller readings per second (default: 1000)
`--list-ports`	List the MIDI output ports and exit
`-h`, `--help`	Show the help

Press `Ctrl+C` to stop. Loops and all other features of the preset work as in the window; the choices of the Settings window do not apply: the D-pad delay stays at 15 ms and humanization is off.

15. Troubleshooting

Most problems come from the route between Arcadance and the receiving program. Check that route first: Arcadance's status bar shows where it sends, and the command `aseqdump` shows what it actually sends.

Checking what Arcadance sends

Switch Arcadance's output to the virtual port "Arcadance" for the test, then watch it while you play:

```
aseqdump -l
```

```
aseqdump -p Arcadance
```

Every press and movement prints a line: *Note on*, *Control change*, *Program change* and so on, with its channel. If lines appear, Arcadance works and the problem lies in the route or the receiving program. The first command lists every port; a VirMIDI port cannot be watched this way, because it shows what leaves the port on the other side, not what Arcadance sends into it.

Common problems

Symptom	Cause	Solution
The status bar shows *No gamepad*	Controller not connected or not paired	Reconnect it by USB, or pair it again over Bluetooth (chapter 2)
+ touchpad is missing, the TOUCHPAD module stays still	No access to the touchpad device	Install the udev rule (chapter 2) and reconnect the controller
The DAW does not list Arcadance	The DAW only lists hardware devices	Use a VirMIDI port (chapter 11)
The MIDI output window appears at every start	The saved port is missing	Choose a port again; with VirMIDI, tick **At every startup**
No sound, but `aseqdump` shows messages	The track does not listen to the port or channel	Set the track's input to the port, on all channels; arm or monitor the track
A stick moves two parameters during MIDI learn	Both axes send at once	Untick **Enabled** for the other axis while learning (chapter 13)
A parameter jumps between two values	A loop and a live axis use the same CC	Give the loop its own CCs (red warning in the window)

Symptom	Cause	Solution
The D-pad plays a wrong direction on diagonals	Delay too short for your playing	Raise the D-pad delay in Settings
Program changes have no effect	The host does not pass them to the plugin, or the numbering differs	Check with a MIDI monitor before the plugin; try the VST2 version; check the bank numbering (chapter 10)
Start / Stop do nothing in the DAW	The DAW does not follow external MIDI sync	Enable external sync, or use a CC with MIDI learn (chapter 10)
Notes keep sounding	An instrument missed a note-off	Click **PANIC**
VirMIDI: *The VirMIDI ports are in use*	A program still has the ports open	Close it, then **Apply** or **Remove** again
VirMIDI: *Not authorized*	The password was refused or the dialog closed	Click **Apply** again and enter the administrator password

Reporting a problem

When something behaves unexpectedly, note the Arcadance version, the controller and how it is connected (USB or Bluetooth), the output port, and the output of `aseqdump` while you reproduce the problem.

16. Reference

Keyboard shortcuts

Shortcut	Action
`Ctrl+S`	Save the preset
`Ctrl+Q`	Quit (asks about unsaved changes)
`F11`	Fullscreen on or off
`Esc`	Close the window or dialog in front
`Wheel, double-click` on the tempo	Change the clock's tempo, or type it (chapter 9)
`Drag` in the note loop editor	Move loop notes, select them in a rectangle, change their length by their end, or the loop's by the right edge (chapter 9)
Right-click on a note in the editor, or on a LOOP panel or the piano roll	Delete the note, or the selection it belongs to (the Delete key too); elsewhere (a lane, a LOOP panel, the piano roll, a clip, a chain step, a channel), its menu (chapter 4)
Tab	The session screen, then the song screen, then back to the main screen

Files and folders

Item	Location
Program	`Arcadance-0.240-x86_64.AppImage`, where you saved it; `build/release/src/app/arcadance` after building
Settings	`~/.local/share/Arcadance/Arcadance/settings.json`
Presets (default)	`~/.local/share/Arcadance/Arcadance/presets/`
Sessions	`~/.local/share/Arcadance/Arcadance/Sessions/` (`.arcadance` files)
Touchpad access rule	`/etc/udev/rules.d/70-dualsense.rules`
VirMIDI at startup	`/etc/modules-load.d/midipad-virmidi.conf`, `/etc/modprobe.d/midipad-virmidi.conf`

Control names

The names used in preset files, with the DualSense labels shown in the window:

Preset key	DualSense	Section
`south`, `east`, `west`, `north`	Cross, Circle, Square, Triangle	`buttons`
`left_shoulder`, `right_shoulder`	L1, R1	`buttons`
`left_trigger`, `right_trigger`	L2, R2 (as buttons)	`buttons`
`left_stick`, `right_stick`	L3, R3 (stick clicks)	`buttons`
`back`, `start`, `guide`	Create, Options, PS	`buttons`
`touchpad`, `misc1`	Touchpad click, Mute	`buttons`
`up`, `up_right`, `right`, `down_right`, `down`, `down_left`, `left`, `up_left`	D-pad directions	`dpad`
`left_x`, `left_y`, `right_x`, `right_y`	Stick axes	`axes`
`left_trigger`, `right_trigger`	L2, R2 (as axes)	`axes`
`finger1`, `finger2`	Touchpad fingers	`touchpad`
`top_left`, `top_right`, `bottom_left`, `bottom_right`	Touchpad zones	`touchpad.fingerN.zones`
`left`, `right`, `finger1`, `finger2`, `triggers`, tilt, `notes`	Loops	`loops`

Action fields

`type`	Fields (default)
`note`	`note` (number or name such as "C4"), `velocity` (100), `mode` ("momentary" or "toggle"), `humanize` (true)
`cc`	`cc`, `value` (127), `off_value` (0), `mode`
`chord`	`chord` (name), `octave` (4), `root_below` (0, 1 or 2), inversion (0), voice_leading (false), `velocity`, `mode`, `humanize`
`transport`	`command`: "start", "stop" or "continue"
`channel`	`step`: 1 or -1
`freeze`	`axes`: list of axis names
`loop_record`	—
`program`	`program` (0–127) or `step` (1 or -1) with `wrap` (true); `bank_msb`, `bank_lsb` (optional)
`shift`	`mode` ("momentary" or "toggle"); `loop_stretch`, from older files, is read as shift

type	Fields (default)
tap_tempo	—
session	—
recenter_tilt	—
effect	effect ("retrigger" or "delay"), count (4; 1 to 16), every ("1/16"; "1/8", "1/8T", "1/16", "1/16T", "1/32", "1/32T" or "1/64"), velocity (a percentage per repeat, 1 to 200; 100 each), transpose (delay: -12 to 12 semitones; 0), mode (delay: "momentary" or "toggle"). The "retrigger" type of 0.2.46 files still reads, as a Retrigger effect

Axis fields

Field	Meaning (default)
cc	Controller number; required unless program is true
min , max	Values at the ends of the travel (0, 127); programs 0–127 in program mode
invert	Reverse the travel (false)
program	Select programs instead of sending a CC (false)
bank_msb , bank_lsb	Bank sent before each program, in program mode (none)
velocity	true: a Velocity axis instead of a CC (false)
transpose	A Transpose axis: {"down": 12, "up": 12, "to": "notes"}, down and up from 0 to 24 semitones, "to": "notes" or "loop"
velocity_to	What a Velocity axis shapes: "notes", "loop" or "both" ("notes")
enabled	false: an axis turned off, its settings kept for when it is turned on again (true)

A touchpad finger takes mode: "axis" (with x and y, each an axis entry) or "zones" (with zones, each an action). A loop entry takes playback ("forward", "reverse", "back_and_forth" or "envelope"; for an envelope, legato: true to start it again only after a silence), cc_x, cc_y and, for an axis in steps, steps_x or steps_y: {"levels": 8, "step": "1/16"} (levels from 2 to 128; step "1/32", "1/16", "1/8", "1/4", "1/2" or "1 bar"). The shift section holds the Shift layer: buttons, dpad and touchpad (finger1 and finger2, each with zones), with the same action entries as the mapping's own; a control left out plays its normal action under Shift too. The tilt section takes enabled (false), active ("held" or "always"; "held"), hold (a button name; "left_shoulder"), angle (15 to 90; 45), and x and y, each an axis entry (CC 64 and 65 by default; null: off).

Timing values

Value	Setting
Controller readings	1,000 per second
D-pad delay	15 ms on press and release, 0–80 ms in Settings
Trigger as button	Press at 25 %, release at 15 % of the travel
Program Change from an axis	Sent after 150 ms on the same program
Overdub tap	Shorter than 500 ms; with Shift, two taps within 350 ms lock or unlock the note loop
Loop recording	200 samples per second, 60 s at most
Note loop	Up to 4,096 note events per channel
Humanize delay	0–500 ms
Loop length (stretch)	-20x to +100x, steps of 0.5; Shift button + X (or Shift key + wheel)
Loop amplitude	0 % to 800 %, steps of 5 % up to 100 % and of 25 % above; softly clipped at the ends of the CC range; eased in; Shift button + Y (or Ctrl + wheel)
Shift with a stick	Dead zone 25 % of the half travel; 2 to 40 length steps, 2 to 20 amplitude steps a second; 0.4 s pause at 1x and at 100 %
Shift with a finger	One step every 3 % of the touchpad's width or height
Loop sync (Ableton Link)	Length rounded to whole snaps (1 beat by default), one at least; start moved to the nearest snap; 4 beats per bar by default (1–16)
Tempo	20–999 BPM; wheel: 1 BPM a notch, 0.1 with the Shift key; internal clock at 120 BPM at first; MIDI clock out at 24 pulses a beat
Tap tempo	Median of the last 4 intervals; starts over after a 2 s pause
Quantize grid	1/8, 1/16 or 1/32 notes: 2, 4 or 8 steps a beat
Transpose	Up to 24 semitones each way; with a tonality, 12 semitones = one octave of degrees