INFORMATION CIRCULATION AND EXTERNAL-FLOW SUPPRESSION UNDER FINITE CAPACITY

YUNJU LEE

Independent Researcher
Seoul, Republic of Korea
eka7268de@aol.com

We study ensemble-averaged information measures in discrete-time stochastic systems whose components have finite state spaces. Their temporal evolution is induced by changes in the underlying joint probability distributions, as occur during relaxation or after an interaction is activated. We first derive the entropy and transfer-entropy balance identities needed for the analysis. Under deterministic reversible dynamics, specified restrictions on synergistic interactions, strong blocking flows, and fixed nonempty information-flow support, a directed cycle is necessary for the vector of component entropies to be constant or periodic. We then consider an external input merging with a pre-existing circulating input at a receiving node with q_P states. Under explicit assumptions on the receiver, the external transfer entropy is bounded by the remaining conditional-entropy margin, $\ln q_P - H(P'|P)$. The result constrains admissible transfer; a decrease in realized transfer is established separately for particular models. A two-bit network with a Fredkin-type gate attains the bound when the external interaction is activated and subsequently exhibits transient information dynamics. The analysis identifies how finite receiving capacity constrains additional information transfer in systems with pre-existing circulation.

Keywords: information circulation; information dynamics; transfer entropy; cross-talk.

1. Introduction

When several signals enter a component with finitely many possible states, the receiving component cannot retain arbitrarily much information about all of them. This raises a concrete question for a system with feedback: how much information can a new external input transfer to a component that already participates in an internal information circulation? We address this question through the evolution of Shannon entropy, mutual information, and transfer entropy at a specified temporal resolution.

Feedback loops occur in gene regulatory networks [1,2,11,15,40], thalamocortical circuits [43], Arctic climate feedbacks [23], and predator-prey systems [6]. Transfer entropy provides a common statistical language for describing directed predictive dependence in such systems [7, 42]. Here, *information circulation* means a directed cycle of nonzero transfer-entropy links between components. Its interpretation is statistical: pairwise transfer entropy alone does not identify an intervention-based causal mechanism.

Information dynamics is studied in information thermodynamics [17, 21, 22, 36, 47], quantum thermodynamics [12, 29, 39], neuroscience [45, 50], and bioinformatics [24]. Mutual information and transfer entropy characterize correlations and directed dependence, while their time dependence describes the reorganization of these relationships [3, 19, 38, 41].

The present work concerns *ensemble-averaged* quantities for finite-state stochastic processes. Nonstationarity is relevant because switching on an external input generally changes the joint distribution and initiates a transient response. A time-independent update rule can also produce nonstationary distributions when the initial ensemble is not invariant. In a strictly stationary process, the ensemble measures considered here are constant, although transfer entropy can remain nonzero. This distinction separates the present question from the evolution of local information values along individual trajectories [30]; both descriptions are useful, but they answer different questions.

Ref. [28] expresses finite-time changes in entropy, mutual information, transfer entropy, and reversed transfer entropy as exact balance identities. The additional terms, denoted by α, are defined combinations of conditional entropies and information measures. They are determined by the underlying stochastic process. Their vanishing defines a restricted class of processes rather than an automatic property of an information measure. Section 2 introduces the process, defines the notation, and derives the pairwise balances used below, so the analysis does not require prior familiarity with that framework.

We obtain two results with distinct assumptions. First, Sec. 3 shows that an active finite information-flow network must contain a directed cycle if its vector of component entropies is constant or periodic, provided the deterministic reversible, blocking-flow, non-synergy, and fixed-support hypotheses hold. The result is a necessary condition within this class; it does not assert that every cycle produces oscillations or that bounded monotone relaxation is impossible. Section 4 then describes a single circulation and its response to an external input under specified zero-control conditions.

Second, Sec. 5 analyzes the receiving node directly. Its finite state space gives an entropy ceiling, and under the stated receiver assumptions the remaining conditional-entropy margin bounds the newly incoming transfer entropy. This is a bound on admissible transfer. Monotonic suppression of the realized transfer requires a specified family of probability laws and is examined separately in the examples. Section 6 gives a two-bit Fredkin-type construction and distinguishes the comparison across input ensembles from the subsequent evolution in time. The scope and assumptions are kept explicit throughout the calculations.

2. Stochastic Setting and Information Balances

2.1. *Finite-state processes and entropy capacity*

Consider an N-component stochastic process $\mathbf{\Gamma}(t) = (\Gamma_1(t), \ldots, \Gamma_N(t))$ at integer times t. Component i takes values in a fixed finite alphabet $\mathcal{M}_i$, with $q_i = |\mathcal{M}_i|$. The joint state space is $\mathcal{M} = \prod_i \mathcal{M}_i$. Thus the basic objects are the joint probability laws of a discrete-time, finite-state process. Deterministic dynamics are included by allowing the probability law to describe uncertainty over initial conditions.

A convenient specification is an initial law p_0 and a first-order transition kernel W_t. In that case,

$$\begin{aligned} p_t(\boldsymbol{x}) &= \Pr\{\mathbf{\Gamma}(t) = \boldsymbol{x}\}, \\ p_{t+1}(\boldsymbol{y}) &= \sum_{\boldsymbol{x}\in\mathcal{M}} p_t(\boldsymbol{x}) W_t(\boldsymbol{y}|\boldsymbol{x}). \end{aligned} \tag{1}$$

The two-time law is $p_t(\boldsymbol{x})W_t(\boldsymbol{y}|\boldsymbol{x})$, and the kernel determines longer joint laws by iteration. The identities below require only the relevant consistent joint laws; they do not require a first-order Markov assumption. For processes with memory, those laws must be supplied separately or the state must be enlarged. No closed autonomous evolution of information measures is assumed.

For a variable X with q_X states, we define its *alphabet entropy capacity* as

$$C_X := \max_{p \text{ on } \mathcal{M}_X} H_p(X) = \ln q_X. \tag{2}$$

All logarithms are natural, so information is measured in nats, and $0 \ln 0 = 0$. In particular,

$$0 \le H(X'|X) \le H(X') \le C_X. \tag{3}$$

This capacity is the maximum over distributions on the chosen alphabet. A particular transition rule can impose a lower attainable maximum. The conditional entropy $H(X'|X)$ is the uncertainty in the next state after observing the present state; it is not itself a channel capacity optimized over inputs.

Finite capacity is an assumption on the modeled variables. It can arise from intrinsically discrete states, as in the logic-gate examples, or from a fixed finite observation partition of a continuous state space. In the latter case, the results concern the partition labels and depend on that partition. Coarse graining need not preserve Markovianity, determinism, or reversibility, so the structural hypotheses must be checked for the observed process. We do not apply the finite-alphabet bound to unpartitioned continuous variables or replace Shannon entropy by differential entropy. In particular, continuous state spaces do not by themselves imply infinite differential entropy; its behavior depends on the admissible distributions and constraints.

2.2. *Nonstationarity and ensemble information dynamics*

The time dependence comes from the joint probability laws of the process. For example, an initial law can relax under a fixed kernel, or an external input can

change the kernel at a specified time. Both mechanisms can change the information shared between components. The interaction protocol in this paper starts from a stationary circulation, activates an external input, and examines the resulting transient. Allowing nonstationarity is therefore necessary to describe the response to that protocol.

Strict stationarity means that all finite-time joint laws are invariant under a common time shift. In that case, the ensemble entropies and transfer entropies used here are constant, although nonzero transfer can persist. A constant one-time marginal alone is insufficient to ensure constant transfer entropy, which also depends on a two-time law. We also distinguish a stationary *information state*, meaning constancy of the specified information measures, from strict stationarity of the full process.

The theory concerns distributions rather than a particular estimation procedure. For repeated realizations prepared under the same initial law and protocol, one can estimate a two-time law from the pairs of observations at t and $t+1$ across realizations. This does not require stationarity across t. By contrast, pooling observations over time in one trajectory requires suitable assumptions, typically stationarity together with an appropriate ergodic sampling argument, or a justified local-stationarity approximation. The simulations in Sec. 6 use independent realizations and estimate distributions separately at each time.

2.3. *One-step information measures and notation*

At a given base time, write $X = X(t)$, $X' = X(t+1)$, and $X'' = X(t+2)$. A prime on an information measure or coefficient shifts *every* time argument by one step. Thus

$$\begin{aligned} \Delta H(X) &= H(X') - H(X), \\ \Delta T_{Y\to X} &= T_{Y'\to X'} - T_{Y\to X}, \\ \Delta H(Y|X,X') &= H(Y'|X',X'') - H(Y|X,X'). \end{aligned} \tag{4}$$

The same rule defines $\Delta^2 F = F'' - 2F' + F$. When needed, $T_{Y\to X}(t)$ makes the base time explicit. Around activation, t_0, t_1, t_2 denote successive times, with $t_0 = t_1 - 1$ and $t_2 = t_1 + 1$.

Definition 1. For finite-state variables, Shannon entropy and conditional entropy are [8, 44]

$$\begin{aligned} H(X) &= -\sum_{x\in\mathcal{M}_X} p(x)\ln p(x), \\ H(Y|X) &= H(X,Y) - H(X). \end{aligned} \tag{5}$$

For a finite collection V of variables, $H(V)$ is their joint entropy, evaluated with their joint law on the corresponding product alphabet.

Definition 2. Mutual information and conditional mutual information are [8]

$$\begin{aligned} I(X,Y) &= H(X) + H(Y) - H(X,Y), \\ I(X,Y|Z) &= H(X|Z) + H(Y|Z) - H(X,Y|Z). \end{aligned} \tag{6}$$

Here the comma separates two arguments, each of which may be a random vector.

Definition 3. The one-step transfer entropy and reversed transfer entropy are

$$\begin{aligned} T_{Y\to X} &:= I(X', Y|X), \\ T^{\dagger}_{Y\to X} &:= I(X, Y'|X'). \end{aligned} \tag{7}$$

The first measures the additional predictive information provided by the present source Y about the next receiver state X', beyond the present receiver state X [7,42]. The second uses reversed time indexing [20, 46, 47].

Both are nonnegative conditional mutual informations. We consistently use one-step conditioning; for longer-memory processes this is a specified finite-history quantity, not a claim that conditioning on one receiver state captures its entire past. The reversed measure does not require a physically reversed experiment. Statistical transfer may also reflect common inputs or indirect paths, which is why structural update dependencies are specified separately below.

For comparison with trajectory-level descriptions, the local one-step transfer entropy at a realized triple (x, x', y) is [30]

$$\tau_{Y\to X}(x, x', y; t) = \ln \frac{p_t(x'|x, y)}{p_t(x'|x)}, \qquad T_{Y\to X}(t) = \mathbb{E}_t[\tau_{Y\to X}]. \tag{8}$$

Here p_t denotes the relevant two-time law. A local value can fluctuate along a trajectory even when its expectation is stationary. All subsequent H, I, T, and $T^{\dagger}$ denote ensemble quantities, rather than these local values.

2.4. *Signed multiple-transfer terms and block transfer*

Ordinary transfer entropy already applies to groups of variables. For disjoint collections V and U, let $\mathbf{V}$ and $\mathbf{U}$ be fixed tuples containing their elements. Their ordinary block transfer entropy is

$$T_{\mathbf{V}\to\mathbf{U}} := I(\mathbf{U}', \mathbf{V}|\mathbf{U}) \geq 0. \tag{9}$$

This quantity measures total predictive information between two blocks. The separate multiple-transfer terms below are used to express exact corrections when a block contribution is decomposed into contributions from individual components.

Definition 4. For a nonempty finite collection V, co-information and conditional co-information are the alternating sums [4, 13, 16, 26, 33, 34, 48, 51]

$$\begin{aligned} I(V) &:= \sum_{\varnothing\neq S\subseteq V} (-1)^{|S|+1} H(S), \\ I(V|W) &:= \sum_{\varnothing\neq S\subseteq V} (-1)^{|S|+1} H(S|W). \end{aligned} \tag{10}$$

In particular, $I(\{X\}) = H(X)$ and $I(\{X,Y\}|W) = I(X,Y|W)$. Braces specify that the entries are separate co-information arguments; a bold tuple specifies one block argument.

Definition 5. For disjoint nonempty collections V, U, define the multiple transfer entropy and multiple reversed transfer entropy [28] by

$$\begin{aligned} T_{V\to U} &:= I(V \cup U'|U), \\ T^{\dagger}_{V\to U} &:= I(V' \cup U|U'), \qquad U' := \{X' : X \in U\}. \end{aligned} \tag{11}$$

The I on the right is conditional co-information, with one argument for each element of the union. Singleton braces may be omitted in subscripts.

For two sources and one receiver, this definition gives

$$\begin{aligned} T_{\{A,B\}\to P} &= I(A, P'|P) - I(A, P'|P, B), \\ T_{(A,B)\to P} &= T_{A\to P} + T_{B\to P} - T_{\{A,B\}\to P}. \end{aligned} \tag{12}$$

Thus the multiple-transfer term corrects the sum of pairwise transfers to recover the block transfer. It can be positive, zero, or negative. For independent fair-bit inputs to an XOR receiver, independent also of its present state, the two pairwise transfers vanish, the block transfer is $\ln 2$, and $T_{\{A,B\}\to P} = -\ln 2$. Negative multiple transfer therefore does not contradict nonnegativity of ordinary transfer entropy. Co-information combines contributions associated with redundancy and synergy; it is not used here as a nonnegative decomposition of either. Appendix Appendix A gives the dynamical XOR construction.

More generally, inclusion–exclusion yields

$$T_{\mathbf{K}\to X} = \sum_{\varnothing \neq S \subseteq K} (-1)^{|S|+1} T_{S\to X}, \tag{13}$$

and the same identity holds for reversed transfer. This identity, rather than a new definition of total block transfer, is the reason for introducing the signed terms. Define their net correction by

$$E_{K\to X} := \sum_{\substack{S\subseteq K \\ |S|\geq 2}} (-1)^{|S|} [T_{S\to X} - T^{\dagger}_{S\to X}]. \tag{14}$$

It follows that $T_{\mathbf{K}\to X} - T^{\dagger}_{\mathbf{K}\to X} = \sum_{k\in K}(T_{k\to X} - T^{\dagger}_{k\to X}) - E_{K\to X}$. An empty sum is zero; E need not have a fixed sign.

2.5. *Derivation of the pairwise information balances*

Let K_i be a fixed collection of other component variables, with $K_i' = \{k' : k \in K_i\}$. The entropy identities below hold for any such collection. Later, the network analysis selects collections that contain the forward and inverse update dependencies. They are called causal-parent sets in that structural sense; this terminology does not infer causation from transfer entropy.

We first derive the entropy balance directly. Applying the entropy chain rule twice gives

$$\begin{aligned}\Delta H(X) &= H(X'|X) - H(X|X') \\ &= T_{\mathbf{K}\to X} - T^{\dagger}_{\mathbf{K}\to X} + \alpha_1^{K\to X}, \\ \alpha_1^{K\to X} &:= H(X'|X,K) - H(X|X',K').\end{aligned} \tag{15}$$

Equation (13) then expresses the block transfers in terms of pairwise transfers and E. No stationarity or dynamical approximation has entered this step.

For a pair of components, expansion into joint entropies gives

$$\begin{aligned}\Delta I(X,Y) &= T_{Y\to X} - T^{\dagger}_{Y\to X} + T_{X\to Y} - T^{\dagger}_{X\to Y} + \alpha_2^{X,Y}, \\ \alpha_2^{X,Y} &:= I(X',Y'|X,Y) - I(X,Y|X',Y').\end{aligned} \tag{16}$$

Finally, the source-entropy representations

$$\begin{aligned}T_{Y\to X} &= H(Y) - I(X,Y) - H(Y|X,X'), \\ T^{\dagger}_{Y\to X} &= H(Y') - I(X',Y') - H(Y'|X,X')\end{aligned} \tag{17}$$

imply, upon taking a simultaneous time shift,

$$\begin{aligned}\Delta T_{Y\to X} &= \Delta H(Y) - \Delta I(X,Y) - \alpha_3^{Y\to X}, \\ \Delta T^{\dagger}_{Y\to X} &= \Delta H(Y) - \Delta I(X,Y) + \alpha_4^{Y} - \alpha_5^{X,Y} - \alpha_6^{Y\to X}.\end{aligned} \tag{18}$$

Here $\alpha_3^{Y\to X} = \Delta H(Y|X,X')$, $\alpha_4^{Y} = \Delta^2 H(Y)$, $\alpha_5^{X,Y} = \Delta^2 I(X,Y)$, and $\alpha_6^{Y\to X} = \Delta H(Y'|X,X')$. Substitution of the entropy and mutual-information balances gives the compact form used subsequently [28]:

$$\begin{cases} \Delta H(\Gamma_i) = \displaystyle\sum_{k\in K_i} [T_{k\to\Gamma_i} - T^{\dagger}_{k\to\Gamma_i}] - E_{K_i\to\Gamma_i} + \alpha_1^{K_i\to\Gamma_i} \\ \Delta I(\Gamma_i,\Gamma_j) = [T_{\Gamma_j\to\Gamma_i} - T^{\dagger}_{\Gamma_j\to\Gamma_i}] \\ \qquad\qquad + [T_{\Gamma_i\to\Gamma_j} - T^{\dagger}_{\Gamma_i\to\Gamma_j}] + \alpha_2^{\Gamma_i,\Gamma_j} \\ \Delta T_{\Gamma_j\to\Gamma_i} = \displaystyle\sum_{k\in K_j\setminus\{\Gamma_i\}} [T_{k\to\Gamma_j} - T^{\dagger}_{k\to\Gamma_j}] \\ \qquad\qquad - [T_{\Gamma_j\to\Gamma_i} - T^{\dagger}_{\Gamma_j\to\Gamma_i}] - E_{K_j\to\Gamma_j} + \alpha_1^{K_j\to\Gamma_j} \\ \qquad\qquad - \alpha_2^{\Gamma_i,\Gamma_j} - \alpha_3^{\Gamma_j\to\Gamma_i} \\ \Delta T^{\dagger}_{\Gamma_j\to\Gamma_i} = \displaystyle\sum_{k\in K_j\setminus\{\Gamma_i\}} [T_{k\to\Gamma_j} - T^{\dagger}_{k\to\Gamma_j}] \\ \qquad\qquad - [T_{\Gamma_j\to\Gamma_i} - T^{\dagger}_{\Gamma_j\to\Gamma_i}] - E_{K_j\to\Gamma_j} + \alpha_1^{K_j\to\Gamma_j} \\ \qquad\qquad - \alpha_2^{\Gamma_i,\Gamma_j} + \alpha_4^{\Gamma_j} - \alpha_5^{\Gamma_i,\Gamma_j} - \alpha_6^{\Gamma_j\to\Gamma_i}, \end{cases} \tag{19}$$

with,

$$\begin{aligned}
\alpha_1^{K_i\to\Gamma_i} &:= H(\Gamma_i'|\Gamma_i, K_i) - H(\Gamma_i|\Gamma_i', K_i')\\
\alpha_2^{\Gamma_i,\Gamma_j} &:= I(\Gamma_i', \Gamma_j'|\Gamma_i, \Gamma_j) - I(\Gamma_i, \Gamma_j|\Gamma_i', \Gamma_j')\\
\alpha_3^{\Gamma_j\to\Gamma_i} &:= \Delta H(\Gamma_j|\Gamma_i, \Gamma_i')\\
\alpha_4^{\Gamma_j} &:= \Delta^2 H(\Gamma_j) = \Delta(\Delta H(\Gamma_j)) = H(\Gamma_j'') - 2H(\Gamma_j') + H(\Gamma_j)\\
\alpha_5^{\Gamma_i,\Gamma_j} &:= \Delta^2 I(\Gamma_i, \Gamma_j) = I(\Gamma_i'', \Gamma_j'') - 2I(\Gamma_i', \Gamma_j') + I(\Gamma_i, \Gamma_j)\\
\alpha_6^{\Gamma_j\to\Gamma_i} &:= \Delta H(\Gamma_j'|\Gamma_i, \Gamma_i').
\end{aligned} \tag{20}$$

In the last two equations we choose K_j to contain Γ_i; if necessary it can be enlarged, since the entropy identity is valid for any chosen collection. The α terms are residuals defined by the displayed entropies and time shifts. In particular, α_1 compares unresolved forward and backward uncertainty, α_2 compares conditional correlations across the two slices, α_3 and α_6 describe changes of conditional uncertainty, and α_4 and α_5 are second time differences.

We retain the term *control variables* for consistency with Ref. [28], but their values are fixed by the underlying joint laws. They are not arbitrary external inputs, and the identities do not close an independent evolution law for $H, I, T, T^\dagger$. A *zero-control reduction* imposes specified vanishing residuals. Each subsequent proposition states which vanishing conditions are assumed, and whether they must hold at every step. Higher-order balance identities and their index sets are collected in Appendix Appendix B; the pairwise derivation above and Eq. (14) provide the balances needed to follow the main argument.

2.6. *Blocking-flow assumptions*

The cycle calculations use a directional restriction on each interacting pair A, B:

$$\begin{cases} [T_{B\to A} = 0 \text{ and } T^\dagger_{A\to B} = 0] \\ \text{or } [T_{A\to B} = 0 \text{ and } T^\dagger_{B\to A} = 0]. \end{cases} \quad \text{at every time considered} \tag{21}$$

This is the *blocking-flows condition*. Its strong version additionally requires $T_{B\to A} > 0$ if and only if $T^\dagger_{A\to B} > 0$, for both orientations of each pair. Consequently, nonzero forward-transfer links have reversed counterparts in the reversed-transfer network. These are assumptions about the process; they do not follow from the definition of transfer entropy or from the presence of an update dependency. Section 3 uses the strong version, while the later calculations specify their own restrictions.

2.7. *Deterministic reversible dynamics: hypothesis for the cycle result*

This hypothesis is used for the cycle-necessity result of Sec. 3; it is not imposed on every receiver example. The full-vector update is assumed to be deterministic and

invertible at each step: $\exists\ U = (U_1, U_2, ..., U_N)$ and U^{-1} such that,

$$\begin{aligned}\Gamma'_i &= U_i(\Gamma_1, \ldots, \Gamma_N, t_0)\\ \Gamma_i &= (U^{-1})_i(\Gamma'_1, \ldots, \Gamma'_N, t_1),\end{aligned} \tag{22}$$

where $i \in \{1, 2, ..., N\}$ and $t_1 > t_0$. Then, with $K_i^{total} := \{\Gamma_1, \ldots, \Gamma_N\} - \{\Gamma_i\}$, the following uncertainty vanishes:

$$\begin{aligned}H(\Gamma'_i|\Gamma_i, K_i^{total}) &= 0\\ H(\Gamma_i|\Gamma'_i, K'^{total}_i) &= 0.\end{aligned} \tag{23}$$

Hence, the control parameter $\alpha_1^{K_i^{total}\to\Gamma_i}$ defined in the equation (20) becomes zero in this case:

$$\alpha_1^{K_i^{total}\to\Gamma_i} := H(\Gamma'_i|\Gamma_i, K_i^{total}) - H(\Gamma_i|\Gamma'_i, K'^{total}_i) = 0. \tag{24}$$

A smaller dependency collection can be selected if it suffices for both the forward and inverse updates. We call such a collection a *causal-parent set* in the remainder of the paper: $K_i := \{k_1, \ldots, k_m\} \subset \{\Gamma_1, \ldots, \Gamma_N\}$, such that,

$$\begin{aligned}\Gamma'_i &= U_i(\Gamma_i, k_1, \ldots, k_m)\\ \Gamma_i &= (U^{-1})_i(\Gamma'_i, k'_1, \ldots, k'_m).\end{aligned} \tag{25}$$

Under the assumption of deterministic reversible dynamics, such a set exists, since the set K_i^{total} satisfies Eq. (25). Hence, by subtracting one by one from K_i^{total} while preserving Eq. (25), the smaller set of the causal parents is obtained. Such a set need not be unique, and its elements need not all be direct forward parents: some may be needed only to reconstruct the inverse update. It is a sufficient two-direction dependency collection, rather than the parent set of a graph inferred from observations. For each component i, we choose one set K_i satisfying both relations in Eq. (25), and this choice is held fixed throughout Section 3.
As a result,

$$\alpha_1^{K_i\to\Gamma_i} := H(\Gamma'_i|\Gamma_i, K_i) - H(\Gamma_i|\Gamma'_i, K'_i) = 0. \tag{26}$$

2.8. *Excluding purely synergistic incoming transfer*

Let the neighbor set of a component v be $K = \{k_1, \ldots, k_m\}$, and define an arbitrary but fixed tuple $\mathbf{K} := (k)_{k\in K}$. Then, the transfer entropy and reversed transfer entropy,

$$\begin{aligned}T_{\mathbf{K}\to v} &:= I(\mathbf{K}, v'|v)\\ T^{\dagger}_{\mathbf{K}\to v} &:= I(\mathbf{K}', v|v'),\end{aligned} \tag{27}$$

are distinct from the multiple transfer entropy $T_{K\to\{v\}}$ and multiple reversed transfer entropy $T^{\dagger}_{K\to\{v\}}$ defined in Sec. 2.4.

Decomposing $T_{\mathbf{K}\to v}$ and $T^{\dagger}_{\mathbf{K}\to v}$ yields:

$$\begin{aligned} T_{\mathbf{K}\to v} &= T_{k\to v} + I(\mathbf{K}_{\setminus k}, v'|v, k) \\ T^{\dagger}_{\mathbf{K}\to v} &= T^{\dagger}_{k\to v} + I(\mathbf{K}'_{\setminus k}, v|v', k'), \end{aligned} \tag{28}$$

for $k \in K$.

Since the right hand terms are non-negative, $T_{k\to v} = 0$ for all $k \in K$ if $T_{\mathbf{K}\to v} = 0$, and $T^{\dagger}_{k\to v} = 0$ for all $k \in K$ if $T^{\dagger}_{\mathbf{K}\to v} = 0$. Nevertheless, the converse is not generally true, as the counterexample is presented in Appendix A. To exclude incoming information that is invisible to every individual source, the analysis of Sec. 3 assumes that the converse holds, i.e., if $T_{k\to v} = 0$ for all $k \in K$, then $T_{\mathbf{K}\to v} = 0$, and if $T^{\dagger}_{k\to v} = 0$ for all $k \in K$, $T^{\dagger}_{\mathbf{K}\to v} = 0$. We refer to this condition as the non-synergy assumption for brevity. It is a zero-detection condition, not a claim that every co-information or correction E vanishes, or that all forms of synergy are absent. It excludes the pure synergistic effect, such as the XOR operation (Appendix A), while including, for example, the ternary additive receiver (Sec. 5.4.1).

3. General Information Dynamics of a Finite System

We now specify precisely which graph is used and which hypotheses support the cycle result. A vertex labels a *component process* $\{\Gamma_i(t)\}_t$, not one state value and not a separate copy of a variable at one time. We take the vertex set to be the component labels $V = \{1, \dots, N\}$ (or named labels such as A, P in examples). Expressions such as $H(v)$ and $T_{u\to v}$ abbreviate $H(\Gamma_v(t))$ and $I(\Gamma_v(t+1), \Gamma_u(t)|\Gamma_v(t))$. This component graph differs from a time-unrolled dependency graph, whose vertices would be (i, t).

The standing hypotheses in this section are finite alphabets, deterministic invertible full-vector updates (Sec. 2.7), fixed sufficient dependency collections K_v, strong blocking flows (Sec. 2.6), the forward and reversed zero-detection conditions of Sec. 2.8, and fixed nonempty information-flow support. To compare the two transfer networks, choose the dependency neighborhoods symmetrically: if $\Gamma_u \in K_v$, include Γ_v in K_u. Such enlargement preserves sufficiency of the forward and inverse updates. The zero-detection assumption is imposed on these chosen collections. These hypotheses are additional restrictions on a process, not generic properties of finite-state dynamics.

We use the following standard graph definitions [9, 25].

Definition 6. A **directed graph** is a pair $G = (V, \overrightarrow{E})$, where V is a finite set of vertices and $\overrightarrow{E} \subset \{(x, y) \in V \times V | x \neq y\}$ is a set of directed edges. Also, the reversed edge set $\overleftarrow{E} := \{(y, x)|(x, y) \in \overrightarrow{E}\}$ is defined. Then, the **in-degree** of a vertex $v \in V$ is $d^-(v) = |\{x \in V|(x, v) \in \overrightarrow{E}\}|$, while the **out-degree** of a vertex $v \in V$ is $d^+(v) = |\{x \in V|(v, x) \in \overrightarrow{E}\}|$.

Throughout this section, a directed graph $G = (V, \overrightarrow{E})$ is assumed to have no isolated vertices; that is, every vertex $v \in V$ satisfies $d^-(v) + d^+(v) > 0$.

Definition 7. A **source** in a directed graph $G = (V, \overrightarrow{E})$ is the vertex $v \in V$ with $d^-(v) = 0$ and $d^+(v) \neq 0$, and a **sink** in a directed graph $G = (V, \overrightarrow{E})$ is the vertex $v \in V$ with $d^+(v) = 0$ and $d^-(v) \neq 0$.

Definition 8. A **cycle** C in a directed graph $(V, \overrightarrow{E})$ is a sequence of distinct vertices $v_1, \ldots, v_n$, with $n \geqslant 2$, such that $(v_i, v_{i+1}) \in \overrightarrow{E}$ for $i = 1, \ldots, n-1$, and $(v_n, v_1) \in \overrightarrow{E}$.

Definition 9. A directed graph is **acyclic** if it contains no cycle.

Let $\mathcal{P}_v := \{u \in V \setminus \{v\} : \Gamma_u \in K_v\}$ be the label set corresponding to K_v. The structural dependency graph has an edge $u \to v$ when $u \in \mathcal{P}_v$. The graph used in the theorem is the *information-flow graph*

$$G_T(t) = (V, \overrightarrow{E}_T(t)), \qquad \overrightarrow{E}_T(t) := \{(u, v) : u \in \mathcal{P}_v,\ T_{u\to v}(t) > 0\}. \tag{29}$$

A structural dependency need not give a positive transfer entropy for a particular ensemble. An information edge records predictive dependence for the actual ensemble within the specified dependency neighborhood. *Fixed support* means that $\overrightarrow{E}_T(t)$ is the same edge set at every time in the interval considered; its positive weights may vary. Under the strong blocking condition and the symmetric neighborhood convention, the reversed-transfer graph has exactly the reversed edges. A cycle of G_T is what we call information circulation.

We discard isolated vertices and require at least one edge. Without this qualification, a collection of independent constant components would give stationary entropies and no information cycle. The result below concerns active information networks, and stationarity refers to constancy of the component-entropy vector.

Propositions 1 and 2 show that acyclic information networks necessarily exhibit monotonic entropy evolution, preventing stationary or periodic entropic dynamics under the present assumptions.

Proposition 1. *An acyclic graph must include at least one source and one sink.*

(proof) Start at a vertex and follow an incoming edge backward whenever possible. A vertex cannot be revisited, because that would produce a directed cycle. Finiteness therefore forces the path to stop at a vertex with no incoming edge. Since isolated vertices have been excluded, this vertex has an outgoing edge and is a source. Applying the same argument to the graph with every edge reversed gives a sink in the original graph. □

While Proposition 1 is a classical result of graph theory, Proposition 2 focuses on the information dynamical consequences within the framework of 2.5, implying that, in acyclic information networks, individual entropy cannot be stationary or periodic.

Proposition 2. *Let $G_T = (V, \overrightarrow{E})$ be a directed network of pairwise transfer entropy with fixed support. Under the standing assumptions of this section and the non-synergistic assumption of Sec. 2.8, if G_T is acyclic, then the individual entropy of every sink is strictly increasing at each step of that interval.*

(proof) From Proposition 1, G_T has a sink $v \in V$: $\exists k \in K_v$ such that $T_{k\to v} > 0$, where K_v is the fixed causal-parent set of v. Then, the dynamics of v's individual entropy (Eq. (19)) is,

$$\begin{aligned}\Delta H(v) &= \sum_{k\in K_v} [T_{k\to v} - T^{\dagger}_{k\to v}] - E_{K_v\to v} + \alpha_1^{K_v\to v} \\ &= \sum_{k\in K_v} [T_{k\to v} - T^{\dagger}_{k\to v}] - E_{K_v\to v} \\ &= T_{\mathbf{K}_v\to v} - T^{\dagger}_{\mathbf{K}_v\to v}, \end{aligned} \tag{30}$$

where $\mathbf{K}_v := (k)_{k\in K_v}$.
Here, $\alpha_1^{K_v\to v} = 0$ due to the assumption of deterministic and reversible dynamics. Since v is a sink, $T_{v\to k} = 0$ for every $k \in K_v$. By the strong blocking flows condition, $T^{\dagger}_{k\to v} > 0$ would imply $T_{v\to k} > 0$, contradicting the sink property. Hence, $T^{\dagger}_{k\to v} = 0$ for every $k \in K_v$. The reversed non-synergy assumption of Section 2.8 requires $T^{\dagger}_{\mathbf{K}_v\to v} = 0$. In addition, by definition, $T_{\mathbf{K}_v\to v} := I(\mathbf{K}_v, v'|v) \geqslant 0$. If $T_{\mathbf{K}_v\to v} = 0$, then $T_{k\to v} = 0$ for all $k \in K_v$ by the argument in Section 2.8, which contradicts the fact that v is the sink.
Therefore,

$$\Delta H(v) = T_{\mathbf{K}_v\to v} > 0. \tag{31}$$

□

Since $\Delta H(v) > 0$ at every step, $H(v)$ is strictly increasing and therefore cannot be constant or periodic over any interval on which the support and the standing assumptions remain valid. If bounded, $H(v)$ may nevertheless converge monotonically to a limiting value. Consequently, one can conclude that the information-dynamical entropic state of a whole system, $\{H(u)\}_{u\in V}$, cannot be stationary or periodic in this acyclic case, as the system has a node with such monotonic behavior. Therefore, we restrict our analysis to finite information networks with cycles to investigate other kinds of dynamical behaviors.

4. Information Dynamics of a Finite System with a Cycle

The information dynamics of finite systems containing a cycle is analyzed within the framework of Sec. 2, focusing on the behavior of a single cycle and its interaction with an external information source. Prior to that, the dynamics of an isolated cycle is considered.

4.1. *The Stationary State of a Single Cycle*

Let an N-component system $\Gamma = \{\Gamma_0, \Gamma_1, \ldots, \Gamma_{N-1}\}$ form a one-dimensional system with periodic boundary condition. In the index notation, $\bmod N$ is assumed in this section. Take $K_i = \{\Gamma_{i-1}, \Gamma_{i+1}\}$ and the oriented blocking conditions $T_{\Gamma_i \to \Gamma_{i-1}} = T^{\dagger}_{\Gamma_i \to \Gamma_{i+1}} = 0$. For this subsection, specialize the balances to $E_{K_i \to \Gamma_i} = \alpha_1^{K_i \to \Gamma_i} = \alpha_2^{\Gamma_i, \Gamma_{i+1}} = 0$ and $\alpha_3^{\Gamma_i \to \Gamma_{i+1}} = \alpha_6^{\Gamma_i \to \Gamma_{i-1}} = 0$, at every step. The zero residuals in the next time slice are included. Substituting into Eq. (19), or using the time-shifted identities in Appendix Appendix C, yields [28]

$$\begin{aligned}
\Delta H(\Gamma_i) &= T_{\Gamma_{i-1} \to \Gamma_i} - T^{\dagger}_{\Gamma_{i+1} \to \Gamma_i} \\
\Delta I(\Gamma_i, \Gamma_{i+1}) &= T_{\Gamma_i \to \Gamma_{i+1}} - T^{\dagger}_{\Gamma_{i+1} \to \Gamma_i} \\
\Delta T_{\Gamma_i \to \Gamma_{i+1}} &= T_{\Gamma_{i-1} \to \Gamma_i} - T_{\Gamma_i \to \Gamma_{i+1}} \\
\Delta T^{\dagger}_{\Gamma_i \to \Gamma_{i+1}} &= 0 \\
\Delta T_{\Gamma_i \to \Gamma_{i-1}} &= 0 \\
\Delta T^{\dagger}_{\Gamma_{i+1} \to \Gamma_i} &= T^{\dagger}_{\Gamma_i \to \Gamma_{i-1}} - T^{\dagger}_{\Gamma_{i+1} \to \Gamma_i}.
\end{aligned} \tag{32}$$

These equations describe the circulation of transfer entropy and reversed transfer entropy along the cycle. A stationary state is achieved when the transfer entropy and reversed transfer entropy are uniformly distributed along the cycle, satisfying $T_{\Gamma_{i-1} \to \Gamma_i} = T_{\Gamma_i \to \Gamma_{i+1}}$, $T^{\dagger}_{\Gamma_i \to \Gamma_{i-1}} = T^{\dagger}_{\Gamma_{i+1} \to \Gamma_i}$, and $T_{\Gamma_{i-1} \to \Gamma_i} = T^{\dagger}_{\Gamma_{i+1} \to \Gamma_i}$. This corresponds to a constant circulation of information along the cycle. As shown in Ref. [27], small deviations from this stationary state remain bounded in the examples analyzed there.

4.2. *The Transient Behaviors of the Single Cycle and a Random Source*

Consider the interaction between a single cycle and an external information source. Let an external component Ext begin to interact with a component p in the cycle at the time $t = t_1$ as shown in Fig. 1, while no interaction is present at earlier times. Therefore, the stationary state of the previous section is assumed for the time $t = t_0 < t_1$. The interaction is a change in the update protocol: $T(t_0)$ uses the pre-activation transition $t_0 \to t_1$, whereas $T(t_1)$ uses $t_1 \to t_2$, the first activated transition. The coefficient abbreviation used below is

$$\alpha_{3456}^{Y \to X} := -\alpha_3^{Y \to X} - \alpha_4^{Y} + \alpha_5^{X,Y} + \alpha_6^{Y \to X}. \tag{33}$$

Proposition 3 gives the resulting balances under its explicitly stated residual conditions. It specializes the identities; it does not determine a response for an unspecified stochastic model.




Fig. 1. Schematic illustrations of information dynamics on a cycle interacting with a random source (*Ext*). Blue arrows represent transfer entropy, and red arrows represent reversed transfer entropy.

Proposition 3. *Consider the activation protocol above with the blocking flows specified in Appendix Appendix C. Impose the residual conditions in Eq. (C.2) at every step, together with the initial condition* $E_{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = 0$ *for* $i \neq p$. *The forward transfers adjacent to the receiving component obey*

$$\begin{aligned}
\Delta T_{\Gamma_{p-1}\to\Gamma_p} &= T_{\Gamma_{p-2}\to\Gamma_{p-1}} - T_{\Gamma_{p-1}\to\Gamma_p} - \alpha_3^{\Gamma_{p-1}\to\Gamma_p}, \\
\Delta T_{\Gamma_{Ext}\to\Gamma_p} &= \alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} - T_{\Gamma_{Ext}\to\Gamma_p} - \alpha_3^{\Gamma_{Ext}\to\Gamma_p}, \\
\Delta T_{\Gamma_p\to\Gamma_{p+1}} &= T_{\Gamma_{p-1}\to\Gamma_p} + T_{\Gamma_{Ext}\to\Gamma_p} - T_{\Gamma_p\to\Gamma_{p+1}} \\
&\quad - E_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}.
\end{aligned} \tag{34}$$

The full system, including entropy, mutual information, and reversed-transfer balances, is given in Eq. (C.1) in Appendix Appendix C.

(proof) Appendix C.

These equations show that the external source modifies the information flow locally at component p, where the incoming flow $T_{\Gamma_{Ext}\to\Gamma_p}$ merges with the circulating flow $T_{\Gamma_{p-1}\to\Gamma_p}$. The corresponding control variables determine how the newly activated interaction is incorporated into the pre-existing circulation.

The changes at activation are recorded in the residual terms associated with the receiving component and the newly opened channel. For example, the external-transfer balance reads

$$\Delta T_{\Gamma_{Ext}\to\Gamma_p} = \alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} - T_{\Gamma_{Ext}\to\Gamma_p} - \alpha_3^{\Gamma_{Ext}\to\Gamma_p}. \tag{35}$$

With zero baseline transfer, the first post-activation value is the difference of the two residual contributions on the right. Evaluating it requires the joint law generated




Fig. 2. Schematic illustration of the merging of two information flows at time **(a)** $t = t_0$ and **(b)** $t = t_1$. Blue arrows denote transfer entropy, and red arrows denote reversed transfer entropy.

by the source and receiver update rules. Thus the residuals describe the response; assigning them independently does not specify a realizable response.

Every actual stochastic process satisfies the exact balance identities, but arbitrary choices of the information variables and residuals need not correspond to consistent probability laws. In particular, a zero-control reduction can fail to respect the alphabet bound when extended beyond its range of applicability, as illustrated in Sec. 5.2. The next section derives an explicit capacity constraint directly from the receiver's conditional entropies.

5. The Merging of Two Information Flows

When a cycle of information flow interacts with an external information source, the manner in which two information flows merge at a single component determines the resulting dynamics. The merging of two information flows is analyzed within the framework of Sec. 2.5.

5.1. *Problem Setting*

Let A, B, P and Q be random variables defined over an ensemble, representing the states of four components. We consider a configuration in which the components represented by A and B interact with the component represented by P, while P also interacts with the component represented by Q (Fig. 2). At time $t = t_0$, the components A, P, and Q interact with each other, with the nonzero stationary transfer entropy $T_{A\to P} = T_{P\to Q} = \mu_A \neq 0$ and reversed transfer entropy $T^{\dagger}_{P\to A} = T^{\dagger}_{Q\to P} = \mu_A$, while the component B is not interacting with the component P, implying $T_{B\to P} = 0$ and $T^{\dagger}_{P\to B} = 0$. Then, the components B and P start

to interact at the time $t = t_1$. Here $q_P := |\mathcal{M}_P|$ is fixed throughout, $C_P = \ln q_P$, and the downstream component Q is a separate random variable. The baseline assumptions include the stated blocking flows and zero higher-order correction before activation. The balance identities (Eq. (19)) express the first post-activation transfers as follows:

$$\begin{aligned}
T_{B'\to P'} &= \Delta T_{B\to P} = \sum_{k\in K_B\setminus\{P\}} [T_{k\to B} - T^{\dagger}_{k\to B}] \\
&\quad - E_{K_B\to B} + \alpha_1^{K_B\to B} - \alpha_2^{B,P} - \alpha_3^{B\to P}, \\
T^{\dagger}_{P'\to B'} &= \Delta T^{\dagger}_{P\to B} \\
&= [T_{A\to P} - T^{\dagger}_{Q\to P}] - E_{\{A,B,Q\}\to P} \\
&\quad + \alpha_1^{\{A,B,Q\}\to P} - \alpha_2^{B,P} + \alpha_4^{P} - \alpha_5^{B,P} - \alpha_6^{P\to B}.
\end{aligned} \tag{36}$$

The conditions $T_{B\to P} = T^{\dagger}_{P\to B} = 0$ and the stationary conditions $\Delta I(B, P) = 0$ imply that $\alpha_2^{B,P} = 0$. We also assume the pre-activation baseline $E_{\{A,B,Q\}\to P} = E_{\{A,Q\}\to P} = 0$. This is a condition on the baseline joint law; absence of a pairwise transfer from B alone would not establish it, because higher-order dependence can be hidden from pairwise measures.

$$\begin{aligned}
T_{B'\to P'} &= \sum_{k\in K_B\setminus\{P\}} [T_{k\to B} - T^{\dagger}_{k\to B}] - E_{K_B\to B} \\
&\quad + \alpha_1^{K_B\to B} - \alpha_3^{B\to P}, \\
T^{\dagger}_{P'\to B'} &= [T_{A\to P} - T^{\dagger}_{Q\to P}] + \alpha_1^{\{A,B,Q\}\to P} \\
&\quad + \alpha_4^{P} - \alpha_5^{B,P} - \alpha_6^{P\to B}.
\end{aligned} \tag{37}$$

5.2. *The Zero-control Limit*

The structural role of control variables α in the merge problem is recognized by analyzing the uncontrolled behavior of dynamical variables. In the zero-control limit with the blocking flow condition, all control variables vanish except those associated with blocked channels. Then, the equation (37) in the limit becomes,

$$T_{B'\to P'} = \sum_{k\in K_B\setminus\{P\}} [T_{k\to B} - T^{\dagger}_{k\to B}] - E_{K_B\to B}. \tag{38}$$

The transfer entropy $T_{B'\to P'}$ is determined solely by incoming information flows and is not constrained by the entropy $H(P)$. Since $T_{A'\to P'} = T_{A\to P} = \mu_A$ and $T^{\dagger}_{Q'\to P'} = T^{\dagger}_{Q\to P} = \mu_A$ by the zero-control limit,

$$\Delta H(P') = [T_{A'\to P'} + T_{B'\to P'} - T^{\dagger}_{Q'\to P'}] = T_{B'\to P'}. \tag{39}$$

Consequently, the formal zero-control evolution does not itself prevent continued increase of $H(P')$. However, such unrestricted growth is not generally realizable. For

instance, if the component P has a binary state, then its entropy $H(P') \leqslant \ln 2$. In summary, the formal zero-control reduction contains no mechanism enforcing the finite-alphabet entropy bound, as the determination of transfer entropy $T_{B'\to P'}$ is independent of the entropy $H(P')$. The finite maximum is already guaranteed by the alphabet. Rather, a realizable process must have residual terms consistent with that bound; setting all relevant residuals to zero need not remain compatible with the assumed transfers. The residuals record this constraint and do not create the entropy ceiling.

5.3. *Receiver assumptions and the remaining conditional-entropy margin*

Define the remaining conditional-entropy margin at the pre-activation transition by

$$\epsilon := C_P - H(P'|P) = \ln q_P - H(P'|P) \geq 0. \tag{40}$$

Thus $\epsilon \to 0$ means saturation of a *conditional* entropy ceiling, a stronger statement than $H(P') \to C_P$ alone. The receiver result uses the following six additional assumptions. Any derivative is taken along a differentiable family of consistent joint laws on the same fixed alphabet, parameterized locally by ϵ; it is not a derivative in physical time. Below we show that this operational definition agrees with Eq. (45).

$$\begin{aligned}
&\text{Assumption 1: } T_{A'\to P'} - T_{\{A',B'\}\to P'} \\
&\qquad\qquad = I(A', P''|P', B') = T_{A\to P} \\
&\text{Assumption 2 : } I(Q, P'|P, A) = 0,\ I(Q', P''|P', A', B') = 0 \\
&\text{Assumption 3 : } \alpha_1^{\{A,Q\}\to P} = \alpha_1^{\{A',B',Q'\}\to P'} \\
&\text{Assumption 4 : } \frac{\partial \alpha_1^{\{A,Q\}\to P}}{\partial \epsilon} > -1 \\
&\text{Assumption 5 : } Q' = P, Q'' = P' \\
&\text{Assumption 6 : } \Delta I(P', P) + T_{B'\to P'} \geqslant 0,
\end{aligned} \tag{41}$$

where ϵ is defined in Eq. (40).

Assumption 1 preserves the baseline contribution from A after conditioning on the newly active input B'. It does not assert that the signed co-information term vanishes. Assumption 2 says that the downstream variable provides no additional predictive information once the listed receiver and source states are known. Assumption 3 equates the residual unresolved uncertainty before and after activation. Assumption 4 specifies how that residual varies along the chosen family; it is needed to relate increased baseline transfer to a reduced margin. Assumption 5 makes Q a one-step delay copy of P. Assumption 6 is a sign condition on the change of the receiver's lag-one mutual information and the external transfer, where $\Delta I(P', P) = I(P'', P') - I(P', P)$. These conditions define the class analyzed here; finite capacity alone does not imply them.

From Eq. (19),

$$T_{B'\to P'} = \Delta H(P') + T^{\dagger}_{Q'\to P'} - T_{A'\to P'} + E_{\{A',B',Q'\}\to P'} - \alpha_1^{\{A',B',Q'\}\to P'}. \tag{42}$$

The term $E_{\{A',B',Q'\}\to P'}$ can be reduced to the single multiple transfer entropy:

Proposition 4. *From Assumption 2, 5,*

$$E_{\{A',B',Q'\}\to P'} = T_{\{A',B'\}\to P'}. \tag{43}$$

(proof) Appendix D.

Proposition 4 and Assumption 1 lead to:

$$T_{B'\to P'} = \Delta H(P') + T^{\dagger}_{Q'\to P'} - T_{A\to P} - \alpha_1^{\{A',B',Q'\}\to P'}. \tag{44}$$

The same margin ϵ can be written as

$$\epsilon := \ln q_P - \alpha_1^{\{A,Q\}\to P} - T_{A\to P}. \tag{45}$$

Under Assumptions 2 and 5, the chain rule gives $H(P'|P) = T_{A\to P} + \alpha_1^{\{A,Q\}\to P}$, as shown in Appendix Appendix E. Here $\alpha_1 = H(P'|P,A) \geq 0$ is the unresolved forward uncertainty in this receiver construction; this interpretation does not apply to an arbitrary signed α_1. Thus Eq. (45) is precisely the margin of Eq. (40). Additionally, define δ by:

$$\delta := \ln q_P - \Delta H(P') - T^{\dagger}_{Q'\to P'}, \tag{46}$$

indicating,

$$T_{B'\to P'} = \epsilon - \delta, \tag{47}$$

from Eq. (44) and Assumption 3.

Before discussing the relationship between ϵ and δ, one can deduce the lemma.

Lemma 1. *Under Assumptions 1, 2, 3, and 5,*

$$H(P''|P') = H(P'|P) + T_{B'\to P'}. \tag{48}$$

(proof) Appendix E.

Appendix Appendix E also establishes that Assumptions 2 and 5 imply $H(P'|P) = \alpha_1^{\{A,Q\}\to P} + T_{A\to P}$. Consequently, the limit $\epsilon \to 0$ corresponds to the saturation of the conditional-entropy ceiling: $\epsilon = \ln q_P - H(P'|P)$.

The main capacity bound now has a short proof. The lemma and the alphabet ceiling give

$$0 \leq T_{B'\to P'} = H(P''|P') - H(P'|P) \leq C_P - H(P'|P) = \epsilon. \tag{49}$$

Assumptions 1, 2, 3, and 5 suffice for this identity and bound. Assumption 4 is used to interpret how the margin varies with the baseline transfer, while Assumption 6 additionally controls the sign of the change in marginal entropy. We next record the auxiliary bounds needed for the boundary analysis.

Proposition 5. *From Assumption 5, 6 and Lemma 1,*

$$\begin{aligned} &(a)\ H(P') \geqslant \ln q_P - \epsilon \\ &(b)\ 0 \leqslant \delta \leqslant \epsilon \\ &(c)\ 0 \leqslant \Delta H(P') \leqslant \epsilon. \end{aligned} \tag{50}$$

(proof) Appendix F.

From Proposition 5, one obtains,

$$\begin{aligned} 0 \leqslant T_{B'\to P'} \leqslant \epsilon &= \ln q_P - \alpha_1^{\{A,Q\}\to P} - T_{A\to P} \\ &= \ln q_P - H(P'|P). \end{aligned} \tag{51}$$

Equation (51) bounds the admissible external transfer entropy by ϵ, the remaining conditional-entropy margin. It therefore establishes competition at the level of an upper bound. Under Assumption 4, increasing the pre-existing transfer entropy reduces ϵ and hence lowers the admissible upper bound on the external transfer entropy. A corresponding decrease in the realized transfer entropy does not follow from the bound alone and must be verified for each specified model. The control variables α_3 and α_6 must accordingly satisfy the conditions leading to Eq. (51) as the conditional-entropy margin approaches zero.

In communication theory [10, 35], this competition is analogous to cross-talk in a two-sender-one-receiver multiple-access channel (MAC). The cross-talk [18, 31, 52] in MAC has been referred to as the difficulty of simultaneous communication with two senders, when the receiver's capacity for information processing is limited. Hence, Eq. (51) states that, as the pre-existing transfer from A to P increases, the admissible upper bound on transfer from B decreases when $H(P'|P)$ is close to $\ln q_P$. A multiplex receiver can avoid this competition by assigning separate state-space coordinates to the two inputs, as illustrated in Sec. 5.4.2.

Intuitively, a finite-capacity receiving component cannot accommodate arbitrarily many independent incoming influences. Eq. (51) makes this competition quantitative by bounding the additional transfer entropy in terms of the remaining conditional-entropy margin, expressing suppression of admissible external information transfer.

Furthermore, under limiting conditions, we derive a more tractable formulation, since the upper bound of Eq. (51) differs from the realized transfer entropy $T_{B'\to P'}$. The defining saturation condition is $H(P'|P) \to \ln q_P$. In this limit, Proposition 5 additionally implies,

$$\begin{aligned} &H(P') \to \ln q_P \\ &\Delta H(P') \to 0 \\ &T^{\dagger}_{Q'\to P'} \to \ln q_P \\ &T_{B'\to P'} \to 0 \\ &H(P''|P') \to \ln q_P. \end{aligned} \tag{52}$$

From this limit, $T_{B'\to P'}$ can be expanded as:

$$T_{B'\to P'}(\epsilon) = \frac{dT_{B'\to P'}}{d\epsilon}|_{\epsilon=0^+}\epsilon + o(\epsilon), \tag{53}$$

assuming the differentiability of $T_{B'\to P'}$ near $\epsilon = 0$.
By Eq. (51),

$$0 \leqslant \left.\frac{dT_{B'\to P'}}{d\epsilon}\right|_{\epsilon=0^+} \leqslant 1, \tag{54}$$

indicating that the derivative at $\epsilon = 0$ is non-negative. Moreover, Assumption 4 ensures from Eq. (45) that $dT_{A\to P}/d\epsilon < 0$; namely, increasing the pre-existing flow reduces the remaining entropy-capacity margin. Hence, under this one-sided boundary condition, the derivative ratio can be expressed as:

$$\begin{aligned}\left.\frac{dT_{B'\to P'}}{dT_{A\to P}}\right|_{\epsilon=0^+} &= \frac{\left.\dfrac{dT_{B'\to P'}}{d\epsilon}\right|_{\epsilon=0^+}}{\left.\dfrac{dT_{A\to P}}{d\epsilon}\right|_{\epsilon=0^+}} \\ &\leqslant 0.\end{aligned} \tag{55}$$

Up to this point, ϵ is defined by Eq. (45), while $T_{B'\to P'}$ has been expanded based on its limiting behavior. No finite-margin monotonicity follows from the boundary result alone. To examine finite-margin behavior, we consider a parameterized family $\{p_\theta\}_{\theta\in\Theta}$ of underlying probability distributions on a fixed alphabet. In this case, $T_{A\to P}$ and $T_{B'\to P'}$ can be denoted $T_{A\to P}(\theta)$ and $T_{B'\to P'}(\theta)$, respectively. For such a family, we test whether the following additional model-dependent condition holds over a finite range of θ:

$$\begin{aligned}\frac{dT_{B'\to P'}}{dT_{A\to P}}(\theta) &= \frac{dT_{B'\to P'}(\theta)/d\theta}{dT_{A\to P}(\theta)/d\theta} \\ &\leqslant 0.\end{aligned} \tag{56}$$

Eq. (56) characterizes local suppression of the newly incoming flow with $\frac{dT_{A\to P}}{d\theta} \neq 0$. In Section 5.4, we examine Eq. (56) for explicit statistical models.

5.4. *Examples of merging information flows*

The following examples examine separately whether the hypotheses of the boundary result (Eq. (41)) are satisfied and whether a particular model exhibits a negative relation, Eq. (56), over a finite parameter range.

5.4.1. *Ternary Additive Receiver*

Let the dynamics at time $t < t_1$ be,

$$\begin{aligned} A' &\sim p_a \\ B' &\sim p_b \\ P' &= A \\ Q' &= P, \qquad \text{for } \ t < t_1 \end{aligned} \tag{57}$$

where $p_\theta := (1-2\theta, \theta, \theta)$ is a one-parameter distribution on $\mathbb{Z}_3$ with $0 < \theta < \frac{1}{3}$ and A' and B' belong to mutually independent i.i.d. time sequences distributed according to p_a and p_b, respectively.

At time $t \geqslant t_1$,

$$\begin{aligned} A'' &\sim p_a \\ B'' &\sim p_b \\ P'' &= A' + B' \qquad \mod 3 \\ Q'' &= P', \end{aligned} \tag{58}$$

Then,

$$T_{A\to P} = H(A) = h(a), \tag{59}$$

where $h(x) := -(1-2x)\ln(1-2x) - (2x)\ln(x)$.
Therefore,

$$\frac{dT_{A\to P}}{da} = h'(a) = 2\ \ln\frac{1-2a}{a} > 0. \tag{60}$$

Since $\mathbb{P}(P''=0) = 1-2(a+b-3ab)$ and $\mathbb{P}(P''=1) = \mathbb{P}(P''=2) = a+b-3ab$,

$$\begin{aligned} T_{B'\to P'} &= I(P'', B') = H(P'') - H(A') \\ &= h(a+b-3ab) - h(a). \end{aligned} \tag{61}$$

This yields,

$$\begin{aligned} \frac{dT_{B'\to P'}}{da} &= (1-3b)h'(a+b-3ab) - h'(a) < 0, \\ &\text{because } h''(x) < 0 \text{ for } 0 < x < \tfrac{1}{3}, \\ &\text{and } 0 < 1-3b < 1. \end{aligned} \tag{62}$$

Hence,

$$\frac{dT_{B'\to P'}}{dT_{A\to P}} = \frac{\frac{dT_{B'\to P'}}{da}}{\frac{dT_{A\to P}}{da}} < 0. \tag{63}$$

For this dynamics, the equation (56) is valid for the overall range. Also, it can be shown that the assumptions of Eq. (41) are valid.

5.4.2. *A Multiplex Receiver*

On the other hand, most artificial networks, such as multi-source networks in communication theory, are designed to prevent the cross-talk effect for a reliable communication. This is accomplished by modeling the multiplex receiver to process input signals independently. Therefore, the multiplex receiver is assigned two independent state-space components, $P = (P_1, P_2)$. Then, the dynamics is set as,

$$\begin{aligned} A' &\sim Uniform(N_{Z_A}) \\ B' &\sim Uniform(N_{Z_B}) \\ P_1' &= A \\ P_2' &= P_2 \\ Q_1' &= P_1 \\ Q_2' &= P_2, \qquad\qquad \text{for} \;\; t < t_1 \end{aligned} \tag{64}$$

where $N_Z := \{0, 1, \ldots, Z-1\}$ and Z_A, $Z_B \in \mathbb{N}$, and $Uniform(N_Z)$ is the uniform distribution for the set N_Z.

$$\begin{aligned} A'' &\sim Uniform(N_{Z_A}) \\ B'' &\sim Uniform(N_{Z_B}) \\ P_1'' &= A' \\ P_2'' &= B' \\ Q_1'' &= P_1' \\ Q_2'' &= P_2'. \qquad\qquad \text{for} \;\; t \geqslant t_1 \end{aligned} \tag{65}$$

As a result,

$$\begin{aligned} T_{A \to P} &= \ln(Z_A) \\ T_{B' \to P'} &= \ln(Z_B), \end{aligned} \tag{66}$$

and, thus, $T_{B' \to P'}$ is independent of Z_A and hence of $T_{A \to P}$ with a fixed Z_B. Since this construction avoids competition by supplying an additional receiver coordinate, it is a contrast model rather than a fixed-alphabet test of the boundary derivative. Consequently, this represents a limiting case in which the cross-talk effect is eliminated.

5.4.3. *AND Gate*

Unlike the previous examples, the merge with AND gate violates some of the assumptions and does not satisfy Eq. (56) in general.

$$\begin{aligned} A' &\sim B(\frac{1}{2}+\rho_A) \\ B' &\sim B(\frac{1}{2}+\rho_B) \\ P' &= A \\ Q' &= P, \qquad\qquad \text{for } \ t < t_1 \end{aligned} \tag{67}$$

where $B(\rho)$ is the Bernoulli distribution with success probability ρ and $-\frac{1}{2} \leqslant \rho_A, \rho_B \leqslant \frac{1}{2}$.

$$\begin{aligned} A'' &\sim B(\frac{1}{2}+\rho_A) \\ B'' &\sim B(\frac{1}{2}+\rho_B) \\ P'' &= AND(A', B') \\ Q'' &= P'. \qquad\qquad \text{for } \ t \geqslant t_1 \end{aligned} \tag{68}$$

Here,

$$\begin{aligned} T_{A\to P} = & -(\tfrac{1}{2}+\rho_A)\ln(\tfrac{1}{2}+\rho_A) \\ & -(\tfrac{1}{2}-\rho_A)\ln(\tfrac{1}{2}-\rho_A), \\ T_{B'\to P'} = & -(\tfrac{1}{2}+\rho_A)(\tfrac{1}{2}+\rho_B)\ln(\tfrac{1}{2}+\rho_B) \\ & +(\tfrac{1}{2}-\rho_A)(\tfrac{1}{2}+\rho_B)\ln(\tfrac{1}{2}-\rho_A) \\ & -\big[1-(\tfrac{1}{2}+\rho_A)(\tfrac{1}{2}+\rho_B)\big] \\ & \quad\times\ln\big[1-(\tfrac{1}{2}+\rho_A)(\tfrac{1}{2}+\rho_B)\big]. \end{aligned} \tag{69}$$

While,

$$\begin{aligned} \frac{\partial T_{B'\to P'}}{\partial \rho_A} &= (\tfrac{1}{2}+\rho_B) \\ &\quad\times\ln\frac{1-(\frac{1}{2}+\rho_A)(\frac{1}{2}+\rho_B)}{(\frac{1}{2}-\rho_A)(\frac{1}{2}+\rho_B)} \geqslant 0, \end{aligned} \tag{70}$$

$$\frac{\partial T_{A\to P}}{\partial \rho_A} = \ln\frac{\frac{1}{2}-\rho_A}{\frac{1}{2}+\rho_A} \begin{cases} <0 & (\rho_A>0) \\ >0 & (\rho_A<0) \\ =0 & (\rho_A=0) \end{cases} \tag{71}$$

Therefore,

$$\frac{dT_{B'\to P'}}{dT_{A\to P}} \begin{cases} \leqslant 0 & (\rho_A>0) \\ \geqslant 0 & (\rho_A<0) \end{cases} \tag{72}$$




Fig. 3. **(a)** Simulation results for competing information flows: $T_{A3\to P}(t_0)$ versus $T_{Ext\to P}(t_1)$. The cycle $P \to A1 \to \cdots \to A3 \to P$ is isolated at time $t = t_0$, and node P begins to interact with the external source (Ext) at $t = t_1$. **(b)** The time-evolution of $T_{A3\to P}$ and $T_{Ext\to P}$ with $\theta = 0.18$. Here, $t_1 = 25$ time steps.

Assumptions 2, 3, and 5 are satisfied; however, Assumption 1 fails except the trivial case where $\rho_B = \frac{1}{2}$, and the validity of Assumption 4 depends on the value of ρ_A and ρ_B.

6. A two-bit circulation with an activated external input

To illustrate the mechanism derived in Sec. 5, we construct a stochastic network with the Fredkin gate [14], which is a standard gate in the literature of reversible computing [5,32,37,49]: a cycle $P \to A1 \to \cdots \to A3 \to P$ and an external node (Ext). Each node has a two-bit state, $\Gamma_{A1}, \ldots, \Gamma_{A3}, \Gamma_P, \Gamma_{Ext} \in \{(0,0),(0,1),(1,0),(1,1)\}$, and the update rule at the merging node P is given by a Fredkin-type controlled-SWAP gate:

$$\Gamma'_P = \begin{cases} (\gamma^{(2)}_{A3}, \gamma^{(1)}_{A3}) & \text{if } \gamma^{(1)}_{Ext} = 1 \\ (\gamma^{(1)}_{A3}, \gamma^{(2)}_{A3}) & \text{if } \gamma^{(1)}_{Ext} = 0 \end{cases}, \tag{73}$$

where $\Gamma_X = (\gamma^{(1)}_X, \gamma^{(2)}_X)$ for a node X with $\gamma^{(1)}_X, \gamma^{(2)}_X \in \{0,1\}$.

Although the gate originates from conservative logic, we analyze its information dynamics under a parameterized input ensemble. For $0 \leqslant \theta < 1/4$, we define the probability mass function p_θ such that, for a random variable $\Gamma_X \sim p_\theta$,

$$\begin{aligned} p_\theta(\Gamma_X = (1,0)) &= \frac{1}{4} + \theta \\ p_\theta(\Gamma_X = (0,1)) &= \frac{1}{4} - \theta \\ p_\theta(\Gamma_X = (0,0)) &= p_\theta(\Gamma_X = (1,1)) = \frac{1}{4}. \end{aligned} \tag{74}$$

Then, the initial ensemble at $t = t_0$ is constructed as:

$$\begin{aligned} &\Gamma_{A1}, \Gamma_{A2}, \Gamma_{A3} \sim p_\theta \\ &\Gamma_P \sim p_\theta \\ &\Gamma_{Ext} \sim p_0, \end{aligned} \tag{75}$$

where $\Gamma_{A1}, \ldots, \Gamma_{A3}, \Gamma_P, \Gamma_{Ext}$ are mutually independent. The source $\Gamma_{Ext}(t)$ is independently resampled from p_0 at every step, independently of the initial cycle state. Before activation, $\Gamma'_P = \Gamma_{A3}$; after activation, the controlled-SWAP rule above is used. The remaining updates are $\Gamma'_{A1} = \Gamma_P$, $\Gamma'_{A2} = \Gamma_{A1}$, and $\Gamma'_{A3} = \Gamma_{A2}$. The full system with a resampled source is stochastic; reversibility of the local gate does not assert global deterministic reversibility of this example.

The remaining nodes in the cycle are modeled as delay-copy units, such as $\Gamma'_{A2} = \Gamma_{A1}$ or $\Gamma'_{A1} = \Gamma_P$, ensuring consistency with Assumption 5 in Sec. 5. Within this construction, the cycle represents a pre-existing internal information circulation, while the node P acts as a finite-capacity processor where internal and external information flows compete.

A network of two-bit nodes is constructed with the cycle $P \to A1 \to \cdots \to A3 \to P$ and the external source (Ext), and the component P and (Ext) begin to interact after time $t = t_1$. The resulting dynamics satisfies all assumptions of Eq. (41): for the construction in this section, Assumptions 1, 2, and 5 follow directly from the conditional bijectivity of the controlled-SWAP operation and the delay-copy relation. At the onset of interaction, independence of the node states gives

$\alpha_1^{\{A,Q\}\to P} = \alpha_1^{\{A',B',Q'\}\to P'} = 0$, $\frac{\partial \alpha_1^{\{A,Q\}\to P}}{\partial \epsilon} = 0$, $\Delta I(P', P) = 0$, so Assumptions 3, 4, and 6 are also satisfied. Then, the exact calculation yields:

$$T_{A3\to P}(t_0) + T_{Ext\to P}(t_1) = \ln 4, \tag{76}$$

where $T_{A3\to P}(t_0) := T_{A3\to P}$ and $T_{Ext\to P}(t_1) := T_{Ext'\to P'}$.
At the onset of interaction, Eq. (76) shows that the realized external transfer entropy equals the remaining capacity margin. Consequently, within this parameterized Fredkin model, increasing $T_{A3\to P}(t_0)$ is accompanied by a corresponding decrease in $T_{Ext\to P}(t_1)$, thereby realizing the finite-range suppression relation in Eq. (56).

Figure 3(a) compares different prepared ensembles indexed by θ, at the two specified transitions. Its horizontal axis is a baseline transfer varied across ensembles, rather than elapsed time. To examine physical-time evolution, Fig. 3(b) instead fixes θ. We simulate an ensemble of independent realizations, collect state pairs at the same two times across realizations, and use empirical frequency tables on the finite joint alphabet to estimate the information measures. No stationarity over the transient is assumed. Simulation results (Fig. 3 (a)) [27] show that increasing the internal circulating flow $T_{A3\to P}(t_0)$ suppresses the external input $T_{Ext\to P}(t_1)$ in accordance with Eq. (76), quantitatively confirming the relation (Eq. (56)).
Furthermore, Fig. 3 (b) shows that both $T_{A3\to P}(t)$ and $T_{Ext\to P}(t)$ evolve over time. Following activation of the interaction, $T_{Ext\to P}(t)$ initially increases to a plateau before dissipating to zero as the probability distribution mixed by (Ext) propagates through the cycle to node P. Since the swapping operation by (Ext) symmetrizes the asymmetry induced by parameter θ in the initial ensemble, the node P ceases to receive influence from node (Ext) under this symmetrized distribution. This demonstrates that the competition between information flows exhibits distinct temporal characteristics.

7. Conclusion

This work establishes two information-dynamical results. First, the circulation of transfer entropy and reversed transfer entropy constitutes a necessary structural condition for stationary or periodic entropic dynamics in active finite-state networks under the stated assumptions and fixed nonempty support. Second, when a preexisting circulating flow and an external flow merge at a finite-capacity node, the remaining conditional-entropy margin provides an upper bound on the admissible external transfer entropy. In this sense, the bound identifies a possible information-transfer constraint associated with cyclic organization. This mechanism corresponds to a cross-talk effect, in which limited entropy capacity constrains simultaneous information transfer.

For the Fredkin model considered here, the bound is attained at the onset of interaction, producing a model-specific negative relation between the circulating and external transfer entropies. The subsequent simulation shows that this relation is

transient and need not remain saturated after the modified distribution propagates around the cycle. Consequently, the quantitative framework developed in this work facilitates an information-dynamical analysis of reversible logic gates.

The current analysis relies on several assumptions introduced in Sec. 2 and Eq. (41). While these assumptions facilitate tractable analysis of interacting information flows and yield baseline cases, their necessity and generality remain to be examined. Further work is required to relax these assumptions, explore a wider class of merging mechanisms, and investigate additional properties of information circulation, including its temporal structure and interactions between multiple cycles.

A further limitation concerns the admissibility of the information-dynamical evolution, as discussed in Section 4.2 and Ref. [28]. A complete characterization of the admissible region of the control variables, subject to Shannon inequalities, alphabet bounds, and temporal consistency of the underlying distributions, remains an open problem.

Furthermore, the present analysis assumes that the directed structure of transfer entropy interactions remains sufficiently stable over the analyzed time interval. Extending the framework to adaptive networks, in which the interaction topology and effective information flow structure evolve dynamically, remains an important direction for future research.

Data Availability Statement

The data that support the findings of this study are openly available in Zenodo at https://doi.org/10.5281/zenodo.22358615 (Version v0.1.4b).

ORCID

Yunju Lee - `https://orcid.org/0009-0000-4636-967X`

Appendix A. A Counterexample to the Assumption of Section 2.8

Let the random variables u_1, u_2, v represent the state of three components in discrete time having the dynamics:

$$\begin{aligned} u_1', u_2' &\sim B(\frac{1}{2}) \\ v' &= u_1 \oplus u_2, \end{aligned} \tag{A.1}$$

where $B(p)$ is the Bernoulli distribution with success probability p, and the operation $\oplus$ represents the binary operation XOR.
Then, $H(v'|v) = H(v'|v, u_1) = H(v'|v, u_2) = \ln 2$, resulting in $T_{u_1 \to v} = T_{u_2 \to v} = 0$. Nonetheless, for $\mathbf{u} = (u_1, u_2)$, $T_{\mathbf{u} \to v} = H(v'|v) - H(v'|v, u_1, u_2) = \ln 2$.

Appendix B. Higher-order information balances

This appendix records the multivariate hierarchy used for the higher-order cancellations in Appendix Appendix C. All variables and time shifts follow Sec. 2.

Here $I(V)$ and $I(V|W)$ are co-informations, including the singleton convention $I(\{X\}) = H(X)$. Transfer quantities with collection subscripts are the signed terms of Eq. (11).

For a collection V containing at least two variables, define the set of ordered nonempty bipartitions by

$$D_V := \{(U, W) : U \cap W = \varnothing,\ U \cup W = V,\ U \neq \varnothing,\ W \neq \varnothing\}. \tag{B.1}$$

Thus (U, W) and (W, U) are both included. All subset sums below range over collections of distinct labeled variables. These identities follow by applying inclusion–exclusion to the same entropy chain rules as the pairwise balances [28]:

$$\begin{cases}
E_{K_i \to \Gamma_i} := \displaystyle\sum_{u=2}^{|K_i|} (-1)^u \sum_{\substack{V \subset K_i \\ |V|=u}} [T_{V \to \Gamma_i} - T^{\dagger}_{V \to \Gamma_i}] \\
\Delta I(V) = \displaystyle\sum_{(U,W) \in D_V} [T_{U \to W} - T^{\dagger}_{U \to W}] + \alpha_2^V \\
\Delta T_{U \to W} = (-1)^{|W|} \Delta I(U \cup W) \\
\qquad + \displaystyle\sum_{u=1}^{|W|} (-1)^{|W|-u} \sum_{\substack{S \subset W \\ |S|=u}} \Big[\Delta I\big(U \cup (W \setminus S)\big) \\
\qquad\quad + \displaystyle\sum_{s=1}^{u} (-1)^s \sum_{\substack{Z \subset S \\ |Z|=s}} \alpha_3^{U \cup (W \setminus S) \to Z} \Big] \\
\Delta T^{\dagger}_{U \to W} = (-1)^{|W|} \Delta I(U \cup W) + (-1)^{|W|} \alpha_5^{U \cup W} \\
\qquad + \displaystyle\sum_{u=1}^{|W|} (-1)^{|W|-u} \sum_{\substack{S \subset W \\ |S|=u}} \Big[\Delta I\big(U \cup (W \setminus S)\big) \\
\qquad\quad + \alpha_5^{U \cup (W \setminus S)} + \displaystyle\sum_{s=1}^{u} (-1)^s \sum_{\substack{Z \subset S \\ |Z|=s}} \alpha_6^{U \cup (W \setminus S) \to Z} \Big],
\end{cases} \tag{B.2}$$

with,

$$\begin{aligned}
\alpha_2^V &:= I(V'|V) - I(V|V') \\
\alpha_3^{X \to Z} &:= \Delta I(X | Z \cup Z') \\
\alpha_5^V &:= \Delta^2 I(V) \\
\alpha_6^{X \to Z} &:= \Delta I(X' | Z \cup Z').
\end{aligned} \tag{B.3}$$

The first line is the definition of E repeated for reference. The second line decomposes the time increment of co-information into signed transfers across ordered bipartitions and a residual. The remaining lines express increments of the multiple-transfer terms through co-information increments and conditional-entropy residual-

s. These are identities for consistent joint laws, without a stationarity assumption; imposing that selected residuals vanish is an additional modeling restriction.

Appendix C. The Proof of Proposition 3

For reference, the full cycle/source balances summarized in the proposition are

$$
\begin{aligned}
&\Delta H(\Gamma_i) = T_{\Gamma_{i-1}\to\Gamma_i} - T^{\dagger}_{\Gamma_{i+1}\to\Gamma_i} \quad (i \neq p)\\
&\Delta H(\Gamma_p) = T_{\Gamma_{p-1}\to\Gamma_p} + T_{\Gamma_{Ext}\to\Gamma_p} - T^{\dagger}_{\Gamma_{p+1}\to\Gamma_p}\\
&\qquad\qquad - E_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}\\
&\Delta I(\Gamma_i,\Gamma_{i+1}) = T_{\Gamma_i\to\Gamma_{i+1}} - T^{\dagger}_{\Gamma_{i+1}\to\Gamma_i}\\
&\Delta I(\Gamma_p,\Gamma_{Ext}) = T_{\Gamma_{Ext}\to\Gamma_p} - T^{\dagger}_{\Gamma_p\to\Gamma_{Ext}}
\end{aligned}
$$

$$
\begin{aligned}
&\Delta T_{\Gamma_i\to\Gamma_{i+1}} = T_{\Gamma_{i-1}\to\Gamma_i} - T_{\Gamma_i\to\Gamma_{i+1}}\\
&\qquad\qquad\qquad\qquad (i \neq p-1, p)\\
&\Delta T^{\dagger}_{\Gamma_i\to\Gamma_{i+1}} = 0\\
&\Delta T_{\Gamma_i\to\Gamma_{i-1}} = 0\\
&\Delta T^{\dagger}_{\Gamma_i\to\Gamma_{i-1}} = T^{\dagger}_{\Gamma_{i-1}\to\Gamma_{i-2}} - T^{\dagger}_{\Gamma_i\to\Gamma_{i-1}}\\
&\qquad\qquad\qquad\qquad (i \neq p, p+1)
\end{aligned}
$$

$$
\begin{aligned}
&\Delta T_{\Gamma_{p-1}\to\Gamma_p} = T_{\Gamma_{p-2}\to\Gamma_{p-1}} - T_{\Gamma_{p-1}\to\Gamma_p}\\
&\qquad\qquad - \alpha_3^{\Gamma_{p-1}\to\Gamma_p}\\
&\Delta T^{\dagger}_{\Gamma_p\to\Gamma_{p-1}} = T^{\dagger}_{\Gamma_{p-1}\to\Gamma_{p-2}} - T^{\dagger}_{\Gamma_p\to\Gamma_{p-1}}\\
&\qquad\qquad - E'_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}\\
&\Delta T_{\Gamma_p\to\Gamma_{p+1}} = T_{\Gamma_{p-1}\to\Gamma_p} + T_{\Gamma_{Ext}\to\Gamma_p}\\
&\qquad\qquad - T_{\Gamma_p\to\Gamma_{p+1}} - E_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}\\
&\Delta T^{\dagger}_{\Gamma_{p+1}\to\Gamma_p} = \alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} - \alpha_3^{\Gamma_{Ext}\to\Gamma_p}\\
&\qquad\qquad + T^{\dagger}_{\Gamma_p\to\Gamma_{p-1}} - T^{\dagger}_{\Gamma_{p+1}\to\Gamma_p}\\
&\qquad\qquad - E'_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} - \alpha_6^{\Gamma_p\to\Gamma_{p-1}}
\end{aligned}
$$

$$
\begin{aligned}
&\Delta T_{\Gamma_{Ext}\to\Gamma_p} = \alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} - T_{\Gamma_{Ext}\to\Gamma_p} - \alpha_3^{\Gamma_{Ext}\to\Gamma_p}\\
&\Delta T^{\dagger}_{\Gamma_p\to\Gamma_{Ext}} = -\alpha_{3456}^{\Gamma_p\to\Gamma_{Ext}},
\end{aligned}
\tag{C.1}
$$

under the zero-control limit,

$$\begin{aligned}
&\alpha_1^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = \alpha_2^{\Gamma_i,\Gamma_{i+1}} = 0 \quad (i \neq p)\\
&\alpha'^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i}_1 = \alpha'^{\Gamma_i,\Gamma_{i+1}}_2 = 0 \quad (i \neq p)\\
&\alpha_1^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} = \alpha'^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}_1\\
&\qquad = \alpha_2^{\Gamma_i,\Gamma_{i+1}} = \alpha'^{\Gamma_i,\Gamma_{i+1}}_2 = 0\\
&\alpha_3^{\Gamma_i\to\Gamma_{i+1}} = 0 \quad (i \neq p-1)\\
&\alpha_6^{\Gamma_{i-1}\to\Gamma_{i-2}} = 0 \quad (i \neq p+1)\\
&\alpha_3^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = \alpha_5^{\{\Gamma_{i-1},\Gamma_{i+1}\}}\\
&\qquad = \alpha_5^{\{\Gamma_{i-1},\Gamma_i,\Gamma_{i+1}\}} = \alpha_6^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = 0\\
&\qquad\qquad (i \neq p). \qquad \text{(C.2)}
\end{aligned}$$

All zero-control conditions in Eq. (C.2) are imposed at every time step over the interval considered, and the initial conditions $E_{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = 0$ for all $i \neq p$ are assumed.

We now derive this specialization from the pairwise identities.

From the intrinsic method of Ref. [28], $\alpha_{3456}^{\Gamma_j\to\Gamma_i} := -\alpha_3^{\Gamma_j\to\Gamma_i} - \alpha_4^{\Gamma_j} + \alpha_5^{\Gamma_i,\Gamma_j} + \alpha_6^{\Gamma_j\to\Gamma_i}$ can be expressed as:

$$\mathbf{x} = \mathbf{A}^{-1}\mathbf{y} - \mathbf{A}^{-1}\mathbf{b}, \qquad \text{(C.3)}$$

where $\mathbf{y}, \mathbf{x}, \mathbf{b} \in \mathbb{R}^n$ and $\mathbf{A} \in \mathbb{R}^{n\times n}$ such that,

$$\begin{aligned}
(\mathbf{y})_l &= \alpha_3^{\Gamma_i\to\Gamma_{j_l}} - \alpha_6^{\Gamma_i\to\Gamma_{j_l}} - \Delta\alpha_2^{\Gamma_i,\Gamma_{j_l}}\\
(\mathbf{x})_l &= \alpha_{3456}^{\Gamma_{j_l}\to\Gamma_i}\\
(\mathbf{b})_l &= \Delta E_{K_i\to\Gamma_i} - \Delta\alpha_1^{K_i\to\Gamma_i}\\
(\mathbf{A})_{lm} &= -1 + \delta_{lm}, \qquad \text{(C.4)}
\end{aligned}$$

Here, the component i's neighbor set is denoted as $K_i = \{\Gamma_{j_1}, \ldots, \Gamma_{j_n}\}$ with $n > 1$. Therefore,

($i \neq p$ case)

$$\begin{aligned}
\alpha_{3456}^{\Gamma_{i-1}\to\Gamma_i} &= -\alpha_3^{\Gamma_i\to\Gamma_{i+1}} + \alpha_6^{\Gamma_i\to\Gamma_{i+1}} + \Delta E^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i}\\
&\quad - \Delta\alpha_1^{\Gamma_i} + \Delta\alpha_2^{\Gamma_i,\Gamma_{i+1}}\\
\alpha_{3456}^{\Gamma_{i+1}\to\Gamma_i} &= -\alpha_3^{\Gamma_i\to\Gamma_{i-1}} + \alpha_6^{\Gamma_i\to\Gamma_{i-1}} + \Delta E^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i}\\
&\quad - \Delta\alpha_1^{\Gamma_i} + \Delta\alpha_2^{\Gamma_i,\Gamma_{i-1}}. \qquad \text{(C.5)}
\end{aligned}$$

($i = p$ case)

$$\begin{pmatrix} \alpha_{3456}^{\Gamma_{p-1}\to\Gamma_p} \\ \alpha_{3456}^{\Gamma_{p+1}\to\Gamma_p} \\ \alpha_{3456}^{\Gamma_{Ext}\to\Gamma_p} \end{pmatrix} = \frac{1}{2}\begin{pmatrix} +1 & -1 & -1 \\ -1 & +1 & -1 \\ -1 & -1 & +1 \end{pmatrix}\mathbf{y} + \frac{1}{2}\mathbf{b}, \qquad \text{(C.6)}$$

where,

$$\mathbf{y} = \begin{pmatrix} \alpha_3^{\Gamma_p\to\Gamma_{p-1}} - \alpha_6^{\Gamma_p\to\Gamma_{p-1}} - \Delta\alpha_2^{\Gamma_p,\Gamma_{p-1}} \\ \alpha_3^{\Gamma_p\to\Gamma_{p+1}} - \alpha_6^{\Gamma_p\to\Gamma_{p+1}} - \Delta\alpha_2^{\Gamma_p,\Gamma_{p+1}} \\ \alpha_3^{\Gamma_p\to\Gamma_{Ext}} - \alpha_6^{\Gamma_p\to\Gamma_{Ext}} - \Delta\alpha_2^{\Gamma_p,\Gamma_{Ext}} \end{pmatrix},$$

$$\mathbf{b} = [\Delta E_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} - \Delta\alpha_1^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}] \begin{pmatrix} 1 \\ 1 \\ 1 \end{pmatrix}. \tag{C.7}$$

Substituting these relations into the dynamical equations (Eq. (19)) and imposing the blocking flows condition, $T_{\Gamma_i\to\Gamma_{i-1}}(t) = 0$, $T^\dagger_{\Gamma_i\to\Gamma_{i+1}}(t) = 0$, $T_{\Gamma_p\to\Gamma_{Ext}}(t) = 0$, $T^\dagger_{\Gamma_{Ext}\to\Gamma_p}(t) = 0$ for $\forall t, i$, yields,

$$\begin{aligned}
\Delta T_{\Gamma_i\to\Gamma_{i+1}} &= T_{\Gamma_{i-1}\to\Gamma_i} - T_{\Gamma_i\to\Gamma_{i+1}} \\
&\quad - E_{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} + \alpha_1^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} \\
&\quad - \alpha_2^{\Gamma_i,\Gamma_{i+1}} - \alpha_3^{\Gamma_i\to\Gamma_{i+1}} \quad (i \neq p), \\
\Delta T^\dagger_{\Gamma_i\to\Gamma_{i+1}} &= 0, \\
\Delta T_{\Gamma_i\to\Gamma_{i-1}} &= 0, \\
\Delta T^\dagger_{\Gamma_i\to\Gamma_{i-1}} &= T^\dagger_{\Gamma_{i-1}\to\Gamma_{i-2}} - T^\dagger_{\Gamma_i\to\Gamma_{i-1}} \\
&\quad - E'_{\{\Gamma_{i-2},\Gamma_i\}\to\Gamma_{i-1}} + \alpha'^{\{\Gamma_{i-2},\Gamma_i\}\to\Gamma_{i-1}}_1 \\
&\quad - \alpha'^{\Gamma_{i-1},\Gamma_i}_2 - \alpha_6^{\Gamma_{i-1}\to\Gamma_{i-2}} \quad (i \neq p+1), \\
\Delta T_{\Gamma_p\to\Gamma_{p+1}} &= T_{\Gamma_{p-1}\to\Gamma_p} + T_{\Gamma_{Ext}\to\Gamma_p} - T_{\Gamma_p\to\Gamma_{p+1}} \\
&\quad - E_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} \\
&\quad + \alpha_1^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} - \alpha_2^{\Gamma_p,\Gamma_{p+1}} - \alpha_3^{\Gamma_p\to\Gamma_{p+1}}, \\
\Delta T^\dagger_{\Gamma_{p+1}\to\Gamma_p} &= \alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} - \alpha_3^{\Gamma_{Ext}\to\Gamma_p} \\
&\quad + T^\dagger_{\Gamma_p\to\Gamma_{p-1}} - T^\dagger_{\Gamma_{p+1}\to\Gamma_p} - \alpha_6^{\Gamma_p\to\Gamma_{p-1}} \\
&\quad - E'_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} \\
&\quad + \alpha'^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}_1 - \alpha'^{\Gamma_p,\Gamma_{p-1}}_2, \\
\Delta T_{\Gamma_{Ext}\to\Gamma_p} &= \alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} - T_{\Gamma_{Ext}\to\Gamma_p} - \alpha_3^{\Gamma_{Ext}\to\Gamma_p}, \\
\Delta T^\dagger_{\Gamma_p\to\Gamma_{Ext}} &= -\alpha_{3456}^{\Gamma_p\to\Gamma_{Ext}},
\end{aligned} \tag{C.8}$$

where E' denotes E evaluated at the following time step.

As Ref. [28], it is required to analyze near the zero-control limit to examine the

effect of merging. Therefore,

$$\begin{aligned}
&\alpha_1^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = \alpha_2^{\Gamma_i,\Gamma_{i+1}} = 0 \quad (i \neq p),\\
&\alpha'^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i}_1 = \alpha'^{\Gamma_i,\Gamma_{i+1}}_2 = 0 \quad (i \neq p),\\
&\alpha_1^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} = \alpha'^{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p}_1\\
&\qquad\qquad = \alpha_2^{\Gamma_i,\Gamma_{i+1}} = \alpha'^{\Gamma_i,\Gamma_{i+1}}_2 = 0,\\
&\alpha_3^{\Gamma_i\to\Gamma_{i+1}} = 0 \quad (i \neq p-1),\\
&\alpha_6^{\Gamma_{i-1}\to\Gamma_{i-2}} = 0 \quad (i \neq p+1),\\
&\alpha_3^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = \alpha_5^{\{\Gamma_{i-1},\Gamma_{i+1}\}}\\
&\qquad = \alpha_5^{\{\Gamma_{i-1},\Gamma_i,\Gamma_{i+1}\}} = \alpha_6^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = 0\\
&\qquad\qquad (i \neq p),
\end{aligned} \tag{C.9}$$

retaining only the control variables associated with the newly opened channel between Ext and p. In this limit,

$$\begin{aligned}
\Delta E = &-\alpha_3^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} - \alpha_5^{\{\Gamma_{i-1},\Gamma_{i+1}\}}\\
&+\alpha_5^{\{\Gamma_{i-1},\Gamma_i,\Gamma_{i+1}\}} + \alpha_6^{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = 0.
\end{aligned} \tag{C.10}$$

as the high-order control variables also vanish. Together with the stated initial condition, this implies $E_{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = E'_{\{\Gamma_{i-1},\Gamma_{i+1}\}\to\Gamma_i} = 0$ for $i \neq p$ throughout the interval considered.

This yields Eq. (C.1).

□

The equation (C.1) requires further specification. Firstly, $\alpha_{3456}^{\Gamma_p\to\Gamma_{Ext}}$ cannot be replaced by α_3, α_6 by the intrinsic method introduced in Ref. [28], since the component Ext has only one neighbor. Therefore, $\alpha_{3456}^{\Gamma_p\to\Gamma_{Ext}}$ has to be determined from its definition, $\alpha_{3456}^{\Gamma_p\to\Gamma_{Ext}} = -\alpha_3^{\Gamma_p\to\Gamma_{Ext}} - \alpha_4^{\Gamma_p} + \alpha_5^{\Gamma_p,\Gamma_{Ext}} + \alpha_6^{\Gamma_p\to\Gamma_{Ext}}$. Secondly, defining the dynamic characteristics of the component Ext can specify the terms, $\alpha_5^{\Gamma_p,\Gamma_{Ext}}$ and $\alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}}$. For instance, $\alpha_5^{\Gamma_p,\Gamma_{Ext}} = 0$ at all times and $\alpha_1^{\{\Gamma_p\}\to\Gamma_{Ext}} = 0$ at $t < t_1$ if the component Ext is regarded as a source of white noise.

On the other hand, if $E_{\{\Gamma_{p-1},\Gamma_{p+1},\Gamma_{Ext}\}\to\Gamma_p} = 0$ permanently, there is no stationary state with nonzero $T_{\Gamma_{Ext}\to\Gamma_p}, T^{\dagger}_{\Gamma_p\to\Gamma_{Ext}}$. This shows that multivariate effects are essential for the existence of a stationary state with nonzero interaction with the external source.

Such transient effects are expected to appear in explicit dynamical realizations of the merging process. The transient behaviors after time $t = t_1$ and the way to approach another stationary state were demonstrated numerically in Ref. [27].

Appendix D. The Proof of Proposition 4

By the definition of E,

$$\begin{aligned} E_{\{A',B',Q'\}\to P'} = &[T_{\{A',B'\}\to\{P'\}} - T^{\dagger}_{\{A',B'\}\to\{P'\}}] \\ &+ [T_{\{A',Q'\}\to\{P'\}} - T^{\dagger}_{\{A',Q'\}\to\{P'\}}] \\ &+ [T_{\{B',Q'\}\to\{P'\}} - T^{\dagger}_{\{B',Q'\}\to\{P'\}}] \\ &- [T_{\{A',B',Q'\}\to\{P'\}} - T^{\dagger}_{\{A',B',Q'\}\to\{P'\}}]. \end{aligned} \tag{D.1}$$

From Assumption 5, one obtains,

$$\begin{aligned} T^{\dagger}_{\{A',Q'\}\to\{P'\}} &= I(\{A'', Q'', P'\}|P'') \\ &= I(A'', Q''|P'') - I(A'', Q''|P'P'') \\ &= I(A'', P'|P'') \quad \text{(Assumption 5: } Q'' = P') \\ &= T^{\dagger}_{A'\to p'} = 0 \quad \text{(blocking-flows condition)}, \end{aligned} \tag{D.2}$$

and $T^{\dagger}_{\{B',Q'\}\to\{P'\}} = 0$ similarly. In addition,

$$\begin{aligned} &T^{\dagger}_{\{A',B',Q'\}\to\{P'\}} \\ &\quad = I(\{A'', B'', Q'', P'\}|P'') \\ &\quad = I(\{A'', B'', P'\}|P'') \\ &- I(\{A'', B'', P'\}|P''Q'') \\ &\quad = I(\{A'', B'', P'\}|P'') \quad \text{(Assumption 5: } Q'' = P') \\ &\quad = T^{\dagger}_{\{A',B'\}\to\{P'\}}. \end{aligned} \tag{D.3}$$

The $T_{\{A',B',Q'\}\to\{P'\}}$ is evaluated using Assumption 2:

$$\begin{aligned} &T_{\{A',B',Q'\}\to\{P'\}} \\ &\quad = I(\{A', B', Q', P''\}|P') \\ &\quad = I(\{A', Q', P''\}|P') - I(\{A', Q', P''\}|P'B') \\ &\quad = T_{\{A',Q'\}\to\{P'\}} - I(Q', P''|P'B') \\ &+ I(Q', P''|P'A'B') \\ &\quad = T_{\{A',Q'\}\to\{P'\}} + [I(Q', P''|P') - I(Q', P''|P'B')] \\ &+ I(Q', P''|P'A'B') \\ &\quad (I(Q', P''|P') = T_{Q'\to P'} = 0) \\ &\quad = T_{\{A',Q'\}\to\{P'\}} + T_{\{B',Q'\}\to\{P'\}}, \\ &\quad \text{since, by Assumption 2,} \\ &\quad I(Q', P''|P'A'B') \\ &\qquad = H(P''|P'A'B') - H(P''|P'A'B'Q') = 0. \end{aligned} \tag{D.4}$$

Combining the preceding results, the Eq. (D.1) becomes,

$$E_{\{A',B',Q'\}\to P'} = T_{\{A',B'\}\to\{P'\}}. \tag{D.5}$$

□

Appendix E. The Proof of Lemma 1

Under Assumptions 2 and 5,

$$\begin{aligned}\alpha_1^{\{A,Q\}\to P} &= H(P'|PAQ) - H(P|P'A'Q') \\ &= H(P'|PA), \\ \alpha_1^{\{A',B',Q'\}\to P'} & \\ &= H(P''|P'A'B'Q') \\ &- H(P'|P''A''B''Q'') = H(P''|P'A'B'). \end{aligned} \tag{E.1}$$

Since,

$$\begin{aligned} H(P'|P) &= T_{A\to P} + H(P'|PA) \\ &= T_{A\to P} + \alpha_1^{\{A,Q\}\to P}, \end{aligned} \tag{E.2}$$

$$\begin{aligned} H(P''|P') &= T_{B'\to P'} + T_{A'\to P'} - T_{\{A',B'\}\to\{P'\}} \\ &\quad + H(P''|P'A'B') \\ &= T_{B'\to P'} + T_{A\to P} + H(P''|P'A'B') \\ &\qquad\qquad \text{(Assumption 1)} \\ &= T_{B'\to P'} + T_{A\to P} + H(P'|PA) \\ &\qquad\qquad \text{(Assumption 3)} \\ &= T_{B'\to P'} + H(P'|P). \end{aligned} \tag{E.3}$$

□

Appendix F. The Proof of Proposition 5

(a)

From Eq. (E.2),

$$\begin{aligned} H(P'|P) &= T_{A\to P} + \alpha_1^{\{A,Q\}\to P} \\ &= \ln q_P - \epsilon, \end{aligned} \tag{F.1}$$

one obtains,

$$H(P') \geqslant H(P'|P) = \ln q_P - \epsilon. \tag{F.2}$$

(b)

From Assumption 5,

$$\begin{aligned} T^{\dagger}_{Q'\to P'} &= H(Q''|P'') - H(Q''|P'P'') \\ &= H(P'|P'') = -\Delta H(P') + H(P''|P'). \end{aligned} \tag{F.3}$$

As a result,

$$H(P''|P') = \ln q_P - \delta. \tag{F.4}$$

Since $H(P''|P') \leqslant H(P'') \leqslant \ln q_P$, one obtains $0 \leqslant \delta$.
Here, $\delta \leqslant \epsilon$ is derived from the non-negativity of $T_{B'\to P'}$.

(c)

From Assumption 6 and Lemma 1,

$$\begin{aligned}\Delta I(P', P) &= \Delta H(P') - \Delta H(P'|P) \\ &= \Delta H(P') - T_{B'\to P'} \geqslant -T_{B'\to P'}.\end{aligned} \tag{F.5}$$

Therefore,

$$\Delta H(P') \geqslant 0. \tag{F.6}$$

Then,

$$\ln q_P \geqslant H(P'') \geqslant H(P') \geqslant \ln q_P - \epsilon. \tag{F.7}$$

Hence,

$$\Delta H(P') \leqslant \ln q_P - (\ln q_P - \epsilon) = \epsilon. \tag{F.8}$$

□

References

[1] Alvarez, J. M., Brooks, M. D., Swift, J., and Coruzzi, G. M., *Annu. Rev. Plant Biol.* **72** (2021) 105–31.

[2] Arcuschin, C. D., Pinkasz, M., and Schor, I. E., *Front. Mol. Neurosci.* **16** (2023) 1114015.

[3] Barato, A. C., Hartich, D., and Seifert, U., *Phys. Rev. E* **87** (2013) 042104.

[4] Bell, A. J., in *Proceedings of the Fifth International Conference on Independent Component Analysis and Blind Signal Separation* (Nara, Japan, 2003), pp. 921–6.

[5] Bennett, C. H., *IBM J. Res. Dev.* **17** (1973) 525–32.

[6] Blasius, B., Rudolf, L., Weithoff, G., Gaedke, U., and Fussmann, G. F., *Nature* **577** (2020) 226–30.

[7] Bossomaier, T., Barnett, L., Harré, M., and Lizier, J. T., *An Introduction to Transfer Entropy: Information Flow in Complex Systems* (Springer International Publishing, Cham, 2016).

[8] Cover, T. M. and Thomas, J. A., *Elements of Information Theory* (Wiley-Interscience, New York, NY, USA, 1991).

[9] Diestel, R., *Graph Theory*, *Graduate Texts in Mathematics*, Vol. 173, 5th edn. (Springer, Berlin, Germany, 2017).

[10] El Gamal, A. and Kim, Y., *Network information theory* (Cambridge university press, 2011).

[11] Elowitz, M. B. and Leibler, S., *Nature* **403** (2000) 335–8.

[12] Esposito, M., Lindenberg, K., and Van den Broeck, C., *New J. Phys.* **12** (2010) 013013.

[13] Fano, R. M., *The Transmission of Information*, Vol. 65 (Massachusetts Institute of Technology, Research Laboratory of Electronics, Cambridge, MA, 1949).

[14] Fredkin, E. and Toffoli, T., *Int. J. Theor. Phys.* **21** (1982) 219–53.
[15] Gonze, D., Halloy, J., and Goldbeter, A., *Proc. Natl. Acad. Sci.* **99** (2002) 673–8.
[16] Han, T. S., *Inf. Control* **46** (1980) 26.
[17] Hartich, D., Barato, A. C., and Seifert, U., *J. Stat. Mech.* (2014) P02016.
[18] Honig, M. L., Steiglitz, K., and Gopinath, B., *IEEE Trans. Commun.* **38** (1990) 551–8.
[19] Horowitz, J. M., *J. Stat. Mech.* (2015) P03006.
[20] Ito, S., *Sci. Rep.* **6** (2016) 36831.
[21] Ito, S. and Sagawa, T., *Phys. Rev. Lett.* **111** (2013) 180603.
[22] Ito, S. and Sagawa, T., *Nat. Commun.* **6** (2015) 7498.
[23] Kashiwase, H., Ohshima, K. I., Nihashi, S., and Eicken, H., *Sci. Rep.* **7** (2017) 8170.
[24] Kim, J., Jakobsen, S. T., Natarajan, K. N., and Won, K., *Nucleic Acids Res.* **49** (2021) e1.
[25] Kleinberg, J. and Tardos, E., *Algorithm Design* (Pearson Education, Boston, MA, USA, 2005).
[26] Krippendorff, K., *Int J Gen Syst* **38** (2009) 669–80.
[27] Lee, Y., Dataset (v0.1.4b) for "robustness of information circulation under entropy constraints" (2026), doi:10.5281/zenodo.22358615, https://doi.org/10.5281/zenodo.22358615.
[28] Lee, Y., Dynamical equations of mutual information and transfer entropy in discrete time, *AIP Adv.* **16** (2026) 055108, doi:10.1063/5.0332016.
[29] Li, S., *Entropy* **21** (2019) 111.
[30] Lizier, J. T., Prokopenko, M., and Zomaya, A. Y., Local information transfer as a spatiotemporal filter for complex systems, *Phys. Rev. E* **77** (2008) 026110, doi:10.1103/PhysRevE.77.026110.
[31] Lyons, S. and Prasad, A., *Biophys. J.* **102** (2012) 591a–2a.
[32] Margolus, N., *arXiv:0805.3357* (2008), doi:10.48550/arXiv.0805.3357.
[33] Matsuda, H., *Phys. Rev. E* **62** (2000) 3096–102.
[34] McGill, W., *Trans. IRE Prof. Group Inf. Theory* **4** (1954) 93.
[35] Niu, X. and Quinn, C. J., in *2020 International Symposium on Information Theory and Its Applications (ISITA)* (IEEE, 2020), pp. 6–10.
[36] Parrondo, J. M., Horowitz, J. M., and Sagawa, T., *Nat. Phys.* **11** (2015) 131–139.
[37] Patel, R. B., Ho, J., Ferreyrol, F., Ralph, T. C., and Pryde, G. J., *Sci. Adv.* **2** (2016) e1501531.
[38] Prokopenko, M., Lizier, J. T., and Price, D. C., *Entropy* **15** (2013) 524.
[39] Ptaszyński, K. and Esposito, M., *Phys. Rev. E* **107** (2023) L052102.
[40] Qiao, L., Zhang, Z., Zhao, W., Wei, P., and Zhang, L., *eLife* **11** (2022) e76188.
[41] Rosinberg, M. L. and Horowitz, J. M., *Europhys. Lett.* **116** (2016) 10007.
[42] Schreiber, T., *Phys. Rev. Lett.* **85** (2000) 461.
[43] Scott, D. N., Mukherjee, A., Nassar, M. R., and Halassa, M. M., *Trends Cogn. Sci.* **28** (2024) 739–56.
[44] Shannon, C. E. and Weaver, W., *The Mathematical Theory of Communication* (Univ. of Illinois Press, Urbana, 1949).
[45] Spinney, R. E. and Lizier, J. T., *Phys. Rev. E* **98** (2018) 012314.
[46] Spinney, R. E., Lizier, J. T., and Prokopenko, M., *Phys. Rev. E* **94** (2016) 022135.
[47] Spinney, R. E., Lizier, J. T., and Prokopenko, M., *Phys. Rev. E* **98** (2018) 032141.
[48] Ting, H. K., *Theory Probab. Appl.* **7** (1962) 439–47.
[49] Wenzler, J. S., Dunn, T., Toffoli, T., and Mohanty, P., *Nano Lett.* **14** (2014) 89–93.
[50] Wibral, M., Vicente, R., and Lizier, J. T. e., *Directed Information Measures in*

Neuroscience, Vol. 724 (Springer, Berlin, 2014).
[51] Yeung, R. W., *IEEE Trans. Inf. Theory* **37** (1991) 466–74.
[52] Zhou, E., Kochman, Y., and Wornell, G. W., *IEEE J. Sel. Areas Commun.* **33** (2015) 1828–38.