## Bill of Materials

Company: University of Concordia Project Name: Smart Front Door Revision: Release 4 BOM

Prepared by: Dean Chong San, Nick Di Marco and Benjamin Lanthier, Team 26
Approved by: Dmitry Rozhdestvenskiy
Production date 1/25/2021

Design Reference	Name	Description	Value	Qty	Unit	Manufacturer	Manufacturer P/N	Package	Туре	Supplier	Supplier P/N	Unit Cost (\$CDN)	Total Cost (\$CDN)
-	Battery Charger	Desktop Battery Charger 7A 300 mA 6V	300mA, 6V	1	pcs	ZEUS Battery Products	PCCG-SLA6V300	Bulk	Desktop	Digi-Key	2059-PCCG- SLA6V300-ND	16.1	16.1
-	Magnet	MAGNET 1.125"L X 0.259"W PLASTIC for 59145-030 Reed switch	57150-000	1	pcs	Littelfuse Inc.	57150-000	Bulk	Alnico 5 (AlNiCo)	Digi-Key	57150-000-ND	4.05	4.05
-	PCB Board	Project 4-Layer PCB board - 63.5mm x 63.5 mm	-	5	pcs	JLCPCB	-	-	-	JLCPCB	-		8
-	SD Card 64 GB	SanDisk A1 Memory micro SD Card 64 GB	64gb	1	pcs	SanDisk	A1 micro sd card	Single card	micro SD	Ali-Express	A1 micro sd card	8.61	8.61
- BT1	USB to Serial Batteries	RF Explorer - Adapter Board  Battery HHR PACK NIMH 6V L-A	317990279 3.7Ah	2	pcs	Seeed Technology Co. Ltd Panasonic - BSG	317990279 HHR-380AB27F5	Evaluation Board 5 cells	Adapter Board side-to-side	Digi-Key Digi-Key	1597-1492-ND P018-F051-ND	8.42 52.26	8.42 104.52
BT2, SW4	Wireless Doorbell	Heath Zenith Wireless Battery Operated	# SL-7306-03	1		Heath Zenith			side-to-side			30	30
C1, C2, C5,		Door Bell Kit with 1-Push Button			pcs		# SL-7306-03	Box		HomeDepot	# 1001341241		
C10, C15, C17	1μF Cap SMD	Ceramic Capacitor 1µF	1 μF	12	pcs	Samsung Electro-Mechanics	CL10B105KO8NFNC	0603	SM	Digi-Key	1276-1943-1-ND	0.14	1.68
C16 C3, C7, C11,	22µF Cap SMD	Ceramic Capacitor 22µF	22 μF	2	pcs	Samsung Electro-Mechanics	CL21A226KPCLRNC CC0603JRX7R7BB10	0805	SM	Digi-Key	1276-6786-1-ND	0.52	1.04
C12, C13, C19 C4, C6, C8, C9,	0.1uF Cap SMD	0.1µF Ceramic Capacitor	0.1 uF	12	pcs	Samsung Electro-Mechanics	4	0603	SM	Digi-Key	311-1776-1-ND	0.14	1.68
C14, C18	10μF Cap SMD	Ceramic Capacitor 10μF	10 μF	12	pcs	Samsung Electro-Mechanics	CL21A106KOQNNNG	0805	SM	Digi-Key	1276-6455-1-ND	0.16	1.92
CR1	Schottky Diode	Diode Schottky 25V 2A SMB	25V, 2A TPD1E1B04DP	4	pcs	STMicroelectronics	STPS2L25U	DO-214AA	SM	Digi-Key	497-5573-1-ND 296-46892-2-ND -	0.51	2.04
D1, D2	TVS Diodes	TVS DIODE 3.6V 8.5V 2X1SON	YT	4	pcs	Texas Instruments	TPD1E1B04DPYT	0402	SM	Digi-Key	Tape & Reel	1.02	4.08
J1, J2, J6, J7	4-wire connector male	Connector Header Surface Mount, Right Angle 4 position	S4B-PH-SM4- TB(LF)(SN)	8	pcs	JST Sales America Inc	S4B-PH-SM4-TB(LF) (SN)	Shrouded	SM, Right Angle	Digi-Key	455-1751-1-ND	1.02	8.16
J14, J19	7-wire connector female	7 Position Terminal Block Plug, Female Sockets 0.100" (2.54mm) 180° Free Hanging (In-Line)	1431071310100 0	2	pcs	HARTING	14310713101000	Shrouded	Free Hanging (In- Line)	Digi-Key	1195-3604-ND	3.72	7.44
J15 - J17	4-wire connector female	4 Position Cable Assembly Rectangular Socket to Individual Wire Leads	CABLE-EH04	4	pcs	Trinamic Motion Control GmbH	CABLE-EH04	Shrouded, Socket to individual wire leads	Free Hanging, (In- Line)	Digi-Key	1460-1292-ND	1.7	6.8
J18	5-wire connector female	5 Rectangular Connectors - Housing Receptable Natural	GHR-05V-S	1	pcs	JST Sales America Inc.	GHR-05V-S	Shrouded	Free Hanging (In- Line)	Digi-Key	455-1595-ND	0.25	0.25
J3, J5	7-connector male	7 Position Terminal Block Header, Male Pins, Shrouded (4 Side) 0.100" (2.54mm) 90°, Right Angle Surface Mount	1411071300200 0	4	pcs	HARTING	14110713002000	Shrouded	SM, Right Angle	Digi-Key	1195-3639-1-ND	2.87	11.48
J4	5-wire connector male	CONN HEADER SMD R/A 5POS 1.25MM	SM05B-GHS- TB(LF)(SN)	2	pcs	JST Sales America Inc	SM05B-GHS-TB(LF) (SN)	Shrouded	SM, Right Angle	Digi-Key	455-1567-1-ND	0.5	1
J8	Barrel Connector	DC POWER JACK, SMT, HORIZONTAL,	DCJ065-05-A-	2	pcs	GCT	DCJ065-05-A-K1-A	Bulk	SM, Right Angle	Digi-Key	2073-DCJ065-05-A- K1-ACT-ND	1.05	2.1
J9	Barrel Plug	Cable Assembly 0.7mm ID, 2.35mm OD	K1-A CA-2192	2	pcs	Tensility International Corp	CA-2192	Bulk	Free Hanging,	Digi-Key	CP-2192-ND	3.79	7.58
		Plug to wire Shielded Wirewound Inductor							Plug to wire leads		SRR1210-181MCT-		
L1	180uH Inductor	Defiant Castle Matte Black Single Cylinder	180 µH	2	pcs	Bourns Inc	SRR1210-181M	Nonstandard	SM	Digi-Key	ND	1.64	3.28
M1	Defiant Door lock	Electronic Keypad Deadbolt	# G7XKD01AA	1	pcs	Defiant	# G7XKD01AA	Box	Electronic Keypad	HomeDepot	# 1001134626	90	90
MS1	Motion Sensor	Motion Sensor SEN0171 PIR (MOTION) SENSOR	Gravity	1	pcs	DFRobot	SEN0171	Board and cables	Sensor	Digi-Key	1738-1129-ND	6.93	6.93
R1, R15, R16	1 kΩ Res	1 kΩ with 1% Tolerance	1 kΩ	6	pcs	Yageo	RE0603FRE071KL	0603	SM	Digi-Key	13- RE0603FRE071KLCT -ND	0.15	0.9
R14	10 kΩ Res (0.1% Tol)	RES SMD 10K OHM 0.1% 1/10W 0603	10 kΩ	2	pcs	Yageo	RE0603BRE0710KL	0603	SM	Digi-Key	13- RE0603BRE0710KLC T-ND	0.48	0.96
R18	931 kΩ Res	RES SMD 931K OHM 1% 1/8W 0805	931 kΩ	2	pcs	Yageo	RC0805FR-07931KL	0805	SM SM	Digi-Key	311-931KCRTR-ND	0.15	0.3
R19 R2 - R7, R10 - R13, R17	300 kΩ Res 10kΩ Res (1% Tol)	RES 300 kΩ  RES 10K OHM 1% 1/10W 0402	300 kΩ 10 kΩ	2 22	pcs	Yageo KOA Speer Electronics Inc	RC0402JR-07300KL RK73G1ETTP1002F	0402	SM	Digi-Key Digi-Key	311-300KJRCT-ND 2019- RK73G1ETTP1002FC	0.15	0.3 8.58
R20 - R22	200 kΩ Res	RES SMD 200K OHM 0.5% 1/10W 0805	200 kΩ	6	pcs	Susumu	RR1220P-204-D	0805	SM	Digi-Key	T-ND RR12P200KDTR-ND	0.15	0.9
R23	150 kΩ Res	RES SMD 150K OHM 0.5% 1/10W 0805	150 kΩ	2	pcs	Susumu	RR1220P-154-D	0805	SM	Digi-Key	RR12P150KDTR-ND	0.15	0.3
R24	499 Ω Res	499 Ω Chip Resistor	499Ω	2	pcs	Stackpole Electronics	RMCF0201FT499R	0201	SM	Digi-Key	RMCF0201FT499RCT -ND	0.15	0.3
R25	10 kΩ Trimmer	Trimmer 10k Ω	10 kΩ	2	pcs	Bourns Inc	TC33X-2-103E	SOD-23	SM	Digi-Key	TC33X-103ECT-ND	0.4	0.8
R26	86.6 kΩ Res	RES SMD 86.6K OHM 1% 1/8W 0805	86.6 kΩ	2	pcs	Yageo	RC0805FR-0786K6L CRCW0805100RJNE	0805	SM	Digi-Key	311-86.6KCRTR-ND	0.15	0.3
R27	100 Ω Res	RES 100 OHM 5% 1/8W 0805	100 Ω	2	pcs	Vishay Dale	AC	0805	SM	Digi-Key	541-4166-2-ND	0.15	0.3
R28	1 kΩ Res	RES 1K OHM 1/4W 1% AXIAL	1 kΩ	2	pcs	Yageo	MFR-25FBF52-1K	Axial	Through hole	Digi-Key	1.00KXBK-ND	0.14	0.28
R8	0.4 Ω Res	400 mΩ Chip Resistor	400 mΩ	2	pcs	Yageo	RL1206FR-070R4L	1206	SM	Digi-Key	3114LWCT-ND	0.54	1.08
R9	1.43 kΩ Res	1.43 kΩ Chip Resistor	1.43 kΩ PTS 647 SK50	4	pcs	Bourns Inc C&K	RT0603BRE071K43L PTS 647 SK50	0603	SM SM	Digi-Key	YAG4654CT-ND PTS647SK50SMTR2L	0.57	0.8
SW1, SW2	Switch Button	Tactile Switch Top Actuated Surface Mount  Tactile Switch SPST-NO Top Actuated	SMTR2 LFS		pcs	TE Connectivity	SMTR2 LFS	PTS647-NO		Digi-Key	FSCT		
SW3	Switch Button	Through Hole	1825910-6	2	pcs	ALCOSWITCH Switches Littelfuse Inc.	1825910-6	SPST-NO	Through hole	Digi-Key	450-1650-ND	0.15	0.3
SW5 U1	Reed Switch OptoCoupler	SENSOR REED SW SPDT WIRE LEADS Optoisolator Transistor Output 2500Vrms 2	59145-030 2500Vrms	2	pcs	ON Semiconductor	59145-030 MOCD207D2M	Wire terminated 8-SOIC	SPDT	Digi-Key Digi-Key	59145-030-ND MOCD207D2MCT-ND	6.58 2.18	6.58 4.36
U2	ESP32-SOLO-1	Channel 8-SOIC  ESP32-SOLO-1 Board, 2.4GHz, 150Mbps, 3.6V	ESP32-SOLO-1	2	pcs	Espressif Systems	ESP32-SOLO-1	38-SMD Module	SMD	Digi-Key	1965-ESP32-SOLO- 1CT-ND	5.12	10.24
U3	Motor Controller	Bipolar Motor Driver Power MOSFET Parallel	296-51093-1- ND	2	pcs	Texas Instruments	DRV8832QDGQRQ1	10-TFSOP. 10- MSOP	SM	Digi-Key	296-51093-1-ND	3.92	7.84
U4	Op-Amp	IC OPAMP GP 2 CIRCUIT 8VSSOP	TLV8812DGKR	2	pcs	Texas Instruments	TLV8812DGKR	8-VSSOP	SM	Digi-Key	296-45065-2-ND	1.28	2.56
U5	Switching Reg.	Buck Switching Regulator IC Positive	296-34972-1- ND	2	pcs	Texas Instruments	TPS5403DR	8-SOIC	SM	Digi-Key	296-34972-1-ND	2.41	4.82
U6	ESP32-CAM	ESP32-CAM DEVELOPMENT BOARD	ESP32-CAM	1	pcs	Seeed Technology Co., Ltd	113990580	DIP-16	DIP	Digi-Key	1597-1687-ND	15.99	15.99
U7	LCD Screen	LCD Screen Serial Port Module With PCB Adapter Micro SD (240x320)	240x320px	1	pcs	Generic	MSP2807	Bulk	DIP	Ali-Express	2.8 inch TFT LCD Modul	7.09	7.09
0,													