

the $\mathcal{H}_\infty$ norm of the closed-loop transfer function. The $\mathcal{H}_\infty$ norm of a transfer function $G(s)$ is defined as the maximum singular value of the frequency response $G(j\omega)$ over all frequencies ω .

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is defined as the maximum singular value of the frequency response $G(j\omega)$ over all frequencies ω .

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.

The $\mathcal{H}_\infty$ norm is a measure of the maximum gain of the system. It is used to quantify the robustness of a control system against uncertainties in the plant and the controller.

The $\mathcal{H}_\infty$ norm is also used to design robust controllers. The $\mathcal{H}_\infty$ norm of the closed-loop transfer function is minimized to achieve robust performance.