

CVSim

Simulation of voltammograms and electrochemical mechanisms

Academic software, free of charge · Windows and Linux

CVSim computes the electrochemical response of a mechanism written as one writes it on the board: $A + e = B$, $B + C = A + D$. Diffusion, electron transfer, solution chemistry, adsorption, ohmic drop and double-layer capacitance are solved together, on a space grid placed automatically.

A single voltammogram can be reproduced by more than one mechanism. CVSim is built to tell them apart: it computes **series** (scan rate, concentration, rate constant...) and sets them against the same series measured.

In practice

- mechanism typed as free text, units checked, equilibrium constants derived from thermodynamic cycles
- impossible values refused, unusual ones flagged
- current, concentration profiles and surface concentrations at every instant
- every result exported as a text file, with a picture of the window




Figure 1 — Fast couple ($k^0 = 1$ cm/s), five scan rates from 0.02 to 0.5 V/s: voltammograms and the lines $I_p = f(v^{1/2})$ drawn by the Series window.

Mechanisms

- Butler-Volmer or Marcus-Hush-Chidsey electron transfer
- concerted transfers between solution and surface
- first- and second-order coupled chemistry: catalysis, dimerisation, disproportionation
- adsorbed species: Langmuir and Frumkin isotherms, Laviron interactions
- mixed steps between a dissolved and an adsorbed species
- electrochemiluminescence: excited states, emission yield, photons per electron

Electrodes and cells

- planar, spherical, hemispherical or cylindrical electrode, down to microelectrodes at steady state
- semi-infinite diffusion, stagnant layer, closed thin layer, rotating disk
- uncompensated resistance and double-layer capacitance
- initial state as entered or brought to equilibrium
- thermodynamic limit for fast equilibria

Techniques

- cyclic and linear sweep voltammetry
- single and double potential step
- square wave voltammetry
- differential pulse voltammetry
- ac voltammetry and its harmonics
- impedance spectroscopy

Analysing, and comparing with measurements

- **Series** over any parameter, with their derived quantities: I_p against $v^{1/2}$ or v , $\log I_p$ against $\log v$, E_p and ΔE_p , Nicholson's peak ratio, Nicholson's ψ and k^0 , convolution and deconvolution, Levich plateaux and the Koutecký-Levich line.
- **Measurements overlaid**: BioLogic EC-Lab, CH Instruments and Metrohm Autolab files, or plain columns of numbers. The same quantities are taken from measurements and simulations, and the gap between the two families is quantified.
- **A mechanism kept on screen**: a frozen series stays as the reference while a constant or a step is changed.

Spectroelectrochemistry

In a thin layer or a stagnant layer, CVSim gives the mean concentration of each species over the thickness of the layer, and its time derivative. These are what the absorbance, or its derivative, follows in spectroelectrochemistry: the simulation compares directly with the optical measurement.




Figure 2 — Stagnant layer of 200 μm , $A + e = B$ followed by $B \rightarrow C$ ($k = 0.05 \text{ s}^{-1}$), 10 mV/s: derivative of the mean concentration of A, B and C over the layer.

Validated

Every version passes more than 500 automated checks. Currents are compared with closed-form solutions: Randles-Ševčík, Cottrell, Laviron, thin layer, Levich plateau, Randles impedance, square wave and differential pulse. Conservation of matter and charge is checked every time.

Numerical method

Finite differences on an expanding grid, sized automatically from the problem; second-order implicit scheme (BDF2); Newton's method on the coupled system, sparse factorisation. The Refine command measures how far the curve moves when the grid is refined.

Getting started

- twenty-three example studies shipped with the program, one per capability, each saying what to look at
- a user guide in French and English: every window and every control, the physical model, the numerical method, the references
- interface in English

Free of charge for everyone

CVSim is free of charge for everyone, students and researchers alike. It is distributed as 64-bit Windows and Linux executables that need only the free MATLAB Runtime: no MATLAB licence is required. Its licence of use, free of charge, allows it to be installed on as many computers as wished and passed on unchanged.

CVSim comes with absolutely **NO WARRANTY**.

To obtain CVSim: write to the developers at echem-tools@univ-angers.fr.

Acknowledgement: if CVSim contributes to a publication, a thesis or a funded project (ANR, ERC, a European programme...), the authors would be grateful for a mention, for instance in the acknowledgements: « Simulations were carried out with CVSim (O. Alévêque and E. Levillain, MOLTECH Anjou, UMR 6200 CNRS, University of Angers), software free of charge, available on request from echem-tools@univ-angers.fr. »

Olivier Alévêque and Eric Levillain — MOLTECH Anjou, UMR 6200 CNRS, University of Angers