核心板与主板接口

J1

PI0	30	31		PI1
H14	29	32		H15
A13	28	33		H13
A11	27	34		A12
A9	26	35		A10
C9	25	36		A8
C7	24	37		C8
G6	23	38		C6
D15	22	39		G3
D13	21	40		D14
D11	20	41		D12
D9	19	42		D10
B15	18	43		D8
B13	17	44		B14
H12	16	45		B12
H10	15	46		H11
H8	14	47		H9
H6	13	48		H7
B10	12	49		B11
E14	11	50		E15
E12	10	51		E13
E10	9	52		E11
E8	8	53		E9
PB2	7	54		E7
PB0	6	55		PB1
PC4	5	56		PC5
PA6	4	57		PA7
PA4	3	58		PA5
H5	2	59		PA3
VBAT	1	60		H4

J2

PI3	30	31		PI2
A15	29	32		A14
C11	28	33		C10
PD0	27	34		C12
PD2	26	35		PD1
PD4	25	36		PD3
PD6	24	37		PD5
G10	23	38		PD7
G12	22	39		G11
G14	21	40		G13
PB4	20	41		PB3
PB6	19	42		PB5
BT0	18	43		PB7
PB9	17	44		PB8
PE1	16	45		PE0
PI5	15	46		PI4
PI7	14	47		PI6
PE3	13	48		PE2
PE5	12	49		PE4
PI8	11	50		PE6
PI11	10	51		C13
F7	9	52		F6
F9	8	53		F8
PC1	7	54		RST
PA0	6	55		VR+
PA2	5	56		PA1
H3	4	57		H2
3V3	3	58		GND
3V3	2	59		GND
3V3	1	60		GND

3710F060046G3FT01

P1

5	5V	
4		VCC3.3
3	JTMS	
2	JTCK	
1		GND

SWD

SWD接口



MCU

U1

	WK_UP	PA0	40
	RMII_REF_CLK	PA1	41
USART2_TX	ETH_MDIO	PA2	42
USART2_RX	PWM_DAC	PA3	47
GBC_LED	STM_DAC	PA4	50
	STM_ADC	PA5	51
	DCMI_PCLK	PA6	52
	RMII_CRS_DV	PA7	53
REMOTE_IN	DCMI_XCLK	PA8	119
	USART1_TX	PA9	120
	USART1_RX	PA10	121
	USB_D-	PA11	122
	USB_D+	PA12	123
	JTMS	PA13	124
	JTCK	PA14	137
DCMI_RESET	JTDI	PA15	138
	LED1	PB0	56
	LED0	PB1	57
	BOOT1	PB2	58
DCMI_SDA	JDTO	PB3	161
DCMI_SCL	JTRST	PB4	162
	LCD_BL	PB5	163
		PB6	164
	DCMI_VSYNC	PB7	165
	DCMI_D6	PB8	167
	DCMI_D7	PB9	168
USART3_TX		PB10	79
USART3_RX	RMII_TX_EN	PB11	80
1WIRE_DQ	IIC_INT	PB12	92
	SPI2_SCK	PB13	93
	SPI2_MISO	PB14	94
	SPI2_MOSI	PB15	95
	FMC_SDNWE	PC0	32
	ETH_MDC	PC1	33
	FMC_SDNE0	PC2	34
	FMC_SDCKE0	PC3	35
	RMII_RXD0	PC4	54
	RMII_RXD1	PC5	55
	DCMI_D0	PC6	115
	DCMI_D1	PC7	116
SDIO_D0	DCMI_D2	PC8	117
SDIO_D1	DCMI_D3	PC9	118
SDIO_D2		PC10	139
SDIO_D3	DCMI_D4	PC11	140
SDIO_SCK		PC12	141
	KEY2	PC13	8
	OSC32_IN		9
	OSC32_OUT		10
	FMC_D2	PD0	142
	FMC_D3	PD1	143
SDIO_CMD		PD2	144
	DCMI_D5	PD3	145
	FMC_NOE	PD4	146
	FMC_NWE	PD5	147
	FMC_NWAIT	PD6	150
	FMC_NE1	PD7	151
	FMC_D13	PD8	96
	FMC_D14	PD9	97
	FMC_D15	PD10	98
	FMC_A16_CLE	PD11	99
	FMC_A17_ALE	PD12	100
	FMC_A18	PD13	101
	FMC_D0	PD14	104
	FMC_D1	PD15	105
	FMC_NBL0	PE0	169
	FMC_NBL1	PE1	170
	SAI1_MCLKA	PE2	1
	SAI1_SDB	PE3	2
	SAI1_FSA	PE4	3
	SAI1_SCKA	PE5	4
	SAI1_SDA	PE6	5
	FMC_D4	PE7	68
	FMC_D5	PE8	69
	FMC_D6	PE9	70
	FMC_D7	PE10	73
	FMC_D8	PE11	74
	FMC_D9	PE12	75
	FMC_D10	PE13	76
	FMC_D11	PE14	77
	FMC_D12	PE15	78

PA0/WKUP0/TIM2_TIM5_CH1/TIM2_TIM8_ETR/TIM15_BKIN/U2_CTS/U4_TX/SDMMC2_CMD/SAI2_SD_B/ETH_MII_CRS/ADC123_INP16
PA1/TIM2_TIM5_CH2/LPTIM3_OUT/TIM15_CH1N/U2_RTS/U4_RX/QSPI_BK1_IO3/SAI2_MCK_B/ETH_MII_RMII_REF_CLK/LCD_R2/ADC1_INN16_INP17
PA2/TIM2_TIM5_CH3/LPTIM4_OUT/TIM15_CH1/U2_TX/SAI2_SCK_B/ETH_MDIO/MDIOS_MDIO/LCD_R1/ADC12_INP14/WKUP1
PA3/TIM2_TIM5_CH4/LPTIM5_OUT/TIM15_CH2/U2_RX/OTG_HS_ULPI_D0/ETH_MII_COL/LCD_B2_B5/ADC12_INP15
PA4/TIM5_ETR/SPI1_SPI3_NSS/I2S1_I2S3_WS/U2_CK/SPI6_NSS/OTG_HS_SOF/DCMI_HSYNC/LCD_VSYNC/ADC12_INP18/DAC1_OUT1
PA5/TIM2_CH1_ETR/TIM8_CH1N/SPI1_SCK/I2S1_CK/SPI6_SCK/OTG_HS_ULPI_CK/LCD_R4/ADC12_INN18_INP19/DAC1_OUT2
PA6/TIM1_TIM8_BKIN/TIM3_TIM13_CH1/SPI1_SPI6_MISO/I2S1_SDI/TIM1_TIM8_BKIN_COMP12/MDIOS_MDC/DCMI_PIXCLK/LCD_G2/ADC12_INP3
PA7/TIM1_TIM8_CH1N/TIM3_CH2/SPI1_SPI6_MOSI/I2S1_SD/TIM14_CH1/ETH_MII_RX_DV/ETH_RMII_CRS_DV/FMC_SDNWE/ADC12_INN3_INP7/OPAMP1_VINM
PA8/MCO1/TIM1_CH1/HRTIM_CHB2/TIM8_BKIN2/I2C3_SCL/U1_CK/OTG_FS_SOF/U7_RX/TIM8_BKIN2_CIMP12/LCD_B3_R6
PA9/TIM1_CH2/HRTIM_CHC1/I2C3_SMBA/SPI2_SCK/I2S2_CK/U1_TX/FDCAN1_RXFD_MODE/ETH_TX_ER/DCMI_D0/LCD_R5/OTG_FS_VBUS
PA10/TIM1_CH3/HRTIM_CHC2/U1_RX/FDCAN1_TXFD_MODE/OTG_FS_ID/MDIOS_MDIO/LCD_B4_B1/DCMI_D1
PA11/TIM1_CH4/HRTIM_CHD1/SPI2_NSS/I2S2_WS/U4_RX/U1_CTS/FDCAN1_RX/LCD_R4/OTG_FS_DM
PA12/TIM1_ETR/HRTIM_CHD2/SPI2_SCK/I2S2_CK/U4_TX/U1_RTS/SAI2_FS_B/FDCAN1_TX/LCD_R5/OTG_FS_DP
PA13/JTMS/SWDIO
PA14/JTCK/SWDCLK
PA15/JTDI/TIM2_CH1__ETR/HRTIM_FLT1/HDMI_CEC/SPI1_SPI3_SPI6_NSS/I2S1_I2S3_WS/U4_RTS/U7_TX
PB0/TIM1_TIM8_CH2N/TIM3_CH3/DFSDM_CKOUT/U4_CTS/LCD_R3_G1/OTG_HS_ULPI_D1/ETH_MII_RXD2/ADC12_INN5_INP9/OPAMP1_VINP/COMP_1_INP
PB1/TIM1_TIM8_CH3N/TIM3_CH4/DFSDM_D1/LCD_R6_G0/OTG_HS_ULPI_D2/ETH_MII_RXD3/ADC12_INP5/COMP_1_INM
PB2/SAI1_SAI4_D1/DFSDM_CKIN1/SAI1_SAI4_SD_A/SPI3_MOSI/I2S3_SD/QSPI_CLK/ETH_TX_ER/COMP_1_INP/RTC_OUT
PB3/JTDO/TIM2_CH2/HRTIM_FLT4/SPI1_SPI3_SPI6_SCK/I2S1_I2S3_CK/SDMMC2_D2/U7_RX
PB4/NJTRST/TIM16_BKIN/TIM3_CH1/HRTIM_EEV6/SPI1_SPI3_SPI6_MISO/I2S1_I2S3_SDI/SPI2_NSS/I2S2_WS/SDMMC2_D3/U7_TX
PB5/TIM17_BKIN/TIM3_CH2/HRTIM_EEV7/I2C1_I2C4_SMBA/SPI1_SPI3_SPI6_MOSI/I2S1_I2S3_SD/FDCAN2_RX/OTG_HS_ULPI_D7/ETH_PPS_OUT/FMC_SDCKE1/DCMI_D10/U5_RX
PB6/TIM16_CH1N/TIM4_CH1/HRTIM_EEV8/HDMI_CEC/I2C1_I2C4_SCL/U1_TX/FDCAN2_TX/QSPI_BK1_NCS/DFSDM_D5/FMC_SDNE1/DCMI_D5/U5_TX
PB7/TIM17_CH1N/TIM4_CH2/HRTIM_EEV9/I2C1_I2C4_SDA/U1_RX/FDCAN2_TXFD_MODE/DFSDM_CKIN5/FMC_NL/DCMI_VSYNC/PVD_IN
PB8/TIM16_CH1/TIM4_CH3/DFSDM_CKIN7/I2C1_I2C4_SCL/SDMMC1_CKIN/U4_RX/FDCAN1_RX/ETH_MII_TXD3/SDMMC12_D4/DCMI_D6/LCD_B6
PB9/TIM17_CH1/TIM4_CH4/DFSDM_D7/I2C1_I2C4_SDA/SPI2_NSS/I2S2_WS//SDMMC1_CDIR/U4_TX/FDCAN1_TX/SDMMC12_D5/I2C4_SMBA/DCMI_D7/LCD_B7
PB10/TIM2_CH3/HRTIM_SCOUT/LPTIM2_IN1/I2C2_SCL/SPI2_SCK/I2S2_CK/DFSDM_D7/U3_TX/QSPI_BK1_NCS/OTG_HS_ULPI_D3/ETH_MII_RX_ER/LCD_G4
PB11/TIM2_CH4/HRTIM_SCIN/LPTIM2_ETR/I2C2_SDA/DFSDM_CKIN7/U3_RX/OTG_HS_ULPI_D4/ETH_MII_RMII_TX_EN/LCD_G5
PB12/TIM1_BKIN/I2C2_SMBA/SPI2_NSS/I2S2_WS/DFSDM_D1/U3_CK/U5_RX/FDCAN2_RX/OTG_HS_ID_ULPI_D5/ETH_MII_RMII_TXD0/TIM1_BKIN_COMP12
PB13/TIM1_CH1N/SPI2_SCK/I2S2_CK/DFSDM_CKIN1/U3_CTS/U5_TX/FDCAN2_TX/OTG_HS_VBUS_ULPI_D6/ETH_MII_RMII_TXD1
PB14/TIM1_TIM8_CH2N/U1_TX/SPI2_MISO/I2S2_SDI/DFSDM_D2/U3_U4_RTS/SDMMC2_D0/TIM12_CH1/OTG_HS_DM
PB15/RTC_REFIN/TIM1_TIM8_CH3N/U1_RX/SPI2_MOSI/I2S2_SD/DFSDM_CKIN2/U4_CTS/SDMMC2_D1/TIM12_CH2/OTG_HS_DP
PC0/DFSDM_CKIN0_D4/SAI2_FS_B/OTG_HS_ULPI_STP/FMC_SDNWE/LCD_R5/ADC123_INP10
PC1/SAI1_SAI4_D1/DFSDM_D0_CKIN4/SPI2_MOSI/I2S2_SD/SAI1_SAI4_SD_A/SDMMC2_CK/ETH_MDC/MDIOS_MDC/ADC123_INN10_INP11/RTC_TAMP3/WKUP5
PC2/DFSDM_CKIN1_CKOUT/SPI2_MISO/I2S2_SDI/OTG_HS_ULPI_DIR/ETH_MII_TXD2/FMC_SDNE0/ADC123_INN11_INP12
PC3/DFSDM_D1/SPI2_MOSI/I2S2_SDO/OTG_HS_ULPI_NXT/ETH_MII_TX_CLK/FMC_SDCKE0/ADC123_INN12_INP13
PC4/DFSDM_CKIN2/I2S1_MCK/SPDIFRX_IN2/ETH_MII_RMII_RXD0/FMC_SDNE0/ADC12_INP14/OPAMP1_VOUT/COMP_1_VINM
PC5/SAI1_SAI4_D3/DFSDM_D2/SPDIFRX_IN3/ETH_MII_RMII_RXD1/FMC_SDCKE0/COMP_1_OUT/ADC12_INN4_INP8/OPAMP1_VINM
PC6/HRTIM_CHA1/TIM3_TIM8_CH1/DFSDM_CKIN3/I2S2_MCK/U6_TX/SDMMC1_D0DIR/FMC_NWAIT/SDMMC12_D6/DCMI_D0/LCD_HSYNC/SWPMI_IO
PC7/HRTIM_CHA2/TIM3_TIM8_CH2/DFSDM_D3/I2S3_MCK/U6_RX/SDMMC1_D123DIR/FMC_NE1/SDMMC12_D7/SWPMI_TX/DCMI_D1/LCD_G6
PC8/HRTIM_CHB1/TIM3_TIM8_CH3/U5_RTS/U6_CK/FMC_NE2_NCE/SWPMI_RX/SDMMC1_D0/DCMI_D2
PC9/MCO2/TIM3_TIM8_CH4/I2C3_SDA/I2S_CKIN/U5_CTS/QSPI_BK1_IO0/LCD_G3_B2/SWPMI_SUSPEND/SDMMC1_D1/DCMI_D3
PC10/HRTIM_EEV1/DFSDM_CKIN5/SPI3_SCK/I2S3_CK/U3_U4_TX/QSPI_BK1_IO1/SDMMC1_D2/DCMI_D8/LCD_R2
PC11/HRTIM_FLT2/DFSDM_D5/SPI3_MISO/I2S3_SDI/U3_U4_RX/QSPI_BK2_NCS/SDMMC1_D3/DCMI_D4
PC12/HRTIM_EEV2/SPI3_MOSI/I2S3_SDO/U3_CK/U5_TX/SDMMC1_CK/DCMI_D9
PC13/RTC_TAMP_1/RTC_TS/WKUP2
PC14/OSC32_IN
PC15/OSC32_OUT
PD0/DFSDM_CKIN6/SAI3_SCK_A/U4_RX/FDCAN1_RX/FMC_D2_DA2
PD1/DFSDM_D6/SAI3_SD_A/U4_TX/FDCAN1_TX/FMC_D3_DA3
PD2/TIM3_ETR/U5_RX/SDMMC1_CMD/DCMI_D11
PD3/DFSDM_CKOUT/SPI2_SCK/I2S2_CK/U2_CTS_NSS/FMC_CLK/DCMI_D5/LCD_G7
PD4/HRTIM_FLT3/SAI3_FS_A/U2_RTS/FDCAN1_RXFD_MODE/FMC_NOE
PD5/HRTIM_EEV3/U2_TX/FDCAN1_TXFD_MODE/FMC_NWE
PD6/SAI1_SAI4_D1/DFSDM_CKIN4_D1/SPI3_MOSI/I2S3_SDO/SAI1_SAI4_SD_A/U2_RX/FDCAN2_RXFD_MODE/SDMMC2_CK/FMC_NWAIT/DCMI_D10/LCD_B2
PD7/DFSDM_CKIN1_D4/SPI1_MOSI/I2S1_SDO/U2_CK/SDMMC2_CMD/SPDIFRX_IN0/FMC_NE1
PD8/DFSDM_CKIN3/SAI3_SCK_B/U3_TX/SPDIFRX_IN1/FMC_D13_DA13
PD9/DFSDM_D3/SAI3_SD_B/U3_RX/FDCAN2_RXFD_MODE/FMC_D14_DA14
PD10/DFSDM_CKOUT/SAI3_FS_B/U3_CK/FDCAN2_TXFD_MODE/FMC_D15_DA15/LCD_B3
PD11/LPTIM2_IN2/I2C4_SMBA/U3_CTS/QSPI_BK1_IO0/SAI2_SD_A/FMC_A16
PD12/LPT1_LPT2_IN1/TIM4_CH1/I2C4_SCL/U3_RTS/QSPI_BK1_IO1/SAI2_FS_A/FMC_A17
PD13/LPT1_OUT/TIM4_CH2/I2C4_SDA/QSPI_BK1_IO3/SAI2_SCK_A/FMC_A18
PD14/TIM4_CH3/SAI3_MCLK_B/U8_CTS/FMC_D0_DA0
PD15/TIM4_CH4/SAI3_MCLK_A/U8_RTS/FMC_D1_DA1
PE0/TIM4_LPT1_LPT2_ETR/HRTIM_SCIN/U8_RX/FDCAN1_RXFD_MODE/SAI2_MCK_A/FMC_NBL0/DCMI_D2
PE1/LPT1_IN2/HRTIM_SCOUT/U8_TX/FDCAN1_TXFD_MODE/FMC_NBL1/DCMI_D3
PE2/SAI1_SAI4_CK1/SPI4_SCK/SAI1_SAI4_MCLK_A/QSPI_BK1_IO2/ETH_MII_TXD3/FMC_A23
PE3/TIM15_BKIN/SAI1_SAI4_SD_B/FMC_A19
PE4/SAI1_SAI4_D2/DFSDM_D3/TIM15_CH1N/SPI4_NSS/SAI1_SAI4_FS_A/FMC_A20/DCMI_D4/LCD_B0
PE5/SAI1_SAI4_CK2/DFSDM_CKIN3/TIM15_CH1/SPI4_MISO/SAI1_SAI4_SCK_A/FMC_A21/DCMI_D6/LCD_G0
PE6/TIM1_BKIN2/SAI1_SAI4_D1/TIM15_CH2/SPI4_MOSI/SAI1_SAI4_SD_A/SAI2_MCK_B/TIM1_BKIN2_COMP12/FMC_A22/DCMI_D7/LCD_G1
PE7/TIM1_ETR/DFSDM_D2/U7_RX/QSPI_BK2_IO0/FMC_D4_DA4/OPAMP2_VOUT/COMP_2_INM
PE8/DFSDM_CKIN2/TIM1_CH1N/U7_TX/QSPI_BK2_IO1/FMC_D5_DA5/COMP_2_OUT/OPAMP2_VINM
PE9/DFSDM_CKOUT/TIM1_CH1/U7_RTS/QSPI_BK2_IO2/FMC_D6_DA6/OPAMP2_VINP/COMP_2_INP
PE10/DFSDM_D4/TIM1_CH2N/U7_CTS/QSPI_BK2_IO3/FMC_D7_DA7/COMP_2_INM
PE11/DFSDM_CKIN4/TIM1_CH2/SPI4_NSS/SAI2_SD_B/FMC_D8_DA8/LCD_G3/COMP_2_INP
PE12/DFSDM_DATIN5/TIM1_CH3N/SPI4_SCK/SAI2_SCK_B/FMC_D9_DA9/COMP_1_OUT/LCD_B4
PE13/DFSDM_CKIN5/TIM1_CH3/SPI4_MISO/SAI2_FS_B/FMC_D10/FMC_DA10/COMP_2_OUT/LCD_DE
PE14/TIM1_CH4/SPI4_MOSI/SAI2_MCK_B/FMC_D11_DA11/LCD_CLK
PE15/TIM1_BKIN/HDMI_TIM1_BKIN/FMC_D12_DA12/TIM1_BKIN_COMP12/LCD_R7
PF0/I2C2_SDA/FMC_A0
PF1/I2C2_SCL/FMC_A1
PF2/I2C2_SMBA/FMC_A2
PF3/FMC_A3/ADC3_INP5
PF4/FMC_A4/ADC3_INN5_INP9
PF5/FMC_A5/ADC3_INP4
PF6/TIM16_CH1/SPI5_NSS/SAI1_SAI4_SD_B/U7_RX/QSPI_BK1_IO3/ADC3_INN4_INP8
PF7/TIM17_CH1/SPI5_SCK/SAI1_SAI4_MCLK_B/U7_TX/QSPI_BK1_IO2/ADC3_INP3
PF8/TIM16_CH1N/SPI5_MISO/SAI1_SAI4_SCK_B/U7_RTS/TIM13_CH1/QSPI_BK1_IO0/ADC3_INN3_INP7
PF9/TIM17_CH1N/SPI5_MOSI/SAI1_SAI4_FS_B/U7_CTS/TIM14_CH1/QSPI_BK1_IO1/ADC3_INP2
PF10/TIM16_BKIN/SAI1_SAI4_D3/QSPI_CLK/DCMI_D11/LCD_DE/ADC3_INN2_INP6
PF11/SPI5_MOSI/SAI2_SD_B/FMC_SDNRAS/DCMI_D12/ADC1_INP2
PF12/FMC_A6/ADC1_INN2_INP6
PF13/DFSDM_D6/I2C4_SMBA/FMC_A7/ADC2_INP2
PF14/DFSDM_CKIN6/I2C4_SCL/FMC_A8/ADC2_INN2_INP6
PF15/I2C4_SDA/FMC_A9
PG0/FMC_A10
PG1/FMC_A11/OPAMP2_VINM
PG2/TIM8_BKIN/TIM8_BKIN_COMP12/FMC_A12
PG3/TIM8_BKIN2/TIM8_BKIN2_COMP12/FMC_A13
PG4/TIM1_BKIN2/TIM1_BKIN2_COMP12/FMC_A14_BA0
PG5/TIM1_ETR/FMC_A15_BA1
PG6/TIM17_BKIN/HRTIM_CHE1/QSPI_BK1_NCS/FMC_NE3/DCMI_D12/LCD_R7
PG7/HRTIM_CHE2/SAI1_MCLK_A/U6_CK/FMC_INT/DCMI_D13/LCD_CLK
PG8/TIM8_ETR/SPI6_NSS/U6_RTS/SPDIFRX_IN2/ETH_PPS_OUT/FMC_SDCLK/LCD_G7
PG9/SPI1_MISO/I2S1_SDI/SPDIFRX_IN3/U6_RX/QSPI_BK2_IO2/SAI2_FS_B/FMC_NE2_NCE/DCMI_VSYNC
PG10/HRTIM_FLT5/SPI1_NSS/I2S1_WS/LCD_G3_B2/SAI2_SD_B/FMC_NE3/DCMI_D2
PG11/HRTIM_EEV4/SPI1_SCK/I2S1_CK/SPDIFRX_IN0/SDMMC2_D2/ETH_MII_RMII_TX_EN/DCMI_D3/LCD_B3
PG12/LPT1_IN1/HRTIM_EEV5/SPI6_MISO/U6_RTS/SPDIFRX_IN1/LCD_B4/ETH_MII_RMII_TXD1/FMC_NE4/LCD_B1
PG13/LPT1_OUT/HRTIM_EEV10/SPI6_SCK/U6_CTS/ETH_MII_RMII_TXD0/FMC_A24/LCD_R0
PG14/LPT1_ETR/SPI6_MOSI/U6_TX/QSPI_BK2_IO3/ETH_MII_RMII_TXD1/FMC_A25/LCD_B0
PG15/U6_CTS/FMC_SDNCAS/DCMI_D13
PH0/OSC_IN
PH1/OSC_OUT
PH2/LPTIM1_IN2/QSPI_BK2_IO0/SAI2_SCK_B/ETH_MII_CRS/FMC_SDCKE0/LCD_R0/ADC3_INP13
PH3/QSPI_BK2_IO1/SAI2_MCK_B/ETH_MII_COL/FMC_SDNE0/LCD_R1/ADC3_INN13_INP14
PH4/I2C2_SCL/LCD_G4_G5/OTG_HS_ULPI_NXT/ADC3_INN14_INP15
PH5/I2C2_SDA/SPI5_NSS/FMC_SDNWE/ADC3_INN15_INP16
PH6/TIM12_CH1/I2C2_SMBA/SPI5_SCK/ETH_MII_RXD2/FMC_SDNE1/DCMI_D8
PH7/I2C3_SCL/SPI5_MISO/ETH_MII_RXD3/FMC_SDCKE1/DCMI_D9
PH8/TIM5_ETR/I2C3_SDA/FMC_D16/DCMI_HSYNC/LCD_R2
PH9/I2C3_SMBA/TIM12_CH2/FMC_D17/DCMI_D0/LCD_R3
PH10/I2C4_SMBA/TIM5_CH1/FMC_D18/DCMI_D1/LCD_R4
PH11/I2C4_SCL/TIM5_CH2/FMC_D19/DCMI_D2/LCD_R5
PH12/I2C4_SDA/TIM5_CH3/FMC_D20/DCMI_D3/LCD_R6
PH13/TIM8_CH1N/U4_TX/FDCAN1_TX/FMC_D21/LCD_G2
PH14/TIM8_CH2N/U4_RX/FDCAN1_RX/FMC_D22/DCMI_D4/LCD_G3
PH15/TIM8_CH3N/FDCAN1_TXFD_MODE/FMC_D23/DCMI_D11/LCD_G4
PI0/TIM5_CH4/SPI2_NSS/I2S2_WS/FDCAN1_RXFD_MODE/FMC_D24/DCMI_D13/LCD_G5
PI1/TIM8_BKIN2/SPI2_SCK/I2S2_CK/TIM8_BKIN2_COMP12/FMC_D25/DCMI_D8/LCD_G6
PI2/TIM8_CH4/SPI2_MISO/I2S2_SDI/FMC_D26/DCMI_D9/LCD_G7
PI3/TIM8_ETR/SPI2_MOSI/I2S2_SDO/FMC_D27/DCMI_D10
PI4/TIM8_BKIN/SAI2_MCK_A/TIM8_BKIN_COMP12/FMC_NBL2/DCMI_D5/LCD_B4
PI5/TIM8_CH1/SAI2_SCK_A/FMC_NBL3/DCMI_VSYNC/LCD_B5
PI6/TIM8_CH2/SAI2_SD_A/FMC_D28/DCMI_D6/LCD_B6
PI7/TIM8_CH3/SAI2_FS_A/FMC_D29/DCMI_D7/LCD_B7
PI8/RTC_TAMP_2/RTC_TS/WKUP3
PI9/U4_RX/FDCAN1_RX/FMC_D30/LCD_VSYNC
PI10/FDCAN1_RXFD_MODE/ETH_MII_RX_ER/FMC_D31/LCD_HSYNC
PI11/LCD_G6/OTG_HS_ULPI_DIR/WKUP4

NRST
BOOT
BYPASS_REG
VBAT
VREF+
VCAP_1
VCAP_2
VDDA
VSSA
PDR_ON

31	RESET		
16	PF0	FMC_A0	
17	PF1	FMC_A1	
18	PF2	FMC_A2	
19	PF3	FMC_A3	
20	PF4	FMC_A4	
21	PF5	FMC_A5	
24	PF6	F_CS	
25	PF7	SPI5_SCK	
26	PF8	SPI5_MISO	
27	PF9	SPI5_MOSI	
28	PF10	LCD_DE	
59	PF11	FMC_SDNRAS	
60	PF12	FMC_A6	
63	PF13	FMC_A7	
64	PF14	FMC_A8	
65	PF15	FMC_A9	
166	BOOT0		
48			
6			
38	VREF+		
81			
125			
39	VDDA		
37			
171			
66	PG0	FMC_A10	
67	PG1	FMC_A11	
106	PG2	FMC_A12	
107	PG3	T_MISO	
108	PG4	FMC_BA0	
109	PG5	FMC_BA1	
110	PG6	LCD_R7	
111	PG7	LCD_CLK	
112	PG8	FMC_SDCLK	
152	PG9	FMC_NCE3	
153	PG10	NRF_CS	
154	PG11	LCD_B3	
155	PG12	NRF_CE	SPDIF_RX
156	PG13	RMII_TXD0	
157	PG14	RMII_TXD1	
160	PG15	FMC_SDNCAS	
29	OSC_IN		
30	OSC_OUT		
43	PH2	KEY1	
44	PH3	KEY0	
45	PH4	IIC_SCL	
46	PH5	IIC_SDA	
83	PH6	T_SCK	
84	PH7	T_PEN	
85	PH8	DCMI_HREF	
86	PH9	LCD_R3	
87	PH10	LCD_R4	
88	PH11	LCD_R5	
89	PH12	LCD_R6	
128	PH13	LCD_G2	
129	PH14	LCD_G3	
130	PH15	LCD_G4	
131	PI0	LCD_G5	
132	PI1	LCD_G6	
133	PI2	LCD_G7	
134	PI3	T_MOSI	
173	PI4	LCD_B4	
174	PI5	LCD_B5	
175	PI6	LCD_B6	
176	PI7	LCD_B7	
7	PI8	T_CS	
11	PI9	LCD_VSYNC	
12	PI10	LCD_HSYNC	
13	PI11	GBC_KEY	NRF_IRQ

D1 BAT54C

R1 10K C1 104 VBAT VCC3.3M

R2 10R VDDA

C2 225 C3 104 C5 225 C4 225 GND

C6 10uF C7 104 R3 10R VCC3.3M GND

R4 0R R5 0R VCC3.3M

R5,默认焊接
R4,不焊接
R2,不焊接

STM32F767\H743-IGT6

VSS VSS VSS VSS VSS VSS VSS VSS VSS VSS VSS
158 148 135 126 113 102 90 71 61 22 14
GND

VDD VDD VDD VDD VDD VDD VDD VDD VDD VDD VDD VDD
172 159 149 136 127 114 103 91 82 72 62 49 36 23 15
VCC3.3 VCC3.3M

VCC3.3 VCC3.3M
R9 0R
R10 0R
R9/R10是为了维修方便而增加的两个电阻
GND

C13 C14 C15 C16 C17 C18 C19 C20 C21 C22 C23 C24 C25 C26 C27
104 104 104 104 104 104 104 104 104 104 104 104 104 104 104
GND

R6 10K
RESET
RST
KEY_M
C12 104
GND

BOOT0 R7 100K
BOOT1 R8 100K
R8暂时不焊接
GND

Title			
Size A3	Number		Revision
Date: 3/13/2026		Sheet of	
File: C:\Users\..\STM32F429_CORE.SchDoc		Drawn By:	

Comment	Description	Designator	Footprint	LibRef	Quantity