



DPUGetPOIInfo

Provides information about POIs as the driver passes them.

1. Parameters:

<i>Family</i>	Family of the POIs to be considered.
<i>ArgumentName[1...15]</i>	Tokens of the arguments being stored when passing by a POI if the POI contains that argument.
<i>MaxDistance</i>	If the EGO-vehicle's position lies within a radius of <i>MaxDistance</i> meters around the POI it counts as 'passed'.
<i>NodeInstanceCounter</i>	Must be connected from SCNX.NodeInstanceCounter

2. Outputs:

<i>POI[10]X</i>	Global X-coordinate of all POIs outside the current route section.
<i>POI[10]Y</i>	Global Y-coordinate of all POIs outside the current route section.
<i>POI[10]Z</i>	Global Z-coordinate of all POIs outside the current route section.
<i>NearestPOIIndex</i>	Index of the POI being closest to the driver.
<i>NearestPOIDistance</i>	Distance of the POI being closest to the driver.
<i>Distance[1...10]</i>	The POIs' distances to the EGO-vehicle in meters.
<i>ArgumentValue[1...15]</i>	The value is stored via passing by a POI containing the argument with the name specified by <i>ArgumentName</i> .

3. Functional principle:

DPUGetPOI reads the data of up to 10 POIs from the database SCNX. Whenever the driver enters a new route node it is searched for new POIs. Their distances to the EGO-vehicle together with their global coordinates can be queried from the values *POI[i]X/Y/Z* and *Distance*.

The parameter *ArgumentName* defines the names of arguments which will be being provided at the outputs *ArgumentValue[1...15]* when the vehicle is located within a radius of *MaxDistance* meters around the POI. If the driver is closer than *MaxDistance* to multiple POIs, the values are sourced from the closest POI.

4. Example

The DPU works well using the following example:

```
DPUGetPOIInfo
{
    Computer = {SCN};
    Index = 100;
    Family = "Intersection";
```



SILAB DRIVING SIMULATION

version Version 7.1 documentation

```
        ArgumentName1 = "IntersectionID";  
};  
Connections = {  
    SCNX.NodeInstanceCounter -> <DPUGetPOIInfo>.NodeInstanceCounter  
};
```