

HX711 Dual-Channel Weighing Sensor Module



Overview

HX711 is an electronic scale module, whose working principle is to convert the measured changes in resistance value changes, through the conversion circuit into electrical output. The module communicates with the host computer through TTL 232.

Specification

- Differential input voltage: $\pm 40\text{mV}$ (Full-scale differential input voltage is $\pm 40\text{mV}$)
- Data accuracy: 24 bit (24 bit A / D converter chip.)
- Refresh frequency: 80 Hz
- Operating Voltage : 5V DC
- Operating current : $< 10\text{ mA}$
- Size: $38\text{mm} \times 21\text{mm} \times 10\text{mm}$