

TECHNICAL DATASHEET



The information contained in this document is subject to change.

10070

Anura Base Hub



SPECIFICATION.....	3
Power supply:.....	3
Typical Power consumption:.....	3
Cabinet material:.....	3
Ingress protection:.....	3
Typical weight:.....	3
Storage Temperature:.....	3
Relative humidity:.....	3
Mounting interface:.....	3
Incoming connections:.....	3
Outgoing connections:.....	4
Includes:.....	4
ACCESSORIES.....	4
Mounts:.....	4
Cables:.....	4
Expected product lifetime:.....	4
SERVICE.....	4
Warranty:.....	4
Support:.....	5
Contact:.....	5

SPECIFICATION

Power supply:

12VDC, 2.1x5.5x9.5mm DC Barrel Socket
Sold with MeanWell OWA-60E-12 (12VDC, 5A).

Typical Power consumption:

w.o. Transceivers connected.
7 W
with 4 transceivers connected
12W

Cabinet material:

Powder coated steel sheet.

Ingress protection:

IP65

Typical weight:

7.5kg

Dimensions: (excluding cables and mounting accessories.)

300x300x210 (height x width x depth)

Operating Temperature:

-20°C to +70°C

Storage Temperature:

-40°C to +80°C (-40°F to +140°F)

Relative humidity:

5% – 95% non-condensing

Mounting interface:

Sold with Wall mount (AX 2508.020) as default.
Optional: Pole clamp (AX 2584.100)

Incoming connections:

External LAN Connections 10/100/1000BASE-T Ethernet on CAT6

Outgoing connections:

4x cable grommets for ethernet connection to ReVibe[®](tm) Anura Transceivers or ReVibe[®](tm) Anura Extension hub.

Includes:

DIN-Rail mounted
Industrial PC (FitPC Fitlet3)
PoE network switch (Teltonika TSW101)

ACCESSORIES

Mounts:

Wall mount, (AX 2508.020)
Pole clamp (AX 2584.100)

Cables:

Ethernet RJ45-NEUTRIK EtherCON CAT6a 10m
Ethernet RJ45-NEUTRIK EtherCON CAT6a 30m

Expected product lifetime:

5 years

SERVICE

Warranty:

ReVibe represents and warrants that: (i) the products are free from defects resulting from faulty design or workmanship, (ii) the products are fit and safe for the intended purpose and use, which is known to ReVibe; and (iii) the product documentation is adequate and clear.

The responsibility of ReVibe under the warranties shall be limited to defects which occur during the warranty period or which can be satisfactorily demonstrated to have been in the products during the warranty period. Buyer shall promptly notify ReVibe of any defects in the Goods and ReVibe shall, at its discretion and without delay, repair or replace the defective products at ReVibe's cost.

ReVibe is not responsible under the warranties for defects caused by (i) a failure by Buyer to follow the instructions in the product documentation, (ii) modifications or alterations made to the products after the delivery without the prior consent of ReVibe, or (iii) materials or structures prescribed or provided by Buyer. Further, the ReVibe is not responsible under the warranties for normal wear and tear, nor misuse of the products.

Warranty is void if original components of the product are replaced with non-original components.

The warranty period shall be 24 months from the date of installation and commissioning, or 36 months from the date of the completed delivery of the products to Buyer, whichever is longer.

Notwithstanding the warranty period provided to Buyer as set out above, in the event of defective products repaired or replaced by Supplier, a new warranty period of 24 months shall commence on the date Buyer accepts the repaired or replaced products. The new warranty period is only intended for the replaced goods, not for any other goods delivered in the same shipments.

If Buyer has given notice of a defect product and no defect is found for which ReVibe is liable, ReVibe shall be entitled to compensation for reasonable and verifiable costs he incurs as a result of the notice.

If a defect in the products is such that Buyer decides it appropriate to carry out a product recall to repair or replace the defective products, Buyer shall promptly notify ReVibe. ReVibe shall at its own cost give such assistance to Buyer as is reasonably requested and pay for Buyer's expenses resulting from such product recall.

2 years from delivery date.

Revibe Energy replaces the unit with a non faulty unit. Customer pays for delivery to the ReVibe office in Sweden. ReVibe pays for delivery to customers.

For non faulty units, the customer pays for delivery both ways and a fault search fee.

Support:

Information on warranty coverage, support channels, and contact details for technical assistance can help users troubleshoot issues or seek further assistance when needed.

Contact:

Revibe Energy AB
Falkenbergsgatan 3
412 85 Göteborg
Sweden
+46 (0) 31 24 23 22
www.revibeenergy.com