THE MANUAL

THIS MANUAL WILL SAVE YOUR LIFE

Serial Number

- 1. SN.55-81-32-23
- 2. SN.44-21-23-4A
- 3. SN.15-94-23-85
- 4. SN.55-89-63-1B
- 5. SN.00-12-59-10
- 6. SN.98-63-12-9C
- 7. SN.15-00-22-43
- 8. SN.00-28-63-8A
- 9. SN.15-00-00-13
- 10. SN.98-00-12-9B
- 11. SN.44-21-23-85
- 12. SN.00-10-00-1C
- 13. SN.98-63-23-43
- 14. SN.11-10-00-4A
- 15. SN.45-67-89-00
- 16. SN.79-02-61-0B
- 17. SN.15-94-32-01
- 18. SN.00-12-12-0C
- 19. SN.19-48-45-45
- 20. SN.15-00-01-3A

Code 1:

• Press the Big Button once.

Code 3:

• Pull out com_capacitor1.

Code 4:

 Enter "101" and Switch on Switch Button 2 when the timer has 1 in it.

Code 6:

Pull out com_resistor2.

Code 9:

• Press the Big button twice.

Code 25:

- Pull out Fuse 2.
- Press the Big Button once with in 9 second.

Code 37:

- Cut the red wire.
- Press the Big button once and Switch on Switch Button 1.

Code 46:

- Pull out Battery 1.
- press the Big button four times.

Code 59:

- Pull out com_transistor_brown.
- Enter "173" and Turn off Switch Button 2 when the timer has 0 in it.

Code 78:

- Enter "0106" on the Keypad.
- Press the Big Button once.

Code 93:

- pull out com_transistor blue.
- Press the Big Button once with in 8 second.

Code 112:

- Pull out chip-main.
- Press the Big Button once.
- Cut the yellow wire.

Code 200:

- Press the Big Button twice.
- If the Serial Number ends with "A", pull out com_capacitor2. If not Enter "19101" in keypad
- Enter "01101" and Switch off Switch Button 1.

Code 375:

- Pull out Fuse 3.
- Cut the blue wire with in 5 second.
- Press the Big Button once.

Code 692:

- Enter "2547" on the Keypad.
- Pull out com_transistor_black.
- Press the Big Button once when the timer has 8 in it.

Code 823:

- Pull out chip-small.
- Enter "8462" on keypad
- "Press button once" and Switch on Switch Button 1.

Code 1124:

- Pull out Battery 2.
- Cut the pink wire when the timer has 5 in it.
- Press the Big Button twice.
- Enter "458" Turn off Switch Button 2.

Code 3333:

- Button 1 and Enter "5322" on the Keypad.
- If the Serial Number end with "B", pull out Fuse 1.If not, Press button twice and turn off Switch.
- Cut the green wire with in 4 second.
- Enter "2235" on the Keypad.
- Press the Big Button once.

Code 5423:

- Pull out com_capacitor3.
- Enter "2345" and Switch on Switch Button 1.
- Cut the yellow wire.
- Press the Big Button once.

Code 6584:

- Enter "2580" on the Keypad.
- Pull out chip-big with in 5 second.
- Enter "1" and Turn off Switch Button 1.
- Press the Big Button twice.

Code 8796:

- Pull out com_resistor1.
- Press the Big Button three times.
- Cut the red wire when the timer has 2 in it.
- Press the big button four times and Switch off Switch Button 2.