

# **THE MANUAL**

---

**THIS MANUAL WILL SAVE YOUR LIFE**

# Serial Number

1. SN.55-81-32-23
2. SN.44-21-23-4A
3. SN.15-94-23-85
4. SN.55-89-63-1B
5. SN.00-12-59-10
6. SN.98-63-12-9C
7. SN.15-00-22-43
8. SN.00-28-63-8A
9. SN.15-00-00-13
10. SN.98-00-12-9B
11. SN.44-21-23-85
12. SN.00-10-00-1C
13. SN.98-63-23-43
14. SN.11-10-00-4A
15. SN.45-67-89-00
16. SN.79-02-61-0B
17. SN.15-94-32-01
18. SN.00-12-12-0C
19. SN.19-48-45-45
20. SN.15-00-01-3A

**Code 1:**

- Press the Big Button once.

**Code 3:**

- Pull out com\_capacitor1.

**Code 4:**

- Switch off Switch Button 2 when the timer has 1 in it.

**Code 6:**

- Pull out com\_resistor2.

**Code 9:**

- If PASS status has 3 green lights, press the Big Button once. if not press the Big button twice.

**Code 25:**

- Pull out Fuse 2.
- Press the Big Button once with in 9 second.

**Code 37:**

- Cut the red wire.
- Switch on Switch Button 1.

**Code 46:**

- Pull out Battery 1.
- If the Strike status has 1 red light, press the Big Button twice. If not, press the Big button forth.

**Code 59:**

- Pull out com\_transistor\_brown.
- Turn off Switch Button 2 when the timer has 0 in it.

**Code 78:**

- Enter "0106" on the Keypad.
- Press the Big Button once.

**Code 93:**

- If the Serial Number ends with "C", pull out com\_transistor blue. If not, turn on Switch Button 1.
- Press the Big Button once with in 8 second.

**Code 112:**

- Pull out chip-main.
- Press the Big Button once.
- Cut the yellow wire.

**Code 200:**

- If the Serial Number ends with "A", pull out com\_capacitor2. If not Enter "19101" in keypad
- Press the Big Button twice.
- Switch off Switch Button 1.

**Code 375:**

- Pull out Fuse 3.
- Cut the blue wire with in 5 second.
- Press the Big Button once.

**Code 692:**

- Enter "2547" on the Keypad.
- Pull out com\_transistor\_black.
- Press the Big Button once when the timer has 8 in it.

**Code 823:**

- If PASS status has 4 green lights, press the Big Button once. If not Enter "8462" and press the Big button three times
- Pull out chip-small.
- Switch on Switch Button 1.

**Code 1124:**

- Pull out Battery 2.
- Cut the pink wire when the timer has 5 in it.
- Press the Big Button twice.
- Turn off Switch Button 2.

**Code 3333:**

- If the Serial Number starts with "B", pull out Fuse 1.If not, turn off Switch Button 1 and Enter "5322" on the Keypad.
- Cut the green wire with in 4 second.
- Enter "2235" on the Keypad.
- Press the Big Button once.

**Code 5423:**

- Pull out com\_capacitor3.
- Switch on Switch Button 1.
- Cut the yellow wire.
- Press the Big Button once.

**Code 6584:**

- Enter "2580" on the Keypad.
- Pull out chip-big with in 5 second.
- Turn off Switch Button 1.
- Press the Big Button twice.

**Code 8796:**

- Pull out com\_resistor1.
- Press the Big Button three times.
- Cut the red wire when the timer has 2 in it.
- Switch off Switch Button 2.