

# 11. Setup & Preferences

## Setup

There are a number of system setup options available on the Stage CL. These options include autosave, network, audio, screen brightness, and date settings. To set these options, touch the Setup button on the Home screen. Stage CL displays the Setup window:

Setup	Preferences	About
Item	Value	
Autosave Interval	5 minutes	
Networked DMX	Off	
Art-Net Sub-Net	0	
Art-Net Universe	0	
sACN Universe	1	
sACN Priority	100	
Network Configuration	DHCP	

To adjust a setting:

1. Use the touchscreen dial to scroll to the field you want to adjust
2. Push the dial button down to select the field.
3. Use the touchscreen dial to set a new value.

This item...	does this...
Autosave Interval	Sets the time before Stage CL saves the current show file. Set to Off if you don't want to save automatically
Networked DMX	Turns DMX output over Ethernet off or on. The options are Off, Artnet Broadcast or Streaming ACN (sACN)
Artnet Sub-Net	Sets the Artnet Sub-Net (a group of 16 consecutive universes). For universes 1-16 set this field to 0
Artnet Universe	Sets the Artnet Universe (a group of 512 channels). For universes 1 set this field to 0
sACN Universe	Sets the sACN universe. Valid universes are 1 to 63999
sACN Priority	Sets the Artnet Priority. Valid settings range from 0 to 200, with higher numbers representing a higher priority.