from MSB-A Q-R1 (sh 1)

from MSB-A Q-R2 (sh 1)

BTS 3 200 A from Q-SB (sh 1)

from MSB-A Q-MB (sh 1)

UPS-A1
1 000 kW · VFI-SS-111
LFP 165 kWh (5 min EoL)

Q-O1
ACB 1 600 A

UPS-A2
1 000 kW · VFI-SS-111
LFP 165 kWh (5 min EoL)

Q-O2
ACB 1 600 A

SBS-A
3 200 A static bypass

Q-SBO
ACB 3 200 A

Q-MBB
ACB 3 200 A
maint. bypass

UPS output bus 3 200 A

Q-UO
ACB 3 200 A

IL-4 key interlock: Q-UO / Q-MBB
(one key, never both closed)

UOSB-A 3 200 A · Icw 65 kA 1 s

49.3 kA

MCCB BW-A1
800 A, Icu ≥ 50 kA
current-limiting

busway 800 A, Icw 36 kA
cond. ≥ 40 kA (IEC 61439-6)

37.1 kA

MCCB BW-A2
busway 800 A
as BW-A1

MCCB BW-A3
busway 800 A
as BW-A1

MCCB BW-A4
busway 800 A
as BW-A1

MCCB BW-A5
busway 800 A
as BW-A1

MCCB BW-A6
busway 800 A
as BW-A1

SPD T2

tap-off 63 A MCCB
Icu ≥ 36 kA
25.1 kA

B-cord from BW-B1 (block B)

PDU-A

PDU-B

14.0 kA · PDU SCCR ≥ 15 kA

rack: 2 PSUs, each 100 %

EQUIPMENT SCHEDULE

Item	Rating (Rev P2)	Basis
UPS-A1/A2	1 000 kW each, VFI-SS-111	N-1 83 %
Battery	LFP 165 kWh per module, ≤ 8 C EoL	B1
Rectifier breaker	Q-R1/Q-R2 2 000 A (1 660 A max)	B2
SBS / MBB	3 200 A, BTS 3 200 A from MSB	B4
Busway MCCB	800 A, Icu ≥ 50 kA, cond. ≥ 40 kA	B3, B15
Tap-off / PDU	63 A Icu ≥ 36 kA; SCCR ≥ 15 kA	B16

NOTES
1. Fault levels in boxes: I″k per CALC-003.
2. SBS is centralised per block; MBB is external wrap-around (IL-4).
3. A2…A6 identical to BW-A1; pairing per SLD-002 sh 2.

P2	2026-10-25	CALC-002/3/4 ratings, IEC symbols, ≥2.5 mm text
P1	2026-10-24	First concept issue

Nordic Hyperscale DC Campus (fictional) · 30 MW IT · SE3
Portfolio D. Wu · public standards and [ASSUMED] data only

Power block A — sheet 2
UPS-A1/A2, SBS, MBB, UOSB-A, busway to rack (typical)
CONCEPT · NOT FOR CONSTRUCTION · scale NTS · A3

Drawing no.	Sheet	Rev
DWU-DC-E-SLD-003	**2 / 2**	**P2**