



A76XX Series_SMTPS _Application Note

LTE Module

SIMCom Wireless Solutions Limited

SIMCom Headquarters Building, Building 3, No. 289 Linhong
Road, Changning District, Shanghai P.R.China

Tel: 86-21-31575100

support@simcom.com

www.simcom.com

Document Title:	A76XX Series_SMTSPS_Application Note
Version:	1.00
Date:	2022.08.03

GENERAL NOTES

SIMCOM OFFERS THIS INFORMATION AS A SERVICE TO ITS CUSTOMERS, TO SUPPORT APPLICATION AND ENGINEERING EFFORTS THAT USE THE PRODUCTS DESIGNED BY SIMCOM. THE INFORMATION PROVIDED IS BASED UPON REQUIREMENTS SPECIFICALLY PROVIDED TO SIMCOM BY THE CUSTOMERS. SIMCOM HAS NOT UNDERTAKEN ANY INDEPENDENT SEARCH FOR ADDITIONAL RELEVANT INFORMATION, INCLUDING ANY INFORMATION THAT MAY BE IN THE CUSTOMER'S POSSESSION. FURTHERMORE, SYSTEM VALIDATION OF THIS PRODUCT DESIGNED BY SIMCOM WITHIN A LARGER ELECTRONIC SYSTEM REMAINS THE RESPONSIBILITY OF THE CUSTOMER OR THE CUSTOMER'S SYSTEM INTEGRATOR. ALL SPECIFICATIONS SUPPLIED HEREIN ARE SUBJECT TO CHANGE.

COPYRIGHT

THIS DOCUMENT CONTAINS PROPRIETARY TECHNICAL INFORMATION WHICH IS THE PROPERTY OF SIMCOM WIRELESS SOLUTIONS LIMITED. COPYING, TO OTHERS AND USING THIS DOCUMENT, ARE FORBIDDEN WITHOUT EXPRESS AUTHORITY BY SIMCOM. OFFENDERS ARE LIABLE TO THE PAYMENT OF INDEMNIFICATIONS. ALL RIGHTS RESERVED BY SIMCOM IN THE PROPRIETARY TECHNICAL INFORMATION, INCLUDING BUT NOT LIMITED TO REGISTRATION GRANTING OF A PATENT, A UTILITY MODEL OR DESIGN. ALL SPECIFICATION SUPPLIED HEREIN ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.

SIMCom Wireless Solutions Limited

SIMCom Headquarters Building, Building 3, No. 289 Linhong Road, Changning District, Shanghai P.R. China

Tel: +86 21 31575100

Email: simcom@simcom.com

For more information, please visit:

<https://www.simcom.com/download/list-863-en.html>

For technical support, or to report documentation errors, please visit:

<https://www.simcom.com/ask/> or email to: support@simcom.com

Copyright © 2022 SIMCom Wireless Solutions Limited All Rights Reserved.

About Document

Version History

Version	Date	Owner	What is new
V1.00	2020.06.19	Yonghang,qin	New version

Scope

Based on module AT command manual, this document will introduce SMTPS application process. Developers could understand and develop application quickly and efficiently based on this document. This document applies to A1603 Series ,A1601 Series, A1803S Series, A1802 Series.

SIMCom
Confidential

Contents

About Document	2
Version History	2
Scope	3
Contents	4
1 Introduction	5
1.1 Purpose of the document	5
1.2 Related documents	5
1.3 Conventions and abbreviations	5
2 AT Commands for SMTPS	6
2.1 Overview of AT Commands for SMTPS	6
3 SMTPS Examples	7
3.1 Send e-mail	7
4 Appendix	9
4.1 Result codes	9

1 Introduction

1.1 Purpose of the document

Based on module AT command manual, this document will introduce SMTPS application process. Developers could understand and develop application quickly and efficiently based on this document.

1.2 Related documents

[1] A76XX Series SMTPS_AT Command Manual

1.3 Conventions and abbreviations

PDP Packet Data Protocol;
URC Unsolicited result codes;

2 AT Commands for SMTPS

2.1 Overview of AT Commands for SMTPS

Command	Description
AT+CSMTSPSCFG	Configure the SMTP context
AT+CSMT PSSRV	Set SMTP server address and port number
AT+CSMTPSAUTH	SMTP server authentication
AT+CSMTPSFROM	Sender address and name
AT+CSMTPSRCPT	Recipient address and name (TO/CC/BCC)
AT+CSMT PSSUB	E-mail subject
AT+CSMTPSBODY	E-mail body
AT+CSMTPSBCH	E-mail body character set
AT+CSMTPSFILE	Select attachment
AT+CSMT PSSEND	Initiate session and send e-mail
AT+CSMT PSSTOP	Force to stop sending e-mail
AT+CSMT PSCLEAN	Clean mail content and setting

NOTE

Currently, only ASR1603 and ASR1803S support SMTPS.

3 SMTPS Examples

Before all SMTPS related operations, we should ensure the following:
Ensure GPRS network is available:

AT+CSQ

+CSQ: 23,0

OK

AT+CREG?

+CREG: 0,1

OK

AT+CGREG?

+CGREG: 0,1

OK

3.1 Send e-mail

Following commands shows how to send e-mail.

AT+CSMTPSSRV="smtp.exmail.qq.com",465,2 //Set the server's host and port

OK

**AT+CSMTPSAUTH=1,"owner@simcom.com",
"password"** //Set the username and password

OK

**AT+CSMTPSFROM="owner@simcom.com",
owner"** //Set the sender

OK

**AT+CSMTPSRCPT=0,0,"owner@simcom.com",
",owner"** //Set the receiver

OK

AT+CSMTPSSUB=2 //Set the subject

>12

OK

AT+CSMTPSBODY=2

//Set the body

>12

OK

AT+CSMTPSEND

//Send e-mail

OK

+CSMTPSEND: 0

SIMCom
Confidential

4 Appendix

4.1 Result codes

Result codes	Meaning
0	SMTSPS operation succeeded
600	Busy
601	Network error
602	Socket error
603	Over size
604	Duplicate file
605	Time out
606	Transfer failed
607	Memory error
608	Invalid parameter
609	EFS error
610	SMTP server error
611	Authentication failure
612	User cancel
655	Unknown error