Schedule LS-2 AD

LIGHTING - STREET AND HIGHWAY - CUSTOMER-OWNED ANCILLARY DEVICE INSTALLATIONS

APPLICABILITY

Applicable for street lighting service in conjunction with a utility approved metering control module and open to governmental agencies and lighting districts for the use of ancillary devices atop street light poles, located on highways and other thoroughfares, and available to other corporate agencies for ancillary devices located on street light poles on non-dedicated streets which are accessible to the public, where the Customer owns the entire installation, including underground lines from a central point of connection with utility facilities.

Customers eligible for this schedule are not eligible for Net Energy Metering(NEM) or any variation of Net Energy Metering or Virtual Net Metering (VNM).

Effective discounts or credits for California Alternative Rate for Energy (CARE) and Local Government Renewable Energy Self-Generation Bill Credit Transfer (RES-BCT) do not apply to service under Schedule LS-2 AD.

Only ancillary devices typically allowed for attachment to street light poles, e.g., cell phone repeaters, security cameras, etc., are eligible for this schedule and actual street light load is not to be captured under this schedule. Please refer to Schedule LS-2 DS for street lights.

Small Business Customers, as defined in Rule 1 and not identified by the California Air Resources Board as Emission Intensive, Trade-Exposed Entities (EITE), qualify for a semi-annual California Climate Credit of $(49.36), which will display as a separate line item per schedule GHG-ARR.

TERRITORY

Within the entire territory served by the Utility.

(Continued)

Schedule LS-2 AD

LIGHTING - STREET AND HIGHWAY - CUSTOMER-OWNED ANCILLARY DEVICE INSTALLATIONS

RATES

Distribution Rates: ($/Month)

Description- LS-2 AD	Base Distribution Rate	Implementation Cost Distribution Rate	O&M Cost Distribution Rate	Total Distribution Rate	UDC Total
Monthly Service Fee ($/Month)	3.18	0.10	0.45	3.73	3.73

Description – LS-2AD	Transm	Distr	PPP	ND	CTC	LGC	RS	TRAC	UDC Total
Energy Charges ($/kWh)									
Summer									
On-Peak Energy	0.04366	0.10081 I	0.02000	0.00000	(0.00007)	0.00864	0.00005	0.00000	0.17309 I
Off-Peak Energy	0.04366	0.10081 I	0.02000	0.00000	(0.00007)	0.00864	0.00005	0.00000	0.17309 I
Super Off-Peak Energy	0.04366	0.10081 I	0.02000	0.00000	(0.00007)	0.00864	0.00005	0.00000	0.17309 I
Winter									
On-Peak Energy	0.04366	0.10081 I	0.02000	0.00000	(0.00007)	0.00864	0.00005	0.00000	0.17309 I
Off-Peak Energy	0.04366	0.10081 I	0.02000	0.00000	(0.00007)	0.00864	0.00005	0.00000	0.17309 I
Super Off-Peak Energy	0.04366	0.10081 I	0.02000	0.00000	(0.00007)	0.00864	0.00005	0.00000	0.17309 I
Minimum Bill ($/day)									

Notes: Transmission Energy charges include the Transmission Revenue Balancing Account Adjustment (TRBAA) of $(0.00304) per kWh and the Transmission Access Charge Balancing Account Adjustment (TACBAA) of $(0.00993) per kWh. PPP Energy charges include Low Income PPP rate (LI-PPP) $0.00000/kWh, and Non-low Income PPP rate (Non-LI-PPP) $0.00192/kWh.

Rate Components

The Total Distribution Rates ($/Month) shown above are comprised of the following distribution components: (1) Base Distribution Rate; (2) Implementation Cost Distribution Rate; and (3) O&M Cost Distribution Rate.

The Utility Distribution Company Total Rates (UDC Total) shown above are comprised of the following components (if applicable): (1) Transmission (Trans) Charges, (2) Distribution (Distr) Charges, (3) Public Purpose Program (PPP) Charges, (4) Nuclear Decommissioning (ND) Charge, (5) Ongoing Competition Transition Charges (CTC), (6) Local Generation Charge (LGC), (7) Reliability Services (RS), and (8) the Total Rate Adjustment Component (TRAC) Utility Distribution Company (UDC) Total Rate shown above excludes any applicable commodity charges associated with Schedule EECC, Schedule DWR-BC (Department of Water Resources Bond Charge and Schedule WF-NBC (Wildfire Fund Non-Bypassable Charge).

(Continued)

Schedule LS-2 AD

LIGHTING - STREET AND HIGHWAY - CUSTOMER-OWNED ANCILLARY DEVICE INSTALLATIONS

Franchise Fee Differential

A Franchise Fee Differential of 5.78% shall be applied to the monthly billings calculated under this schedule for all customers within the corporate limits of the City of San Diego. Such Franchise Fee Differential shall be so indicated and added as a separate item to bills rendered to such customers.

Time Periods

All Time periods listed are applicable to local time

TOU Period	Weekdays		Weekends and Holidays	
	Summer	Winter	Summer	Winter
On-Peak	4 PM – 9 PM	4 PM – 9 PM	4 PM – 9 PM	4 PM – 9 PM
Off-Peak	All other hours	All other hours	All other hours	All other hours
Super Off-Peak	Midnight – 6AM; 10 AM – 2 PM	Midnight – 6AM; 10 AM – 2 PM	Midnight – 2 PM	Midnight – 2 PM

T

T

Seasons: Summer June 1 - October 31
Winter November 1 – May 31

(Continued)

Schedule LS-2 AD

LIGHTING - STREET AND HIGHWAY - CUSTOMER-OWNED ANCILLARY DEVICE INSTALLATIONS

SPECIAL CONDITIONS: N

1. Relocation of Facilities: Relocation of Utility's Facilities at the Customer's request or because of governmental requirements shall be made providing the Customer pays the actual costs incurred by the utility for such relocation.
2. Shut-off for Non-Payment: If a Customer's ancillary devices are shut off due to non-payment of the monthly energy bill, the Customer shall be subject to a turn-on fee of $10.00 per device, with a minimum charge of $50.00. This fee is in addition to the Service Re-Establishment Fee and normal credit deposits.
3. Ancillary Device Service Requirements: To be eligible for service under this schedule, the installation must include a control device (herein referred to as "node") that is approved by the Utility for the specific purpose of revenue-grade metering applications. The node must comply with the Utility's metering specifications. Additionally, customers electing to take service under this schedule must provide and accept the following:
    a. Data Send/Receive: Consumption data, defined as register reads and/or intervals, must be sent to the Utility no later than 3 a.m. the day following the recorded usage. If data is received later than this time, the Utility shall estimate consumption to fill in the missing data as described in 3(d) below.
    b. Initial Ancillary Device Inventory Setup/Establishment: Customer shall submit to the Utility inventory data that consists of Customer control module identification and required meter inventory information. This includes, but is not limited to, meter accuracy testing results and node manufacturing information. The required fields and their format are subject to change by the Utility.
    c. Ancillary Device Inventory: Inventory data fields and format are determined by the Utility's Street Light Billing and are subject to change as systems often evolve. Fields and format must be sent for proper billing account establishment. Required fields include, but are not limited to, the location of the ancillary devices and their associated meter attributes. If data does not conform to the Utility requirements, the Utility may reject the data and delay account establishment until data is corrected. N

(Continued)

Schedule LS-2 AD

LIGHTING - STREET AND HIGHWAY - CUSTOMER-OWNED ANCILLARY DEVICE INSTALLATIONS

SPECIAL CONDITIONS (Continued)

d. Missing, erroneous or otherwise unusable Usage Data: If Customer data is not received, is wholly or in part missing, erroneous, or is unusable, the Utility shall estimate usage in a manner consistent with its applicable tariff rules and shall not perform any corrective billing for missing or unusable data. D, N

e. Control Module/Node Hardware: Only metering control modules/nodes and associated hardware that have been tested and approved by the Utility can be used under this schedule. If a node is changed out or replaced with a newer version, the newer version must be tested by the Utility before it is installed to ensure the new node complies with Utility meter specifications.

f. Node Manufacturer: Prior to installing an approved node, the node manufacturer must perform an accuracy test and provide results of that test to the Utility.

g. Data Requests/Random Sampling: All meters/nodes under this schedule are subject to data request in full or by random sample. Requests for data or random sample must be complied with and any excessive costs for such work shall be mutually agreed upon and paid by the Customer.

h. Node Management: Customers under this rate schedule assume full responsibility for the accurate and timely submission of nodes installed under this rate schedule. The Utility is not responsible for billing on an existing rate should Customer or third party fail to notify the Utility of meter/node changes subject to this rate.

i. Release of Liability: By installing any devices under this schedule, Customer releases the Utility of any liability associated with any damages or claims that result from the use of such devices. It is the Customer's sole responsibility to ensure installations are safe and properly maintained.

4. Billing Process: The following billing process shall be used for this schedule.

   a. Electronic Data Interface (EDI) is the preferred billing mechanism.
   b. Non-EDI customers shall be billed using summary billing.
   c. The bill shall be comprised of one bill account per pole (one or more streetlights or devices on a single pole location) with limited exceptions and only as approved by the Utility.
   d. The Utility shall bill all devices under the applicable unmetered schedule until notice that a node has been installed, has been received.
   e. Nodes temporarily or permanently removed are subject to billing using estimated consumption under Section 4.d. above until the Utility is advised of removal.
   f. New install, shall be billed as described in Section 4.d. until Customer provides the inventory information as outlined in Section 4.b above.

(Continued)

Schedule LS-2 AD

LIGHTING - STREET AND HIGHWAY - CUSTOMER-OWNED ANCILLARY DEVICE INSTALLATIONS

SPECIAL CONDITIONS (CONTINUED) N

5. Transitional Period: Customer has 60 days from the time of rate transition to switch to a different rate, otherwise Customer is subject to Rule 12 for any changes in rate schedule. If Customer elects to change the rate before the end of the transitional period, Customer must communicate that to the Utility through e-mail or other mutually agreed upon method.

6. Adaptive Controlled Pilot Program Termination: This tariff replaces the Adaptive Controlled Streetlight Pilot Program approved in AL 2883-E. The pilot is terminated when this tariff takes effect.

7. Node Mandatory Data Send Requirement: If Customer installs a node that is registering electricity consumption, Customer is required to establish service under an applicable rate. If a node is installed and notification is not provided, the Utility reserves the right to disconnect devices and invoice Customer for any associated labor.

8. Definitions:

   a. Node: A node is the device that enables an ancillary device to be remotely controlled and monitored. The node is also referred to as a control module in this and other documents.

   b. Consumption Data: Device register reads and/or interval-level electricity usage that captures both the streetlight load and control module load.

   c. Inventory Data: Records that clearly identify which device numbers correspond to which nodes. This data is used for account maintenance functions. N

   d. Connected Devices: Those remote controlled devices typically allowed by the customer for service or security reasons, e.g., cell phone repeaters, security cameras, etc.

(Continued)