

1 Quantities

- $J \in \mathbb{Z}^+ =$ number of scales decomposition
- $T = 2^J =$ number of time periods
- $N \in \mathbb{Z}^+ =$ number of cross-section elements
- $K(\leq N) =$ number of common factors

2 Multivariate Locally Stationary Wavelet process (Park et al. (2014))

The vector $(N \times 1)$ of stochastic processes $\mathbf{X}_{t;T}$ follows the given decomposition :

$$\mathbf{X}_{t;T} = \sum_{j=-J}^{-1} \sum_{k=0}^T \mathbf{W}_j(k/T) \boldsymbol{\xi}_{j,k} \psi_{j,k}(t) \quad (2.1)$$

where

- $\mathbf{W}_j(z)$ is a lower-triangular $(N \times N)$ matrix.
For each (m, n) -element,

$$W_j^{(m,n)}(z) \text{ is a Lipschitz continuous function on } z \in (0, 1) \quad (2.2)$$

$$\sum_{j=-\infty}^{-1} \left| W_j^{(m,n)}(z) \right|^2 < \infty, \quad \forall z \in (0, 1) \quad (\text{finite energy}) \quad (2.3)$$

$$\sum_{j=-\infty}^{-1} 2^{-j} L_j^{(m,n)} < \infty \quad (\text{uniformly bounded Lipschitz constants } L_j) \quad (2.4)$$

- $\boldsymbol{\xi}_{j,k}$ is the vector $(N \times 1)$ of random orthonormal increments.

$$\mathbb{E} \left[\boldsymbol{\xi}_{j,k}^{(u)} \right] = 0, \quad \forall j, k, u \quad (2.5)$$

$$\text{Cov} \left[\boldsymbol{\xi}_{j,k}^{(u)}, \boldsymbol{\xi}_{j',k'}^{(u')} \right] = \delta_{j,j'} \delta_{k,k'} \delta_{u,u'}, \quad \forall j, j', k, k', u, u' \quad (2.6)$$

- $\psi_{j,k}(t) = \psi_{j,k-t}$ is a scalar representing a non-decimated wavelet.

We can define the *Cross-Evolutionary Wavelet Spectrum* $(N \times N)$ matrix : $\mathbf{S}_j(z) = \mathbf{W}_j(z) \mathbf{W}_j(z)'$. This gives us the ability to express the *local autocovariance* : $c^{(u,u')}(z, \tau) = \sum_{j=-\infty}^{-1} S_j^{(u,u')}(z) \boldsymbol{\Psi}_j(\tau)$ where $\boldsymbol{\Psi}_j(\tau) = \sum_k \psi_{j,k}(0) \psi_{j,k}(\tau)$, the *autocorrelation wavelet*. The latter also define the *inner product matrix of discrete autocorrelation wavelets* : $A_{jl} = \sum_{\tau} \boldsymbol{\Psi}_j(\tau) \boldsymbol{\Psi}_l(\tau)$, $A = \{A_{jl}\}_{j,l \in \mathbb{N}}$ and its inverse : $\bar{A} = A^{-1}$.

2.1 Estimation of MvLSW

- $\mathbf{d}_{j,k} = \sum_{t=0}^{T-1} \mathbf{X}_t \psi_{j,k}(t)$ (empirical wavelet coefficients)

- $\mathbf{I}_{j,k} = \mathbf{d}_{j,k} \mathbf{d}_{j,k}'$ (raw wavelet periodogram)

$$- \mathbb{E}[\mathbf{I}_{j,k}] = \sum_{l=-J}^{-1} A_{jl} \mathbf{S}_l(k/T) + O(T^{-1}) \quad (\text{biased estimator})$$

- $\bar{\mathbf{I}}_{j,k} = \sum_{l=-J}^{-1} \bar{A}_{j,l} \mathbf{I}_{l,k}$ (corrected periodogram) \Rightarrow (unbiased estimator)

- $\tilde{\mathbf{I}}_{j,k} = \frac{1}{2M+1} \sum_{m=-M}^M \mathbf{I}_{j,k+m}$ (smooth periodogram) \Rightarrow (consistent estimator)

- $\hat{\mathbf{S}}_j(k/T) = \sum_{l=-J}^{-1} \bar{A}_{j,l} \tilde{\mathbf{I}}_{l,k} = \frac{1}{2M+1} \sum_{m=-M}^M \bar{\mathbf{I}}_{j,k+m} = \frac{1}{2M+1} \sum_{m=-M}^M \sum_{l=-J}^{-1} \bar{A}_{j,l} \mathbf{I}_{l,k+m}$ (final estimator of CEWS)

2.2 Notes

- The dependence structure is entirely in $\mathbf{W}_j(z)$, not in $\boldsymbol{\xi}_{j,k}$.
- The lower-triangular form of $\mathbf{W}_j(z)$ allows us to use the Cholesky decomposition on $\mathbf{S}_j(z)$.

3 Factor Model

- The factor structure is imposed on the following :

$$\mathbf{W}_j(k/T) \boldsymbol{\xi}_{j,k} = \boldsymbol{\Lambda}_{j,k} \mathbf{F}_k + \boldsymbol{\epsilon}_{j,k} \quad (3.1)$$

, not only on $\boldsymbol{\xi}_{j,k}$ since they are assumed orthonormal.

- Assumptions :

1. $\mathbf{F}_k \sim (\mathbf{0}, \boldsymbol{\Sigma}_F)$, where $\boldsymbol{\Sigma}_F$ is a diagonal positive definite $(K \times K)$ matrix.
2. $\mathbf{F}_k \perp \boldsymbol{\epsilon}_{j,k'}, \forall j, k, k'$
3. $\boldsymbol{\epsilon}_{j,k} \sim (\mathbf{0}, \boldsymbol{\Sigma}_\epsilon)$, where $\boldsymbol{\Sigma}_\epsilon$ has bounded eigenvalues. **Note : make $\boldsymbol{\Sigma}_\epsilon$ dependent on time ? what about serial dependence ?**

- We can then represent the CEWS with the factor structure :

$$\begin{aligned} \text{Var}[\mathbf{W}_j(k/T) \boldsymbol{\xi}_{j,k}] &= \text{Var}[\boldsymbol{\Lambda}_{j,k} \mathbf{F}_k] + \text{Var}[\boldsymbol{\epsilon}_{j,k}] \\ \mathbf{W}_j(k/T) \text{Var}[\boldsymbol{\xi}_{j,k}] \mathbf{W}_j(k/T)' &= \boldsymbol{\Lambda}_{j,k} \text{Var}[\mathbf{F}_k] \boldsymbol{\Lambda}_{j,k}' + \text{Var}[\boldsymbol{\epsilon}_{j,k}] \\ \mathbf{W}_j(k/T) \mathbf{W}_j(k/T)' &= \boldsymbol{\Lambda}_{j,k} \boldsymbol{\Sigma}_F \boldsymbol{\Lambda}_{j,k}' + \boldsymbol{\Sigma}_\epsilon \\ \mathbf{S}_j(k/T) &= \boldsymbol{\Lambda}_{j,k} \boldsymbol{\Sigma}_F \boldsymbol{\Lambda}_{j,k}' + \boldsymbol{\Sigma}_\epsilon \end{aligned} \quad \text{from (2.6)}$$

An important quantity to analyse is :

$$\mathbf{W}_j(k/T) \boldsymbol{\xi}_{j,k} \boldsymbol{\xi}_{j',k'}' \mathbf{W}_{j'}(k'/T)' = \boldsymbol{\Lambda}_{j,k} \mathbf{F}_k \mathbf{F}_{k'}' \boldsymbol{\Lambda}_{j',k'}' + \boldsymbol{\epsilon}_{j,k} \mathbf{F}_{k'}' \boldsymbol{\Lambda}_{j',k'}' + \boldsymbol{\Lambda}_{j,k} \mathbf{F}_k \boldsymbol{\epsilon}_{j',k'}' + \boldsymbol{\epsilon}_{j,k} \boldsymbol{\epsilon}_{j',k'}'$$

3.1 Estimation

The estimation of the loadings and common factors is carried out by a non-linear least square procedure in the wavelet domain.

$$\begin{aligned} \min_{\boldsymbol{\Lambda}_{j,k}, \bar{\mathbf{F}}_k} \quad & (NT)^{-1} \sum_t \left[\mathbf{X}_{t;T} - \sum_{j=-J}^{-1} \sum_{k=0}^T (\bar{\boldsymbol{\Lambda}}_{j,k} \bar{\mathbf{F}}_k) \psi_{j,k}(t) \right]' \left[\mathbf{X}_{t;T} - \sum_{j=-J}^{-1} \sum_{k=0}^T (\bar{\boldsymbol{\Lambda}}_{j,k} \bar{\mathbf{F}}_k) \psi_{j,k}(t) \right] \\ \text{s.t.} \quad & \frac{\bar{\boldsymbol{\Lambda}}_{j,k}' \bar{\boldsymbol{\Lambda}}_{j,k}}{N} = \mathbf{I}_K \end{aligned} \quad (3.2)$$

After distributing the objective function becomes,

$$\begin{aligned} (NT)^{-1} \sum_t \left[\mathbf{X}_{t;T}' \mathbf{X}_{t;T} - \mathbf{X}_{t;T}' \sum_{j=-J}^{-1} \sum_{k=0}^T \bar{\boldsymbol{\Lambda}}_{j,k} \bar{\mathbf{F}}_k \psi_{j,k}(t) - \sum_{j=-J}^{-1} \sum_{k=0}^T \psi_{j,k}(t) \bar{\mathbf{F}}_k' \bar{\boldsymbol{\Lambda}}_{j,k}' \mathbf{X}_{t;T} + \sum_{j=-J}^{-1} \sum_{k=0}^T \sum_{l=-J}^{-1} \sum_{m=0}^T \psi_{j,k}(t) \psi_{l,m}(t) \bar{\mathbf{F}}_k' \bar{\boldsymbol{\Lambda}}_{j,k}' \bar{\boldsymbol{\Lambda}}_{l,m} \bar{\mathbf{F}}_m \right] \\ (NT)^{-1} \left[\sum_t \mathbf{X}_{t;T}' \mathbf{X}_{t;T} - \sum_{j=-J}^{-1} \sum_{k=0}^T \sum_t \mathbf{X}_{t;T}' \psi_{j,k}(t) \bar{\boldsymbol{\Lambda}}_{j,k} \bar{\mathbf{F}}_k - \sum_{j=-J}^{-1} \sum_{k=0}^T \bar{\mathbf{F}}_k' \bar{\boldsymbol{\Lambda}}_{j,k}' \sum_t \mathbf{X}_{t;T} \psi_{j,k}(t) + \sum_t \sum_{j=-J}^{-1} \sum_{k=0}^T \sum_{l=-J}^{-1} \sum_{m=0}^T \psi_{j,k}(t) \psi_{l,m}(t) \bar{\mathbf{F}}_k' \bar{\boldsymbol{\Lambda}}_{j,k}' \bar{\boldsymbol{\Lambda}}_{l,m} \bar{\mathbf{F}}_m \right] \end{aligned}$$

By definition of the empirical wavelet coefficients,

$$(NT)^{-1} \left[\sum_t \mathbf{X}_{t;T}' \mathbf{X}_{t;T} - \sum_{j=-J}^{-1} \sum_{k=0}^T \mathbf{d}_{j,k}' \bar{\boldsymbol{\Lambda}}_{j,k} \bar{\mathbf{F}}_k - \sum_{j=-J}^{-1} \sum_{k=0}^T \bar{\mathbf{F}}_k' \bar{\boldsymbol{\Lambda}}_{j,k}' \mathbf{d}_{j,k} + \sum_t \sum_{j=-J}^{-1} \sum_{k=0}^T \sum_{l=-J}^{-1} \sum_{m=0}^T \psi_{j,k}(t) \psi_{l,m}(t) \bar{\mathbf{F}}_k' \bar{\boldsymbol{\Lambda}}_{j,k}' \bar{\boldsymbol{\Lambda}}_{l,m} \bar{\mathbf{F}}_m \right]$$

The First Order Condition with respect to $\bar{\mathbf{F}}_k$ are :

$$\bar{\mathbf{F}}_k' \sum_{j=-J}^{-1} \bar{\boldsymbol{\Lambda}}_{j,k}' \bar{\boldsymbol{\Lambda}}_{j,k} = \sum_{j=-J}^{-1} \mathbf{d}_{j,k}' \bar{\boldsymbol{\Lambda}}_{j,k} \quad , \forall k$$

With the constraint (3.2) and taking the transpose,

$$\bar{\mathbf{F}}_k = (JN)^{-1} \sum_{j=-J}^{-1} \bar{\boldsymbol{\Lambda}}_{j,k}' \mathbf{d}_{j,k} \quad (3.3)$$

Replace (3.3) in the original minimization problem,

$$\min_{\bar{\boldsymbol{\Lambda}}_{j,k}} (NT)^{-1}$$