Table 2.2 Binary, Octal, Hexadecimal equivalent of Decimal Numbers

Decimal	Binary	Octal	Hexadecimal
0	0000	000	0000
1	0001	001	0001
2	0010	002	0002
3	0011	003	0003
4	0100	004	0004
5	0101	005	0005
6	0110	006	0006
7	0111	007	0007
8	1000	010	0008
9	1001	011	0009
10	1010	012	A
11	1011	013	B
12	1100	014	C
13	1101	015	D
14	1110	016	E
15	1111	017	F

Example

The hexadecimal sequence $(25)_{16}$ has the decimal equivalent:

$$(25)_{16} = 2\times16^1 + 5\times16^0$$
$$= 32+5$$
$$= (37)_{10}$$

Workshop

1. Identify the number system for the following numbers

S. No.	Number	Number system
1	$(1010)_{10}$	Decimal Number system
2	$(1010)_{2}$	
3	$(989)_{16}$	
4	$(750)_{8}$	
5	$(926)_{10}$	

2. State whether the following numbers are valid or not. If invalid, give reason.

S.No.	Statement	Yes / No	Reason (If invalid)
1.	786 is an Octal number		
2.	101 is a Binary number		
3.	Radix of Octal number is 7		

2.4 Number System Conversions

2.4.1 Decimal to Binary Conversion

Generally two methods followed.

Method 1: To convert Decimal to Binary "**Repeated Division by 2**" method can be used. Any Decimal number divided by 2 will leave a remainder of 0 or 1. Repeated division by 2 will leave a sequence of 0s and 1s that become the binary equivalent of the decimal number. Suppose it is required to convert the decimal number N into binary form, dividing N by 2 in the decimal system, we will obtain a quotient N1 and a remainder R1, where R1 can have a value of either 0 or 1. The process is repeated until the quotient becomes 0 or 1. When the quotient is '0' or '1', it is the final remainder value. Write the final answer starting from final remainder value obtained to the first remainder value obtained.

Example

Convert $(65)_{10}$ into its equivalent binary number

Chapter 2 Page 014-040.indd 17 3/24/2020 12:03:06 PM