back on the buffer. If the buffer already had a 1 at the `index`-th bit, then it won't change, otherwise only that bit will be updated. We are assuming, here, that we only write ones, never zeroes (as our version does of Bloom filter does not support the `delete` operation).

Let's go through an example for `readBit` and `writeBit`. Suppose we have this buffer: `B=[157, 25, 44, 204]`, with `BITS_PER_INT=8`.

We call `readBit(B, 19)`, then we have: `element==2`, `bit==3`.

Therefore:

- `bitsArray[element] == 44`
- `(1 << bit) == 8`
- `bitsArray[element] & (1 << bit) == 8`

And the returned value will be `1`.

If, instead, we call writeBit(B, 15), then we have: (element==1, bit==7).

Therefore:

- `bitsArray[element] == 25`
- `(1 << bit) == 128`
- `bitsArray[element] | (1 << bit) == 153`

And the buffer will be updated to `B=[157, 153, 44, 204]`.

4.6.3 Find Where a Key is Stored