

3.2.3 The monitor is producing a high-pitched whine

Cause: This is often noticed in cheaper monitors, and it will become more pronounced with age.

Solution: Try adjusting the brightness and contrast controls, this may reduce the noise somewhat. You can also try ignoring the noise and let it merge with the background, like the hum from your TV. If it is bothersome, take it to repair shop; there might be some components that can be changed to reduce the noise.

3.2.4 The screen is totally white or grey in colour

Cause: There is no signal from the video card.

Solution: Check the signal cable as explained above. If the signal cable is fine, check the *Troubleshooting the Video Card* section for further details.

3.2.5 The display is too bright or dim; the contrast is too high or low

Cause: The brightness and contrast settings may not be set correctly. The CRT may be wearing out.

Solution: Check the brightness and contrast settings. As the CRT ages, the screen will start to dim. In some cases, your repair shop may be able to tweak the monitor to improve the brightness. Change the lighting in the room so that there is no direct light falling on the monitor. Turn off the monitor when not in use. In any case, this might well be an indication of age catching up with the monitor—time to go shopping!

3.2.6 The screen has a bluish, greenish or purplish tint

Cause: This is usually caused by a break in one of the three colour signals between the video card and the monitor. The problem is especially common in older monitors, and is caused by heat stresses that break the connections between the cable and the circuit board inside the monitor.

Solution: Check the signal cable for kinks, frays and other signs of wear and tear. If the cable is not integrated, have it replaced, else take the monitor to the repair shop and they should replace it for you at very little cost.