



Australia supports Blockchain

Newly elected Australian PM Scott Morrison is pushing for blockchain to take on big banks. <https://digit.in/oct18-32-1>



Blockchain detects fake Diamonds

A Hong Kong based jeweler has introduced a Blockchain based app to verify authenticity of Diamonds. <https://digit.in/oct18-32-2>

PUBG Controller

This is a DIY guide to making your own PUBG trigger controller. You place these on top of your smartphone screen, and you can fire using your right finger, and a custom control option for the left. The DIY requires cheap materials available at a stationery shop.

Aditya Madanapalle | aditya@digit.in



STEP 0

Materials required

- Double Sided Tape
- Double Sided Padding Tape
- Scissors
- Instant Glue
- Aluminum Sheet
- Ice Cream Sticks
- Pen Knife.

Craft ice cream sticks are available, which are nice and colourful but may not be of a uniform size. This includes both the width, as well as the thickness. However, if the ice cream sticks are not of a uniform size, it can actually work to your advantage. The sticks required for the base of the trigger can be chosen depending on the thickness of the phone. The thinner ice cream sticks are also easier to cut with scissors. Disposable wooden spoons or forks can also be used. If you get your hands on aluminum tape, then there is no need for the alu-

minum sheet and double sided tape. All the parts required for the build should be available for less than ₹200.



STEP 1

Step 1: Setting up the controls

This is the most important step towards making sure that the triggers work as intended. To set up the triggers, it is a good idea to change the control options in the training mode. Go to Settings > Controls > Customise. This allows you to drag around the buttons anywhere on the screen, as well as adjust their size and transparency. It is a good idea to make the buttons nice and big, but you can increase the transparency to compensate. The buttons will be hidden under the arms of the controller anyway. Make sure that you do not place any buttons from the top edge of the screen, till where the controller buttons are located. Once this is done, it is a good idea to measure the distance from the top of the screen, to where your button is placed. This will decide the length of the front arms of your controller. The complete build involves a pair of controllers, but you can just as well use just one.



STEP 2

Take the measurements

Once you have all your measurements, we can get to building the trigger. The first step is cutting up the sticks to create two triggers. You need two rectangular pieces to sit on top of the phone. The front and back pieces for the phone can have the rounded ends on one side. The back piece, and the two top pieces can measure 3.5 cm. We used a 2.5 cm piece for the front, but this can be modified according to your button placing and size of the phone. It is good to keep the piece less than 3.5 cm. Mark all these out on the ice cream sticks, and cut them up. You need two sets for the left and right controller, so after this step you should have 4x 3.5 cm long rectangular pieces, two 3.5 cm long rounded edge pieces and two 2.5 cm long rounded edge pieces.



STEP 3

Forming the base

Now stick two of the rectangular pieces together. If they do not align properly during the sticking, or they are not the